EEG-based neurofeedback with network components extraction: a data-driven approach by multilayer ICA extension and simultaneous EEG-fMRI measurements

Takeshi Ogawa[1*], Hiroki Moriya[1], Nobuo Hiroe[2], Motoaki Kawanabe[1,3], Jun-ichiro Hirayama[3,4]

[1]Cognitive Mechanisms Laboratories, Advanced Telecommunications Research Institute International, Seika-Cho, Soraku-gun, Kyoto, Japan

[2]Neural Information Analysis Laboratories, Advanced Telecommunications Research Institute International, Seika-Cho, Soraku-gun, Kyoto, Japan

[3]RIKEN Center for Advanced Intelligence Project, Seika-Cho, Soraku-gun, Kyoto, Japan

[4]Human Informatics and Interaction Research Institute, National Institute of Advanced Industrial Science and Technology (AIST), Tsukuba City, Ibaraki, Japan

*Correspondence:

Takeshi Ogawa, Ph.D

t.ogawa@atr.jp

Abstract

Several studies have reported advanced treatments for depressive symptoms, such as real-time neurofeedback (NF) with functional MRI (fMRI) and/or electroencephalogram (EEG). NF focusing on a regularization of brain activity associated with the amygdala or functional connectivity (FC) between the executive control network (ECN) and default mode network (DMN) has been applied to reduce depressive symptoms. However, it is practically difficult to install the fMRI-NF system and to consistently provide treatment, because of high cost. Additionally, no practical signal processing techniques have been developed extracting FC-related features from EEG signals, particularly when no physical forward models are available. In this regard, stacked pooling and linear components estimation (SPLICE), recently proposed as a multilayer extension of independent component analysis (ICA) and related independent subspace analysis (ISA), can be a promising alternative. The resting-state EEG network features can be correlated with fMRI network activity corresponding to the DMN or ECN. This may enable the modulation of the target FC-related features in EEG-based NF.

In this study, we developed a real-time EEG NF system for improving depressive symptoms by using the SPLICE. Utilizing information from the fMRI biomarkers, we evaluated our paradigm for effectiveness with regard to upregulation of the dorsolateral prefrontal cortex /middle frontal gyrus or downregulation of the precuneus/posterior cingulate cortex. We conducted an NF experiment in participants with subclinical depression; the participants were divided into the NF group (n=8) and the sham group (n=9). We found a significant reduction and a large effect size in the rumination response scale (RRS) score (reflection) in the NF group, compared to the sham group. However, we did not find a significant relationship between the training score and

difference in symptoms. This suggests that increased controllability of the EEG signals

did not directly reduce the RRS reflection score. This could be due to various reasons

such as improper feature extraction, individual differences, and the targeted brain

regions. In this paper, we also discuss the possible ways to modify our NF protocol

including the design of the experiment, sample size, and online processing. We then

discuss way to improve the NF training, based on our results.

Keywords: neurofeedback, depression, EEG-fMRI, blind source separation,

functional connectivity

1. Introduction

Advanced treatments for depressive symptoms have been formulated using brain or physiological measurements instead of traditional medical treatments. One of the noninvasive ways to accurately monitor brain activity that may represent depressive symptoms is functional MRI (fMRI). This technique is well suited because of its high spatial resolution, even when applied to deep brain areas. Recently, several groups have proposed real-time fMRI neurofeedback (NF) paradigms to regulate participants' brain signals for converting depressive brain states into healthier states (Young et al., 2017; Yamada et al., 2017; Taylor et al., 2021; Takamura et al., 2020). It is assumed that at the end of the NF training period, improvement in the controllability of participant brain activity could help reduce their depressive symptoms.

The fMRI NF, focusing on regularizing functional connectivity (FC) between the executive control network (ECN) and default mode network (DMN), has been applied to alleviate depression (Yamada et al., 2017; Taylor et al., 2021; Tsuchiyagaito et al., 2021). The relationship between the time courses of the ECN and DMN in healthy individuals is generally negatively correlated, and is associated with the distinction between internal (own thoughts) and external (perceptions of the external environment) contents (Northoff, 2016). In contrast to healthy individuals, patients with depressive disorders tend to be dysbalanced, such as positively or not significantly correlated, and show increased self-focus (rumination, guilt, fear) and decreased environment-focus (social withdrawal, psychomotor retardation) (Drysdale et al., 2017). This relationship was elucidated using an fMRI biomarker comprised of FCs; utilizing data-driven approaches, this biomarker was used to successfully distinguish between patients with

melancholic depression and healthy controls (Ichikawa et al., 2020; Yamashita et al.,

2020). They found the FCs including the dorsolateral prefrontal cortex (DLPFC)/middle

frontal gyrus (MFG) in ECN and the precuneus/posterior cingulate cortex (PCC) in

DMN. According to the results of the fMRI biomarker analysis, NF with a specific FC,

termed as FC neurofeedback (FCNef), shows potential to be a novel treatment

modality for depression, and can be applied in a targeted manner.

However, real-time fMRI NF takes high costs; it is practically difficult to install this

system and constantly provide treatment. This is a significant obstacle for applying this

technique to treat depressive symptoms. On the other hand, real-time NF using

electroencephalography (EEG) has been proposed as an alternative approach, such as

NF applied with frontal alpha asymmetry (Wang et al., 2019), peak alpha frequency (Yu

et al., 2020), and alpha-theta ratio (Cheon et al., 2016). In particular, frontal alpha

asymmetry EEG NF has been shown to modulate left-side alpha power associated with

brain activity in the left amygdala (Davidson et al., 1990). EEG has many practical

benefits such as reasonable cost, high temporal resolution, and fewer physical

constraints; its main limitation is low-spatial resolution. Recent studies of EEG-fMRI

data have reported the possible effectiveness of real-time EEG-fMRI NF paradigms for

depression (Zotev et al., 2014; Zotev et al., 2016; Zotev et al., 2020) and improved

reliability of EEG signatures for NF. In these NF training studies, participants were

asked to imagine a positive autographic memory, such as a happy event, and were

instructed to increase brain activity in the left amygdala and simultaneously try to

increase frontal alpha asymmetry. This NF modality aims to reinstate healthy brain

function in the left amygdala.

However, in contrast to real-time fMRI NF or FCNef, an EEG NF using network

features has been poorly investigated. This is mainly because there are no practical

signal processing techniques extracting FC-related features from EEG, particularly

when no physical forward models are available. Especially in real-time process, a brain

signal source localization is a difficult issue that requires to solve inverse problems with

constraints. In fact, most studies have used sensor-level features such as time-varying

powers of particular frequency bands, or have sought to extract source-level features

by a blind source separation (BSS) technique such as independent component

analysis (ICA). Neither method is designed to detect EEG features that reflect FC and

modular organization related to resting-state networks. Therefore, it is imperative to

develop a new BSS-based technique combined with a signal model that explicitly

assumes network structures at the source level related to FC. In this regard, stacked

pooling and linear components estimation (SPLICE; Hirayama et al., 2017), which has

been recently proposed as a multilayer extension of ICA and related independent

subspace analysis (ISA; Hyvärinen & Hoyer, 2000), can be a promising alternative.

However, its application to resting-state EEG has not yet been investigated. We

expected that if the extracted EEG network features correlate with fMRI network activity

corresponding to the DMN or ECN, these features may be used to modulate the target

networks in EEG-based NF training.

In this study, we attempted to apply an EEG network estimated by SPLICE for a real-

time EEG NF paradigm. We have developed EEG-based NF training to improve

depressive symptoms in healthy individuals with subclinical depression. We evaluated

the effectiveness of EEG NF in modulating estimated brain activity; targeted

modulation included upregulation of DLPFC/MFG activity or the downregulation of

precuneus/PCC activity, which was expected to reduce depressive symptoms. We

conducted a four-day EEG-NF study with two groups (NF, sham) of participants with

sublicinal depression; we targeted specific regions (DLPFC/MFG or precuneus/PCC)

while applying an FCNef paradigm (Yamada et al., 2017; Taylor et al., 2021). To train

the SPLICE model, participants completed a two-day EEG-fMRI experiment; in this

experiment, we obtained simultaneously recorded EEG-fMRI data at rest and during a

working memory task such as the N-back task which evoked brain activity in the ECN.

We selected EEG network features that correlated with fMRI signals in the DLPFC or

precuneus/PCC for NF training, by modeling SPLICE from the resting-state data.

Scores on the Beck Depression Inventory-II (BDI-II; Beck et al., 1996) and the

Rumination Response Scale (RRS; Hasegawa, 2013; Treynor et al., 2003) were

measured pre-and post-NF training. Finally, we evaluated the effect size of the

difference between pre-and post-training among NF and sham groups. In this paper,

we present the results of these experiments and also discuss the possibility of

formulating an EEG NF protocol using EEG network features relevant to fMRI network

information.

2 Materials and Methods

2.1 SPLICE

SPLICE (Hirayama et al., 2017) is a multilayer extension of ICA that is based on a

probabilistic model that simplifies the generative process of EEG. This concept can be

mathematically described as follows:

Let x and s denote the vectors of the EEG measurements and unobserved source

signals, respectively, at a single time point. Then, we assume a linear model (first layer)

similar to ICA, given by

$$\mathbf{x} = \mathbf{As}, \tag{1}$$

where the mixing matrix A is a square matrix and invertible; the inverse $\mathbf{W} := \mathbf{A}^{-1}$ is

called the demixing matrix. Both $\mathbf{x}$ and $\mathbf{s}$ are zero-mean, without loss of generality, by

subtracting the sample mean in advance from the original data vectors. Note that the

sources (entries in $\mathbf{s}$) lack explicit physical mapping to the cortex. However, they can

still be interpreted as reflecting cortical activations based on their associated

topographies (i.e., corresponding columns of $\mathbf{A}$), exactly as in ICA. For mathematical

convenience, the number of sources, d, is assumed to be the same as the

dimensionality of $\mathbf{x}$; in practice, we apply PCA beforehand to determine an appropriate

number of sources as customarily done in ICA.

Additional layers are introduced on top of the first layer to model the statistical

dependency among the sources and the parametric structures behind it. Specifically,

SPLICE introduces 1) the functional modularity of sources and 2) the intrinsic

correlations (coactivations) among modules into the multilayer generative model. Both

are reasonable assumptions, particularly for resting-state EEG data. This is because

cortical activity at rest is known to exhibit functional organization with multiple modules

(e.g., resting-state network) that are often mutually correlated or anticorrelated.

First, we divide the d first-layer sources into m modules $\mathbf{s}[j]$ without overlapping, where

$\mathbf{s}[j]$ denotes the vector consisting of dj sources belonging to module j ($d = \sum_{j=1}^{m} d_j$). $\mathbf{s}_{[j]}$

represents a d_j-dimensional subspace spanned by the corresponding columns in $\mathbf{A}$.

Then, we assume that the (squared) L2-norms $||\mathbf{s}_{[j]}||^2$ of modules $\mathbf{s}_{[j]}$ are generated by

an additional ICA-like linear generative model with pointwise nonlinearity, such that

generated by an additional ICA-like linear generative model with pointwise nonlinearity,

such that

$\qquad ||\mathbf{s}_{[j]}||^2 = F_j^{-1}\ ([\mathbf{Bt}]_j),\ j = 1,\ 2,\ ...,\ m,$ (2)

where an appropriate link function F_j is used for a convention between non-negative

(norm) and real random variables (we set F_j = log in our analysis); $\mathbf{B}$ and $\mathbf{t}$ constitute

the invertible mixing matrix, and source vector (and $\mathbf{V} := \mathbf{B}^{-1}$ is a demixing a matrix) of this

layer, and $[\cdot]_j$ denotes the j-th entry of a vector. Then, the norms are either mutually

uncorrelated or correlated, depending on specific values of $\mathbf{B}$ (see below). Here, the

squared L2-norm of a vector is simply the sum-of-squares of entries and it represents

the total power of the sources within each module. In this study, we focus on modeling

and analyzing the module norms (powers), making a minimal assumption on module

direction $\mathbf{s}[j]/||\mathbf{s}[j]||$. Thus, we assume module directions $\mathbf{s}[j]/||\mathbf{s}[j]||$ are mutually

independent and each follows a spherically uniform distribution, which maximizes the

entropy under restriction of unit norm constraints. This is equivalent that we assume

every modules vectors $\mathbf{s}[j]$ to be spherically distributed. Note that the model can be

recursively extended to have additional layers to further model the dependency in

higher-layer sources (Hirayama et al., 2017). However, we assume Eq.(2) describes

the top layer in the present study. Thus, the entries in t are assumed to be independent

of each other, given a typical prior in ICA (e.g., the one corresponding to the standard

tanh nonlinearity).

To recapitulate the generative model, a conceptual diagram of SPLICE is presented in

Figure 1. The model consists of three layers, as follows: two linear layers, and an

intermediate L2-pooling layer for calculating the norms. Here, we define **y**: = **Bt**. If the

highest layer **B** is not diagonal, the modules are mutually independent, and the model

reduces to independent subspace analysis (Hyvärinen & Hoyer, 2000). If not diagonal,

the modules are not independent, and are thus expected to be suitable for representing

correlated or anticorrelated cortical modules. Note that modeling non-diagonal **B**

affects the higher layer and influences the first layer through the joint learning of the

two layers (see below) because it makes a different (possibly improved) prior

assumption on the first-layer sources from that of ICA or ISA.

A striking property of SPLICE is that both parameter estimation (learning) and posterior

inference on latent variables can be performed in a principled manner without resorting

to any approximative techniques or heavy numerical computation. Learning is done

based on conventional maximum likelihood (ML) estimation. The corresponding loss

function, i.e., the negative log-likelihood for a single datum $L(\mathbf{x})$: = − *ln* $p(\mathbf{x})$ + const.

where $p(\mathbf{x})$ is the probability density function of **x**, is analytically given by

$$L(\mathrm{x}) = \sum_{k=1}^{m} H_k \left(\sum_{k=1}^{m} v_{kj}\, F_j \left(\|\mathbf{W}_{[j]}\mathbf{x}\|^2 \right) \right) - \ln|det\mathbf{V}| + \sum_{k=1}^{m} G_j \left(\|\mathbf{W}_{[j]}\mathbf{x}\|^2 \right) - c \ln|det\mathbf{W}|$$

(3)

where ***H*** and ***G*** are functions derived from the prior distribution of ***t*** and the link function

Fj. The dimensionality of every module (subspace) *dj* is adaptively determined before

ML estimation using a clustering-like technique (see Hirayama et al., 2017 for details).

Once demixing matrices **W** and **V** are learned, the generative process can be readily

inverted by computing $\mathbf{s} = \mathbf{Wx}$ and $\mathbf{y} = \mathbf{Bt}$, with the L2-pooling $||\mathbf{s}[j]||^2$ (followed by F_j)

between them. In practice, the pooled outputs (squared norm) may fluctuate too heavily

owing to the noisy nature of the EEG technique. Thus, as a slight extension of the

original SPLICE, we also implemented the L2-pooling across successive time points for

smoothing; this was done in a principled manner by modifying the model and likelihood,

so that the top linear layer determines the L2 norm of $\mathbf{s}[j]$ that now concatenates

several instances of the dj sources across time points. As noted above, pooling just

means taking the sum of squares (of the filtered outputs). Thus, the squared module

norm essentially provides the total power or energy of a source module's activity.

Therefore, we focused primarily on the estimated module norms as the main output of

the analysis, rather than the top-layer sources $\mathbf{t}$ which the multilayer computation

eventually produces, because we expected to associate EEG features with the activity

of cortical modules.

235   (Insert Figure 1 here)

2.2 Experiment procedures

2.2.1 Participants

The workflow pertaining to this experimental procedure is illustrated in Figure 2A. The

experiment consisted of three steps, as follows: "Screening," "EEG-fMRI experiment,"

and "NF training experiment." All participants were recruited by screening

questionnaires and clinician assessment (n = 102; 49 women, 53 men; mean age =

29.88 ± 9.8 years) at the Screening step. Before the EEG-fMRI experiment,

participants, who (a) were prone to suicidal thoughts as measured in the BDI, (b) had

current/past mental/psychiatric diseases, (c) did not understand the Japanese

language, (d) showed a BDI score less than 3, or (e) declined to attend due to time

unavailability or other personal reasons, were excluded. Twenty-eight participants with

subclinical depression, designated as "subclinical individuals", were included in the

EEG-fMRI experiment which was conducted for two days. Furthermore, we excluded

participants who had excessive body/head movements in fMRI scanning and declined

to attend due to time unavailability or other personal reasons. Finally, 17participants

(NF group, n = 8; sham group: n = 9) completed the NF training experiment conducted

for four days. All participants provided written informed consent prior to participating in

the experiment. After each experiment, all participants received cash remuneration for

their involvement. This study was approved by the ethics committee of the Advanced

Telecommunications Research Institute International (ATR) and was conducted in

accordance with the Declaration of Helsinki.

259   (Insert Figure 2 here)

2.2.2 Psychological questionnaires

In the Screening experiment (visit 1), all participants completed self-reported

questionnaires that included queries pertaining to demographic characteristics, BDI,

RRS, Obsessive-Compulsive Inventory (OCI), Autism-Spectrum Quotient (AQ), State-

Trait Anxiety Inventory (STAI2), Snaith-Hamilton Pleasure Scale (SHAPS), Schizotypal

Personality Questionnaire (SPQ), Barratt Impulsiveness Scale 11 (BIS-11), Zimbardo

Time Perspective Inventory (ZTPI); participants were rated using the 21-item Hamilton

Depression Rating Scale (HAM-D), the Hamilton Anxiety Rating Scale (HAM-A), and

the Structured Clinical Interview for DSM-IV-TR Axis disorders (SCID). To evaluate the

effects of the EEG NF training, participants completed the BDI, RRS, OCI, AQ, STAI2,

BIS-11, and ZTPI on Day 1 (visit 4) and Day 4 (visit 7) of the NF training experiment

(Figure 2B). We found a significant positive correlation between the BDI and RRS

score (total: 0.66; brooding: 0.44; reflection: 0.59), including the subscale, which

presented in Supplementary Figure 1.

2.2.3 N-back task

The N-back task is a cognitive task associated with the functioning of the working

memory. We conducted the N-back task test to induce brain activities with anti-

correlation between the ECN and DMN (Yamada et al., 2017; Liu et al., 2017; Cao et

al., 2021). This enabled us to select a SPLICE module for the NF training. Participants

completed a behavioral experiment, such as N-back tasks, outside the MRI screener

during the Screening experiment (visit 1) (baseline), and during the NF training

experiment (visit 4: Day 1, visit 7: Day 4). We used these data to evaluate changes in

cognitive performance resulting from the NF training (see Figure 2C). Customized code

generated using Presentation ® software (Version 18.0, Neurobehavioral Systems, Inc.,

Berkeley, CA) controlled the N-back task and to display the task on the monitor. When

ready to start the N-back task, participants clicked the left button of a mouse to begin

each session, shown in Figure 2C. The participants were instructed to relax and simply

focus at the center of the monitor. In the 0-back condition, participants were asked to

promptly click the left mouse button when the number "0" appeared on the monitor. In

the 1-back, 2-back, and 3-back conditions, participants were asked to click the left

mouse button promptly when matching a currently displayed number and a number

presented one, two, or three trials prior. A single session consisted of four blocks with

four randomly aligned conditions (0-, 1-, 2-, and 3-back). A single trial had an inter-trial

interval of 1300 ms duration, after which a number from 1 to 9 was displayed at the

center of the monitor for 200 ms. In total, a single block had 64 trials that lasted for 100

s; therefore, it took approximately 13 min to complete two sessions of this task.

In the EEG-fMRI experiment, participants also completed the N-back task with EEG

recording outside the MRI scanner and fMRI scanning inside the MRI scanner (see

Figure 2D). When in the MRI scanner, participants were asked to press the response

buttons using an MRI-compatible response device (HHSC-2 × 2, Current Designs, Inc.,

PA, USA). A single session consisted of the following: a first 30-s resting period (a

white fixation cross at the center of the screen), three randomly ordered blocks of three

conditions (0-, 1-, and 2-back), a second 30-s resting period, three blocks of N-back

tasks, and a third 30-s resting period. At the beginning of each block, participants were

informed of a rule corresponding to the condition, and were then asked to complete 20

trials. It took participants 5 min 45 s to complete a single session.

2.3 Data acquisitions

Figure 2B summarizes the measurements performed at each visit. MRI data were

acquired with a 3T MRI scanner, MAGNETOM Verio (Siemens, Erlangen, Germany),

using a Siemens 12-channel head coil installed at the Brain Activity Imaging Center

located in the ATR. High-resolution, T1-weighted structural images (TR = 2250 ms, TE

= 3.06 ms, flip angle = 9 °, inversion time = 900 ms, matrix = 256 × 256, 208 sagittal

slices, 1 mm isotropic) were acquired for normalization to a standard brain for echo-

planar image (EPI) registration. Functional images such as those using fMRI data were

acquired with an EPI sequence (TR = 2450 ms, TE = 30 ms, flip angle = 80 °, matrix =

64 × 64, field of view = 192 mm, slice thickness = 3.2 mm, 35 axial slices, scan

sequence: ascending). We measured 150 volumes (6 min 7 s) for the resting state and

141 volumes (5 min 45 s) for the N-back task.

EEG signals were measured using an MR-compatible amplifier (BrainAMP MR plus,

Brain Products GmbH, Germany) and a 64-channel EEG electrode cap (BrainCap MR,

Brain Products GmbH, Germany); this included 63 EEG channels and one

electrocardiogram (ECG) channel. The EEG cap was correctly placed on the

participant's head as per the International 10-10 system. The ground electrode and

online reference electrode were placed at AFz and FCz positions, respectively. For

safety reasons, the impedance of all the EEG electrodes and the ECG electrode were

maintained below 10 kΩ and 50 kΩ, respectively, throughout the experiment. We

placed the ECG electrode on the participant's back to enable the subsequent

correction of ballistocardiographic artifacts. Using the Brain Vision Recorder (Brain

Products GmbH, Germany), raw data were recorded with a 5 kHz sampling frequency,

with filtering between 0.1 and 250 Hz. The amplifier system was placed on the MRI

scanner beside the subject's head during fMRI scanning with fixation of MR-compatible

sandbags to reduce artifacts caused by the tinny vibration of the scanner. The EEG

recording system clock was synchronized using a SyncBox device (Brain Products

GmbH, Germany) and the MRI scanner's 10 MHz master synthesizer to achieve phase

synchronization clocks for digital sampling between the MRI data and the EEG system.

To remove artifacts caused by fMRI scanning from the EEG data, we simultaneously

recorded each TR trigger signal to mark the onset of every instance of single fMRI

volume acquisition. During the EEG-fMRI data acquisition, we used a projector (DLA-

X7-B, JVC; frame rate = 60 Hz) to present the visual stimulation on an opaque screen.

The EEG-fMRI experiment was conducted as follows: first, EEG measurements of the

resting-state (two sessions) and the N-back task (0-, 1-, 2-back; two sessions) were

obtained for each participant in a soundproof shield room. A single session of the

resting-state and that of the N-back task took five minutes and six minutes, respectively.

Second, participants moved to the MRI scanner and completed the resting-state (two

sessions), the N-back task (two sessions), the T1-weighted structural image scan, and

the resting state (two sessions). Finally, EEG data (resting-state: four sessions; N-back

task: four sessions) and EEG-fMRI data (resting-state: eight sessions; N-back task:

four sessions) were obtained and used to estimate the SPLICE filter for the NF.

During the NF training experiment, EEG signals were measured in the soundproof

shield room from Day 1 to Day 3; EEG-fMRI data were obtained in the MRI scanner on

Day 4 as well as during the EEG-fMRI experiment. The resting-state EEG signals were

measured for five minutes during the NF training (Days 1, 2, and 3). Subsequently, the

NF training was conducted for each participant for nine minutes in a single session;

each participant completed five sessions.

2.4 Data analysis

2.4.1 Preprocessing of fMRI data

Figure 3A summarizes the workflow of preprocessing of the EEG and fMRI data and

the integration process. The preprocessing parameters and methods were as per

previous studies (Ogawa et al., 2018; Aihara et al., 2020). The data were processed

using SPM8 toolbox in MATLAB software (Wellcome Trust Centre for Neuroimaging).

The first four volumes were removed to allow for T1 equilibration. The remaining data

were subjected to slice-timing correction and realignment of the mean image of that

sequence to compensate for head motion. The structural image was coregistered to

the mean functional image and segmented into three tissue classes in the MNI space.

The functional images were normalized and single voxels were resampled with a 2 × 2

× 2 mm grid. Finally, the normalized images were spatially smoothed using an isotropic

Gaussian kernel of 8 mm full-width at half maximum.

For each participant, we extracted the fMRI time courses within each region of interest

(ROI). To remove several sources of spurious variance and their temporal derivatives,

linear regression was performed, including six motion parameters in addition to

averaged signals over gray matter, white matter, and cerebrospinal fluid. Furthermore,

to reduce spurious changes caused by head motion, the data were using a method that

reduces motion-related artifacts. A high-pass filter (< 0.008Hz) was applied to these

sets of time courses prior to the regression procedure.

(Insert Figure 3 here)

2.4.2 Preprocessing of EEG data

To extract the EEG network features, the SPLICE model was optimized from the

resting-state EEG data simultaneously recorded with fMRI, applying leave-one-session

out cross-validation for each individual. Before the training of the SPLICE model, the

raw EEG data were cleaned using Brain Analyzer software (Brain Products) to remove

i) fMRI scanning artifacts and ii) ballistocardiographic artifacts. In the next step, we

used the EEGLAB toolbox in MATLAB software (Delorme and Makeig, 2004) to

process the data as follows: iii) remove noisy channels by visual inspection; iv) apply a

high-pass filter (> 1 Hz) to detrend the EEG signal; v) remove harmonic noise with

CleanLine (add-on in EEGLAB); vi) apply Artifact Subspace Reconstruction (ASR;

Mullen et al., 2013) to remove stationary/non-stationary noise for continuous data; vii)

interpolate removed channels to the original channel space and re-reference the data;

and viii) apply a bandpass filter between 8 and 12 Hz (alpha band), as per a previous

publication by de Munck et al. (2007).

2.4.3 EEG-fMRI integration analysis for the selection of a module for NF

training

We set 63, 20, and 20 dimensions for the first layer (sources), the second layer

(modules), and the third layer (top-level ICs), respectively, similar to a previous study of

resting-state brain networks using fMRI (Laird et al., 2011); we then estimated the

parameters of the SPLICE model from the resting-state EEG data recorded in the fMRI

scanning. We used a FCNef protocol (Yamada et al., 2017; Taylor et al., 2021) to

create a functional localizer during the N-back task, and evaluated the SPLICE

modules using EEG-fMRI data collected during the N-back task. We estimated the time

courses of the output of modules through the SPLICE model and then downsampled

them at 5 Hz. We applied the fMRI signal to the general linear model (GLM, SPM12) to

identify a module that modulated the time course during the N-back task. The design

matrix consisted of six motion parameters pertaining to head motions and the EEG

network features, convoluted with the hemodynamic response function (HRF), and

decimated to match the time instant of the fMRI signal (Mantini et al., 2007; Tsuchimoto

et al., 2017). In the correlation analysis, we identified the modules that significantly

correlated with brain activity, based on whether a statistical cluster existed in the

DLPFC/MFG or PCC/Precuneus with a thresholding p-value < 0.001, uncorrected, and

cluster-level p < 0.05 corrected by Family-Wised Error (FWE). Five participants with

clusters identified in the DLPFC/MFG performed to upregulate the EEG network

feature, and three participants with clusters identified in the PCC/precuneus performed

to downregulate the one in the NF training. The participants were blinded to the group

allocation and to their upregulation/downregulation status until the end of NF training.

Separately from this, we also validated the use of the SPLICE model in comparison to

a standard ICA. Specifically, we calculated the mean log-likelihood of the SPLICE

model, i.e., the negative of $L(\mathbf{x})$ in Eq.(3) averaged over test data, using a leave-one-

session-out cross validation scheme. Similar to this, we also obtained the mean log-

likelihood of a standard ICA model, estimated by FastICA (the initial values of the first

layer of the SPLICE model; Hyvärinen, 1999), with the same source prior as that in the

top layer of SPLICE. For a fair comparison, we did not incorporate pooling across time

points into the SPLICE model in this validation. We compared the cross-validated log-

likelihood values, evaluated for all the individuals, between the SPLICE model and ICA

using a paired t-test.

2.5 Neurofeedback protocol

Figure 3B shows the workflow of the online EEG NF training process. The real-time NF

system consisted of OpenViBE software (v1.0.0; Renard et al., 2010) for real-time EEG

signal acquisition, a feedback module programmed using MATLAB, and a Brain Amp

MR (Brain Products) amplifier with a 63-ch EEG electrode cap. Raw EEG signals were

acquired at 500 Hz using Brain Amp MR and the OpenViBE Acquisition Server. Using

OpenViBE Designer (and interactive graphical user interface: GUI), the EEG data were

subjected to electrooculography artifact removal (e.g., blinking, eye movement) using

online recursive ICA (ORICA; Hsu et al., 2016) and a bandpass filter between 8 and 12

Hz. Subsequently, the signals were analyzed by MATLAB wrapper to predict EEG

network features using the SPLICE model. According to a SPLICE module that was

selected in advance, the L2-norm of the module was estimated as a targeting EEG

network feature. It then displayed a feedback score depending on the task design. In

this process, the output of the selected modules was downsampled at 5 Hz.

In the NF training, we modified the training protocols used in previous studies of FCNef

(Yamada et al., 2017; Taylor et al., 2021) for EEG NF (see Figure 3C). We implicated

an intermittent design as the NF training inducing reinforcement learning. We obtained

a 5-min resting-state EEG recording and conducted five EEG NF sessions for all

participants. We collected 20 trials in each session. A single trial consisted of "rest" for

6 s, "induction" for 10 s, and "feedback" for 4 s. Feedback was calculated as a score (-1

to 1) presented as a circle on a monitor. For the NF group, the score was a difference

of the mean power of between "induction" and "rest" period with the logarithm scale in

eleven steps (resolution = 0.2; if the score was less than -1 or more than 1, the circle

size was minimum or maximum). For the sham group, the NF system randomly

generated a score between -1 and 1. Participants were asked to try to increase the disc

size as feedback on each trial by doing their best to "do something with their brain"

during the induction period. In the instructions, participants were provided with

examples such as performing mental calculations or recalling words to help imagine as

to how to manipulate their own brain signals, at the beginning of the training.

Participants did not receive specific, explicit strategies associated with the analysis of

feedback scores during the NF training.

We randomly divided the participants into two training groups (NF and sham); however,

we controlled the number of men and women in each group. Applying a two-sample t-

test, we found no significant differences in depressive symptoms (BDI-II: $p = 0.257$;

RRS: $p = 0.317$) between the two groups (Table 1). We compared scores from the

psychological questionnaires to evaluate the effects of NT training on depressive

symptoms using 2-way analysis of variance (ANOVA) for scores across time (pre/post)

and groups (NF/sham); we used t-test (function of 'anovan.m', and 'ttest2.m' in the

statistics toolbox of MATLAB) and effect size such as Cohen's d for analyzing

differences between pre-and post-scores (computeCohen_d.m;

https://www.mathworks.com/matlabcentral/fileexchange/62957-computecohen_d-x1-

x2-varargin). The sample sizes of the groups were small, so we assumed that it would

be difficult to detect statistically significant differences using a typical statistical test,

such as a t-test or ANOVA. To estimate a sufficient sample size, we calculated sample

sizes from Cohen's d in this comparison using G*Power 3.1.9.2 software (Faul et al.,

2007; https://www.psychologie.hhu.de/arbeitsgruppen/allgemeine-psychologie-und-

arbeitspsychologie/gpower.html). To evaluate participants' performances in the N-back

task, we calculated d' (d-prime), a variable which is used in signal detection analysis

(Palamedes toolbox in MATLAB; Prins and Kingdom, 2018).

488　　　　　　　　　　　　　　(Insert Table 1 here)

3. Results

3.1 Comparison of the mean log-likelihoods with ICA and SPLICE

We compare the mean log-likelihoods of the SPLICE model to the standard ICA

(FastICA in the first layer) with a leave-one-session-out cross validation using test data

set across all participants. We found significant improvement (the paired t-test, t-score

= 3.78, p = 0.0015; Supplementary Figure 7). We also obtained the mean log-

likelihoods of initial values of the SPLICE model and found significant improvement (the

paired t-test, t-score = 4.16, p = 6.5e-4). These results suggested that the SPLICE

model sufficiently represents the resting-state EEG data simultaneously recorded with

fMRI more than the conventional ICA.

3.2 Changes in feedback scores and psychological questionnaire scores

Figure 4 illustrates changes in depressive symptoms across time periods (pre- and

post-NF) and groups (NF, sham) in the left panels, and differences in pre- and post-NF

scores across the groups. Table2 summarizes statistical comparisons of BDI and RRS

scores. We found an interaction among the RRS reflection scores (time × group, F-

value = 2.99, p = 0.09) and a significant reduction (two-sample t-test, t-score = -2.16, p

= 0.048) in these scores for the NF groups compared to the sham group (Figure 4G).

Two-way ANOVA results showed that NF training did not significantly affect the

psychological questionnaire scores. We found large effect sizes in RRS scores (RRS: -

0.722, brooding: -0.626), but did not find sufficient effect sizes in the BDI scores (BDI:

0.184; cognitive depression: -0.390; somatic depression: 0.479). These results

suggested that the RRS reflection scores in the group with NF training were reduced;

however, these data do not imply an increase in the controllability of their EEG signals

of participants during the NF training.

517   (Insert Figure 4 and Table 2 here)

To identify changes in depressive symptoms depending on the type of regulation

(upregulation/downregulation) of brain activity, we compared changes in the scores for

each regulation type with changes in the scores in the sham group (Table 3). A large

effect size and a significant difference were observed in the RRS reflection scores

(Cohen's d = -1.429, t-score = -2.56, p = 0.025) of the upregulation type. Similarly, a

large effect size was found in the RRS scores (Cohen's d = -0.765, t-score = -1.37, p =

0.195) of the upregulation type. However, we did not find a significant correlation

between differences in the NF score and the RRS reflection score (Supplementary

Figure 3G). Additionally, the other scores did not show a significant relationship with the

NF scores. This suggests that our NF protocol may not have sufficiently effected

depressive symptoms.

531   (Insert Table 3 here)

3.3   Relationships   between   feedback   scores   and   depressive

symptoms/behavioral performance

To clarify the effect of training on depressive symptoms, we examined the feedback

scores for each group across days, as shown in Figure 5. At the end of the NF training,

six of the eight participants showed slightly increased feedback scores compared to the

scores from Day 1 and Day 3, but there was no significant difference. We did not find a

significant improvement in the NF score within the NF group and also did not find

noticeable differences in the feedback scores depending on the type of regulation of

brain activity (up/down). Moreover, regarding correlations between differences (post –

pre) in feedback scores and depressive symptoms, we examined the influence of the

feedback scores on changes in symptoms. However, we did not find any significant

differences (see Supplementary Figure 3) in the NF group. There were slight changes

in NF scores (though not significant), but there were no changes in depressive

symptoms. For this reason, the feedback scores did not reflect changes in depressive

symptoms.

To evaluate changes in cognitive function, we evaluated changes in the discriminability

index d', which represents the behavioral performance in the N-back task (0-, 1-, 2-,

and 3-back) at visit 4 (Day 1) and visit 7 (Day 4). We applied two-way ANOVA and two-

sample t-tests across all conditions of the N-back task (see Supplementary Figure 4

and Supplementary Table 4). We expected to find a negative correlation between

changes in feedback score and changes in d' under conditions with higher cognitive

load, such as 3-back. Differences in d' for the 3-back task showed a large effect size (-

0.730) in the sham group. We found significant effects in the group across all

conditions (0-back: 9.35, 1-back: 5.34, 2-back: 9.51, 3-back: 3.59; Supplementary

Figure 5). These results suggest that the performance baseline for the N-back task in

the sham group was significantly higher than that in the NF group. Therefore, we could

not capture the effects of the NF training on the cognitive function in this experiment.

Among other scores not directly related to depressive symptoms, we found large effect

sizes in AQ (total, attention switching) and OCI (total, obsessing) (Supplementary

Table1). In the NF group, we observed other effects such as an increase in STAI2 trait

(Cohen's d = 0.612) compared to the sham group, but not in STAI2 state (Cohen's d =

0.320). This may also be because the participants found it difficult to control their brain

activity to increase feedback scores during the training.

568   (Insert Figure 5 here)

570   **4. Discussion**

This study explored the application of the SPLICE model for EEG NF training, and

investigated the effectiveness of this technique in depressive symptoms (particularly

targeting rumination-related brain regions) in participants with subclinical depression.

With the exception of one participant, none of the participants were able to control their

training scores. In this section, we attempt to discuss the possible reasons behind the

lack of success in controlling depressive symptoms using our NF paradigm in this study.

We have categorized the section as follows: i) individual/environmental differences; ii)

controllability of EEG signals during NF training; and iii) experimental procedure and

the NF protocol design.

4.1 Individual/environmental differences affect SPLICE modeling

The analysis of the feedback scores suggested that the participants in the NF group

were not able to control their own brain activity. We conducted SPLICE analysis in

which the source signal was pooled and the temporally correlated networks

corresponding to deactivation in the DMN or activation in the ECN observed in the fMRI

signal at rest were extracted. Using GLM analysis, we selected a module that

correlated with brain activity during the working memory task associated with

modulation of the ECN. In this process, however, we realized that there were large

individual differences among participants with reference to the modules and their

correlated brain regions.

During the EEG-fMRI simultaneous recording (laying), the resting-state EEG data were

used to optimize the SPLICE model, and EEG-fMRI data (laying) simultaneously

recorded during the N-back task were used for module selection. Based on this, NF

training was conducted by exclusively applying the EEG signal that was recorded

outside the MRI scanner (sitting). Participants were asked to lie down inside the MRI

scanner for the EEG-fMRI recording, which helped reduce artifacts caused by

body/head movements. However, even slight movements by the participant caused

significant artifacts in the EEG signal because of the high magnetic field. Therefore, the

participants were asked to sit on a chair outside the scanner which caused less stress

than being inside the scanner. Our data processing procedure did not sufficiently

validate the robustness of the optimized model for different types of datasets such as

tasked EEG inside/outside the scanner. Before every recording, as part of a quality

check, we confirmed that the impedance of the EEG below was 10 kOhm. However, we

did not sufficiently quantify the preprocessed EEG data. To resolve these problems, in

future studies, the equivalence of the EEG signal quality should be evaluated by

methos such as power spectrum analysis and ICA-based noise reduction (manually or

machine-learning-based).

Another solution to minimize the data quality difference is the use of EEG/EEG-fMRI

simultaneous NF (Wang et al., 2019; Zotev et al., 2020; Cury et al., 2020). For example,

Wang et al. (2019) demonstrated proof of concept for the EEG NF protocol in patients

with comorbid major depressive disorder (MDD) and anxiety symptoms; they compared

three groups; frontal alpha asymmetry (ALAY group), high-beta downregulation training

(Beta group), and control. Eighty-seven patients completed ten sessions of NF training

twice a week, for five weeks. The ALAY and Beta groups showed a reduction of

approximately 10 points in the BDI scores and a decrease of the Beck Anxiety

Inventory (BAI) score by about eight points. Both psychological questionnaires showed

significant interactions compared to the control group. This intensive and long-term NF

training may be sufficient to induce significant effects on depressive symptoms. Zotev

et al. (2020) continuously displayed fMRI signals in the left amygdala and left rostral

anterior cingulate cortex (rACC), and frontal EEG asymmetries in the alpha and high-

beta bands simultaneously as feedback for patients with MDD. A significant

upregulation of the fMRI signal and frontal EEG asymmetries could enhance FC

between the left amygdala and left rACC. Finally, they demonstrated a significant

reduction in psychological measures such as the profile of mood state (POMS) and

STAI (state), and correlations between EEG asymmetry changes and depressive

symptoms. These NF trainings were performed in the same experimental environment

and focused directly on the target regions. Further studies need to incorporate

preprocessing ingenuity to reduce environmental differences, and to apply a sufficiently

robust model.

4.2 NF design for NF training

Our NF protocol consisted of intermittent feedback with implicit strategies as detailed in

fMRI NF studies based on reinforcement learning (Yamada et al., 2017; Taylor et al.,

2021). In this framework, participants were required to concentrate on controlling the

EEG signal for 10 s and then received feedback for 6 s. This paradigm is similar to that

of a cognitive task such as working memory task. Therefore, we estimated the module

from the tasked EEG data (n-back task); we assumed that our method could fit this

framework such as reinforcement learning. On the other hand, a continuous feedback

strategy seems be more suited for feedback-error learning, like motor control. In this

case, short-time feedback with quick online processing is essential, and EEG a more

suitable technique than fMRI (Zotev et al., 2020; Wang et al., 2019; Cury et al., 2020).

This will allow participants to quickly understand how they need to control their brain

time over time.

Additionally, previous studies have explicitly instructed participants on how to control

brain activity during training. An advantage of the explicit strategy is that it makes it

easy for the participants to imagine certain scenarios, such as positive autographical

memory (Zotev et al., 2020; Wang et al., 2019), and motor imagery (Cury et al., 2020),

and to monitor their own brain signals without a long delay. If the relationship between

brain activity and its related cognition/image is firmly defined, it may help participants

control their brain activity more easily during the NF. However, our protocol had a

mismatch, and involved activation-based feature extraction and intermittent NF. We did

not combine the advantages of both the above mentioned characteristics in the NF

training. In future studies, we aim to resolve these methodological compatibility issues.

We did not find a significant improvement in the feedback score within the NF group

with reference to the training effect (Figure 5). We examined the distributions of the

feedback scores across three days for each participant (Supplementary Figure 6). We

found that two participants did not exhibit positive scores during the NF training, five

participants showed negative scores in most of the trials, and one participant showed

scores spanning from the negative to positive. This suggests that we were not able to

choose the proper module for each participant individually; therefore, most participants

could not learn how to control their brain signals. In our study, only one participant

showed improved feedback scores. If we could have chosen the modules precisely for

each participant, all the participants would have been able to control their EEG signals

day after day with improved efficiency.

Another possible reason for lack of success of the methodology is the selection of the

frequency band. Based on previous studies (de Munck et al., 2007), we assumed that

the alpha band of EEG signals correlated mainly with fMRI data. However, we did not

find common changes in the time-frequency component, such as event-related

desynchronization/event-related synchronization, across the participants during the NF

training. Other frequency bands should also be examined in the optimization process to

identify the best model for each participant.

4.3 Limitations of this study

A major limitation of this study is that we could not recruit a sufficient number of
participants to evaluate our NF training protocol. We tested the NF training protocol in
healthy participants with subclinical depression who showed BDI scores of more than
three points, because our project aimed to focus on the maintenance of mental health
in daily life of healthy individuals. We could not recruit participants with severe MDD in
this study; therefore, the scores pertaining to depressive symptoms were lower than
those in previous patient studies (Wang et al., 2019; Young et al., 2017; Zotev et al.,
2020). Some participants had low scores from the beginning (Day 1) and did not show
enough improvement due to the NF training, possibly because of the floor effect. One
of the difficulties we faced was in recruiting appropriate participants; in actuality, we
recruited and screened about a hundred potential participants for subclinical
depression. Difficulties in recruiting the approximate population have been reported in
previous studies as well; Wang et al. (2019) showed a drop-off rate of about 5% in
MDD patients. To improve the sensitivity of pre-screening, the Self-rating Depression
Scale (SDS; Zung, 1965) questionnaire should also be used in addition to the BDI
questionnaire. We completed the NF training for 17 participants (a drop-off rate from
the Screening to EEG-fMRI experiment: 27%, and that from the EEG-fMRI to the NF
experiment: 64%). However, this reduction in sample size led to a reduction in
statistical power during the evaluation. According to the effect size (such as Cohen's d),
we estimated sufficient sample sizes ($p < 0.05$, two-sample t-test) for each group to be
as follows: BDI: 671 samples; BDI cognitive: 150 samples; BDI somatic: 100 samples;
RRS: 45 samples; RRS brooding: 60 samples; RRS reflection: 22 samples. Thus, the

sample number (NF: n = 8; sham: n = 9) was insufficient to support the evaluation of

the effects of NF training with solid statistical power at a high significance level. In

future studies, the procedure for participant recruitment should be improved.

From a systematic point of view, we considered noise reduction in the online process.

We applied online recursive ICA (ORICA; Hsu et al., 2016) that optimized the weights

of the independent components (ICs) with the real-time process and was practical to

remove artifacts such as blinking or eye movements. To select artifact ICs, we focused

on the time course of Fp1/Fp2, which was close to the eyes. With the time-window

approach, we automatically selected the IC that was most correlated with the EEG

signals of Fp1/Fp2. This method chose a proper IC when static EOG artifacts occur.

However, it did not work if there was no EOG artifact in Fp1/Fp2. In an on-going study,

we have improved EOG artifact removal.

We expected that functional regularization in the DMN or ECN might reduce depressive

symptoms, such as those represented in the BDI and RRS. We found a large effect on

RRS (total, brooding, and reflection) in the NF group compared to the sham group.

Additionally, in the subgroup analysis (based on activity upregulation and

downregulation), large effect sizes were observed in RRS total and reflection scores in

the subgroup that showed upregulation of DLPFC/MFG. In a previous study, ROI-

based fMRI NF training targeting the left DLPFC led to reductions in depressive

symptoms, as reflected in BDI, the 17-item Hamilton rating scale for depression

(HRSD), and RRS scores (Takamura et al., 2020). The authors applied fMRI NF for six

MDD patients for five days. This training was aimed at upregulating an fMRI signal

within the left DLPFC that was identified based on a functional localizer task such as

the N-back task. They found a significant correlation between RRS rumination score

changes and fMRI signal changes in the left DLPFC during the NF training. In this

study, we performed EEG-based NF training without measuring the fMRI signal

simultaneously; therefore, our results are not comparable to their results of this

previous study. Examining the fMRI signal during the EEG NF training, may thus help

identify the brain activity evoked by the training.

We attempted to develop an EEG NF method analogous to the fMRI NF method. In the

integration analysis of EEG-fMRI data, HRF-convoluted frequency powers were

calculated to match time instants between EEG and fMRI data, and then GLM was

applied to identify brain regions or networks (Mantini et al., 2007). Another approach

combines EEG-microstate analysis which categorized the data into four to six states

based on the clustering algorithm, and then identifies brain regions using correlation

analysis (Brechet et al., 2019; Al Zoubi et al., 2020). These methods may achieve

dimension reductions and describe the relationship between fMRI and EEG data. In

future studies, we plan to evaluate EEG-fMRI data in several categories pertaining to

different conditions to quantify the accuracy of the SPLICE model.

In summary, we proposed a new framework of EEG NF training focusing on EEG

network features combined with fMRI information such as the ECN and DMN. In the

three-day NF training, we found a significant reduction in depressive symptoms as

reflected by the RRS reflection scores; however, this reduction was not associated with

the feedback score during the NF training. Because of suboptimal module selection for

the NF training, the participants could not control their brain activity, and thus we did

not see significant improvement in their depressive symptoms. In future studies,

several points must be considered, such as changing of the NF protocol

(intermittent/continuous), type of instruction (explicit/implicit), frequency bands of EEG,

and artifact removal method.

References

Aihara, T., Shimokawa, T., Ogawa, T., Okada, Y., Ishikawa, A., Inoue et al. (2020).
Resting-state functional connectivity estimated with hierarchical Bayesian diffuse
optical tomography. Front. Neurosci, https://doi.org/10.3389/fnins.2020.00032.

Beck, A. T., Steer, R. A., Brown, G. K. (1996). Beck Depression Inventory-II (BDI-II) The
Psychological Corporation, Harcourt Brace; Toronto.

Cao, W., Liao, H., Cai, S., Peng, W., Liu, Z., Zheng, K. et al. (2021). Increased
functional interaction within frontoparietal network during working memory task in
major depressive disorder. Hum Brain Mapp, https://doi.org/10.1002/hbm.25611.

Cheon, E. J., Koo, B. H., Choi, J. H. (2016). The efficacy of neurofeedback in patients
with major depressive disorder: an open labeled prospective study. Appl
Psychophysiol Biofeedback, 41 (1), 103-10.

Cury, C., Maurel, P., Gribonval, R., Barillot, C. (2020). A sparse EEG-Informed fMRI
model for hybrid EEG-fMRI neurofeedback prediction. Front Neurosci, 13.
https://doi.org/10.3389/fnins.2019.01451.

Davidson, R., J., Ekman, P., Saron, C. D., Senulis, J. A., Friesen, W. V. (1990).
Approach-withdrawal and cerebral asymmetry: emotional expression and brain
physiology: I. J. Pers Soc Psychol, 58, 330-41. https://doi.org/10.1037/0022-
3514.58.2.330.

Delorme, A., Makeig, S. (2004). EEGLAB: an open-source toolbox for analysis of

single-trial EEG dynamics, J Neurosci Methods, 134, 9-21.
https://doi.org/10.1016/j.jneumeth.2003.10.009.

de Munck J. C., Gonçalves, S. I., Huijboom, L., Kuijer, J. P. A., Pouwels, P. J. W.,
Heethaar, R. M. et al. (2007). The hemodynamic response of the alpha rhythm: an
EEG/fMRI study. Neuroimage, 35 (3), 1142-51.
https://doi.org/10.1016/j.neuroimage.2007.01.022.

Drysdale, A.T., Grosenick, L., Downar, J., Dunlop, K., Mansouri, F., Meng, Y. et al.
(2017). Resting-state connectivity biomarkers define neurophysiological subtypes of
depression. Nat Med. 23, 28-38. https://doi.org/10.1038/nm.4246.

Faul, F., Erdfelder, E., Lang, A. G., Buchner, A. (2007). G*Power 3: A flexible statistical
power analysis program for the social, behavioral, and biomedical sciences. Behav
Res Methods. 39 (2), 175-91. https://doi.org/10.3758/bf03193146.

Hasegawa, A. (2013). Translation and initial validation of the Japanese version of the
Ruminative Responses Scale. Psychol. Rep. 112 (3), 716-26.
https://doi.org/10.2466/02.08.PR0.112.3.716-726.

Hirayama, J., Hyvärinen, A., Kawanabe, M. (2017). SPLICE: fully tractable hierarchical
extension of ICA with pooling. PMLR, 70, 1491-500.

Hsu, S. H., Mullen, T. R., Jung T. P., Cauwenberghs (2016). Real-Time Adaptive EEG
source separation using online recursive independent component analysis. IEEE
Trans on Neural Syst Rehabil Eng, 24(3), 309-19.
https://doi.org/10.1109/TNSRE.2015.2508759

Hyvärinen, A. (1999). Fast and robust fixed-point algorithms for independent
component analysis. IEEE Trans Neural Netw,10 (3), 626–34.

Hyvärinen, A. and Hoyer, P. O. (2000). Emergence of phase and shift invariant features
by decomposition of natural images into independent feature subspaces. Neural
Comput, 12 (7), 1705-20. https://doi.org/10.1162/089976600300015312.

Ichikawa, N., Lisi, G., Yahata, N., Okada, G., Takamura, M., Hashimoto, R., -I et al.

(2020). Primary functional brain connections associated with melancholic major
depressive disorder and modulation by antidepressants. Sci Rep. 10 (1), 3542, doi:
10.1038/s41598-020-60527-z.

Laird, A. R., Fox, P. M., Eickhoff, S. B., Turner, J. A., Kimberly, L. R., MacKay, D. R. et
al. (2011). Behavioral interpretations of intrinsic connectivity networks. J Cogn
Neurosci., 23 (12), 4022-37. http://doi.org/10.1162/jocn_a_00077.

Liu, Y., Zhong, M., Xi, C., Jin, X., Zhu, X., Yao, S et al. (2017). Event-related potentials
altered in patients with borderline personality disorder during working memory tasks.
Front in Behav Neurosci, 11, 67. https://doi.org/10.3389/fnbeh.2017.00067.

Mantini, D., Perrucci, M. G., Cugini, S., Ferretti, A., Romani, G. L., Del Gratta, C. (2007).
Complete artifact removal for EEG recorded during continuous fMRI using
independent component analysis. Neuroimage, 34 (2), 598-607.
https://doi.org/10.1016/j.neuroimage.2006.09.037.

Northoff, G. (2016). Spatiotemporal psychopathology I: no rest for the brain's resting
state activity in depression? Spatiotemporal psychopathology of depressive symptoms.
J Affect Disord. 190, 854-66. https://doi.org/10.1016/j.jad.2015.05.007.

Ogawa, T., Aihara, T., Shimokawa, T., Yamashita, O. (2018). Large-scale brain network
associated with creative insight: combined voxel-based morphometry and resting-
state functional connectivity analyses. Sci. Rep, 8, 6477.
https://doi.org/10.1038/s41598-018-24981-0.

Prins, N., Kingdom, F. A. A. (2018). Applying the model-comparison approach to test
specific research hypotheses in psychophysical research using the Palamedes
toolbox. Front Psychol, 9, 1250. https://doi.org/10.3389/fpsyg.2018.01250.

Renard, Y., Lotte, F., Gibert, G., Congedo, M., Maby, E., Delannoy, V. et al. (2010).
OpenViBE: an open-source software platform to design, test and use brain-computer
interfaces in real and virtual environments, Presence, 19(1), 35-53, Spielberger, C.D.
(1983). State-trait anxiety inventory for adults. Palo Alto, CA: Mind Garden.

Takamura, M., Okamoto, Y., Shibasaki, C., Yoshino, A., Okada, G., Ichikawa, N. et al.

(2020) Antidepressive effect of left dorsolateral prefrontal cortex neurofeedback in
patients with major depressive disorder: a preliminary report. J Affect Disord, 271,
224–27.

Taylor, J. E., Yamada, T., Kawashima, T., Kobayashi, Y., Yoshihara, Y., Miyata, J. et al.
(2021). Reduction of brooding and more general depressive symptoms after fMRI
neurofeedback targeting a melancholic functional-connectivity biomarker. medRxiv,
https://doi.org/10.1101/2021.01.21.20248810.

Treynor, W., Gonzalez, R., Nolen-Hoeksema, S. (2003). Rumination reconsidered: A
psychometric analysis. Cognit Ther Res, 27, 248-59.
https://doi.org/10.1023/A:1023910315561.

Tsuchimoto, S., Shibusawa, S., Mizuguchi, N., Kato, K., Ebata, H., Liu, M. et al. (2017).
Resting-state fluctuations of EEG sensorimotor rhythm reflect BOLD activities in the
pericentral areas: a simultaneous EEG-fMRI study. Front Hum Neurosci, 11, 356.
https://doi.org/10.3389/fnhum.2017.00356.

Tsuchiyagaito, A., Misaki, M., Al Zoubi, O., Tulsa 1000 Investigators, Paulus, M.,
Bodurka, J. (2021). Prevent breaking bad: A proof of concept study of rebalancing the
brain's rumination circuit with real-time fMRI functional connectivity neurofeedback,
Hum Brain Mapp, 42 (4), 922-40. https://doi.org/10.1002/hbm.25268.

Wang, S. Y., Lin, I. M., Fan, S. Y., Tsai, Y. C., Yen, C. F., Yeh, Y. C. et al. (2019). The
effects of alpha asymmetry and high-beta down-training neurofeedback for patients
with the major depressive disorder and anxiety symptoms. J Affect Disord 257 (6),
287–96. https://doi.org/10.1016/j.jad.2019.07.026.

Yamashita, A., Sakai, Y., Yamada, T., Yahata, N., Kunimatsu, A., Okada, N. et al. (2020).
Generalizable brain network markers of major depressive disorder across multiple
imaging sites. PLoS Biol, 18(12), e3000966.
https://doi.org/10.1371/journal.pbio.3000966.

Yamada, T., Hashimoto, R., Yahata, N., Ichikawa, N., Yoshihara, Y., Okamoto, Y. et al.
(2017) Resting-state functional connectivity-based biomarkers and functional MRI-
based neurofeedback for psychiatric disorders: a challenge for developing theranostic

biomarkers. Int. J. Neuropsychopharmacol. 20 (10), 769-81.
https://doi.org/10.1093/ijnp/pyx059.

Young, K.D., Siegle, G., J., Zotev, V., Phillips, R., Misaki, M., Yuan, H. et al. (2017).
Randomized clinical trial of real-time fMRI amygdala neurofeedback for major
depressive disorder: effects on symptoms and autobiographical memory recall. Am. J.
Psychiatry, 174 (8), 748-55. https://doi.org/10.1176/appi.ajp.2017.16060637.

Yu, S. H., Tseng, C. Y., Lin, W. L. (2020). A neurofeedback protocol for executive
function to reduce depression and rumination: a controlled study. Clin
Psychopharmacol Neurosci, 18 (3), 375-85. https://doi.org/10.9758/cpn.2020.18.3.375.

Zotev, V., Phillips, R., Yuan, H., Misaki, M., Bodurka, J. (2014). Self-regulation of
human brain activity using simultaneous real-time fMRI and EEG neurofeedback.
Neuroimage, 85 (3), 985-95. 10.1016/j.neuroimage.2013.04.126.

Zotev, V., Yuan, H., Misaki, M., Phillips, R., Young, K. D., Feldner, M. T. et al. (2016).
Correlation between amygdala BOLD activity and frontal EEG asymmetry during real-
time fMRI neurofeedback training in patients with depression. Neuroimage Clin, 11,
224-38.

Zotev, V., Mayeli, A., Misaki, M., Bodurka, J. (2020). Emotion self-regulation training in
major depressive disorder using simultaneous real-time fMRI and EEG neurofeedback.
Neuroimage. Clin 27, 102331. https://doi.org/10.1016/j.nicl.2020.102331.

Zung, W. W. (1965). A self-rating depression scale. Arch Gen Psychiatry, 12, 63-70.
https://doi.org/10.1001/archpsyc.1965.01720310065008.

Conflict of Interest

The authors declare that the research was conducted in the absence of any

commercial or financial relationships that could be construed as a potential conflict of

interest.

Author Contributions

Takeshi Ogawa and Hiroki Moriya designed the study. Takeshi Ogawa and Nobuo Hiroe performed data acquisition. Takeshi Ogawa and Jun-ichiro Hirayama analyzed the data. Takeshi Ogawa, Jun-ichiro Hirayama, and Motoaki Kawanabe performed data analysis and interpreted the results. Takeshi Ogawa and Jun-ichiro Hirayama wrote the original draft of this manuscript.

Funding

This study was supported by JSPS KAKENHI Grant Numbers JP17H06041, JP18H05395, JP18KK0284, JP21K12620, JP21K12055, JP21H03516, the ImPACT Program of the Council for Science, Technology, and Innovation (Cabinet Office, Government of Japan), CREST, JST, and the MIC/SCOPE/ #192107002.

Acknowledgments

We thank the following individuals for their contributions: Yoko Matsumoto for her help in recruiting participants, scheduling, and experimentation; Kana Inoue and Tachi Kaori for their help in screening participants during the Screening experiment; Mihoko Sato, Ayumi Yuki, and Yoshiko Itakura for their support in the preparation of the EEG-fMRI and NF training experiments; and Takashi Yamada for discussing the design the neurofeedback experiment. We would also like to thank the ATR Brain Activity Imaging Center (BAIC) team, and in particular, Akikazu Nishikido and Ichiro Fujimoto, for their technical support.

Data Availability Statement

The data that support the findings of this study are available from the corresponding author, Takeshi Ogawa, upon reasonable request.

Contribution to the Field Statement

Advanced treatments for depressive symptoms, such as real-time fMRI neurofeedback (NF), have been proven in several studies. Regularization of brain activity/functional connectivity (FC) between the executive control network (ECN) and the default mode network (DMN) during fMRI NF has been proposed to be effective in reducing depressive symptoms. However, it is difficult to install this system in practice because the cost is high, and no practical signal processing techniques have been developed to extract FC-related features from EEG. In this regard, stacked pooling and linear components estimation (SPLICE), recently proposed as a multilayer extension of independent component analysis and related independent subspace analysis, can be a promising alternative, although its application to resting-state EEG has never been investigated. This method may help modulate the target FC in EEG-based NF training. This study applied the SPLICE model in EEG NF training and explored its possible effectiveness in targeting depressive symptoms; rumination-related brain regions in participants with subclinical depression. We optimized the SPLICE model with simultaneous EEG-fMRI data to extract EEG network features such as a module correlated with fMRI signals in the DLPFC/MFG or in the PCC/precuneus by GLM analysis. As a result of the NF training using the extracted module, a large effect size and significant differences were found in the RRS reflection scores of the NF group.

However, no significant correlation was found between the training scores and

depressive symptoms, suggesting that this observation may not be a training-specific

effect. Other scores showed that RRS and RRS brooding scores had large effect sizes,

but no statistically significant improvement was seen when the NF group was

compared to the sham group. Therefore, our NF protocol was unsuccessful in

improving depressive symptoms and cognitive function.

Figure legends

Figure 1.

Figure1. Structure of stacked pooling and linear components estimation

(SPLICE).

s, unobserved source signal; **A**, mixing matrix; **W**, demixing matrix of **A**; **x**, EEG

measurements; **B**, invertible mixing matrix; **t**, source vector; F_j, link function; **V**,

demixing matrix of **B**.

Figure 2.

Figure2. Experimental workflow

(**A**) A schema of the experimental procedure (**B**) A summary of measurements made at

each visit (**C**) A diagram depicting the N-back task for the behavioral experiment at

visits 1, 4 and 7. (**D**) A diagram depicting the N-back task for electroencephalography

(EEG)/EEG-functional magnetic resonance imaging (fMRI) experiment at visits 2, 3,

and 7.

BDI-II: Beck Depression Inventory II; RRS: Rumination Response Scale; OCI:

Obsessive-Compulsive Inventory; AQ: Autism-Spectrum Quotient; STAI2: State-Trait

Anxiety Inventory, SHAPS: Snaith-Hamilton Pleasure Scale; SPQ: Schizotypal

Personality Questionnaire; BIS-11: Barratt Impulsiveness Scale 11; ZTPI: Zimbardo

Time Perspective Inventory; HAM-D: 21-item Hamilton Depression Rating Scale; HAM-

A: Hamilton Anxiety Rating Scale; SCID: Structured Clinical Interview for DSM-IV-TR

Axis disorders (SCID); NF: Neurofeedback.

Figure 3.

Figure3. A flowchart of preprocessing of the electroencephalography-functional

magnetic resonance imaging (EEG-fMRI) data and its integration analysis in this

study.

(**A**) A flowchart of preprocessing of the EEG and fMRI data for the optimization of the

stacked pooling and linear components estimation (SPLICE). (**B**) A flowchart of online

processing for the EEG neurofeedback (NF). (**C**) A diagram depicting the EEG NF

paradigm.

SPLICE, stacked pooling and linear components estimation; HRF, hemodynamic

response function; MNI, Montreal Neurological Institute; FWHM, full width at half

maximum; GLM, General Linear Model; BOLD, blood-oxygen-level-dependent; CSF,

cerebrospinal fluid; FWE, family-wise error.

Figure 4.

Figure4. Effects of neurofeedback (NF) training on the depressive symptoms in

the NF and sham groups.

(**A**) Left panel shows boxplots and scatterplots displaying changes of in the Beck

Depression Inventory II (BDI) score, and the right panel shows a violin plot displaying

the differences between pre-and post-NF across the groups. (**B-G**) Same as (A) for

BDI cognitive, BDI somatic, Rumination Response Scale (RRS), RRS brooding, RRS

depression, and RRS reflection. In boxplots in the left panel in (**A-G**), the vertical line

marks the median, 25th and 75th percentile, and cross presents outliers. In the violin

plots in the right panel in (**A-G**), the compact boxplot shows median (circle), 25th and

75th percentile (bold lines), and data points (bright blue painted circle). An asterisk

presents *p<0.05; two-sample t-test.

BDI: Beck Depression Inventory II; RRS: Rumination Response Scale; NF:

neurofeedback.

Figure 5.

Figure 5. Changes in feedback scores across the training days.

(**A**) Boxplots showing the distribution of the mean feedback scores across training days

for the neurofeedback (NF) group. Red lines with black painted triangles and blue lines

with white painted triangles represent each participant's mean feedback score in a day.

(**B**) Boxplots showing the distribution of the mean feedback scores across training days

for the sham group. Gray lines with white painted circles show the mean feedback

score in a day for each participant. The feedback scores were randomly generated;

therefore, the mean scores are distributed around 0. Bars in the boxplots present the

25th percentile, median, and 75th percentile. NF: neurofeedback.

1005

Tables

Table 1. The demographics of the participants who underwent neurofeedback (NF) training

Variables		NF group (n = 9)	Sham group (n = 9)	p-value of t-test
Age (years)		28.62 (10.84)	25.97 (7.22)	0.606
Gender	Women	2	2	
	Men	7	7	
BDI-II		7.89 (3.26)	10.44 (6.50)	0.257
RRS		40.67 (9.18)	35.44 (12.91)	0.317

NF: neurofeedback; BDI-II: Beck Depression Inventory II; RRS: Rumination Response Scale

1013 **Table 2. Comparison of statistical effect size associated with depressive**

1014 **symptom scores between the neurofeedback (NF) and sham groups**

Variables	NF group (n = 8)		Sham group (n = 9)		Two-way ANOVA {time, group}	Two-sample t-test (post-pre)	Cohen's d
	Pre	Post	Pre	Post	F-value (p-value)	t-score (p-value)	
BDI-II (total)	5.25 (5.52)	3.75 (4.43)	7.22 (7.72)	5.33 (6.34)	time: 0.70 (0.41) group: 0.63 (0.43) time x group: 0.01 (0.92)	0.38 (0.710)	0.184
-Cognitive depression	2.25 (3.37)	1.75 (2.76)	2.56 (3.47)	2.44 (3.05)	time: 0.21 (0.65) group: 0.08 (0.78) time x group: 0.03 (0.86)	-0.80 (0.434)	-0.390
-Somatic depression	3.00 (3.46)	2.00 (2.61)	4.67 (4.66)	2.89 (3.76)	time: 0.99 (0.33) group: 1.17 (0.29) time x group: 0.09 (0.76)	0.99 (0.340)	0.479
RRS (total)	31.00 (5.68)	28.25 (4.40)	31.33 (8.00)	31.67 (8.70)	time: 0.60 (0.44) group: 0.25 (0.62) time x group: 0.41 (0.53)	-1.49 (0.158)	-0.722
-Brooding	7.50 (5.68)	6.63 (1.92)	7.78 (2.11)	7.89 (2.93)	time: 0.94 (0.34) group: 0.23 (0.63) time x group: 0.39 (0.54)	-1.23 (0.220)	-0.626
-Depression	16.25 (2.96)	15.88 (2.95)	17.67 (5.48)	17.56 (5.00)	time: 1.08 (0.31) group: 0.03 (0.87) time x group: 0.01 (0.93)	-0.21 (0.837)	-0.101
-Reflection	7.25 (1.98)	5.75 (0.89)	5.89 (1.45)	6.22 (1.64)	time: 0.70 (0.41) group: 1.21 (0.28) time x group: 2.99 (0.09)	-2.16 (0.048)	-1.050

1015 NF, neurofeedback; ANOVA, analysis of variance; BDI-II, Beck Depression Inventory II;

1016 RRS, Rumination Response Scale

1017

 Table 3. Statistical comparison between the neurofeedback (NF) group (as

 per upregulation/downregulation) and the sham group.

Variables	NF group (upregulate, n = 5)		Two-sample t-test (post-pre)	Cohen's d	NF group (downregulate, n = 3)		Two-sample t-test (post-pre)	Cohen's d
	Pre	Post	t-score (p-value)		Pre	Post	t-score (p-value)	
BDI-II (total)	7.40 (5.98)	5.80 (4.49)	0.24 (0.815)	0.134	1.67 (2.08)	0.33 (0.58)	0.35 (0.736)	0.232
-Cognitive depression	3.40 (3.91)	2.60 (3.29)	-1.16 (0.270)	-0.645	0.33 (0.58)	0.33 (0.58)	0.16 (0.876)	0.106
-Somatic depression	4.00 (3.87)	3.20 (2.68)	1.14 (0.276)	0.636	1.33 (2.31)	0.00 (0.00)	0.38 (0.709)	0.256
RRS (total)	31.00 (6.78)	28.00 (5.52)	-1.37 (0.195)	-0.765	31.00 (4.58)	28.67 (2.52)	-0.78 (0.455)	-0.518
-Brooding	7.40 (2.61)	6.60 (2.07)	-0.95 (0.362)	-0.528	7.67 (1.16)	6.67 (2.01)	-0.92 (0.380)	-0.613
-Depression	16.40 (3.72)	16.20 (3.83)	-0.06 (0.954)	-0.033	16.00 (1.73)	15.33 (0.58)	-0.27 (0.791)	-0.182
-Reflection	7.20 (2.17)	5.20 (0.45)	-2.56 (0.025)	-1.429	7.33 (2.08)	6.67 (0.58)	-1.04 (0.321)	-0.696

 BDI: Beck Depression Inventory II; RRS: Rumination Response Scale; NF:
 neurofeedback