Novelty detection and multiple timescale integration drive *Drosophila* orientation dynamics in temporally diverse olfactory environments

Aarti Sehdev[1,2*], Viraaj Jayaram[,2,3*], Nirag Kadakia[1,2,4], Ethan Brown[1,2,5], and Thierry Emonet[1,2,3,6**]

[1]Department of Molecular, Cellular, and Developmental Biology, Yale University, New Haven, CT, USA
[2]Quantitative Biology Institute, Yale University, New Haven, CT, USA
[3]Department of Physics, Yale University, New Haven, CT, USA
[4]Swartz Foundation for Theoretical Neuroscience, Yale University, New Haven, CT, USA
[5]Yale College, Yale University, New Haven, CT, USA
[6]Interdepartmental Neuroscience Program, Yale University, New Haven, CT, USA

*Equal contribution
**Correspondence: thierry.emonet@yale.edu

ABSTRACT

To survive, insects must effectively navigate odors plumes to their source. In natural plumes, turbulent winds break up smooth odor regions into disconnected patches, so navigators encounter brief bursts of odor interrupted by bouts of clean air. The timing of these encounters plays a critical role in navigation, determining the direction, rate, and magnitude of insects' orientation and speed dynamics. Still, disambiguating the specific role of odor timing from other cues, such as spatial structure, is challenging due to natural correlations between plumes' temporal and spatial features. Here, we use optogenetics to isolate temporal features of odor signals, examining how the frequency and duration of odor encounters shape the navigational decisions of freely-walking *Drosophila*. We find that fly angular velocity depends on signal frequency and intermittency – fraction of time signal can be detected – but not directly on durations. Rather than switching strategies when signal statistics change, flies smoothly transition between signal regimes, by combining an odor offset response with a frequency-dependent novelty-like response. In the latter, flies are more likely to turn in response to each odor hit only when the hits are sparse. Finally, the upwind bias of individual turns relies on a filtering scheme with two distinct timescales, allowing rapid and sustained responses in a variety of signal statistics. A quantitative model incorporating these ingredients recapitulates fly orientation dynamics across a wide range of environments.

INTRODUCTION

Olfactory navigation is an incredibly challenging task, owing to the complexity and variability of natural odor scenes. The distribution of odors in nature depends sensitively on the physical properties of the environment, such as airflow and proximity to surfaces and boundaries, creating a diversity of signals varying in their spatial and temporal statistics (Baker et al., 2018; Connor et al., 2018; Reddy et al., 2022). Animals such as insects must extract relevant odor information from these complex landscapes, and use it to inform rapid behavioral decisions to progress toward the odor source.

In diffusion-dominating odor environments such as near food-laden surfaces, animals can locate odor sources by sampling concentration gradients temporally (Gepner et al., 2015; Gomez-Marin et al., 2011; Hernandez-Nunez et al., 2015; Schulze et al., 2015) and spatially (Borst and Heisenberg, 1982; Gaudry et al., 2013). In stronger airflows, further away from boundaries, and above rough terrain such as rocks or trees, complex airflows break up smooth odor regions into discrete packets and filaments swept along by the wind (Cardé and Willis, 2008; Celani et al.,

2014; Connor et al., 2018; Crimaldi and Koseff, 2001; Murlis et al., 1992; Murlis et al., 2000; Riffell
et al., 2008; Yee et al., 1993). As a result, animals experience discrete encounters with odor
packets separated by blanks (moments when odor concentration is below detection threshold).
The durations of these encounters can span a wide range of timescales (Celani et al., 2014).
Under such conditions, insects navigate by orienting upwind within the odor and moving
crosswind or downwind when the odor is lost, in an attempt to regain the plume (Kennedy and
Marsh, 1974). Similar behaviors (with some variations between species) are observed in
laboratory experiments where walking and flying moths (Baker and Haynes, 1989; Baker and
Vickers, 1997; Cardé and Willis, 2008; Haynes and Baker, 1989; Kanzaki et al., 1992; Kennedy
and Marsh, 1974; Mafra-Neto and Cardé, 1994; Vickers and Baker, 1994) and fruit flies (Alvarez-
Salvado et al., 2018; Budick and Dickinson, 2006; Demir et al., 2020; van Breugel and Dickinson,
2014) are made to navigate straight odor ribbons. We recently discovered that flies can also detect
the direction of motion of odor signals, by resolving inter-antennal concentrations differences over
time. Odor motion provides a directional cue complementary to the wind, and is especially useful
in turbulent plume navigation (Kadakia et al., accepted). In sum, despite variations between
species and locomotive regimes, the general picture of insect odor navigation is that the wind
(along with recently-discovered odor motion) indicate the *direction* in which to reorient, while the
timing of odor encounters indicate *when* to reorient.
70
Careful analyses of moth turning responses following odor encounters have implicated the
frequency of odor encounters as a key driver of upwind progress (Kanzaki et al., 1992; Mafra-
Neto and Cardé, 1994; Vickers and Baker, 1994). Frequency-driven turning is also observed in
walking flies navigating complex odor plumes when odor encounters are brief (~100 ms) and
frequent (Demir et al., 2020). Conversely, flies experiencing longer and sparser odor encounters
progress upwind by integrating the odor concentration over time – thus responding to odor
intermittency or duration (Alvarez-Salvado et al., 2018; Bell and Wilson, 2016; Steck et al., 2012),
rather than encounter onset time or frequency. Thus, insects are clearly able to sense and process
various temporal features of the odor signal during plume navigation; moreover, this broad and
versatile sensing capability has been shown theoretically to enable efficient source localization
across a diversity of plume structures (Boie et al., 2018; Jayaram et al., 2022; Rigolli et al., 2022).
Still, how these multiple features are precisely weighted within a single navigation strategy, and
whether the strategy itself modulates as signal statistics change, remains unclear.
84
In this study, we address these questions using an optogenetic assay developed in previous
studies (Demir et al., 2020; Kadakia et al., accepted). We present spatially uniform but temporally-
structured fictive odor stimuli to freely-walking blind *Drosophila melanogaster* in a steady laminar
flow. In addition to decoupling odor signal from wind, the spatially uniform stimulus removes both
the effect of behavioral feedback on the received odor signal, and any bilateral differences
between antennae in timing or intensity from the odor encounters (Borst and Heisenberg, 1982;
Gaudry et al., 2013; Kadakia et al., accepted). Thus, flies must navigate using the temporal
features of the odor signals and the fixed wind direction alone.
93
Our main findings are the following. i) Fly angular velocity is controlled by the frequency and
intermittency of odor encounters, but not their duration. ii) Flies demonstrated "novelty detection"
in turn rate and turn speed: they responded more strongly to signal onset when the prior period
without stimulus was longer than ~2 seconds. As in previous studies (Alvarez-Salvado et al.,
2018) we also observed an "offset response" in turning behavior, which peaks both at the end of
a long odor encounter or a block of many encounters at high frequency or high intermittency.
Importantly these two features combine to smoothly transition the behavioral response of the flies
between low and high frequency regimes. iii) The upwind bias of turns (likelihood to orient upwind
when turning) was independently modulated by frequency and intermittency of the signal. This

dependency resulted from a rapid increase in upwind bias at the onset of odor pulses, followed
by a slower decay at the offset, and allowed for strong upwind responses across a wide range of
temporally diverse odor environments. We incorporated these findings into a model combining
novelty and offset responses together with a two-timescale integrator. This versatile but
parsimonious model could recapitulate turn rate, turn speed, and upwind bias across the full
spectrum of temporally diverse environments, thus unifying results from previous studies into one
framework (Alvarez-Salvado et al., 2018; Demir et al., 2020; Jayaram et al., 2022).

RESULTS

An optogenetic setup to examine the olfactory response of free-walking flies to the
temporal features of odor signals

To investigate how fly navigation decisions depend directly on the temporal features of odor
signals, we created an optogenetic stimulus (henceforth referred to as a 'fictive' plume) that had
only a temporal component yet drove clear navigational responses. Using the wind tunnel walking
assay previously described (Demir et al., 2020) (**Figure 1A**), we presented a temporally variable
but spatially uniform optogenetic odor stimulus (**Figure 1B**) to freely-walking blind flies that
expressed *Chrimson* in their olfactory sensory neurons (OSNs) (*w;+;Orco-GAL4, w;gmr-hid;UAS-*
20XChrimson), from here referred to as *Orco>Chr* mutants. The stimulus was presented in a 15s
ON block, where the entire arena was illuminated with a uniform red light stimulus (same intensity
as in (Kadakia et al., accepted)) and flashed regularly at a frequency of 2 Hz and duration of 0.05s
(consistent with naturalistic complex plumes (Demir et al., 2020; Kadakia et al., accepted)),
followed by a 15s OFF block with no stimulus. A steady unidirectional laminar wind was used as
a directional cue for flies to follow. Wind speed was 150 mm/s, matching the wind speed in (Demir
et al., 2020).

In our previous study – which used an identical behavioral setup and genotype – we showed that
optogenetically-active flies navigated straight ribbons and complex plumes similarly to real odors
(Kadakia et al., accepted). Moreover, light-driven ORN firing responses were well-maintained
within their expected physiological range (Kadakia et al., accepted). Here, to further confirm that
our optogenetic stimulus drove responses similar to wildtype flies encountering a real odor plume,
we examined fly orientation during stimulus presentation. We compared to previous studies in
which wildtype *Canton-S* (CS) flies navigated two real odors: ethyl acetate (EA) and smoke (Demir
et al., 2020). Indeed, flies responding to the optogenetic stimulus showed qualitatively similar
navigational trends as flies experiencing real odor plumes, directing their orientation upwind (i.e.
towards the fictive odor source) to a very similar degree (**Figure 1C**).

To confirm that *Orco>Chr* mutants were orienting upwind due to the fictive plume stimuli and not
some other confounding factor, such as ambient lighting in the experimental arena, we obtained
the mean orientation of all trajectories during the ON block (3-12 s) for each environment (CS in
EA, CS in smoke, *Orco>Chr* in fictive plume), along with the parental controls of the

Figure 1: Optogenetic stimulation with high frequency fictive odor pulses drives similar navigation behaviors as real odor plumes. A. Top and side view of the fly walking assay. Red light (same intensity as in (Kadakia et al., accepted)) is projected from above as fictive odor stimuli, uniformly illuminating the entire arena with high temporal (< 6 ms) precision. Wind speed is 150 mm/s like in (Demir et al., 2020). **B.** Four sequential ON and OFF blocks are presented to flies (15 s per block). During the ON block, flashes of red light are presented with a given duration and frequency. No flashes are presented during the OFF block. **C.** Orientation of flies during the ON and OFF block, for odor plumes of ethyl acetate (EA; left column, orange) and smoke (middle column, blue) with turbulent wind (data from Demir et al. 2020) and fictive odor plume presentation at 2 Hz, 0.1 s (right column, red) with laminar wind. Black: mean response over all trajectories. Grey shade indicates SEM. Only walking flies (ground speed > 2 mm/s) were included. Canton-S flies were used for both smoke (114-282 trajectories per frame) and EA (243-582 trajectories per frame) plume presentation. *w;gmr-hid/+;Orco-GAL4/UAS-20XChrimson* mutants (60-99 trajectories per frame) were used for fictive odor plume presentation. We reflected flies orientation greater than 180° orientations were always between 0° (directly downwind) and 180° (directly upwind). Thus, a uniform spread of orientations results in an average orientation of 90°. **D.** Mean orientation response across all trajectories during 3-12 s of ON block. EA: Canton-S flies in turbulent ethyl acetate plume; Smoke: Canton-S flies in turbulent smoke plume. Orco>Chr: *w; gmr-hid/+; Orco-GAL4/UAS-20XChrimson* in fictive plume. NO ATR: *Orco>Chr* mutant without feeding all-trans retinal, in fictive plume. GAL4 parent: *w;+;Orco-Gal4*, in fictive plume. UAS parent: *w;gmr-hid;UAS-Chrimson*, in fictive plume.. Ns are 918, 412, 144, 272, 126 and 114 trajectories respectively. **E.** Full range of optogenetic stimuli presented, varying in encounter frequency (0.2, 0.5, 1.0, 1.5, 1.75, 2, 2.5, 3, 4, 5 Hz) and encounter duration (0.02, 0.05, 0.10, 0.25, 0.50, 1.00 s). Combinations of duration and frequency that created indeterminable flashes (i.e. intermittency >= 1) were excluded.

optogenetically active line (*w;+;Orco-GAL4, w;gmr-hid;20XUAS-Chrimson*). *Orco>Chr* mutant
responses were additionally measured in the absence of all-trans-retinal (ATR). We compared
the mean orientation in these environments to the mean of uniformly distributed headings (which

due to the way we reflect orientations results in a mean of 90°-see **Figure 1** caption) in both
laminar and turbulent wind environments (**Figure 1-Figure Supplement 1**). During the ON block,
both CS flies in EA or smoke and *Orco>Chr* mutants in the fictive plume oriented more upwind
than crosswind (one-sample t-test, EA: 115.7°±1.4°, pval < 1e^{-6}, Smoke: 130.6°±1.7°, pval < 1e^{-6}
Orco>Chr: 119.9°±2.9°, pval < 1e^{-6}) (**Figure 1D**). In comparison, the orientation of both the UAS-
parental control line and the *Orco>Chr* mutant line without ATR did not differ from uniform
orientation (*UAS*: 92.4°±3.5°, pval = 0.491, NO ATR: 92.2°±2.4°, pval = 0.343), (**Figure 1D, grey,**
Figure Supplement 2). Interestingly, the GAL4-parental control line oriented more downwind
than expected (79.1°±2.9°, pval = 0.0002), which we attributed to a mild influence of background
visual stimuli, since this parent was not blind.

The similarity in gross behaviors between wildtype flies navigating real odors and optogenetically
stimulated flies navigating fictive odors indicate that spatially uniform, dynamic optogenetic stimuli
can drive upwind naturalistic plume navigation. This is consistent with previous results that used
real odors (Alvarez-Salvado et al., 2018), though an added benefit here is that bilateral information
is entirely removed by using full-field optogenetic flashes. Temporal signal variation alone is
enough to drive persistent upwind navigation, emphasizing the importance of temporal stimuli
features in the absence of spatially-variable concentrations or local gradients.

Upwind heading correlates with signal frequency and intermittency, but not duration

Next, we asked how frequency, duration and intermittency modulate upwind heading. We
generated 45 fictive odor environments with pulse durations between 0.02s and 1s, and pulse
frequency between 0.2 Hz and 5 Hz (**Figure 1E**). Intermittency – the fraction of time signal is
present – is equal to frequency multiplied by duration (Jayaram et al., 2022), and varied between
0.004 and 0.875 (intermittency is bounded between 0 (signal is never present) and 1 (signal is
always present)). Combinations that produced indeterminable encounters (i.e. intermittency ≥ 1)
were excluded.

Average upwind heading exhibited common trends across environments (**Figure 2A**). At ON
block onset, flies oriented toward the upwind direction (180°) when the odor was present, and
went downwind at odor offset, similar to behavior in real odor plumes (see **Figure 1**). For low
frequencies, where there was sufficient time between encounter onsets to distinguish individual
encounter responses (i.e. 0.2Hz, 0.5Hz), flies oriented upwind at each encounter onset,
maintained their upwind orientation for the duration of the encounter, then oriented downwind at
the end of the encounter. Beyond 1Hz, individual encounter responses were largely
indistinguishable, but we observed that flies drove their orientation upwind for the duration of the
ON block, and turned downwind at ON block offset. For low frequencies, average upwind
orientation increased with duration, but this effect tapered beyond ~1Hz. Meanwhile, for a given
pulse duration, mean orientation increased with frequency up to around 3Hz, before decreasing
at very high frequencies. This aligns with previous studies that have shown that olfactory receptor
neurons can respond to high frequencies (Fox and Nagel, 2021).

To quantify how the frequency, duration, and intermittency of odor encounters influence upwind
bias, we calculated the instantaneous angular velocity as a function of orientation at each time
point during the ON block (Materials and Methods) (**Figure 2B**). Here, angular velocity was signed
such that upwind turns were positive and downwind turns were negative. Average angular velocity
was nearly zero when flies were oriented upwind or downwind, but became increasingly positive
with signal frequency for those oriented crosswind, up to around 3 Hz. Similar trends were found
with intermittency, but not duration (**Figure 2, Figure Supplement 1A-1B**). Since these trends
were most apparent when flies were oriented crosswind (grey region in **Figure 2B**), we pooled

Figure 2: Flies use the frequency and intermittency of odor signals to navigate upwind across temporally diverse fictive odor environments. A. Population mean orientation response across 45 fictive odor environments. Each environment projected stimuli with a fixed duration and frequency. Each row represents a different tested frequency: 0.2 Hz, 0.5 Hz, 1 Hz, 1.5 Hz, 1.75 Hz, 2 Hz, 2.5 Hz, 3 Hz, 4 Hz and 5 Hz, from top to bottom. Each column represents a different duration: 0.02 s, 0.05 s, 0.1 s, 0.25 s, 0.5 s and 1 s from left to right. Red bars denote the signal simultaneously encountered by all flies within an experiment (Materials and Methods). Upwind is 180°, downwind is 0°. Grey-blue dashed line: crosswind direction (90°). Black: Population mean orientation; orientation was flipped over 180° as before. Grey shading: SEM for each time point (recording rate = 60 Hz). Between 176 and 407 trajectories were recorded per environment. Between 72 and 237 trajectories were recorded per time point across all environments. **B.** Instantaneous angular velocity of flies as a function of their orientation during the ON block (0-15 s). Upwind is at 180°, downwind at 0°. Orientation was split into 8 bins with width 22.5°. Vertical dashed line indicates crosswind orientation 90°. Positive (negative) angular velocities correspond to upwind (downwind) turning. Black horizontal line at 0 °/s indicates no change in orientation. Color indicates environment frequency; yellow: low frequencies (0.2 Hz, 0.5 Hz), orange: medium frequencies (1 Hz, 1.5 Hz, 1.75 Hz, 2 Hz, 2.5 Hz, 3 Hz), red: high frequencies (4 Hz, 5 Hz). **C.** Mean angular velocity of individual flies oriented within the crosswind range (90°± 22.5°; grey shading in **B**) over duration of ON block (0-15 s) as a function of environment frequency (left), duration (middle) and intermittency (right). Each point represents a different environment with defined frequency and duration. Error bars: SEM for that environment. Dotted grey line represents no mean change in orientation. ρ value is the Pearson's correlation coefficient between mean angular velocity and the temporal feature (frequency, duration, intermittency), obtained from linear least-squares regression. Correlations with environment frequency and intermittency were significantly different from 0 (frequency: ρ=0.63, p < 0.001; intermittency: ρ=0.55, p < 0.001). Correlation with duration was not significantly different from 0 (ρ=0.07, p = 0.633).

the angular velocities over all instances in which flies were oriented within a 45° sector around
the crosswind (90°) direction, and calculated correlations with signal frequency, duration, or
intermittency (**Figure 2C**). We found a significant positive correlation between angular velocity
and either frequency (Pearson's correlation coefficient, R=0.59, *p<0.001*) or intermittency
(R=0.55, *p<0.001*), but not duration (R=0.10, *p=0.496*). This result indicated that flies use odor
frequency and intermittency to drive upwind motion, prompting us to examine behavioral models
that respond to these particular signal features.

Turn dynamics exhibit novelty-response and offset-response

Fly orientation results from the cumulative effect of individual turns. To understand how temporal
features of the odor signal drive turn dynamics, we first explored how the average angular speed
(the magnitude of the angular velocity) was modulated during the signal block across
environments (**Figure 3A**). For clarity, we focus on four example odor environments chosen from
the 45 environments shown in **Figure 2.** We chose these 4 cases to illustrate the different signal
and response regimes present in the full dataset (**Figure 3 Figure Supplement 1**).

In low frequency and intermittency environments (e.g. 0.2Hz, 1s), where responses to individual
odor encounters could be clearly resolved, the angular speed was dynamic and peaked at each
encounter onset (**Figure 3A, Figure 3 Figure Supplement 1**). For higher frequency
environments >~1.5 Hz, angular speed peaked sharply only at the onset of the ON block, rather
than at each individual encounter. It quickly dropped towards the pre-stimulus baseline and
remained roughly steady for the remainder of the ON block. We first wondered whether this was
because in higher frequency environments, flies had maintained their upwind orientation upon
receiving new pulses and hence did not need to reorient upwind. However, we found that in higher
frequency environments, even flies facing crosswind or downwind at the onset of later pulses did
not show large changes in mean angular speed (**Figure 3, Figure Supplement 2).**This suggests
a type of "novelty response", where angular speed will spike at the onset of a new encounter
provided the previous odor encounter was in the sufficiently distant past. In high intermittency
environments e.g. 3 Hz, 0.25 s, we observed a second large, sharp peak in angular speed at the
end of the ON block, which was also seen at the end of individual, long duration encounters (e.g.

0.2Hz, 1s) similar to previous observations (Alvarez-Salvado et al., 2018). These data suggest
that turn dynamics exhibit novelty detection and offset-response, and that they are modulated by
both odor frequency and intermittency. While odor offset responses have been seen and
quantified before (Alvarez-Salvado et al., 2018), the "novelty response" following an unexpected
odor encounter has not yet been characterized, though it is also observable in previous studies
(see fig 1F, 2A in (Alvarez-Salvado et al., 2018)).
238

Figure 3: Flies change orientation in discrete turn events modulated by the signal. A. Population mean
angular speed during stimulus presentation for four conditions – 0.2 Hz, 1 s (left), 0.5 Hz, 0.25 s, (middle-left),
1.5Hz, 0.1s (middle right) and 3 Hz, 0.25 s (right) – obtained from the instantaneous absolute angular velocity of
tracked flies (Materials and Methods). Black line: population mean at each time point. Grey shading: SEM at each
time point. Red bars: stimulus. 0.2 Hz, 1 s, n=93-154 trajectories per time point. 0.5Hz, 1s, n=86-130 trajectories.
1.5Hz, 0.1s, n=72-120 trajectories. 3 Hz, 0.25 s, n=105-181 trajectories. **B.** Definition of turn and fixation events.
Black: angular speed of an individual fly. Turns must have a minimum angular speed of 25 deg/s (green dotted line;
see **Figure 3, Supplement 2A, 2B**) and a minimum duration of 0.18 s (see **Figure 3, Supplement 2C, 2D**). **C.**
Distribution of fixation durations across all 45 frequency-duration experiments at different times during the
experiment. Fixation durations are roughly exponentially distributed with a rate (slope) that depends on signal timing
(see **Figure 3**, **Supplement 3**). Orange: turn rate during ON block onset (0-0.4 s). Pink: turn rate at OFF block
onset (from t_{last} to $t_{last}+0.5$ s) where t_{last} is the time at the end of the last stimulus of a ON block. Purple: baseline
turn rate during OFF block (20-25 s). Lines are PDFs. Light shade indicates standard error estimated using
bootstrapping (repeats = 1000). **D.** Same as **C** but for the distribution of turn durations. Turn duration distributions
do not vary much over time **E.** Distribution of mean angular speed during turns across all 45 frequency-duration
experiments at different times. Colors and shading are the same as in **C**. The shifting mean indicates that turns are
faster during ON block onset and offset as compared to the baseline turn speed when no stimulus is present.

To unravel the decisions underlying these angular speed dynamics, we turned from population
averages to individual trajectories. At the level of individual trajectories, changes in angular speed
exhibited large, discrete jumps (**Figure 3B**), that occurred both during ON and OFF blocks across
all odor environments. Angular speed also underwent small fluctuations that we posited to occur
from the fly's walking gait (DeAngelis et al., 2019) and measurement noise. Following previous
work (Cruz et al., 2021; Dan et al., 2021; Demir et al., 2020), we attributed the large angular
changes to turn events, i.e. intentional, large-scale reorientations that align the navigator's

heading to the direction of interest. We defined turn events by setting a threshold on angular speed. Events above threshold were called "turns", those below threshold were called "fixations". The threshold (25 deg/s) was chosen to remove small fluctuations that contribute little to the overall change in heading, but keep large angular changes that drive navigation behaviors. We also set a minimum turn duration of 0.18s to remove very short fluctuations in angular speed that were potentially artefacts of the tracking (**Figure 3 - Figure Supplement 3** and **Materials and Methods**).

Having defined turn and fixation events, we examined how the rate, duration, and angular speed of these discrete events, which modulate total angular speed, are influenced by signal statistics. To obtain the turn rate, we note that >95 % of fixation events (times between turns) lasted less than 1.5 s (**Figure 3, Figure Supplement 4A,4B**), and within this range, the distribution of fixation events appeared approximately exponential (**Figure 3, Figure Supplement 4C**), suggesting that turn events obeyed a Poisson process. The slope of the distribution, i.e. the turn rate, changed with time (**Figure 3C**). It was high at the onset (4.92 ± 0.18 turns/s) and offset (4.18 ± 0.09 turns/s) of ON blocks, but lower (3.19 ± 0.02 turns/s) during OFF blocks. Turn durations also appeared exponentially distributed, but with a rate that varied less over time (**Figure 3D**). Finally, the mean turn speed exhibited a unimodal distribution that resembled a Gamma distribution with mean that strongly depended on the signal (**Figure 3E**): higher at the onset and offset of the ON block, and lower otherwise. Together, this suggested that angular speed dynamics depended more on changes in turn rate and turn speed than on temporal variations in turn duration.

To get a qualitative understanding of how turn rate and speed depend on the signal, we plotted them as a function of time (**Figure 4A**). We observed a similar novelty response and offset responses as we observed for angular speed (**Figure 3A**): turn rate and turn speed spiked at each pulse onset, however for the higher frequencies the responses were stronger at the onset of the ON block than for the subsequent odor encounters. At high intermittencies there was also an off-response at the offset of the ON block (**Figure 4A** grey, **Figure 4 Figure Supplement 1**, **2** grey). We conclude that turn dynamics are mainly controlled by signal-driven modulations of the turn rate and turn speed, which exhibit both a novelty-response and offset-response.

To model turn rate and turn speed at signal offset, we defined an intermittency-dependent offset response *OFF(t)* analogous to the OFF response reported by (Alvarez-Salvado et al., 2018), who used real odors to stimulate flies in a setup similar to ours. The *OFF(t)* function computes the difference between two integrative filters which decay at different timescales, one long and one short, producing a transient spike after long duration encounters or higher intermittency signals (**Figure 4B**) (Materials and Methods). This makes it a good candidate for modeling the observed offset behavior in turn rate and angular speed.

For the frequency-dependent novelty detection, we defined the function *N(t)* that would spike at pulse onsets and then decay until the next pulse onset. The height of a spike increases with the time since the last pulse onset (i.e. when a pulse has more "novelty" to it):

$$N(t) = A(t)\, e^{-\frac{t-t_L}{\tau_d}}\,, \tag{1}$$

where t_L is the time of the latest pulse onset, and τ_d is the decay timescale of the response to individual odor pulse. $A(t)$ controls the height of the response to each pulse. It is maximal (= 1) for the initial odor encounter but decays for successive encounters that occur within a novelty timescale τ_N (see Materials and Methods). Odor encounters that occur after a time τ_N are treated as novel signals and elicit maximal response again (**Figure 4B**).

Figure 4: Novelty detection and offset response together can predict turn rate, angular speed given turning, and angular speed dynamics. A. Population mean turn rate (top) and mean turn speed (bottom) from four of the 45 odor environments: 0.2 Hz 1 s, 0.5 Hz 0.25 s, 1.5 Hz 0.1s s, 3 Hz 0.25 s. Grey shading: mean ± SEM. We used a 0.25s sliding window shifted by 1 frame (0.016s) to obtain turn rate and turn speed (see Materials and Methods). Pink line: mean predicted turn rate over time ($\lambda(t)$, top) and mean predicted turn speed over time (bottom). Parameters of equations (1-3) were estimated using Maximum Likelihood Estimation (Materials and Methods). Pink shading: standard deviation obtained from repeated simulation of model prediction (Materials and Methods and Figure 4 Figure Supplement 1 caption). Red bars: fictive odor pulses. We had 8-103 turns per frame across all 45 odor environments. **B.** Model of turn dynamics. Flies initiate discrete turn events (green) with a defined mean turn speed. Turn initiations are modelled as an inhomogeneous Poisson process with rate $\lambda(t)$ calculated as a linear combination of a baseline turn rate, a novelty detector (N(t), blue), and an offset detector (Off(t), yellow) (Equation 2). Mean turn speed was modelled similarly (Equation 3). Fits and their errors are shown in pink in **A**. **C.** Grey: Mean angular speed of the flies. Grey shade: mean ± SEM. Pink: model prediction for the mean, pink shade: mean ± SEM.

Given these two response functions, $OFF(t)$ and $N(t)$, we attempted to capture the dynamics of both the turn rate and turn speed by simple linear combination. We modeled the turn rate $\lambda(t)$ as

$$\lambda(t) = \lambda_0 + \lambda_1 N(t) + \lambda_2 OFF(t) \tag{2}$$

318 and the mean turn speed $\mu(t)$ as

$$\mu(t) = \mu_0 + \mu_1 N(t) + \mu_2 OFF(t), \tag{3}$$

where λ_i and μ_i for $i = 0, 1, 2$ are constant parameters. We note that turn duration was weakly modulated by the signal statistics (**Figure 4, Figure Supplement 3**), but the modulation was much smaller compared to modulations in turn rate and turn speed. Thus, for simplicity, we treated turn duration as exponentially-distributed with fixed parameters determined from data (**Figure 3D**). We first estimated the parameters for $\lambda(t)$ using maximum likelihood estimation (see Materials and Methods), carrying out the estimation by pooling data from all 45 stimulus environments. This fixed λ_0, λ_1, and λ_2, as well as the timescales involved in the $N(t)$ and $OFF(t)$ responses (Materials and Methods, Table 1). Then, holding the timescales fixed, we estimated the μ coefficients, again fitting to the data pooled from all 45 environments (Materials and Methods, Table 1)**.** Our model captured both turn rate and turn magnitude well, albeit slightly underestimating both at lower frequencies (**Figure 4A**, pink, **Figure 4 Figure Supplements 1,2** pink).

Up to this point, our model captures how the stimulus modulates the rate and magnitude of discrete turn events. These two aspects, along with turn duration, which we held fixed, should predict angular speed across environments with diverse signal frequency and intermittency. To test this, we simulated virtual agents enacting our dynamic model. Agents executed turns via an inhomogeneous Poisson process following Equation 2. The mean angular speed of each turn was sampled from a Gamma distribution with signal-dependent mean (Equation 3 and Materials and Methods). The turn duration was sampled from a fixed exponential distribution (Materials and Methods). In our dataset there are at most 240 fly trajectories at any given time. Therefore, we simulated 240 agents in each of the 45 environments to get a population-averaged trace, and then repeated this process 10,000 to get an estimate of the model-predicted mean and error. To quantify model accuracy, we calculated the ratio of the root-mean-square error of the model fit to the data standard deviation (NR score) across all environments (Geffen et al., 2009; Martelli et al., 2013). An NR score of <1 indicates a model prediction within the noise of the data. The NR score across all 45 environments was 0.16, indicating that the model recapitulates the dynamics of the fly angular speed well across experiments, albeit with some underestimation at the lowest frequencies (**Figure 4C**; predictions for all 45 environments are shown in **Figure 6A** below**).**

The model reproduces two important aspects of the turning dynamics and its dependency on signal frequency and intermittency: a varying turn rate at the onset and offset of longer odor encounters, and a roughly constant turn rate when the frequency of encounters is high (after the initial spike), both of which have been observed experimentally in separate paradigms investigating these distinct odor environments (Alvarez-Salvado et al., 2018; Demir et al., 2020).

Upwind bias responds to odor signal with two timescales: a fast rise time and a slow decay

Up until now, we are able to describe fly angular speed dynamics well, through a dynamic turn rate and turn speed. In order to describe fly orientation, we must also understand the direction of these turns, controlled by the upwind bias – the probability that a given turn is upwind (Demir et al., 2020). To illustrate how the upwind bias depends on signal, we plotted it in time (Materials and Methods), finding that in general it was dynamic and high during the ON block, but otherwise slightly below 0.5 (**Figure 5A**, grey, **Figure 5 Figure Supplement 1** grey). Unlike the turn rate

367 and turn speed, upwind bias also depended on fly orientation, and was largest for crosswind-
368 facing flies (**Figure 5B**).
369
370 Following our previous work (Demir et al., 2020), we model upwind bias $B(t)$ as a sigmoid (**Figure
371 5C**):
372

$$B(t) = \frac{1}{1 + \exp\left[-\left(a_0 + g\, u(t)\right) \cdot \sin^2\theta\right]} \qquad (4)$$

374
where a_0 represents a baseline bias (i.e. when no signal is present), and the $\sin^2\theta$ term ensures
that the bias is maximal at crosswind angles (**Figure 5C)**. $u(t)$ is the output of a signal processing
model and g is a gain factor controlling how much the signal affects upwind bias. To best capture
the upwind bias, we consider four simple signal processing models $u(t) = I(t), F(t), H(t), R(t)$
hereafter called: intermittency sensing $I(t)$, frequency sensing $F(t)$, dual-frequency-intermittency
sensing $H(t)$ and two-timescale integrator $R(t)$. The intermittency sensing model exponentially
filters the binary signal $S(t)$ with timescale τ:
382

$$I(t) = \int_0^t \frac{1}{\tau} e^{-\frac{(t-t')}{\tau_I}} S(t')dt' \qquad (5)$$

384
385 By construction, $I(t)$ responds uniquely to signal intermittency (Jayaram et al., 2022). The
386 frequency sensing model $F(t)$ was proposed in (Demir et al., 2020). Here, the duration of the
387 signal is ignored, and the signal is converted to a time-series $w(t)$ of delta function spikes at the
388 onset of each odor encounter. The onsets are exponentially filtered to produce the output, which
389 is effectively a running estimate of odor encounter frequency:
390

$$F(t) = \int_0^t e^{-\frac{(t-t')}{\tau_F}} w(t')dt' \qquad (6)$$

392
393 The third model examined was a dual frequency and intermittency sensing model $H(t)$, outlined
394 in (Jayaram et al., 2022). This model linearly combines *I(t)* and *F(t)*, but the contributions of *F(t)*
395 and *I(t)* are independently weighted:
396

$$H(t) = g_I \cdot I(t) + g_2 \cdot F(t) \qquad (7)$$

398
399 Here g_I and g_F are gain factors. In this case the gain g in Equation (4) is set to be 1 and the same
400 timescale is assumed for I and F. Finally, in the two-timescale integrator model, the response
401 $R(t)$ adapted to the signal with one timescale τ_g when the signal turned on, but another timescale
402 τ_d when the signal was lost. This is expressed mathematically as:
403

$$\frac{dR}{dt} = \frac{1}{\tau_g} \cdot \left(S(t) - R(t)\right) \qquad (8)$$

405 when the signal is on and
406

$$\frac{dR}{dt} = \frac{-1}{\tau_d} \cdot R(t) \qquad (9)$$

409
407

410　when no signal is present. This model always responds to signal intermittency, but also responds
411　to frequency independently, up to frequencies of $\frac{1}{\tau_d}$, provided $\tau_g \ll \tau_d$ (see Materials and
412　Methods). Equations (4-9) define 4 alternative models for the upwind bias. Together with the turn
413　dynamics model described in the previous section, this provides us with 4 alternative models to
414　predict fly orientation dynamics.

Figure 5: Comparison of flies orientations with simple models suggests that upwind bias is modulated over two timescales. A. Probability to turn upwind given turning (i.e. upwind bias) as a function of time for the same 4 environments as in **Figure 3A** (grey) and predictions from a two-timescale integrator with an instantaneous rise timescale (purple). Experimental upwind bias is estimated using a 0.25s sliding window (Materials and Methods). **B.** Upwind bias vs orientation at two different signal times, across all 45 fictive odor environments. 0 degrees denotes downwind facing flies; 180 degrees denotes upwind facing flies. During the signal (times when the fictive odor flashes were on), turns tend to be oriented upwind with crosswind-facing flies showing the strongest bias (red). When there is no signal present (20s-30s, i.e. last 10s of the OFF block), flies tend to turn downwind and the bias is strongest for crosswind-facing flies (black). Dashed purple: model fit for upwind bias vs orientation when there is no signal. **C.** A model for turn bias suggested by the data. We use a sigmoidal form as in (Demir et al., 2020; Jayaram et al., 2022) where the likelihood to turn upwind given turning increases with $R(t)$, the two-timescale integrating response with an instantaneous rise timescale and finite decay timescale, while the $\sin^2\theta$ factor ensures that the bias is maximal for crosswind orientations and suppressed at upwind or downwind orientations. **D.** Comparison of prediction from the four signal processing models in the same four odor environments as in panel A. Grey: mean fly orientation. Grey shading: the standard mean error of the experimental response data. Color: best prediction for each model (Parameters in Materials and Methods, Table 1). Yellow: best prediction of intermittency-sensing model $I(t)$, blue: best predition of frequency-sensing model $F(t)$, green: best prediction of dual intermittency and frequency sensing model $H(t)$, purple: best prediction of two-timescale integrating model $R(t)$. Black dashed line indicates crosswind orientation at 90°. Scales for time and orientation are given by the horizontal and vertical black solid bars respectively. NR scores are calculated using all 45 environments.

To find out which of these 4 models best describes fly behavior, we fit all of them to data. To constrain a_0 we took advantage of the fact that the upwind bias returns to baseline within a couple of seconds following the offset of the ON block (**Figure 5A**, grey, **Figure 5 Figure Supplement 1** grey). Accordingly, we estimate a_0 by using the last 10s of the OFF block (**Figure 5D**, black) to fit Equation (4) with $u(t) = 0$ (**Figure 5A**, purple). To estimate the remaining parameters we simulated stochastic agents. Turn initiation, speed and duration were simulated as explained above using the best fit parameter values extracted from the analysis in the previous section. Turn bias parameters were estimated using Equation (4) to generate a stochastic turn direction for each turn executed by the agents. For each environment, 240 sample trajectories were generated. We constrained the parameters by minimizing the mean squared error between the mean orientation of agents and flies (Materials and Methods).

We found that the two-timescale integrator model $R(t)$ best fit the data across all environments **(Figure 5D).** For the intermittency sensing model ($I(t)$, overall NR = 0.27, the optimal parameters τ_I = 0.04s, g = 12.6) predicted well the response for long encounters or lower frequencies, but underestimated responses at higher frequencies or lower durations, and overestimated the response at the highest intermittencies (**Figure 5D**, yellow). Conversely, the frequency sensing model ($F(t)$, overall NR = 0.29; best fit parameters τ_F = 0.08s, g = 9.3) exhibited the opposite trend: satisfactory fits for frequencies > ~1.5 Hz, but clear underestimates for lower frequencies (**Figure 5D**, blue). This suggested that a simple sum of these models might resolve these individual failure modes. Indeed, the dual-frequency-intermittency model was more accurate overall ($G(t)$, NR = 0.25), and with optimally fit gains g_I = 2.7, g_F = 3.2 and timescale τ_H = 0.1s, captured the mean and dynamics the orientation response across a range of odor environments (**Figure 5D**, green). Still, it underestimated the response at low frequencies < 1.5 Hz. The two-timescale integrator model, however, predicted the mean orientation responses across all panels better ($R(t)$, NR = 0.20) than the than the dual-frequency-intermittency model. The optimally fit rise time for the response at signal onset was almost instantaneous (τ_g = 0.01s-Materials and Methods for details about this value), whereas the decay timescale was much longer (τ_d = 1s). We also verified that the two-timescale integrator models with best-fit parameter values reproduces upwind bias in the data (**Figure 5A**, purple).

470 We conclude that models that combine frequency and intermittency sensing to determine upwind
471 bias perform better than single-sensor models (Jayaram et al., 2022). However, a linear
472 combination of the frequency and intermittency sensors is not sufficient. The data is better
473 reproduced by sensor that responds to these features through integrating the odor signal over
474 two different timescales.
475
476 **A single model captures general trends in angular speed and orientation across a broad**
477 **spectrum of temporally diverse fictive odor environments**
478
To better examine the limits of our model, we now plot mean angular speed and orientation
predictions on top of the data across all 45 environments. As mentioned above, angular speed is
predicted well across most environments (**Figure 6A** NR=0.16) and the model captures the
variation of the turning dynamics with respect to signal frequency and intermittency, recapitulating
differences previously seen between experiments that explored different signal parameter
regimes (Alvarez-Salvado et al., 2018; Demir et al., 2020).
485
486 The model also captures the general trend in orientation (**Figure 6B** NR=0.20), albeit less well
487 than for angular speed. This is to be expected given the cumulative effect that errors in the
488 prediction of angular speed and turning bias have on orientation. Maxima in mean fly orientation
489 were underestimated at low frequencies, but overall general trends across all 45 panels were
490 captured.
491
492 We conclude that flies navigate diverse temporal statistics by: 1) modulating their turn decisions
493 and turn speed via a frequency-dependent novelty detector and an intermittency-dependent offset
494 detector of odor signals; and 2) biasing the orientation of these turns using a response function
495 that integrates the signal over two timescales, a very fast rise timescale (tens of ms) and a slow
496 decay timescale (seconds).
497
498 **DISCUSSION**
499
500
It is well-known that animals from crabs (Keller and Weissburg, 2004) to moths (Vickers and
Baker, 1994) and *Drosophila* (Sehdev et al., 2019b; van Breugel and Dickinson, 2014) use various
temporal features of olfactory stimuli to modulate navigation. Previous studies in walking flies
have shown that turns can be modulated by the frequency of odor encounters in complex plumes,
and by encounter duration in low frequency environments (Alvarez-Salvado et al., 2018; Demir et
al., 2020; Jayaram et al., 2022). Here we carefully examined the transition between these two
regimes. To isolate temporal features from spatial information such as the spatial structure of
odor encounters, local odor gradients, and turbulent wind structure, we used optogenetics. This
allowed us to probe a broad range of odor frequency and durations.
510
A key finding of this study is that a model incorporating both a frequency-dependent novelty
response (this study) and a previously observed intermittency-driven offset response (Alvarez-
Salvado et al., 2018) can successfully describe the dynamics of turns across the spectrum of
temporally diverse environments studied. This single model predicts that in environments with
high odor intermittency, the turn rate is dynamic and spikes at the encounter offset, as seen in
(Alvarez-Salvado et al., 2018), whereas in environments of high frequency odor encounters, the
turn rate remains roughly constant, as seen in (Demir et al., 2020), after the initial response to the
first encounter. Although the novelty response was not observed in (Demir et al., 2020), such a
feature was likely highlighted in our current study due to all flies receiving identical odor stimuli
simultaneously.

521
522
523

A

B

	0.02 s	0.05 s	0.10 s	0.25 s	0.50 s	1.00 s
0.2 Hz						
0.5 Hz						
1.0 Hz						
1.5 Hz						
1.75 Hz						
2.0 Hz						
2.5 Hz						
3.0 Hz						
4.0 Hz						
5.0 Hz						

Orientation (deg)
120
90
60

0 5 10 15 20 25
Time (s)

527
528
529
530

Figure 6: A single model with fixed parameters captures general trends in angular speed and orientation across a spectrum of temporally diverse fictive odor environments. A. Population mean angular speed (grey) and model predictions (pink). Grey shading denotes standard error of the mean while pink shading denotes simulated standard deviation (see Materials and Methods). Trends in population angular speed, which is modelled as the result of dynamic turn rates and mean turn angular speeds (Equations 2 and 3, respectively), are well captured by the model across all 45 experiments. **B.** Population mean orientation (grey) and standard error (grey shading) along with model predictions (purple) and estimated model errors (purple shading). 180 degrees is upwind, 90 degrees is crosswind and 0 degrees is downwind. Dashed blue line indicates 90 degrees. Model orientation is the result of simulated turns occurring with dynamic rates (Equation 2) and average angular speeds (Equation 3) as well as a dynamic bias towards the upwind direction (Equation 4). We see that general trends and mean values across all 45 different environments are well-approximated by our model. Number of trajectories per time point is the same as in **Figure 2A**.

The novelty response reveals that after ~2s of no stimulus a fly is very likely to execute a large turn in response to a new odorant encounter, whereas more frequent encounters are not as likely to trigger such a deterministic response. In turbulent odor plumes, times between encounters (blank times) are power-law distributed and odor packets tend to arrive in clumps (Celani et al., 2014; Connor et al., 2018; Murlis et al., 2000). Thus, even within a plume a fly may not experience any odor packet for an extended period of time. It would be interesting to compare this novelty timescale with the distribution of blank times and clumps durations in natural plumes. Flying flies also experience very different signal statistics from walking flies, which begs the question of whether this novelty timescale is the same in flying flies. The observed spikes in turn rate and turn speed are also transient, decaying with a timescale of about 0.5 s. Probing the basis of this novelty response and how these observed timescales emerge from the neural circuitry could be a fruitful avenue for future study. It would also be insightful to investigate theoretically the optimality of varying turn rate and turn speed in such a way--whether modulation with this novelty response and offset response is optimal for navigation success across a range of temporally diverse environments.

In addition to the modulation of turn rate and turn speed, another important finding of this study is that the likelihood for a turn to be oriented upwind increases with a very fast timescale (fit to be roughly 10ms) at signal onset and decays with a slower timescale of roughly 1s. We show (Materials and Methods) that as a result, upwind bias increases independently with both signal frequency and intermittency, thus allowing for a sustained upwind bias across environments. The response to both frequency and intermittency is largely consistent with previous findings that intermittency dominates upwind motion in high-duration, low frequency environments whereas frequency dominates in low-duration, high frequency environments (Alvarez-Salvado et al., 2018; Demir et al., 2020; Jayaram et al., 2022).

The multiple timescale integration observed here in fly behavior is within the range of the fast and precise processing capabilities of the *Drosophila* olfactory circuit. *Drosophila* ORNs process signal as fast as 100 Hz (Schuckel et al., 2009). This information is preserved downstream where 2nd-order projection neurons (PNs) encode a broad range of signal frequencies via multiple post-synaptic currents (Nagel et al., 2015) (Fox and Nagel, 2021; Fulterer et al., 2018; Pooryasin et al., 2021). These features enable rapid behavioral responses (~50ms) (Bhandawat et al., 2010). A recurring theme in *Drosophila* temporal odor processing, both in behavior and circuitry, is the importance of two distinct timescales. At the first processing relay, ORNs synapse onto PNs with two kinetically distinct fast and slow postsynaptic currents which promote a wide range of frequency transmission (Nagel et al., 2015) and promote robust navigation of simulated flies across environments with diverse temporal statistics (Jayaram et al., 2022). Our model of fly turning exhibit similar fast and slow timescales: the turning bias increases rapidly ~10ms at odor

onset but decays slowly ~1s at odor offset. Moreover, our analysis shows that, for a simple integrating response to increase independently with frequency and intermittency, it is necessary for the rise timescale to be faster than the decay timescale.

Drosophila OSNs adapt their activity to both the mean and variance of fluctuating odor stimuli (Gorur-Shandilya et al., 2017; Martelli et al., 2013; Martelli and Fiala, 2019; Nagel and Wilson, 2011), which aids preservation of both response dynamics (Martelli et al., 2013) and odor encounter timing in OSN spiking (Gorur-Shandilya et al., 2017; Kadakia and Emonet, 2019). Here we used optogenetics to drive behavior, thus bypassing the part of the ORN adaptation dynamics that takes place upstream of the firing machinery (Gorur-Shandilya et al., 2017; Nagel and Wilson, 2011). In a previous paper that used the exact same experimental setup and light intensity, we verified that the type of stimuli used here drives ORN responses within their physiological range and that fly behavior resembles that in real odor plumes (Kadakia et al., accepted). Since the odor encounters in this study neither fluctuated in intensity nor lasted longer than 1 second, it is perhaps unsurprising that we did not need to include ORN adaptive dynamics in our model. However, in experimental paradigms with longer light stimuli or varying intensity, adaptation could play an important role in navigational behavior.

Other aspects of olfactory navigation have not been considered in this study. As we wanted to focus solely on orientation dynamics, we did not factor changes in ground speed or transitions between stops and walk bouts into our predictive models, although these locomotory behaviors are known to be modulated by odor encounter timing and duration (Alvarez-Salvado et al., 2018; Demir et al., 2020). Further analyses with these data studying the effect of temporally varying stimuli on walking speed would be useful. We acknowledge that this paradigm creates a simplistic odor landscape in which other sensory inputs such as visual cues are removed, which when present can improve navigation success (Budick et al., 2007; Frye et al., 2003). Moreover, any information available to the fly from bilateral sensing was removed due to the spatially uniform signal. Doing so was important to isolate odor timing since insects respond to timing differences across antennae (Takasaki et al., 2012), use them to detect odor motion (Kadakia et al., accepted) and respond to bilateral concentration differences (Duistermars et al., 2009; Gaudry et al., 2013). Since our fictive odor signal activated all Orco-expressing ORNs (Tao et al., 2020), we did not examine the effect of odor identity or valence on turning dynamics (Jung et al., 2015; Tao et al., 2019). We additionally did not investigate any potential effects of flies learning the structure of the odor scene during navigation (Buehlmann et al., 2015; Pang et al., 2018), as well as potential collective behavior that could improve odor environment recognition (Sehdev et al., 2019a).

We have demonstrated that processing odor signals over multiple timescales allows for temporally driven navigational behaviors across diverse environments. Further extensions of this work include investigating the neural bases for these different timescales, as well as how temporal information from individual odor encounters, combined with the overall spatial structure of an odor scene can be exploited for successful navigation.

MATERIALS AND METHODS

Flies/Handling

All fly genotypes used were reared at 25°C and 60% humidity on a 12 hr/12 hr light-dark cycle in plastic vials containing 10 mL standard glucose-cornmeal medium (Archon Scientific, NC). All flies used in experiments were female, aged 3-10 days old.

To obtain our experimental genotype, we crossed *w;gmr-hid;20X-UAS-CsChrimson* (GMUCR)
males with *w;+;Orco-GAL4* (117) virgin females (F1: *w; +/gmr-hid; Orco-GAL4/20X-UAS-*
CsChrimson). Adults were removed from vials after 3 days, and the F1 females were collected 1-
3 days after eclosion. All F1 flies contained a copy of *gmr-hid*, making them blind, and expressed
the channelrhodopsin *Chrimson* in their *Orco*-expressing olfactory receptors. 20-30 females were
starved 72 hours prior to the experiment in empty plastic vials containing water-soaked cotton
plugs at the bottom and top. 24 hours before the experiment, flies were fed 1 mM all trans-Retinal
(ATR) (MilliporeSigma) dissolved in water. The vials were covered in foil for these last 24 hours
to avoid ATR degradation. For control experiments without ATR **(Figure 1D**, **Figure 1-**
Supplement 2), flies were instead given 1 mM deionized water.

Behavioral apparatus

The fly walking arena in this study is identical to that used in (Kadakia et al., accepted), based on
(Demir et al., 2020). The arena was 270 mm x 170 mm x 10 mm (length x width x height). The
top and bottom surfaces were made of glass, and walls were acrylic. A plastic mesh was placed
downstream of the airflow to prevent flies from escaping, near to which flies were aspirated into
the arena through a sealable hole. The arena was illuminated using 850 nm IR LED strips
(Waveform Lighting) placed parallel to the sidewalls. Note that although the experimental line is
blind, two of the control lines (*Canton-S* and GAL4 parent) are not blind, thus we additionally
shone green light using an LED (Luxeon Rebel LED 530 nm) throughout the arena to flood the
visual response to simplify comparisons. All other light sources were removed.

Dry air (Airgas) was passed into the arena through a stack of heavy duty plastic coffee stirrers
(Mr. Coffee) to present laminarized wind with a flow rate at 150 mm/s. In all experiments, laminar
wind was used. To present complex wind within the arena for wind control experiments (Figure
1- Supplement 1, Figure 2- Supplement 1), airflows perpendicular to the laminar flow either side
of the laminar mesh were alternately turned on with 100 ms correlation time to perturb the wind
structure.
Experiments were recorded at 60 frames per second with a camera (FLIR Grasshopper USB 3.0)
with an IR-pass filter. Optogenetic stimuli were delivered using a projector (DLP LightCrafter
4500) mounted above the arena, with resolution 912 x 1140 pixels, which illuminated the entire
walking arena with pixels of size 292 μm (along wind axis) x 292 μm (perpendicular to wind axis).
Only the red LED (central wavelength 627 nm) was used throughout this study. All experiments
used a 60 Hz stimulus update rate. The projector and camera were aligned by minimizing the
least square difference between the two coordinate systems, as described in detail in (Kadakia et
al., accepted).

673
674
675
676
Stimulus protocol

All stimuli were written using custom scripts in Python 3.6.5. All stimuli were delivered to the
projector using the Python package PsychoPy, version 2020.2.4.post1.

During signal presentation, the entire arena was illuminated with a spatially uniform pulse of red
light ("odor encounter"), presented at the maximum intensity (LED 255). We note that flies
demonstrated similar albeit weaker responses to odor encounters with a lower intensity (data not
shown). The odor encounter was presented regularly at a defined frequency (0.2 Hz, 0.5 Hz, 1.0

Hz, 1.5 Hz, 1.75 Hz, 2 Hz, 2.5 Hz, 3.0 Hz, 4.0 Hz, or 5.0 Hz) and a defined duration (0.02 s, 0.05 s, 0.1 s, 0.25 s, 0.5 s, or 1.0 s). Any combinations of frequency and duration that produced overlapping encounters with indistinguishable onsets and offsets were excluded from the environment sweep.

Within one experiment, the stimulus paradigm was repeated four times. Each repeat consisted of an "ON block" and an "OFF block". Odor encounters were presented only during the ON block, which lasted for maximum 15 s. Note that the end of the ON block (i.e. the offset of the last odor encounter) is dependent on the combination of encounter frequency and duration used and thus could be as short as 10.02 s (0.2 Hz, 0.02 s). Any signal that ended after 15 s (i.e. 1.75 Hz 0.25 s, 1.75 Hz 0.5 s, 2.5 Hz, 0.25 s) was terminated at 15 s. The ON block was followed by a 15 s long OFF block, in which no odor was presented. Note that due to the variability in the end of the ON block means that the OFF block could last between 15 s and 19.98 s. Thus each repeat lasted for 30 s, and the entire experiment lasted 120 s. Laminar wind was presented continuously for the span of the experiment unless otherwise stated. Up to 10 experiments were presented to the same set of flies within one session, with a 60 s interval between experiments. The order of the experiments within a session were pseudo-randomized so that two consecutive experiments would not present same stimulus to avoid flies possibly learning from the environment.

Experimental protocol

Experiments were performed between 08:00 and 12:00 as *Drosophila* activity peaks during this time (van Breugel et al., 2018), in a temperature- and humidity-controlled environment (temperature: 22.2 °C ± 0.2 °C, humidity: 52.3 % ± 2.7 %). Female flies were aspirated into the arena and allowed to acclimatize to the new surroundings and the laminar wind flow for one minute. To ensure that the cross had been successful and that the F1 were healthy and correctly expressing *Chrimson* in their *Orco*-receptors, we presented flies with three parallel static red fictive odor ribbons for 1 minute in laminar airflow. Responsive flies, when encountering the ribbon, tend to turn upwind and weave along the edges of the ribbon towards the expected odor source (Demir et al., 2020). Sets of flies that did not show this behavior were discarded. For each combination of encounter frequency and duration investigated, between 6 and 12 videos/experiments were recorded/performed with between 11 and 27 individuals in one session.

Fly tracking/data acquisition

All tracking scripts were custom written by Nirag Kadakia in Python 3.7.4 and are described in detail in (Kadakia et al., accepted).

Briefly, fly centroids were determined using the SimpleBlobDetector function in OpenCV, and assigned to a trajectory identity by matching to other nearby centroids. Centroids that could not be connected to existing trajectories within 30 frames were excluded, and subsequent detected centroids were thus marked as a new trajectory. Orientation was obtained using the *canny* function in *scikit-image* to determine fly "edges", defined between 0 and 360. Measurement noise was removed using a Savitsky-Golay filter (4th order polymonial, window size of 21 frames (0.3 s). The ground velocity in the individual x and y directions were defined by taking the analytical derivative of the fitted polynomials for x and y, and was used to resolve the head and rear of the fly (Kadakia et al., accepted). The angular velocity was determined in the same manner using the orientation. Any potential location bias in the arena due to physical constraints from the stimulus projection were removed by randomly selecting half of the trajectories from each odor environment and flipping the y coordinates and heading along the y axis (axis perpendicular to

737 the airflow). Any trajectory where the fly's mean speed across all the time it was tracked was less
738 than 2mm/s was considered as a non-responsive individual and removed from all further
739 analyses. For Figure 1 only (and its corresponding supplemental figures), individual time points
740 where the fly moved less than 2mm/s were additionally removed to ensure equal treatment of
741 data for comparison with data taken from (Demir et al., 2020).
742
743 *Defining turns*
744
To define a turn event, we sought to determine a threshold angular speed and minimum duration,
above which the reorientation event would be classified as a turn. This method is robust against
artificial detections of spurious events that may occur due to measurement fluctuations. However,
arbitrarily setting the angular speed threshold too high will neglect large angular changes that
likely drive changes in the overall heading. To determine a suitable minimum angular speed
threshold for this dataset, we pooled trajectories across all 45 odor environments, and examined
how changing the threshold angular speed for a turn event affected the distribution of the angular
change for "fixation" events, i.e. the change in orientation for events where the angular speed was
below threshold. We set the threshold at between 5 deg/s and 150 deg/s. For each of the 17
tested thresholds, we obtained the distribution of angular change magnitudes during fixation
events, and extracted the 95[th] percentile to obtain a comparable measure representing the
majority of angular changes made (**Figure 3, Figure Supplement 3A**).
757
A suitable threshold would have smaller angular changes during fixations, and larger changes
during turns. We found that initially, as the threshold increased, smaller angular changes that are
likely caused by trivial reorientations were classed as "fixations", and thus would be disregarded
as a turn event. Increasing the turn speed threshold beyond 25 deg/s led to much greater changes
in orientation during fixation events, (**Figure 3, Figure Supplement 3A**) (see also **Figure 3B**).
Thus we set the minimum angular speed threshold for a turn event at 25 deg/s.
764
We observed that the distribution of angular change magnitude for events above the 25 deg/s
threshold angular speed was bimodal (**Figure 3, Figure Supplement 3B**). The first peak indicates
a proportion of events with small angular changes; the second peak centralized around much
larger angular changes. We reckoned that the distribution of smaller angular changes could be
from very short, sharp changes in orientation, which were potentially artefacts of the tracking to
be removed.
771
We fit a Gaussian mixture to the distribution and found that the standard deviation of the low-
mean Gaussian was approximately 4.5°. A navigating agent is more likely to regulate the duration
of its turn, rather than the magnitude of the angular change and thus we instead set a minimum
duration for turn events. With a minimum angular speed of 25°/s, and a minimum angular change
of 4.5°, we get a minimum turn duration of 0.18 s. We removed all above angular speed threshold
events with an event duration of less than 0.18 s; the resultant angular change distribution for turn
events was no longer bimodal (**Figure 3, Figure Supplement 3C**).
779
780 *Plotting turn quantities as a function of time*
781
To estimate the turn rate as a function of time, at any time point we considered trajectories where
flies were in a fixation state or had just transitioned from fixation to turn at that time point.
Assuming an inhomogeneous Poisson process, the probability to transition from fixation to turn
at a timepoint t is given by $\lambda(t) \cdot \Delta t$, where Δt is the time-step resolution of our data, 1/60s. Thus
the fraction of all considered trajectories that had just transitioned from fixation to turn, divided by
Δt, provides an estimate of $\lambda(t)$. We smoothed this estimate with a rectangular smoothing window

of width 0.25s, sliding the window across each time step, and plotted the results in **Figure 4A**,
grey, and **Figure 4, Figure Supplement 1**, grey. Errors bars were estimated by bootstrapping
the data 500 times at each time point.
791
We estimated mean turn speed, mean turn duration and upwind bias as a function of time in the
following way. We defined a 0.25s wide window and considered all turns that started in this
window. For each turn, we then computed its mean angular speed, its duration and whether it
was upwind (+1) or downwind (0). We then averaged these quantities to get an estimate of the
mean turn speed, mean turn duration or upwind bias, respectively, for that window. As for the turn
rate, we slid the window across each time step and plotted our results against the center of the
time window. Error bars were estimated by resampling the data 1000 times at each time point.
799
800 *Modeling fly turning behavior*
801
802 The *OFF* function is defined as
803
$$OFF(t) = \max{(0, I_{slow} - I_{fast})}, \tag{10}$$

805
analogously to how it was defined in (Alvarez-Salvado et al., 2018). Here I_{slow} and I_{fast} are
defined as in Equation 5, with characteristic timescales $\tau_{slow} > \tau_{fast}$. At signal offsets, I_{slow}
decays slower than I_{fast} , so their difference (and thus *OFF*) is positive for some time. At signal
onset or presence, I_{fast} rises faster and is greater in value than I_{slow}, thus the max operation
ensures that *OFF* is 0. Due to the integrative nature of the *I* filters, this *OFF* function reaches a
higher peak after high intermittency signals.
812
813 The novelty function *N(t)* was defined as
814
$$N(t) = A_t e^{-\frac{t-t_L}{\tau_{Nd}}}, \tag{11}$$

816
where t_L is the time of the latest pulse onset. For the time between the onsets of the first and
second pulse, $A_t := 1$. Otherwise, $A_t = 1 - e^{-(t_L - t_L')/\tau_N}$, where again t_L is the time of the latest
pulse onset and t_L' is the onset time of the pulse before the latest pulse. For a square wave signal,
$t_L - t_L'$ becomes $T = \frac{1}{f}$, i.e. the period of the signal. Thus at first pulse onset, *N* spikes to 1 and
decays with timescale τ_{Nd} . At subsequent pulses, N spikes to a height of A_t before decaying with
timescale τ_{Nd}. The τ_N timescale defines the time required between pulses to induce a strong
response—if $T \ll \tau_N$, $A_t \approx 0$ and the novelty response is suppressed. On the other hand if $T \gg$
τ_N, $A_t \approx 1$ and the novelty response is maximal.
825
826 *Parameter Estimation*
827
To estimate parameters for turn rate (Equation 2), we considered time points where flies were in
fixations (i.e. not turning) or had just transitioned from fixation to turn. We excluded fixations that
lasted longer than 1.5s, as more than 95% of fixations were shorter than 1.5s and beyond this
duration, fixation durations were no longer exponentially distributed **(Figure 3 Figure**
Supplement 2). For a time point t, the probability to not initiate a turn at that time point is $e^{-\lambda_t \Delta t}$
where Δt is our sampling time (1/60s) and λ_t denotes the turn rate from Equation 2 at that time
point. The probability to initiate a turn at that time point is $1 - e^{-\lambda_t \Delta t}$. We then constructed a
likelihood function:

$$L = \Pi_{\text{fixations}} e^{-\lambda_t \cdot \Delta t} \Pi_{\text{turn starts}} (1 - e^{-\lambda_t \cdot \Delta t}) \qquad (12)$$

and minimized the negative log of this likelihood using scipy.optimize.minimize with the standard L-BFGS-B method for minimization with bounds. All subsequent log-likelihood functions were minimized similarly. Note that for all timescales we estimated the log of the inverse timescale, i.e. the log of the 'rate' and then converted that back into a timescale.

To estimate turn speed parameters, we calculated the mean angular speed for each turn and subtracted our minimum turn speed of 25 deg/s (this is added back later when simulating the turns). The distribution of the resultant mean angular speeds was assumed to be a Gamma distribution with fixed shape parameter 2, based off the observations in **Figure 3**. The mean of this Gamma distribution was assumed to depend on the signal and is given by Equation 3. Assuming individual turns are independent, we could then construct a likelihood function as the product of the likelihood of each mean turn speed:

$$L = \Pi_{\text{turns}} \frac{1}{\left(\frac{\mu_t}{2}\right)^2} x_t \cdot e^{-\frac{x_t}{\frac{\mu_t}{2}}} \qquad (12)$$

where x_t is the observed mean angular speed (after subtracting 25 deg/s) for the turn and μ_t is the predicted mean angular speed for a given set of parameters, using Equation 3. As the timescales for the *N* and *OFF* responses were already estimated from the turn rate analysis, only the three μ coefficients were estimated from this likelihood function, by minimizing its negative logarithm.

For turn duration, for each turn we calculated its duration and subtracted the minimum turn duration, 0.18s (this is added back later when simulating turns). We then assumed an exponential distribution for these resultant turn durations and computed a likelihood function as

$$L = \Pi_{\text{turns}} \lambda_{dur} e^{(-x_t \lambda_{dur})} \qquad (13)$$

where here x_t denotes the turn duration (after subtracting 0.18s). We found the constant λ_{dur} that minimized the negative log-likelihood. The inverse of this constant is reported as τ_{dur} in Materials and Methods, Table 1.

For the turn bias (Equation 4), we first fit the a_0 parameter as explained in the main text. Given that the elevated upwind bias returns to baseline within a couple of seconds of ON block offset (**Figure 5C**, grey, **Figure 5 Figure Supplement 4** grey), we assumed that the bias in the last 10 s of the OFF block (**Figure 5D**, black) had no remaining signal dependence and so takes the form $1/(1 + \exp[-a_0 \cdot \sin^2 \theta])$. We then minimized the squared error between this functional form and the no-signal turn bias curve obtained from data (**Figure 5D**, black), using scipy's optimize.least_squares routine and its default method, the Trust Region Reflective algorithm. The remaining turn bias parameters (timescales and gain factors in Equations 4-9) were fit by simulating 240 flies (roughly how many trajectories were in the experiment) executing our full turning strategy (see below for simulation details) with all other parameters fixed to their fit value and minimizing the squared error between the observed mean $\theta(t)$ and predicted $\theta(t)$ over the first 20s of the experiment. The minimization was done with a brute-force search over the parameter space, where g was discretized to 20 values linearly spaced between bounds shown in Materials and Methods, Table 1, while for the timescales we fit the log of the rates (i.e. $1/\tau$) by considering 20 values linearly spaced between the log of the minimum rate and log of the

884 maximum rate, corresponding to fitting the timescales with logarithmic spacing. The parameters
885 that minimized the mean squared error were used.
886
887 *Analysis of two-timescale integrating model*
888
889 Following our analysis of a single timescale integrator $I(t)$ in (Jayaram et al., 2022), we consider
890 the response $R(t)$ to a binary square-wave signal with frequency f and duration D. If we let R_n
891 denote the value of $R(t)$ at the onset of the nth pulse, then by straightforwardly integrating
892 Equations 8 and 9, we get the relation
893

$$R_{n+1} = \left(R_n \cdot e^{-\frac{D}{\tau_g}} + 1 - e^{-\frac{D}{\tau_g}} \right) \cdot e^{-\frac{\frac{1}{f}-D}{\tau_d}} . \tag{14}$$

895
896 Expanding and simplifying, we get
897

$$R_{n+1} = k \cdot R_n + k \cdot \left(e^{\frac{D}{\tau_g}} - 1 \right) \tag{15}$$

899
900 where we define $k = e^{-\frac{D}{\tau_g}} \cdot e^{-\frac{1}{f\tau_d}} \cdot e^{\frac{D}{\tau_d}}$. We can then see that in general
901

$$R_n = R_0 k^n + k \left(e^{\frac{D}{\tau_g}} - 1 \right) \cdot \frac{1-k^n}{1-k} . \tag{16}$$

903
904 Note that $\frac{1}{f} = T$, the period of the square wave and so $k = e^{-\frac{D}{\tau_g}} \cdot e^{\frac{D-T}{\tau_d}}$, which we can see is less
905 than 1. If we denote the asymptotic value of R_n as R_n^*, we get
906

$$R_n^* = \left(e^{\frac{D}{\tau_g}} - 1 \right) \cdot \frac{k}{1-k} . \tag{17}$$

908
909 We can then compute the asymptotic average value of $R(t)$ over one period of the signal, which
910 we denote as $\bar{R}$ as
911

$$\bar{R} = \frac{1}{T} \cdot \left[\int_0^D R_n^* \cdot e^{-\frac{t}{\tau_g}} + 1 - e^{-\frac{t}{\tau_g}} \, dt + \int_0^{\frac{1}{f}-D} (R_n^* \cdot e^{-\frac{D}{\tau_g}} + 1 - e^{-\frac{D}{\tau_g}}) \cdot e^{-\frac{t}{\tau_d}} \, dt \right]. \tag{18}$$

913
914 If we note that $f \cdot D = Int$, the intermittency of the signal, we get
915

$$\bar{R} = \frac{e^{\frac{Int}{f\tau_g}} \cdot \left(Int \cdot \left(e^{\frac{Int}{f\tau_d}} - e^{\frac{1}{f\tau_d}+\frac{Int}{f\tau_g}} \right) + f \cdot \left(e^{\frac{Int}{f\tau_d}} - e^{\frac{1}{f\tau_d}} \right) \cdot \left(e^{\frac{Int}{f\tau_g}} - 1 \right) \cdot (\tau_d - \tau_g) \right)}{\left(e^{Int\left(\frac{1}{\tau_d}+\frac{1}{\tau_g}\right)} - e^{-\frac{1}{f\tau_d}+\frac{2Int}{f\tau_g}} \right)}. \tag{19}$$

917
918
919

We can see here that the response depends independently on both the intermittency and
frequency of the signal. Since the response is integrating the signal (Equations 8 and 9), $\bar{R}$
increases with signal intermittency. To see how it depends on frequency, we consider the
difference between the timescales. Firstly, note that if $\tau_g = \tau_d$ then we just have a single
timescale integrator and $\bar{R} = Int$, as we would expect from (Jayaram et al., 2022). For the case
where $\tau_g \ll \tau_d$ and can be approximated as 0 (as in our fits), one can readily compute $\bar{R}$, noting
that $R(t)$ is 1 when the signal is present and decays with timescale τ_d when the signal is absent.
We get
928

$$\bar{R} = Int + f\tau_d \left(1 - e^{\frac{Int-1}{f\tau_d}} \right) \tag{20}$$

930
931 which we can see grows with f until $f \gg 1/\tau_d$ at which point it levels off.
932
933 On the other hand, if $\tau_d \ll \tau_g$ and is taken to be 0 instead, we get
934

$$\bar{R} = Int + f\tau_g \left(e^{\frac{-Int}{f\tau_g}} - 1 \right) \tag{21}$$

936
937 and in this case decreases with increasing frequency, before leveling off. Thus we see that a
938 short rise timescale and longer decay timescale are necessary for a positive response to both
939 intermittency and frequency.
940
941 *Table 1-All Fit Parameters*
942

Parameter	Explanation	Estimation Bounds	Fit value
τ_N	novelty detection timescale	0.01-1200s	2.04 s
τ_{ND}	novelty response decay timescale	0.01-1200s	0.55 s
τ_{fast}	off response fast timescale	0.01-1200s	0.19 s
τ_{slow}	off response slow timescale	0.01-1200s	0.22 s
λ_0	base turn rate	-infinity to infinity	3.06 /s
λ_1	turn rate novelty response coefficient	-infinity to infinity	2.80 /s
λ_2	turn rate off response coefficient	-infinity to infinity	45.14 /s
μ_0	base mean turn speed* (see below)	-infinity to infinity	68.1 deg/s

μ_1	mean turn speed novelty response coefficient	-infinity to infinity	47.1 deg/s
μ_2	mean turn speed off response	-infinity to infinity	582.0 deg/s
τ_{dur}	turn duration timescale* (see below)	0.01-1200s	0.18s
a_0	upwind bias baseline shift	-infinity to infinity	-0.49
g for $I(t)$	upwind bias response gain using intermittency-sensing model	0-16	12.6
τ_I	intermittency-sensing model integration timescale	0.01-5s	0.04s
g for $F(t)$	upwind bias response gain using frequency-sensing model	0-16	9.3
τ_F	frequency-sensing model integration timescale	0.05-5s	0.08s
g_I for $H(t)$	intermittency sensor gain for dual frequency and intermittency sensing model	0-4	2.7
g_F for $H(t)$	frequency sensor gain for dual frequency and intermittency sensing model	0-4	3.2
τ_H	dual frequency and intermittency sensing model integration timescale	0.05-5s	0.1s

g for $R(t)$	upwind bias response gain using two-timescale integrator	0.15-3	1.5
τ_g	upwind bias rise timescale for two-timescale integrator	0.01-5s	0.01s**
τ_d	upwind bias decay timescale for two-timescale integrator	0.05-5s	0.97 s

*Note that to fit turn speed and turn duration, we first subtracted the minimum turn speed (25 deg/s) and minimum turn duration (0.18s) set by our thresholding method. These values (μ_0 and τ_{dur}) represent the addition to the minimum threshold values set, that were fit. Thus in the absence of signal the mean turn speed is actually 25 + 68.1 = 93.1 deg/s and the mean turn duration is 0.18 + 0.18 = 0.36s: the mean turn duration beyond the minimum duration coincidentally was also fit to 0.18s.

**Note that the found value of 10ms for τ_g was on the edge of the minimization bounds. We did not probe shorter timescales as the time-resolution of our data was ~16ms. However we verified that even for an instantaneous rise timescale the cost was higher than the cost for 10ms but within 3% of its value. The same was true for a τ_g of 20ms. For values greater than 20ms the cost started to grow more significantly. Hence we concluded that the rise timescale was between 0-20ms.

Simulating Fly Turning Dynamics

To simulate flies executing our turn model, we first determined whether a simulated fly would initiate a turn or not by taking the probability to initiate a turn in a time step Δt as $\lambda(t) \cdot \Delta t$, where $\lambda(t)$ is given by Equation 2. If a fly was not turning its angular velocity was assumed to be 0. If a turn was initiated, its duration in excess of 0.18s was sampled from an exponential distribution with timescale τ_{dur}, and added to 0.18s to get the total turn duration. The mean angular speed of the turn in excess 25 deg/s was sampled from a Gamma distribution with shape parameter 2 and mean given by Equation 3, then added to 25 deg/s to get the total mean angular speed. We assumed a turn had a parabolic angular speed profile (see Figure 3B). Given the mean value and duration (i.e. time between two zeros) of this parabola, we could compute $|\dot{\theta}|$ for the duration of the turn as $|6\mu/d^2(t - t_{start})(t - (t_{start} + d))|$ where t_{start} is the start time of the turn, μ is the mean angular speed of the turn, d is the duration of the turn and the factor in front ensures that the average angular speed over the turn is equal to μ. To determine the sign of the turn, we determined whether it was upwind or downwind by simulating a Bernoulli variable with probability given by Equation 4. Once $\dot{\theta}$ was specified for the whole turn, we could use Euler integration with timestep $\Delta t = 1/60$s (the frame rate of our experiments) to evolve a simulated agent's heading. Values for response functions $u(t)$ except for $F(t)$ were computed by Euler integration with a step-size of 1/10th our sampling rate and then resampled for agent simulation. $F(t)$ was computed as in (Jayaram et al., 2022). Agents were initialized with headings sampled from the distribution of experimental flies' initial headings for that environment and initialized to all not be turning for simplicity (thus the first 0.1s of our simulated total angular speed is not shown in Figure 5C and 6A as the comparison with data would not be fair).

980
981
DATA AND CODE AVAILABILITY

986
AUTHOR CONTRIBUTIONS

989 AS and VJ contributed equally to this work. AS, NK and TE conceived the project and designed
990 the experiments. AS performed all experiments with help from EB. VJ and AS performed the data
991 analysis with help from NK and TE. VJ performed the mathematical modeling, stochastic agent-
992 based simulations, and parameter fitting. AS, VJ, NK, and TE wrote the manuscript. All authors
993 revised the final manuscript.

994
ACKNOWLEDGMENTS

997 We thank G. Madeira Santana, M. Demir, H. Mattingly, and K. Kamino for helpful discussions. NK
998 was supported by a postdoctoral fellowship through the Swartz Foundation for Theoretical
999 Neuroscience, by postdoctoral fellowships NIH F32MH118700 and NIH K99DC019397. VJ and
1000 TE were partially supported by the Program in Physics, Engineering, and Biology at Yale. The
1001 project was supported by TE's setup funds from Yale University.

1002
REFERENCES

1004

Alvarez-Salvado, E., Licata, A.M., Connor, E.G., McHugh, M.K., King, B.M., Stavropoulos, N., Victor, J.D.,
Crimaldi, J.P., and Nagel, K.I. (2018). Elementary sensory-motor transformations underlying olfactory
navigation in walking fruit-flies. Elife *7*, e04577.

Baker, K.L., Dickinson, M., Findley, T.M., Gire, D.H., Louis, M., Suver, M.P., Verhagen, J.V., Nagel, K.I., and
Smear, M.C. (2018). Algorithms for Olfactory Search across Species. J Neurosci *38*, 9383-9389.

Baker, T., and Haynes, K. (1989). Field and laboratory electroantennographic measurements of
pheromone plume structure correlated with oriental fruit moth behaviour. Physiological entomology *14*,
1-12.

Baker, T.C., and Vickers, N.J. (1997). Pheromone-mediated flight in moths. In Insect Pheromone Research
(Springer), pp. 248-264.

Bell, J.S., and Wilson, R.I. (2016). Behavior Reveals Selective Summation and Max Pooling among Olfactory
Processing Channels. Neuron *91*, 425-438.

Bhandawat, V., Maimon, G., Dickinson, M.H., and Wilson, R.I. (2010). Olfactory modulation of flight in
Drosophila is sensitive, selective and rapid. J Exp Biol *213*, 3625-3635.

Boie, S.D., Connor, E.G., McHugh, M., Nagel, K.I., Ermentrout, G.B., Crimaldi, J.P., and Victor, J.D. (2018).
Information-theoretic analysis of realistic odor plumes: What cues are useful for determining location?
PLoS Comput Biol *14*, e1006275.

Borst, A., and Heisenberg, M. (1982). Osmotropotaxis inDrosophila melanogaster. Journal of comparative
physiology *147*, 479-484.

Budick, S.A., and Dickinson, M.H. (2006). Free-flight responses of Drosophila melanogaster to attractive
odors. Journal of experimental biology *209*, 3001-3017.

Budick, S.A., Reiser, M.B., and Dickinson, M.H. (2007). The role of visual and mechanosensory cues in
structuring forward flight in Drosophila melanogaster. J Exp Biol *210*, 4092-4103.

Buehlmann, C., Graham, P., Hansson, B.S., and Knaden, M. (2015). Desert ants use olfactory scenes for
navigation. Anim Behav *106*, 99-105.

Cardé, R.T., and Willis, M.A. (2008). Navigational strategies used by insects to find distant, wind-borne
sources of odor. Journal of Chemical Ecology *34*, 854-866.

Celani, A., Villermaux, E., and Vergassola, M. (2014). Odor landscapes in turbulent environments. Physical
Review X *4*, 041015.

Connor, E.G., McHugh, M.K., and Crimaldi, J.P. (2018). Quantification of airborne odor plumes using planar
laser-induced fluorescence. Experiments in Fluids *59*, 137.

Crimaldi, J.P., and Koseff, J.R. (2001). High-resolution measurements of the spatial and temporal scalar
structure of a turbulent plume. Experiments in Fluids *31*, 90-102.

Cruz, T.L., Perez, S.M., and Chiappe, M.E. (2021). Fast tuning of posture control by visual feedback
underlies gaze stabilization in walking Drosophila. Curr Biol *31*, 4596-4607 e4595.

Dan, C., Hulse, B.K., Jayaraman, V., and Hermundstad, A.M. (2021). Flexible control of behavioral
variability mediated by an internal representation of head direction. bioRxiv, 2021.2008.2018.456004.

DeAngelis, B.D., Zavatone-Veth, J.A., and Clark, D.A. (2019). The manifold structure of limb coordination
in walking Drosophila. Elife *8*.

Demir, M., Kadakia, N., Anderson, H.D., Clark, D.A., and Emonet, T. (2020). Walking Drosophila navigate
complex plumes using stochastic decisions biased by the timing of odor encounters. Elife *9*, e57524.

Duistermars, B., Chow, D., and Frye, M. (2009). Flies require bilateral sensory input to track odor gradients
in flight. Current Biology *19*, 1301-1307.

Fox, D., and Nagel, K.I. (2021). Synaptic control of temporal processing in the Drosophila
olfactory system. bioRxiv, 2021.2005.2003.442428.

Frye, M.A., Tarsitano, M., and Dickinson, M.H. (2003). Odor localization requires visual feedback during
free flight in Drosophila melanogaster. J Exp Biol *206*, 843-855.

Fulterer, A., Andlauer, T.F.M., Ender, A., Maglione, M., Eyring, K., Woitkuhn, J., Lehmann, M., Matkovic-
Rachid, T., Geiger, J.R.P., Walter, A.M.*, et al.* (2018). Active Zone Scaffold Protein Ratios Tune Functional
Diversity across Brain Synapses. Cell Rep *23*, 1259-1274.

Gaudry, Q., Hong, E.J., Kain, J., Bivort, B.L.D., and Rachel, I. (2013). Asymmetric neurotransmitter release enables rapid odor lateralization in Drosophila. Nature *493*, 424-428.

Geffen, M.N., Broome, B.M., Laurent, G., and Meister, M. (2009). Neural encoding of rapidly fluctuating odors. Neuron *61*, 570-586.

Gepner, R., Skanata, M.M., Bernat, N.M., Kaplow, M., and Gershow, M. (2015). Computations underlying Drosophila photo-taxis, odor-taxis, and multi-sensory integration. Elife *4*, e06229.

Gomez-Marin, A., Stephens, G.J., and Louis, M. (2011). Active sampling and decision making in Drosophila chemotaxis. Nature Communications *2*.

Gorur-Shandilya, S., Demir, M., Long, J., Clark, D.A., and Emonet, T. (2017). Olfactory receptor neurons use gain control and complementary kinetics to encode intermittent odorant stimuli. Elife *6*, e27670.

Haynes, K., and Baker, T. (1989). An analysis of anemotactic flight in female moths stimulated by host odour and comparison with the males' response to sex pheromone. Physiological entomology *14*, 279-289.

Hernandez-Nunez, L., Belina, J., Klein, M., Si, G., Claus, L., Carlson, J.R., and Samuel, A.D. (2015). Reverse-correlation analysis of navigation dynamics in Drosophila larva using optogenetics. Elife *4*, e06225.

Jayaram, V., Kadakia, N., and Emonet, T. (2022). Sensing complementary temporal features of odor signals enhances navigation of diverse turbulent plumes. Elife *11*.

Jung, S.H., Hueston, C., and Bhandawat, V. (2015). Odor-identity dependent motor programs underlie behavioral responses to odors. Elife *4*, 44.

Kadakia, N., Demir, M., Michaelis, B.T., DeAngelis, B.D., Reidenbach, M.A., Clark, D.A., and Emonet, T. (accepted). Odor motion sensing enhances complex plume navigation. Nature, (preprint available at bioRxiv doi: 2021.2009.2029.462473).

Kadakia, N., and Emonet, T. (2019). Front-end Weber-Fechner gain control enhances the fidelity of combinatorial odor coding. Elife *8*, e45293.

Kanzaki, R., Sugi, N., and Shibuya, T. (1992). Self-generated zigzag turning of Bombyx mori males during pheromone-mediated upwind walking. Zoological science *9*, p515-527.

Keller, T.A., and Weissburg, M.J. (2004). Effects of odor flux and pulse rate on chemosensory tracking in turbulent odor plumes by the blue crab, Callinectes sapidus. Biol Bull *207*, 44-55.

Kennedy, J.S., and Marsh, D. (1974). Pheromone-regulated anemotaxis in flying moths. Science *184*, 999-1001.

Mafra-Neto, A., and Cardé, R.T. (1994). Fine-scale structure of pheromone plumes modulates upwind orientation of flying moths. Nature *369*, 142-144.

Martelli, C., Carlson, J., and Emonet, T. (2013). Intensity Invariant Dynamics and Odor-Specific Latencies in Olfactory Receptor Neuron Response. The Journal of Neuroscience *33*, 6285-6297.

Martelli, C., and Fiala, A. (2019). Slow presynaptic mechanisms that mediate adaptation in the olfactory
pathway of Drosophila. eLife *8*, 1-26.

Murlis, J., Elkinton, J., and Carde, R. (1992). Odor plumes and how insects use them. Annual Review of
Entomology *37*, 505-532.

Murlis, J., Willis, M.A., and Cardé, R.T. (2000). Spatial and temporal structures of pheromone plumes in
fields and forests. Physiological entomology *25*, 211-222.

Nagel, K.I., Hong, E.J., and Wilson, R.I. (2015). Synaptic and circuit mechanisms promoting broadband
transmission of olfactory stimulus dynamics. Nat Neurosci *18*, 56-65.

Nagel, K.I., and Wilson, R.I. (2011). Biophysical mechanisms underlying olfactory receptor neuron
dynamics. Nat Neurosci *14*, 208-216.

Pang, R., van Breugel, F., Dickinson, M., Riffell, J.A., and Fairhall, A. (2018). History dependence in insect
flight decisions during odor tracking. PLoS Comput Biol *14*, e1005969.

Pooryasin, A., Maglione, M., Schubert, M., Matkovic-Rachid, T., Hasheminasab, S.M., Pech, U., Fiala, A.,
Mielke, T., and Sigrist, S.J. (2021). Unc13A and Unc13B contribute to the decoding of distinct sensory
information in Drosophila. Nat Commun *12*, 1932.

Reddy, G., Murthy, V.N., and Vergassola, M. (2022). Olfactory Sensing and Navigation in Turbulent
Environments. Annual Review of Condensed Matter Physics *13*, 191-213.

Riffell, J.A., Abrell, L., and Hildebrand, J.G. (2008). Physical processes and real-time chemical measurement
of the insect olfactory environment. Journal of Chemical Ecology *34*, 837-853.

Rigolli, N., Magnoli, N., Rosasco, L., and Seminara, A. (2022). Learning to predict target location with
turbulent odor plumes. Elife *11*.

Schuckel, J., Torkkeli, P.i.H., and French, A.S. (2009). Two interacting olfactory transduction mechanisms
have linked polarities and dynamics in Drosophila melanogaster antennal basiconic sensilla neurons.
Journal of neurophysiology *102*, 214-223.

Schulze, A., Gomez-Marin, A., Rajendran, V.G., Lott, G., Musy, M., Ahammad, P., Deogade, A., Sharpe, J.,
Riedl, J., and Jarriault, D. (2015). Dynamical feature extraction at the sensory periphery guides chemotaxis.
Elife *4*, e06694.

Sehdev, A., Mohammed, Y.G., Tafrali, C., and Szyszka, P. (2019a). Social foraging extends associative odor-
food memory expression in an automated learning assay for Drosophila melanogaster. J Exp Biol *222*.

Sehdev, A., Mohammed, Y.G., Triphan, T., and Szyszka, P. (2019b). Olfactory Object Recognition Based on
Fine-Scale Stimulus Timing in Drosophila. iScience *13*, 113-124.

Steck, K., Veit, D., Grandy, R., Badia, S.B.I., Mathews, Z., Verschure, P., Hansson, B.S., and Knaden, M.
(2012). A high-throughput behavioral paradigm for Drosophila olfaction - The Flywalk. Scientific Reports
2, srep00361.

Takasaki, T., Namiki, S., and Kanzaki, R. (2012). Use of bilateral information to determine the walking
direction during orientation to a pheromone source in the silkmoth Bombyx mori. J Comp Physiol A
Neuroethol Sens Neural Behav Physiol *198*, 295-307.

Tao, L., Ozarkar, S., Beck, J.M., and Bhandawat, V. (2019). Statistical structure of locomotion and its
modulation by odors. Elife *8*, 425.

Tao, L., Ozarkar, S., and Bhandawat, V. (2020). Mechanisms underlying attraction to odors in walking
Drosophila. PLoS Comput Biol *16*, e1007718.

van Breugel, F., and Dickinson, M.H. (2014). Plume-tracking behavior of flying Drosophila emerges from a
set of distinct sensory-motor reflexes. Current Biology *24*, 274-286.

van Breugel, F., Huda, A., and Dickinson, M.H. (2018). Distinct activity-gated pathways mediate attraction
and aversion to CO_2 in Drosophila. Nature *564*, 420-424.

Vickers, N.J., and Baker, T.C. (1994). Reiterative responses to single strands of odor promote sustained
upwind flight and odor source location by moths. Proceedings of the National Academy of Sciences *91*,
5756-5760.

Yee, E., Wilson, D., and Zelt, B. (1993). Probability distributions of concentration fluctuations of a weakly
diffusive passive plume in a turbulent boundary layer. Boundary-Layer Meteorology *64*, 321-354.
1139
1140
1141
1142

Figure 1-Supplement 1: In absence of fictive or real odor, flies orient on average crosswind in both laminar and complex wind. A. Population mean orientation of flies in absence of odor stimulus, in laminar (green) or complex (purple) wind. Wind was presented continuously for 5 minutes. *Orco>Chr: w; gmr-hid/+; Orco-GAL4/UAS-20XChrimson* (experimental line responsive to fictive odor stimulus). GAL4 PARENT: *w;+;Orco-Gal4*. UAS PARENT: *w;gmr-hid;UAS-20XChrimson.* Canton-S: wildtype (same as in Demir 2020). Recorded at 60 fps, but presented by subsampling every 5 frames. Dashed line indicates orienting crosswind (90°). All flies that moved less than 2mm/s on average for their entire trajectory were removed. Orco>Chr: laminar, n=5-69 trajectories per time point across the entire 5 minute recording; complex, n=8-56. GAL4 PARENT: laminar, n=1-18; complex, n=1-17. UAS PARENT: laminar, n=1-13;complex, n=1-12. Canton-S: laminar, n=1-13; complex, n=1-12. **B.** Population orientation mean and SEM across all trajectories for laminar (green) and complex (purple) wind without odor stimulus over 5 minute recording. Any time points where the fly moved less than 2 mm/s were removed. Orco>Chr: laminar, 91.1° ± 1.1°, n = 678 trajectories; complex, 91.9° ± 1.4°, n = 519. GAL4 parent: laminar, 84.1° ± 2.9°, n = 152, complex, 82.2° ± 3.3°, n = 119. UAS parent: laminar, 87.2° ± 3.7°, n = 102, complex, 89.8° ± 3.0°, n=114. Canton-S: laminar, 90.2° ± 4.4°, n = 120, complex, 90.3° ± 4.3°, n = 111.

Figure 1-Supplement 2: Parent flies and Orco>Chr flies without ATR do not respond to the fictive odor signal. Traces of mean orientation over time for control lines in presence of 2 Hz, 0.1 s fictive odor. Population mean orientation of GAL4 parent (left) and UAS parent (middle) genotypes of optogenetically active flies, and the optogenetically active line without feeding ATR (right). Black line is mean across all trajectories at that time point, grey shading indicates SEM. Dashed black line indicates crosswind orientation at 90°. Red bars indicate fictive odor presence. Any time points where the fly moved less than 2 mm/s were removed. GAL4 parent: 52-74 trajectories per frame, UAS parent: 50-89 trajectories per frame, Orco>Chr (no ATR): 108-159 trajectories per frame.

1178
1179
1180
Figure 2 Supplement 1: Population mean behavioral responses of flies navigating fictive odor stimuli are
similar in laminar and complex wind.
Mean population orientation response measured from flies navigating one of 6 from the 45 fictive odor environments:
0.2 Hz 1 s, 0.5 Hz 0.1s, 0.5 Hz 1s, 1 Hz 0.5 s, 2 Hz 0.1 s, 2 Hz 0.25 s (from left to right), in either laminar (green) or
complex (purple) wind structure. 235-485 trajectories were recorded per odor and wind environment, and 104-242
trajectories were recorded per time frame (recording rate = 60 frames per second). Red bars indicate odor presence.
1187
1188

1189
1190
1191
Figure 2 Supplement 2: Instantaneous angular velocity as a function of environment duration and
intermittency. A. Instantaneous angular velocity of flies as a function of their orientation during the ON block (0-15 s).
Upwind orientation is at 180°, downwind at 0°. Orientation was split into 8 bins with width 22.5°. Vertical dashed line at
90° indicates flies facing crosswind during ON block. Positive angular velocity represents turning upwind, negative
represents turning downwind. Horizontal solid line at 0 °/s indicates no change in angular velocity, thus no change in
orientation. Angular velocity is colored by environment duration. Blue: 0.02 s, indigo: 0.05 s, magenta: 0.1 s, red: 0.25
s, orange: 0.5 s, yellow: 1.0 s. The grey bar indicates the crosswind range (90°± 22.5°) over which the mean angular
velocity during the ON block per odor environment was calculated in **Figure 2C**. **B.** Same as **A** but colored by
environment intermittency. Blue: 0-0.05, purple: 0.05-0.2, red: 0.2-0.5, yellow: 0.5-0.875.
1201
1202
1203
1204

1205
1206
Figure 3 Supplement 1: Angular speed responses vary across stimulus frequency and intermittency. Population
mean instantaneous angular speed, obtained from the absolute of the angular velocity, across 45 fictive odor
environments, derived from the orientation (see Materials and Methods). Stimuli presented are the same as in **Figure**
2A. Red bars denote the signal simultaneously encountered by all flies within an experiment. Between 176 and 407
trajectories were recorded per environment. Between 72 and 237 trajectories were recorded per time point across all
environments at 60 fps.
1213

1215
Figure 3 Supplement 2: Angular speed response is consistent across fly orientations: Angular speed from 4 of
the 45 odor environments (0.2 Hz 1 s, 0.5 Hz 0.25 s, 1.5 Hz 0.1s s, 3 Hz 0.25 s). Heading was split into three bins of
60 degrees; upwind facing (120°-180°, blue), crosswind facing (60°-120°, orange) and downwind facing (0°-60°,
green). Orientation was flipped over 180° as before. Solid line: population mean angular speed of flies oriented within
the corresponding 60° bin at each time point. Lighter shading: mean ± SEM at each time point. Red bars: fictive odor
pulses. Between 170 and 305 trajectories were recorded per environment for each 60° heading bin. Between 9 and
105 trajectories contribute to the data at each time point.

1228

Figure 3 Supplement 3: Defining turn events. A. The 95th percentile of the distribution of angular change magnitude
during fixation events, $\Delta\theta_{95}$, as a function of the angular speed threshold set to define a turn event. Thresholds tested
ranged from 5 deg/s to 150 deg/s. Red dashed line highlights the inflection point in the curve at ~25 deg/s, indicating
that thresholds greater than 25 deg/s ignore larger angular changes that could contribute to changes in heading. **B.**
After applying the 25 deg/s threshold angular speed to turn events, the distribution of angular change during turns is
bimodal: there is a shorter range distribution centralized around small mean angular changes, and a much wider
distribution of angular changes around centralized around a larger mean angular change. The smaller changes are
less likely to influence heading compared to the larger angular changes, thus we sought to exclude them. Distribution
can be fit using a Gaussian mixture model with a low mean, low variance Gaussian and a high mean, high variance
Gaussian. The standard deviation of the low-mean Gaussian is 4.5°, which we used to set a minimum turn event
duration of 0.18 s, given a minimum turn angular speed of 25 deg/s.. **C.** After applying the 0.18 s threshold duration for
a turn event, the distribution of angular change is no longer bimodal, meaning that only turn events of significant
magnitude are selected.
1242
1243
1244

1257
Figure 3 Supplement 4: Defining turn rate. A. Distribution of fixation durations (bin number = 60), having applied the
turn speed and turn duration thresholds. Slope of the distribution (i.e. the turn rate) is non-linear; fixation durations can
reach up to ~40 s. **B.** Cumulative probability density function of fixation durations. Red line indicates 95th percentile of
fixation durations. Vertical line indicates that more than 95 % of fixation events have a duration of less than 1.5 s. **C.**
Distribution of fixation durations, for fixations lasting up to 1.5 s. These are exponentially distributed, allowing us to
model turn rate as a Poisson process.

A

Figure 4 Supplement 1: Turn rate is dynamic and well-predicted by the combination of novelty and offset responses.
Experimental population turn rate estimated with a sliding 0.25s window (grey line) and bootstrapped error (grey shading) (see Materials and Methods) for all 45 fictive odor environments as well as model predictions (pink) and simulated error (pink shading) using Equation 2 and fit with one fixed set of parameters to all 45 environments using Maximum Likelihood Estimation (see Materials and Methods). Turn rate is dynamic and reasonably well-approximated by the model. Each panel had ~150 trajectories contributing at any timepoint. To generate model predictions and error, for each panel we generated ~150 turn series (1 if a turn starts at that time point, 0 if not) and averaged and smoothed this data to get a single time-varying turn rate estimate. We repeated this process 10000 times, taking the mean of all these as the model turn rate and the standard deviation as the model error. For more details see Materials and Methods. N = 8-103 turn events per time point for all 45 environments.

Figure 4 Supplement 2: Mean turn speed is also dynamic and well-predicted by the combination of novelty and offset responses. Experimental population mean angular speed given turning estimated with a sliding 0.25s window (grey line) and bootstrapped error (grey shading) (see Materials and Methods) for all 45 fictive odor environments as well as model predictions (pink) and simulated error (pink shading) using Equation 3 and fit with one fixed set of parameters to all 45 environments using Maximum Likelihood Estimation (see Materials and Methods), and using timescales for N and OFF responses extracted from the turn rate parameter estimates. Angular speed given turning is dynamic and reasonably well-approximated by the model. To generate model predictions and error, artificial turns were simulated occurring at the same times as the real turns. The speed of these turns in excess of the 25 deg/s threshold was sampled from a gamma distribution with time varying mean, given by Equation 3. Average turn speed on this simulated data was then calculated with the same sliding 0.25s window. We repeated this process 10000 times, taking the mean of all these as the model turn angular speed and the standard deviation as the model error. For more details see Materials and Methods. Ns are the same as in Figure 4 Supplement 1.

Figure 4 Supplement 3: Mean turn duration is roughly constant in time for high frequency environments but shows a small signal dependency for low frequency long duration signal: Mean turn duration (grey) and estimated error (grey shading) vs. time for all 45 environments considered as well as the MLE estimate of a constant duration (pink line) and uncertainty (pink shading) (see Materials and Methods). We do see some signal modulation of turn duration, particularly at lower frequencies and often see an increase in turn duration at the offset of the ON block. However, the strength of this modulation is rather mild overall and the response at block offset is somewhat unpredictable and not well fit with the off response timescales found for turn rate. Thus, to keep our model as simple as possible we neglected modulations in turn duration. To generate model predictions and error, artificial turns were simulated occurring at the same times as the real turns. The duration of these turns in excess of the 0.18s threshold was sampled from an exponential distribution with fixed parameter. Average turn speed on this simulated data was then calculated with the same sliding 0.25s window. We repeated this process 10000 times, taking the mean of all these as the model turn duration and the standard deviation as the model error. For more details see Materials and Methods. Ns are the same as in Figure 4 Supplement 1.

Figure 5 Supplement 1: Turn bias is dynamic and well approximated by a two-timescale integrator with an instantaneous rise timescale. Probability to turn upwind given turning (i.e. upwind bias) vs time (grey) and estimated error (grey shading) for all 45 fictive odor environments along with model predictions (purple) and estimated error (purple shading) for a two-timescale integrating response (Equations 8-9) with instantaneous rise timescale and finite decay timescale (see Materials and Methods). Upwind bias was estimated by calculating the fraction of turns that were upwind in a sliding 0.25s window. We see that upwind bias generally rises during signal presence and otherwise is slightly less than 0.5, suggesting that in the absence of signal flies display a preference for downwind orientation. To generate model predictions and error, artificial turns were simulated occurring at the same times as the real turns, with the same initial orientations. The direction of these turns (upwind or downwind) was assigned according to the probability given by the time varying bias, Equation 4. Turn bias on this simulated data was then calculated with the same sliding 0.25s window. We repeated this process 10000 times, taking the mean of all these as the model turn bias and the standard deviation as the model error. For more details see Materials and Methods. N = 8-103 turn events per time point for all 45 environments.