Power Series Template Matching Model for Pitch Perception

Jun-ichi TAKAHASHI [1]

[1] 8-3-5 Nagaura-ekimae Sodegaura, Chiba, 299-0246, Japan

e-mail: takajun@joy.ocn.ne.jp

Author Note

The author and the present work have no support from anyone and no conflict of interest with any other works.

Abstract

The problem of pitch perception has been the subject of a long debate between place theory and time theory. Here, we propose a Power Series Template (PoST) model to answer the problem of how and why pitch perception comes about. The sensitive measurement of acoustic signals requires efficient Sound Amplification, which inevitably accompanies mode coupling due to the perturbative non-linearities. Under reinforcement learning for Sound Localization with the second- and third-order modes as default teacher signals, a chain of coincidence is generated. After learning in Sound Localization is completed, two power series templates of 2^n and 3^m are generated, and the $2f_1 - f_2$ coupling of the elements contained therein fills the blanks of matchable harmonics up to N=10 in the template, providing the well-known harmonic template. When complex tones containing multiple harmonics are input into the trained network, two power series are evoked from each harmonic, and from their intersection, the brain acquires the fundamental of the complex tone as the pitch. Based on this template model, consistent explanations are given for the problems of missing fundamental, pitch shift, pitch and chroma, and resolvability jump without the help of time theory.

Keywords: Pitch perception, template matching, missing fundamental, Auditory Scene Analysis, Sound Localization, Sound Integration

Introduction

Theories of pitch perception have wavered between place theory and time theory (de Cheveigné, 2004, Oxenham 2013). The theory of pitch perception began with Ohm's resonance hypothesis and place theory (Helmholtz 1954) and was given anatomical evidence by Békésy (1949), who observed frequency-resolved auditory nerves in the cochlea. However, the fact that the fundamental in a complex tone was perceived as a pitch even when its intensity was reduced (Schouten 1940) or masked by noise (Licklider 1954) negated the simple place theory, and a theory focusing on the temporal structure was put forward. On the other hand, low-numbered, resolved harmonics were found to produce a much more robust and salient pitch than high-numbered, unresolved harmonics (Carlyon and Shackleton 1994). This produced another challenge for time theory, which typically did not predict a benefit for low-numbered harmonics over high-numbered harmonics. In the 70s, it was shown that altering the temporal structure of a sound by manipulating the phase of the harmonics that make up the complex tone had no effect on pitch perception (Wightman 1973). The idea of pitch perception as a direct physical measurement was rethought, and in the direction of considering pitch perception as pattern recognition, the pattern-transformation model was proposed by Wightman (1973), the optimum processor theory was proposed by Goldstein (1973), and a template model was proposed by Terhardt (1974). However, it was pointed out that it might be difficult to describe pitch perception by a single mechanism, because analysis by pattern matching also made it difficult to separate harmonics in higher-order complex tones, making template matching difficult (Houtsma and Smurzynski 1989). On the other hand, it was shown that fundamentals were perceived when different higher-order harmonics nf_0 and $(n-1)f_0$

were presented separately to the two ears, indicating that pitch perception is not the result of physical information processing in the auditory peripheral system, but rather in the central system after the crossing of the left and right auditory nerves (Houtsma and Goldstein 1972). Revising the choice between spectral or temporal, an approach emerged that uses a flexible learning process in the neuronal system to calculate the fundamental for acoustic data that describes the two-dimensional information of frequency and temporal information as spectrograms on an equal basis. Shamma and Klein (2000) proposed a network model of pitch perception based on the coupling between harmonics due to the non-linearity response in the cochlear filter. Recently, Saddler et al. (2021) developed a deep neural network (DNN) model trained to estimate the fundamental frequency and showed that many properties of pitch perception could be quantitatively reproduced by incorporating cochlear filter properties into a DNN. However, Shamma and Klein (2000) noted the shortcomings of the template model. "The lack of convincing biological evidence so far for the existence of these templates or for how they might be generated." The DNN model has a serious problem as it is a teleological procedure to optimize a given parameter. Sound pitch is a very limited piece of acoustic information. How much information about the object can we get from the pitch? Is the cost of creating a pitch perception system worth it? Why does the system choose the pitch as the target parameter for learning and not the center of gravity of the spectrum? Or why does the system perceive discrete harmonics without perceiving the continuous spectral envelope contrary to the Gestalt principle? The main problem with the DNN approach is that today's DNNs are too powerful. If we consider a DNN as a transformation from an input signal to an output signal, then under the appropriate formulation of the problem and with the appropriate

teacher data the DNN can give a formally accurate solution to almost any problem. The main

focus of research using DNNs has shifted from how accurate transformations can be given to

what internal mechanisms are responsible for high accuracy, and how they are formed.

How have organisms handled acoustic signals under survival strategies? In this paper,

we consider a model of the neural network with a nonlinear input filter for pitch perception,

going back to the origin of hearing. The various constraints imposed on the system cause

deficiencies in the behavior in an ideal DNN and characterize the output of the DNN. We derive

the system from Sound Amplification for the detection of small auditory signals and Sound

Localization of Auditory Scene Analysis (ASA) (Bregman 1990). The production and operation of

the system are represented by chains of discrete processes, which behave like state transitions

of a finite state machine (FSM) in the mathematical modeling of computation (Hopcroft et al.,

2001). We show that even under weak non-linearity limited to second- and third-order, chains

of correlation learning enable the perception of higher harmonics, while at the same time

multilayering of the network by chains leads to the loss of octave perception, which results in

octave equivalence, and that the third-order nonlinearity, $2f_1 - f_2$ coupling fills the deficit in

the chain, which improves the pitch resolvability at lower orders and explains the resolvability

jump at the 10th harmonic. We show that the template model can derive the basic properties

of pitch perception without the help of time theory.

Model

Sound signals are characterized by their amplitude and frequency. Sounds with significantly

lower or higher frequencies have no invasive effect on the organism, as resonant interaction

with the organism is lost. Each animal has its own species-specific perceptible frequency range.

Sounds incident on the ear are converted into vibrations in the lymphatic fluid and stimulates

the firing of the corresponding auditory nerves through the vibration of frequency-resolved

inner hair cells. On the other hand, signals with excessive amplitude cause irreversible damage

to the sensory system, so there is an upper limit to the sensitivity of hearing. Despite this,

humans have a large dynamic range of up to 120 dB. It is thought that amplification in the

cochlea due to active and mechanical movement in outer hair cells contributes to this (Davis

1983, Dallos 2008, Avan et al. 2012). In general, non-linear distortions often accompany the

amplification with a wide dynamic range. Kadia and Wang (2003) measured the firing of

neurons in open marmosets, and directly observed second- and third-order nonlinear mode

coupling in the sensory response of auditory neurons in the A1 auditory cortex, showing that

the central nerve uses mode-transformed harmonics and that there is strong nonlinear mode

coupling that cannot be ignored (Wang 2013, Feng and Wang 2017). Aside from the sensory

input, it had been known since the end of the 70s that when sound waves are incident on the

ear, the ear radiates sound waves with frequencies that are two and three times the frequency

of the incident sound wave. This phenomenon is called Distortion Product Otoacoustic Emission

(DPOAE) (Kemp 1979, Bian and Chen 2008). The observation of second- and third-order DPOAEs

is also direct evidence of non-linear mode coupling in the auditory organ and shows that the

non-linear coupling of the response is sufficiently weak that it is valid to treat intermodal

coupling as a perturbation. Although the DPOAE is a mechanical response of the organ to an

externally emitted auditory signal and does not directly represent the sensory input, we

consider it sufficiently feasible to consider that the properties of the DPOAE are quantitatively correlated with sound perception.

In response to stimulus input from the external world, animals localize objects (in which direction and how distant), judge their attribution (whether to approach, escape from or ignore), and determine their behavior. Behavior decisions are not mere reflex responses to stimuli, but are considered to be the output of a simulation in a model of the external world (representation) according to the location and attribution of the object in the brain through segregation and integration to the input signal. The process of reconstructing the placement of an object in the brain from acoustic signals is called Auditory Scene Analysis (ASA). The localization of objects by sound signals is called Sound Localization. As sounds of various frequencies arrive at the ear at different times, Sound Localization is the process of performing ASA by segregating and integrating sounds emanated by objects, using sound intensity, binaural time differences, and other factors as keys.

Based on these previous studies, we propose a model for creating the auditory network through the following processes. In the undifferentiated early stages of hearing, auditory cells are randomly distributed. Signals from multiple auditory cells are sent to neurons to measure their coincidence which is used to segregate and integrate sounds. Learning in neurons is considered to follow the Hebbian rule. That is, when signal input is superimposed in the presence of teacher signals, the neuron undergoes reinforcement learning. The second- and third-order overtones described above always satisfy the coincidence with the fundamental, so they act as pre-prepared teacher signals in learning. Furthermore, when a sound matching these overtones is superimposed from the outside, the neuron undergoes reinforcement

learning for the correlations between the fundamental and these overtones. The reinforcement

learning is bidirectional, so for each frequency f, correlations are implemented not only with

$2f$ and $3f$, but also with $\frac{1}{2}f, \frac{1}{3}f$ and their combinations $2^n 3^m f$ over any integer order (-∞<n,

m<∞). (Fig.1)

Figure 1. *Network of evoked signals.*

$$-\frac{9}{4}f \;-\; \frac{9}{2}f \;-\; 9f \;-\; 18f \;-\; 36f-$$

$$-\frac{3}{4}f \;-\; \frac{3}{2}f \;-\; 3f \;-\; 6f \;-\; 12f-$$

$$-\frac{1}{4}f \;-\; \frac{1}{2}f \;-\; \boxed{f} \;-\; 2f \;-\; 4f-$$

$$-\frac{1}{12}f \;-\; \frac{1}{6}f \;-\; \frac{1}{3}f \;-\; \frac{2}{3}f \;-\; \frac{4}{3}f-$$

$$-\frac{1}{36}f \;-\; \frac{1}{18}f \;-\; \frac{1}{9}f \;-\; \frac{2}{9}f \;-\; \frac{4}{9}f-$$

Note: When a sound with frequency f is heard, neurons associated with fire simultaneously.

Under the third-order nonlinearity of $2f_1 - f_2$, $5f$ and $7f$ neurons can be fired by the recursive

interaction from $2^n 3^m f$ neurons. If a sound with $2^n 3^m f$ is overlapped, the coincidence with f

is perceived.

Since learning is performed in parallel for all frequencies $\{f^{(k)}\}$ consisting of the input

sound, where $f^{(k)} = k f_0$ with the fundamental frequency f_0 and harmonic number k=1 to ∞,

power series matching templates, $[\langle 2^n 3^m f \rangle]$ for every frequency f are formed on the

distributed neurons. The neurons in the series fire simultaneously for all individual inputs, so frequency discrimination within it is not possible. At the same time, as described below, the third-order nonlinearity $2f_1 - f_2$ adds 5th and 7th matching template harmonics. Finally, harmonic templates, $[\langle 2^n 3^m f \rangle, \langle 5f \rangle, \langle 7f \rangle]$ are produced. The first column in Table 1 shows the harmonics linked by chains of second- and third-order nonlinearities. Here n=5,7 are prime to 2,3 and each other, so they cannot be directly linked by second- and third-order harmonics with the fundamental. On the other hand, under third-order nonlinearity, a third wave $2f_1 - f_2$ is generated from two different waves of f_1 and f_2. Consider this three-wave pair: when two sounds with f_1 and f_2 are input, a signal with a frequency of $2f_1 - f_2$ acts as a prepared teacher signal. When a sound with $2f_1 - f_2$ are superimposed simultaneously, the neuron undergoes reinforcement learning of the coincidence among the three waves. After learning, when any two of f_1, f_2 and $2f_1 - f_2$ are input, regardless of the order of frequency, signals with the remaining frequency is perceived simultaneously. The blank n=5, 7 in the column of Table 1 can be learned to correlate with the harmonics in the second and third columns by 5=2*4-3, 7=2*8-9, respectively. Similarly, n=10, 14, and 15 can be learned by the coincidences with the harmonics in the second and third columns by 10=2*9-8, 14=2*16-18, and 15=2*12-9, respectively. Although n=14, 15 can also be decomposed into 2*7, 3*5, the learning efficiency would be lower because $2f_1 - f_2$ learning requires two teacher signals whereas overtone learning requires only one externally provided teacher signal, and the joint strength of the coincidences learned in $2f_1 - f_2$ learning is considered weaker than in overtone learning. Therefore, for n=14 and 15, matching 14=2*16-18 and 15=2*12-9 are considered to be preferred. Also, n=11, 13, 17, and 19 are prime to 2 and 3 each other and cannot be factorized

by 2 and 3. It seems that $2f_1 - f_2$ learning is possible using the second- and third-column

harmonics as these are decomposed, e.g., 11=2*6-1, 13=2*8-3, 17=2*9-1. However, DPOAE

shows a sharp decrease in coupling strength for f_1/f_2>1.4 (Bian and Chen 2008). Considering

the contribution of amplification by outer hair cells, learning at f_1/f_2>1.4 seems to be difficult.

Therefore, the harmonics learned by the system should be restricted to the numbers without

brackets in the first column of Table 1. Once the learning is established, the system acts as a

coincidence detector between the fundamental and the harmonics. The discrete internal

structure acquired after the convergence of learning with statistical data will give the system

robustness to minor variations in details of the linear properties of input filters, fluctuations in

network parameters, etc. We name the harmonic template system derived from the chain of

correlation learning Power Series Template (PoST) system. Here, the PoST system includes the

5th and 7th harmonics through the $2f_1 - f_2$ coupling. As mentioned above, learning the $2f_1 -$

f_2 coupling is less efficient than direct power series learning. If it is necessary to consider a PoST

system without 5th and 7th harmonics, we call the system pre PoST (Fig.1). In the inference

process of the PoST system, the input acoustic signal undergoes a step-by-step transformation

to a pitch, as will be shown in the next chapter. The production and operation of the PoST

system are depicted in Fig.2. The step-by-step transformation can be considered an operation

in an FSM if it is regarded as a transition between states. The system acts as a discrete signal

processor and the FSM provides a simple description of operations that is robust for small

fluctuations in the parameters. In the following, the operation of the PoST system and its

characteristics are described in detail.

Table.1 *Harmonic template learned by the second- and third-order nonlinearities.*

N	2^n	3^m	$2f_1 - f_2$	N	2^n	3^m	$2f_1 - f_2$
1				14			2*16-18
2	1			15			2*12-9
3		1		16	4		
4	2			(17)			
5			2*4-3	18	1	2	
6	1	1		(19)			
7			2*8-9	20			2*18-16, 2*16-12
8	3			(21)			
9		2		(22)			
10			2*9-8, 2*8-6	(23)			
(11)				24	3	1	
12	2	1		...			
(13)							

Note. First column: the order of harmonics, second and third columns: the number of iterations of second-order and third-order nonlinear coupling required to access the harmonics, fourth column: the combinations of those defined from the second and third columns to access the harmonics by the $2f_1 - f_2$ coupling. Here, those of $f_1/f_2 > 1.4$ are not written (see text). The numbers in brackets are not accessible by the second- and third-order nonlinearities.

Figure 2 *Learning and inference of PoST system.*

Note. $\{f^{(k)}\}$ are harmonic series of kf_0 with a fundamental frequency f_0 and k=1 to ∞.

$\{f^{(k)}, 2f^{(k)}, 3f^{(k)}\}$ are combined series with second- and third-order harmonics. $[\langle 2^n 3^m f \rangle]$ are

power series harmonic templates for each f. $[\langle 2^n 3^m f \rangle, \langle 5f \rangle, \langle 7f \rangle]$ are the PoST template to

which 5th and 7th matching harmonics are added. In the learning process, nonlinear cochlear

amplification provides second and third harmonics and they are exploited by the NN as teacher

signals, producing PoST. In the inference process, PoST outputs chains of the power series of

second- and third-order couplings from each $f^{(k)}$. If they have an overlap, they are integrated

into a single series with the fundamental frequency f_0. If f_0 is consistent with all of $f^{(k)}$, f_0 is

output as the fundamental frequency of the input sound.

Discussion

Missing fundamental

It has been a fundamental problem in pitch perception that fundamental missing harmonic

sequences induce pitch sensation (Seebeck 1841, Schouten 1940, Licklider 1954).

Examples of the matching scheme of the PoST system is shown in Fig.3. When a sound

consisting of multiple harmonics $\{f^{(k)}\}$ is input to a trained neural system, 2^n and 3^m series are

evoked separately for each harmonic and are cross-checked for coincidence. (Here, only two

tones are shown in Fig.3.) If there is an intersection between the two series, the frequency of

the intersection is the fundamental for the input harmonics (Fig.3a). Even when there is no

intersection between the respective series of the two input harmonics, the third-order

nonlinearity evokes $2f_1 - f_2$ and $2f_2 - f_1$ harmonics from f_1 and f_2, which gives another path

for matching in the PoST (Fig.3b). If their networks have an intersection f_0 with the network of

f_1 or f_2, the neuronal system returns f_0 as the missing fundamental and f_1 and f_2 are written as

the harmonics of f_0. When the input sound has more than three harmonics, matching is

performed in parallel in all pairs of auditory neurons. However, it is not necessary to complete

matching on every pair. If a harmonic template generated by the fundamental determined from

any two harmonic pairs is consistent with the rest of the harmonic group, no further matching

is required, and the Sound Localization can be terminated. The determination of the pitch signal

would give a cue to take the exit action while matching is not completed in other neurons,

which would act on the auditory system to interrupt attention to the object and prevent it from

wasting further resources for perception. It is noted that the fundamental is not prepared a

priori as a generator of the harmonic template (and is sometimes missing in the auditory input),

but rather it is more appropriate to think of it as being defined recursively from the input

harmonics. The system does not perceive the auditory signal as a whole spectrum, but integrates it into a special single scalar quantity, the pitch of the sound, which allows the target signal to be incorporated into the ASA with minimal resources in perception just as the edge detection in vision. The parsimony would be critical for quick behavior decisions.

Figure 3 *Matching scheme of PoST system.*

Note. (a): when 800 Hz and 900 Hz tones are input simultaneously, each evokes 2^n and 3^m power series templates, respectively. The intersection 100 Hz (bold) is uniquely determined from the former 2^n template and the latter 3^m template. (b): when the 800 Hz and 1000 Hz tones are input simultaneously, there is no intersection in the power templates evoked from each. However, they evoke a 600 Hz tone by the $2f_1 - f_2$ coupling, defining the intersection 200 Hz (bold) uniquely from the 2^n template of 800 Hz and the 3^m template of 600 Hz.

Pitch shift

When all of the components in a harmonic complex tone are shifted in frequency by Δf, the perceived pitch of the complex shifts roughly in proportion to Δf. The proportionality factor can be approximated by the reciprocal of the harmonic order of the carrier frequency of the complex tone regarding the pitch fundamental frequency (Schouten 1940, Schouten et al. 1962).

The learning of the power series template is carried out in parallel at all frequencies. When a frequency is fixed, the tuning width of its harmonics learned by power harmonics cannot be infinitesimally small and always has a finite width. Once the learning is complete, matching at the higher harmonics with a detuning is possible. In listening to complex tones composed of multiple harmonics of a common fundamental, when the harmonics are shifted by the same frequency, the fundamentals determined by power series template matching for each harmonic will have different values. However, if the modulation is within the tuning width, the brain will prefer to match them with a common frequency. In a trained network, the firing probability of a neuron continuously decreases with greater detuning. Approximating the likelihood for detuning by the simplest additive quadratic function, for example, the likelihood in a three-tone complex is $\sum_{k=n-1}^{n+1}(k\omega_0 + \Delta f - k(\omega_0 + \Delta p))^2$, and the best estimate is $\Delta p = \Delta f/(n + \frac{2}{3n}) \sim \Delta f/n$ (the first effect of pitch shift), where $k\omega_0 + \Delta f$ is the kth harmonic including the frequency shift Δf used in the experiment, and $\omega_0 + \Delta p$ is the virtual fundamental. It is known that the proportionality factor obtained experimentally deviates systematically from $1/n$ (the second effect of pitch shift) (Schouten et al. 1962, Smoorenberg 1970). Its origin could be attributed to the characteristics of the likelihood function.

Pitch and chroma

It is well known that sounds with twice the frequency are perceived as having the same pitch. (Octave circularity in pitch perception) (Deutsch 2010, Shepard 1982).

In our model, harmonics that differ by a factor of 2^n in frequency are integrated into a single series during learning and are no longer distinguishable. This is consistent with octave circularity. Similarly, harmonics with different 3^m fold frequencies are integrated into a single series, which is known as the perfect 5th consonance. Shepard has geometrically represented the periodicity including octave and perfect 5th in pitch with the double helix model (Shepard 1982). In general, the harmonics of the sounds that make up the object sound consist of harmonics of the natural number of orders of the fundamental harmonic. On the other hand, the power series templates contain harmonics with negative integer powers, and the perception of subharmonics would be learned simultaneously due to the bidirectionality of the learning, whereas they do not contribute to the Sound Localization. The subharmonics can be folded back to a region above the fundamental frequency by multiplying by 2^n or 3^m. These are frequencies with a rational ratio to the fundamental and define a chroma. Which chroma is preferred or survives will depend on culture, and resulting musical scales.

Resolvability

The fundamental discrimination threshold (F0DT) of the complex harmonics tone, which consists of several harmonics, shows a critical threshold around N=10 (Houtsma and Smurzynksi 1990, Bernstein and Oxemham 2003). Bernstein and Oxemham investigated it using amplitude-

modulated tones consisting of three consecutive harmonics, showing high discrimination performance at N$\leqq$10, with a sharp drop at N>10. However, there is no significant change in discrimination performance at much higher orders. Because the components of a harmonic complex are equally spaced on a linear frequency scale, but the absolute bandwidths of auditory filters increase with increasing center frequency, the density of harmonics per auditory filter increases with increasing harmonic number. As a result, low-order harmonics are resolved from one another, but higher-order harmonics begin to interact within single auditory filters and eventually become unresolved. Then, it was proposed that the pitch perception was attributed to matching with the harmonic template for low-order harmonics and reading the period pattern of the acoustic waveform for higher-order harmonics.

This discontinuous change has been one of the biggest problems in pitch perception theory. Let us look at this problem from the standpoint of power series template matching. Consider a complex tone consisting of several harmonics (Table 2). If the tone contains two consecutive orders of harmonics, the $2f_1 - f_2$ coupling produces the perception of two harmonics below and above the orders at the same time (underlined). A power series template matching is performed among a total of four harmonics. In each complex tone, the 2^n and 3^m power series template intersections are calculated consistently by the harmonics in bold, which give matching solutions listed in the third column. The matching calculation has a solution for all combinations up to N$\leqq$10. In this case, it is not necessarily the fundamental that is determined by the calculation, but the doubling for the pairs (5,6) and (6,7) and the tripling for the pairs (10,11). The multiples do not match the original harmonic pairs. They are folded again into the fundamental to complete the template matching.

Even if the complex tone contains more harmonics, if they match a harmonic template, they will be integrated into the same power series templates, giving the same fundamentals. The matching calculation using two harmonics except (16,17) and (17,18) does not have a solution for N≧11, but by using three consecutive harmonics, it is possible to have solutions up to (18,19,20). An increase in the number of harmonics for matching calculation decreases the efficiency of the matching calculation and therefore the fundamental discrimination thresholds for N≧11 would have to be larger than that for N≦10. Our answer to the problem of resolved and unresolved harmonics for pitch perception is the special structure of the matching template itself rather than the transition to the perception of time-structure.

Table 2 *Calculation of fundamentals in complex tones with consecutive harmonics.*

Given	Evoked	Matched	Given	Evoked	Matched
(2,3)	(**2**,**3**,<u>**4**</u>)	1	(10,11,12)	(**8**,<u>**9**</u>,10,11,**12**,<u>13</u>,<u>14</u>)	1
(3,4)	(<u>**2**</u>,**3**,**4**,<u>5</u>)	1	(11,12,13)	(**9**,<u>10</u>,11,**12**,13,<u>14</u>,<u>15</u>)	3
(4,5)	(<u>**3**</u>,**4**,5,<u>**6**</u>)	1	(12,13,14)	(10,<u>11</u>,**12**,13,14,<u>15</u>,<u>**16**</u>)	4
(5,6)	(<u>**4**</u>,5,**6**,<u>7</u>)	2	(13,14,15)	(11,<u>**12**</u>,13,14,15,<u>**16**</u>,<u>17</u>)	4
(6,7)	(<u>5</u>,**6**,7,<u>**8**</u>)	2	(14,15,16)	(<u>**12**</u>,<u>13</u>,14,15,**16**,<u>17</u>,<u>**18**</u>)	2
(7,8)	(<u>**6**</u>,7,**8**,<u>**9**</u>)	1	(15,16,17)	(<u>13</u>,<u>14</u>,15,**16**,17,<u>**18**</u>,<u>19</u>)	2
(8,9)	(<u>7</u>,**8**,**9**,<u>10</u>)	1	(16,17,18)	(<u>14</u>,<u>15</u>,**16**,17,**18**,<u>19</u>,<u>20</u>)	2
(9,10)	(<u>**8**</u>,**9**,10,<u>11</u>)	1	(17,18,19)	(<u>15</u>,<u>**16**</u>,17,**18**,19,<u>20</u>,<u>21</u>)	2
(10,11)	(<u>**9**</u>,10,11,<u>**12**</u>)	3	(18,19,20)	(<u>**16**</u>,<u>17</u>,**18**,19,20,<u>21</u>,<u>22</u>)	2

(11,12)   (<u>10</u>,11,**12**,<u>13</u>)   ×   (19,20,21)   (<u>17</u>,**18**,19,20,21,<u>22</u>,<u>23</u>)   ×

    ...   ...

Note. Left: two tone complexes (N≦11), right: three tone complexes (N≧10). First column: given harmonic combinations. Second column: evoked harmonics by the $2f_1 - f_2$ coupling (underlined) and those used for 2^n and 3^m template matchings (bold). Third column: harmonics determined as the intersection of power series template matching. The determined harmonics are folded into fundamental under octave and perfect 5th circularity to give a pitch perception so that the harmonic template is consistent with the harmonic series in the first column. Up to (10,11), only two harmonics are enough to determine the fundamental, whereas three harmonics are necessary above that, up to (18,19,20).

Conclusion

We have approached the problem of pitch perception with the help of nonlinear dynamics of the cochlear amplifier, evolution of hearing, auditory psychology based on ASA, and discrete mathematics in it. We started from perturbative second- and third-order nonlinearity of cochlear amplification of small auditory signals, and considered the chains of the reinforcement learning of neural network, which produced a power series harmonic template. The third-order nonlinearity, $2f_1 - f_2$ coupling filled some blanks in the raw-power series harmonic template, which gave the harmonic template system named PoST. The chains enabled the perception of coincidence between the fundamental and higher harmonics at the cost of losing the octave perception, resulting in the octave equivalence. The $2f_1 - f_2$ coupling

filled the 5th and 7th blanks of the raw-power series harmonic template, resulting in an

improvement of F0DT for complex tones below 10th. We attributed the characteristic features

of pitch perception to the constraints on the ideal DNN. Our model could give not only

explanations about the characteristic features of pitch perception without the help of time

theory but also the answers to fundamental problems of pitch perception. What is pitch

perception? The success of Sound Integration of emanated sound from a single object. Why

was pitch perception born? Reinforcement learning of Sound Localization using second- and

third-order nonlinearity as teacher signals. Why is the pitch classified into discrete chroma?

Subharmonic perception from the bidirectional coupling in harmonic folding.

Open practices statement

Neither of the studies reported in this article has been pre-registered. No data other

than those presented here are available.

References

Avan, P., Büki, B., and Petit, C., (2013) "Auditory Distortions: Origins and Functions," Physiol.

Rev., *93*, 1563–1619. https://doi:10.1152/physrev.00029.2012

Békésy, G., (1949) "The vibration of the cochlear partition in anatomical preparations and in

models of the inner ear," J. Acoust. Soc. Am. *21*, 233-245.

https://doi.org/10.1121/1.1906502

Bernstein, J.G., and Oxenham, A. J., (2003) "Pitch discrimination of diotic and dichotic tone

complexes: Harmonic resolvability or harmonic number?" J. Acoust. Soc. Am. *113*(6),

3323-3334. https://doi.org/10.1121/1.1572146

Bian, L., and Chen, S., (2008) "Comparing the optimal signal conditions for recording cubic and

quadratic distortion product otoacoustic emissions," J Acoust Soc Am., *124*(6): 3739–

3750. https://doi: 10.1121/1.3001706

Bregman, A. S., (1990) "Auditory scene analysis: The Perceptual Organization of Sound.

Cambridge," MA: MIT Press. ISBN 9780262022972.

Carlyon, R. P., and Shackleton, T. M., (1994) "Comparing the fundamental frequencies of

resolved and unresolved harmonics: Evidence for two pitch mechanisms?" J. Acoust.

Soc. Am., *95*, 3541-3554. https://doi.org/10.1121/1.409971

de Cheveigné, A., (2004) "Pitch perception models-a historical review," CNRS-Ircam, Paris,

France.

Dallos, P., (2008) "Cochlear amplification, outer hair cells and prestin," Curr. Opin. Neurobiol.,

18(4), 370–376. doi:10.1016/j.conb.2008.08.016,

Davis, H., (1983) "An active process in cochlear mechanics," Hearing Research, *9*(1), 79-90.

> https://doi.org/10.1016/0378-5955(83)90136-3

Deutsch, D., (2010) "The Paradox of Pitch Circularity," Acoustics Today, July, 8-15

Feng, L., and Wang, X., (2017) "Harmonic template neurons in primate auditory cortex

> underlying complex sound processing," Proc. Natl. Acad. Sci. USA, *114*(5), E840-E848,

> https://doi.org/10.1073/pnas.1607519114

Goldstein, J. L., (1973) "An optimum processor theory for the central formation of the pitch of

> complex tones," J. Acoust. Soc. Am., *54*, 1496-1516. https://doi.org/10.1121/1.1914448

Helmholtz, H., (1954) "On the Sensations of Tone: As a Physiological Basis for the Theory of

> Music," New York: Dover.

Hopcroft, J. E., Motwani, R., & Ullman, J. D. (2001). Introduction to automata theory, languages,

> and computation. Acm Sigact News, *32*(1), 60-65.

Houtsma, A. J. M., and Goldstein, J. L., (1972) "The Central Origin of the Pitch of Complex Tones:

> Evidence from Musical Interval Recognition," J. Acoust. Soc. Am., *51*, 520-529.

> https://doi.org/10.1121/1.1912873

Houtsma, A. J. M. and Smurzynski, J., (1989) "Pitch of complex tones with many high-order

> harmonics," J. Acoust. Soc. Am., *85*, S142. https://doi.org/10.1121/1.2026776

Houtsma, A. J. M. and Smurzynski, J., (1990) "Pitch identification and discrimination for complex

> tones with many harmonics," J. Acoust. Soc. Am., *87*, 304-310.

> https://doi.org/10.1121/1.399298

Kadia, S. C., and Wang, X., (2003) "Spectral Integration in A1 of Awake Primates: Neurons With

　　　Single- and Multipeaked Tuning Characteristics" J. Neurophysiol. *89*, 1603–1622.

　　　https://doi: 10.1152/jn.00271.2001

Kemp, D. T., (1979) "Evidence of mechanical nonlinearity and frequency selective wave

　　　amplification in the cochlea," Arch. Otol. Rhino. Laryngol. *224*, 37–45.

　　　https://doi.org/10.1007/BF00455222

Licklider, J. C. R., (1954) "Periodicity pitch and place pitch," J. Acoust. Soc. Am., *26*, 945.

　　　https://doi.org/10.1121/1.1928005

Oxenham, J. A., (2013) "Revisiting place and temporal theories of pitch," Acoust. Sci. & Tech.

　　　34, 6. https://doi.org/10.1250/ast.34.388

Saddler, M. R., Gonzalez, R., and McDermott, J. H., (2021) "Deep neural network models reveal

　　　interplay of peripheral coding and stimulus statistics in pitch perception," Nat Commun

　　　12, 7278. https://doi.org/10.1038/s41467-021-27366-6

Schouten, J. F., (1940) "The Perception of Pitch," Phillips Tech. Rev, 5, 286-294.

Schouten, J. F., Ritsma, R. J., and Cardozo, B. L.,(1962) "Pitch of the Residue," J. Acoust. Soc. Am.

　　　34, 1418-1424. https://doi.org/10.1121/1.1918360

Seebeck, A. (1841) "Beobachtungen uber eineige bedingungen der entstehung von tonen,"

　　　Ann. Phys. Chem. *53*, 417-436,

Shackleton, T. M., and Carlyon, R. P., (1994) "The role of resolved and unresolved harmonics in

　　　pitch perception and frequency modulation discrimination," J. Acoust. Soc. Am. *95*(6),

　　　3529-3540. https://doi.org/10.1121/1.409970

Shamma, S., and Klein, D., (2000) "The case of the missing pitch templates: How harmonic

templates emerge in the early auditory system," J. Acoust. Soc. Am., *107*, 2631-2644.

https://doi.org/10.1121/1.428649,

Shepard, R. N., (1982) "Psychological Review, Geometrical Approximations to the Structure of

Musical Pitch," *89*(4) 305-333. https://doi.org/10.1037/0033-295X.89.4.305

Smoorenburg, G. F., (1970) "Pitch Perception of Two-Frequency Stimuli," J. Acoust. Soc. Am. *48*,

924-942. https://doi.org/10.1121/1.1912232

Terhardt, E., (1974) "Pitch, consonance, and harmony," J, Acoust, Soc. Am. *55*, 1061-1069.

https://doi.org/10.1121/1.1914648

Wang, X. (2013) "The harmonic organization of auditory cortex," Front. Syst. Neurosci. 7:114.

https://doi: 10.3389/fnsys.2013.00114

Wightman, F. L., (1973) "The pattern-transformation model of pitch," J. Acoust. Soc. Am.*54*,

407-416. https://doi.org/10.1121/1.1913592