Real-time in vivo thoracic spinal glutamate sensing reveals spinal hyperactivity during myocardial ischemia

Siamak Salavatian[1,2]†, Elaine Marie Robbins[3]†, Yuki Kuwabara[1], Elisa Castagnola [3], Xinyan Tracy Cui [3,4,5]*, Aman Mahajan[1,3]*

[1]Department of Anesthesiology and Perioperative Medicine, University of Pittsburgh, Pittsburgh, PA, USA

[2] Department of Medicine, Division of Cardiology, University of Pittsburgh, Pittsburgh, PA, USA

[3] Department of Bioengineering, University of Pittsburgh, Pittsburgh, PA, USA

[4] Center for Neural Basis of Cognition, Pittsburgh, PA, USA

[5] McGowan Institute for Regenerative Medicine, Pittsburgh, PA, USA

†These authors contributed equally to this work

* Correspondence

Aman Mahajan, M.D., Ph.D., MBA.

Peter and Eva Safar Professor and Chair

Department of Anesthesiology and Perioperative Medicine

University of Pittsburgh School of Medicine

A-1305 Scaife Hall,3550 Terrace St

Pittsburgh, Pennsylvania 15261

Email address: mahajana@upmc.edu

X. Tracy Cui, Ph.D.

William Kepler Whiteford Professor Department of Bioengineering

University of Pittsburgh

5057 Bioscience Tower 3

3501 Fifth Ave.

Pittsburgh, PA 15261

Email:xic11@pitt.edu

Summary: Custom-made spinal glutamate sensing probe reveals the spinal hyperexcitation during
myocardial ischemia

Abstract

Myocardial ischemia-reperfusion (IR)-induced sympathoexcitation leads to ventricular arrhythmias and
sudden cardiac death. The spinal cord neural network plays a critical role in triggering these ventricular
arrhythmias. Thus, assessing the spinal neural signaling and neurotransmitter activity during IR is essential
to understanding spinal control of ventricular excitability. In this study, we have developed a flexible
glutamate-sensing multielectrode array to evaluate in-vivo the spinal cord network activity in a large animal
model using amperometry. IR injury was induced by ligating the left anterior descending artery for 1hour,
followed by reperfusion. A glutamate sensing probe was inserted into the dorsal horn of the thoracic spinal
cord at the thoracic (T2-T3) level, where neural signals generated by the cardiac sensory neurons are
processed and provides sympathoexcitatory feedback to the heart. Using the glutamate sensing probe, we
have shown that the spinal neural network is excited during the IR, particularly after 15 mins of the onset
of the ischemia and remains elevated even during the reperfusion. The glutamate release signal is correlated
with the reduction in the cardiac myocyte activation recovery interval which is a surrogate for the action
potential duration, as well as dispersion of the repolarization which is a marker for increased risk of
arrhythmias. This study illustrates a new technique that is capable of measuring the spinal glutamate at
different levels of the spinal cord as a surrogate for the spinal neural network activity during cardiac
interventions that engage the cardio-spinal neural pathway.

INTRODUCTION

Myocardial ischemia-induced ventricular arrhythmias are the leading cause of sudden cardiac death (*1*). The cardiac autonomic nervous system (CANS) plays a key role in regulating cardiac function after myocardial ischemia(*2*). The autonomic balance between the sympathetic tone and parasympathetic tone when the heart is not stressed is the critical component of cardiac function regulation. When the heart is stressed, for instance during myocardial ischemia-reperfusion (IR) injury, the cardiac sensory neurons in the dorsal root ganglion transmit excitatory signals to the spinal cord. These excitatory signals are processed in the dorsal horn of the spinal cord and are translated to the activation of the sympathetic preganglionic neurons in the intermediolateral nucleus which results in the sympathoexcitation (*3, 4*). This sympathoexcitation is a necessary mechanism for the CANS to regulate the function of the heart during stress; however, if the cardiac stress persists, the excessive sympathoexcitation will cause autonomic imbalance that results in cardiac dysfunction. Autonomic imbalance is one of the main causes for the initiation and maintenance of the fatal arrhythmias (*5-10*).

It has been shown that short myocardial ischemia causes excitatory sensory response (*11*). However, it is not fully known how the cardiac sensory neurons respond to the longer myocardial ischemia (1 hr) and how the spinal cord neural network processes the cardiac sensory information. Myocardial ischemia has a different mechanism of action during different phases of ischemia which results in different sensory inputs to the spinal cord and hence different spinal cord network processing. Regional ischemia causes two phases of ventricular arrhythmia: i) Early phase which occurs between 5-7 mins after the coronary artery occlusion and results in mild intracellular and extracellular acidification and membrane repolarization, ii) the second phase happens between the 20-30 mins after the onset of myocardial ischemia while the ischemia-induced K^+ and pH changes are stable (*12*). It is therefore important to understand how the spinal cord is processing the cardiac sensory information at different levels of the spinal cord and at different time points during myocardial ischemia.

Glutamate serves as the major excitatory neurotransmitter that is released in the spinal cord (*13, 14*) and the its concentration can be used as a biomarker for the neural network activation level in the pathological state (*15*) but not the normal state due to the glutamate uptake mechanism (*16*). Some techniques have been tried to measure glutamate concentration in the spinal cord; for example, microdialysis was used to analyze glutamate concentrations in the pig spinal cord following aortic cross-clamping (*17*). However, a minimum amount of sample is needed for offline assay or HPLC analysis, which takes several minutes to be collected – in this case, one sample every 10 minutes (*18*). The resulting poor time resolution means that microdialysis does not provide time resolution sufficient to track the glutamate concentration change during IR events. Electrochemical glutamate detection with amperometry allows for sub-second time resolution. The current state-of-the-art glutamate electrochemical sensor is a ceramic microelectrode array consisting of a glutamate-sensitive electrode and a sentinel control electrode (*19*). We advance this technology by fabricating microelectrode arrays on a flexible SU-8 substrate for superior tissue integration (*20*). We also demonstrate decreased noise from movement artifacts with the flexible substrate, which is particularly important in a large preclinical animal model. Additionally, probes were fabricated with multiple glutamate sensing channels for simultaneous measurement across different laminae of the spinal cord. This is an important capability of multichannel sensing electrodes as different spinal cord laminae and nuclei process different information and have different functions (processing sensory information, motor neurons that innervate skeletal muscle for movement, preganglionic sympathetic neurons that innervate the paravertebral sympathetic chain to increase the sympathetic tone)(*21*). Further, therapeutic approach of spinal cord stimulation during myocardial ischemia-reperfusion injury has differential effects on spinal neurons in superficial lamina vs. deeper lamina (*22*). To study the impact of cardiac IR on the lamina-specific neural networks in the spinal cord or for potential optimization of neuromodulation therapies, it is undeniably essential to investigate the spinal neurotransmitter activity using multichannel sensing probes.

In this study, we have evaluated the spinal neural network activity during IR injury using a newly
developed custom-made flexible probe that is capable of measuring glutamate concentrations at different
levels of the spinal cord. The glutamate detection of the developed probe is almost instantaneous and can
measure the glutamate concentration continuously. Using this developed continuous spinal glutamate
measurements, we have shown that, the glutamate concentration increases during the myocardial ischemia
and reperfusion injury which causes sympathoexcitation and increases the risk of ventricular arrhythmias.
A large animal porcine model was used in this study due to its high translatability to humans in terms of
the cardiovascular system and the CANS.

RESULTS
Design of the flexible microelectrode array

The final microelectrode array (MEA) design is schematically represented in Figure 1A. The flexible
MEAs were successfully fabricated on the SU-8 flexible substrate following a direct-writing maskless
photolithography process (Fig. 1B). SU-8 has demonstrated excellent chronic performance as a neural
probe substrate(23-27). The device is composed of a singular shank (140 μm wide and ~16 μm thick) with
6x 100 μm diameter platinum electrode sites, organized into two groups of three electrodes each. The total
length of the shank is 6.5 mm to easily target the spinal cord dorsal horn and IML of the pig. An anchor
hole was patterned at the shank tip for the insertion of a 50 μm sharpened tungsten shuttle, which facilitates
the handling and implantation of the flexible device into the spinal cord (Fig. 3C). The flexible MEAs are
connected to the PCB using a zero-insertion force (ZIF) connector (Fig. 3A), to be interfaced with
characterization and recording systems. The PCB is sealed with epoxy to protect the connection from fluids
and blood exposure. The final MEA is highly flexible and can be bent significantly without breaking (Fig.
3A).
Electrochemical impedance spectroscopy (EIS) of all 6 electrode sites on three arrays (for a total
of 18 sites) show excellent reproducibility both between sites on a single MEA as well as across multiple
MEAs (Fig. 1C). The average impedance at 1 kHz of these sites was 36 ± 3 kΩ (mean $\pm$ SEM). Similarly,
cyclic voltammetry measurements between -0.6 and 0.8 V vs. Ag/AgCl, measured at 0.1 V/s have an
average charge storage capacity of 3.5 ± 0.3 μC (Fig. 1D)

Sensitivity of the glutamate electrodes

The MEAs were modified to be glutamate-sensitive electrodes. A schematic of the layers on the electrode
sites is shown in Figure 2A. The final MEA contains electrode sites that are either sensitive to glutamate
(the GluOx sites) or are controls (the sentinel sites). In a GluOx site, GluOx bound to the surface of the
electrode reacts with glutamate to produce H_2O_2, which is oxidized at the Pt electrode surface to produce
a current. The sentinel sites are not sensitive to glutamate but will react to ambient H_2O_2 in the tissue,
along with any other potential interferences. The final glutamate-derived signal is calculated as the
difference between the GluOx sites and the sentinel site. The two types of sites are constructed
identically, except the sentinel sites do not have GluOx crosslinked on their surface. Full details of sensor
construction are in the Methods; to briefly summarize the process, a size-exclusion screening layer of m-
phenylenediamine (mPD) was first electrochemically deposited onto the surface. Subsequently, either a
glutamate oxidase (GluOx)-containing layer, or a control sentinel layer was carefully drop casted under a
microscope onto each electrode site and allowed to crosslink overnight.
The final electrodes were highly selective to their desired target. Both the GluOx and sentinel
sites have no response to the main interfering compound, ascorbic acid. However, the GluOx sites (red,
green, and blue traces) respond robustly to repeated addition of glutamate to the solution and as expected,
the sentinel site (purple) does not respond (Fig. 2B). However, as expected, every site responds to H_2O_2.
When calibrated, the GluOx sites show sensitivity to glutamate across a wide range of concentrations
between 10 μM and 1 mM (blue, green, and red traces), while the sentinel site shows no response (purple
trace) (Fig 2C). All final in vivo concentrations presented here were calculated using a post-calibration

curve constructed by exposing the electrodes to standard concentrations of glutamate after the electrode
was removed from the spinal cord.
176   To validate the sensing capabilities in tissue, we inserted the electrodes into a piece of pig spinal
177 cord that had been carefully dissected from the animal. A needle was inserted near the electrode, and a
178 series of injections of vehicle phosphate-buffered saline (PBS) or glutamate were performed. As
179 expected, the electrodes did not respond to the vehicle; however, there was a robust response to the
180 injection of glutamate (Fig. 3G).
181   We have also tested the sensing capabilities of our probe in a sham condition and observed a
slight decrease in the detected current over 2 hours of recordings (Fig. S2A). The sham recording was
performed after a stabilization period of at least 30 minutes. We attribute this slow, linear decrease in
current to the decrease in sensitivity of our electrode over time, which could be the result of enzyme
degradation or biofouling. We have corrected this by fitting a line to the first 30 minutes of the baseline
data and then subtracting the slope of the fitted line to correct the data for the slight decrease in sensitivity
over time in vivo (Fig. S2A, S2B). Figure S2C shows the glutamate concentration changes during the 30
minutes baseline after the correction of the loss of glutamate sensitivity.
189
Performance of the flexible probe during movement
Because ambient movement due to breathing, heartbeat, etc. is increased in a large animal model, we
fabricated the MEA on a highly flexible SU-8 substrate. Flexible probes have been demonstrated to
reduce inflammatory tissue responses caused by micromotion of the brain following implantation in
rodents (*20*). However, in a large animal model, continuous passive movements caused by a biological
process such as breathing are much more dramatic. The spinal cord itself also presents an additional
challenge; touching the spinal cord can inadvertently stimulate neuron firing resulting in muscle spasms.
These spasms are common during electrode insertion and may damage the tissue and break silicon-based
probes that are brittle and fragile, like those we have used previously to study the spinal cord (*3, 4*). Our
previous experience with stiff probes led us to believe that a flexible probe will be more likely to better
accommodate the animal's movement.
201   To investigate this, we inserted both a flexible and a stiff probe into the spinal cord. The stiff
probe was a commercially available probe purchased from Neuronexus with 30 μm platinum electrode
sites, while the flex probe was a specially fabricated MEA that also had 30 μm platinum electrode sites
(compared to the 100 μm sites used in the rest of this work) for an accurate comparison to the stiff probe.
Sites from both electrodes were connected to a multichannel potentiostat for simultaneous amperometric
measurements at 0.7 V vs. Ag/AgCl reference. After a 30-minute stabilization time, the spinal cord was
lightly brushed with a cotton swab to induce a mild muscle spasm. This movement induced a sudden and
dramatic change in the baseline of the stiff probe (red trace) but not in the baseline of the flex probe (blue
trace) (Fig. 3E) This test was repeated multiple times with a five-minute re-stabilization period between
each trial (Fig. S1B). The response of the stiff probe decreased with each subsequent spasm, presumably
due to damage and loss of tissue cohesion around the stiff probe.
212
Optimization of the spinal cord insertion procedure
While flexible probes can move with the tissue during micromotions and improve device-tissue
integration(20, 28-30), insertion of these flexible devices into the tissue becomes more difficult(31-33)
. Flexible materials often are too soft to penetrate tissue on their own, so shuttle systems are common to
aid insertion (20, 27, 34, 35).
To that end, we compared two insertion methods from the literature to determine the optimal procedure
for neurochemical sensing in the spinal cord. In one scheme, a 50 μm diameter tungsten guide wire was
threaded through a 100 μm insertion guide hole at the tip of the SU-8 shank. The wire was then glued to
the MEA with 30% polyethylene glycol (PEG) (Fig. 3C). In the second procedure, the hole in the SU-8
shank was 40 μm wide, and a 50 μm SU-8 wire was sharpened by applying 5 V vs. Ag/AgCl and
repeatedly dipping it into a solution of 5 M potassium hydroxide to etch the surface. The final needle-like
wire was threaded through the insertion hole without the PEG glue (Fig. 3C).

When comparing the PEG-assisted and tungsten shuttle insertion methods, the PEG-assisted
insertion technique (red, n=8 electrode sites) has a signal several orders of magnitude lower than the
sharpened-shuttle method (blue, n=4 electrode sites) (Fig. 3F). Figure S1A shows the mean ± SEM of all
functional, glutamate-detecting electrodes (n=12 GluOx sites in n=6 pigs).

Spinal cord hyperactivity during myocardial ischemia
Glutamate signaling was measured as a biomarker for spinal cord neural activity. We measured the
glutamate concentration during the 30 minutes of baseline recording (in 5 mins intervals) and we did not
see a difference in glutamate concentration during these 30 minutes (n=12 electrodes, P= 0.61, Friedman
test) (fig. S2C). Glutamate percentage change from baseline was assessed during the baseline, every 15
minutes of ischemia, and the 15 minutes of reperfusion. The percentage change in glutamate was not
significant during the first 15 minutes of the LAD ischemia (BL: -0.03 [-1.85, 1.90] % to LAD15: 11.04
[4.75, 17.94] %, P= 0.63) Glutamate concentration started to increase significantly between the 15-30
minutes of ischemia (BL: -0.03 [-1.85, 1.90] % to LAD30: 24.40 [12.81, 259.77] %, P= 0.03) (Fig. 5A,
5C). Glutamate augmentation persisted during the rest of the myocardial ischemia during 30-45 minutes
(BL: -0.03 [-1.85, 1.90] % to LAD45: 53.788 [19.46, 285.46] %, P= 0.0002) and 45-60 minutes of LAD
(BL: -0.03 [-1.85, 1.90] % to LAD60: 69.64 [29.75, 205.63] %, P< 0.0001). Glutamate concentration did
not decrease during the 15 minutes of the reperfusion and was still elevated compared to the baseline (BL:
-0.03 [-1.85, 1.90] % to Reperfusion: 69.35 [36.87, 159.02] %, P <0.0001) (Fig. 5A, 5C).

Shortening of the activation recovery interval during IR injury

The activation recovery interval (ARI) is a surrogate for the action potential duration (Fig. 4D). The action
potential duration becomes shorter when the sympathetic tone is high and therefore the ARIs shortens
during the sympathoexcitation. In this study, the ARIs were shortened (285.06 ± 15.75 ms to 256.08 ± 13.88
ms, P=0.01) during myocardial ischemia (Fig. 6B) which shows the augmentation in the sympathetic tone.
The ARI shortening occurred within the first 5 minutes of the ischemia and persists until the termination of
the myocardial ischemia (Fig. 5B, 5C). The sympathetic activation was not mitigated during the reperfusion
as the ARI was still shorter during the reperfusion compared to the baseline (285.06 ± 15.75 ms to 260.29
± 19.01 ms, P=0.04) (Fig. 6B).

Increased dispersion of repolarization during the myocardial ischemia
Dispersion of repolarization (DOR) is a potential marker for arrhythmogenicity. Increased DOR indicates
an increased arrhythmia potential. The DOR started to increase within the first 5 minutes of the
myocardial ischemia (Fig. 5B, 5C) and stayed elevated by the end of myocardial ischemia (296.42 ±
42.18 ms^2 to 2051.48 ± 337.91 ms^2, P= 0.01) (Fig. 6C). The DOR was not decreased during the 15 mins
reperfusion (296.42 ± 42.18 ms^2 to 2039.72 ± 435.00 ms^2, P=0.02) and therefore the risk of arrhythmia
events was still high during the reperfusion (Fig. 6C).

Increased arrhythmias during myocardial ischemia
Arrhythmia scores were measured during myocardial ischemia and reperfusion to evaluate the occurrence
of premature ventricular contractions and ventricular arrhythmias. The arrhythmia score was augmented
during ischemia (0 ± 0 to 1.17 ± 0.31, P=0.02) and reperfusion (0 ± 0 to 2.00 ± 0.37, P=0.005) (Fig. 6D).

Hemodynamic changes during myocardial ischemia
Heart rate and left ventricular end-systolic pressure were assessed during the myocardial ischemia and 15
mins reperfusion. Heart rate increased during the myocardial ischemia (104.76 ± 4.49 bpm to 110.31 ±
4.99 bpm, P=0.03) and reperfusion (104.76 ± 4.49 bpm to 118.88 ± 5.67 bpm, P= 0.04) (Fig. 6E). Left
ventricular end-systolic pressure decreased during the ischemia (109.23 ± 8.84 mmHg to 96.61 ± 7.08
mmHg, P=0.01). There was not a significant change in left ventricular end-systolic pressure from baseline
to reperfusion (109.23 ± 8.84 mmHg to 98.15 ± 7.08 mmHg, P=0.30) (Fig. 6F).

DISCUSSION

In this study, we have investigated the effect of myocardial ischemia on the neural processing at the T2-T3
level of the spinal cord by measuring the spinal dorsal horn glutamate concentration via amperometry
technique. We have developed a new tool with a flexible probe to measure the spinal glutamate signaling
in-vivo in a large animal model. Then we used this developed technique to measure the spinal glutamate
signaling during myocardial ischemia and reperfusion which causes ventricular arrhythmias that are a
leading cause of death. We have shown that the glutamate concentration increases during the myocardial
ischemia, and it persists during the reperfusion and is associated with sympathoexcitation and increases in
myocardial substrate excitability.

Flexible glutamate sensing probe

A flexible probe was developed in this study for minimizing probe insertion trauma to the spinal cord during
the glutamate probe insertion. Several studies have evaluated the effect of probe stiffness on neuronal tissue
injury, and they support the use of softer and more flexible probes (*20, 28*). Further studies confirmed the
advantage of using flexible probes in terms of their capabilities to move with the neural tissue during
micromotion that might be caused by cardiac pulsation or respiration (*20, 28, 36, 37*). In the current study,
we have also shown that the flexible probe is resistant to movement artifacts during larger movements
caused by other stimuli. This demonstrates the value of a flexible probe in large animal models, where
motion caused by breathing, heartbeat, etc. is more intense than in a rodent model. Large tissue
displacements around a stiff probe can cause damage to both the tissue and the electrode itself; a flexible
probe can minimize these effects (*38*). Another study investigated the effect of probe stiffness in modulating
the glial cells and their results indicate that glial cells respond greater to mechanical signals that are caused
by stiff probes. (*39*). The flexible probe design provides a great opportunity for more reliable and robust
recordings without causing significant trauma in the neural tissue. Though isolated use of flexible glutamate
sensors has been reported as proof-of-concept in rodents by a few investigators, we provide a
comprehensive testing and in-vivo study of the sensors in a large pre-clinical disease model (*40-44*). The
flexible glutamate sensors were successfully produced with the fabrication process described in Figure 1,
followed by the coating procedure illustrated in Figure 2. The flexible sensors demonstrated selectivity to
glutamate as well as sensitivity in the range of the concentration detected in vivo. To our knowledge, this
is the first report of a flexible glutamate sensor used in a large animal model. An experiment to analyze the
effect of physical motion on the electrode determined that the dramatic motion artifacts created by
movement in a stiff probe were almost completely absent in a flexible probe (Fig. 3E).

One of the major drawbacks of flexible sensors in vivo is the difficulty of inserting a probe that
may buckle and fail to penetrate the neural tissue. Stiff shuttles or temporary stiffening approaches are often
employed to aid in probe insertion into tissue and prevent buckling (*20, 27, 29, 45, 46*). Here, we compared
two common techniques from the literature: a sharpened shuttle "needle-and-thread" approach, and PEG-
assisted insertion, where PEG is used as a dissolvable glue to attach the flexible probe to the stiff shuttle.
We found that the sharpened shuttle approach resulted in a much more robust detection of glutamate. We
hypothesize this to be the result of two phenomena. First, adhering the flexible probe to the shuttle required
a very thick layer of PEG that may not be effectively washed away for hours *in vivo*. The glutamate sensors
require glutamate to be able to diffuse to and come into contact with the coating surface to react. While
PEG is very soluble in an aqueous environment, residual PEG may still cover part of the sensing surface,
which will decrease the effectiveness of the sensor. Second, the PEG-assisted insertion was much more
difficult. In our hands, inserting the electrode with the PEG-assisted method frequently required several
attempts. This may have resulted in both damage to the tissue as well as damage to the enzyme coatings on
the sensor. The sharpened shuttle approach, therefore, resulted in more robust signals due to the ease of
insertion and a more pristine electrode surface.

Our multielectrode array sensor was fabricated with 6 total channels – 3 glutamate sensing sites,
and 3 redundant sentinel sites. By performing measurements with a 4-channel multi-potentiostat, we
monitored the 3 glutamate-sensitive channels and one sentinel channel simultaneously. At different sites,
we detected different concentrations of glutamate, possibly indicating local spatially-resolved concentration
differences, and at some locations, we detected no glutamate at all despite the post-calibration confirming
the sensor is functional (Fig. S2D, S2E). Future experiments to correlate the position of each electrode to
the detected glutamate concentration will provide valuable insight into lamina-specific glutamatergic
activity in the spinal cord.

Sympathoexcitation and Myocardial Ischemia-induced Ventricular Arrhythmias

A large animal porcine myocardial ischemia-reperfusion model was used in this study. This model is well-
established and studied by our group and others and it closely mimics the myocardial ischemia-reperfusion
condition in humans. The myocardial ischemia was created and confirmed by at least 9 (out of 56) ST-
segment elevated leads (Fig. 4C). The ischemia-reperfusion injury increased the sympathoexcitation which
was manifested by the shortening of the ARIs (*4, 47*). IR also increased the DOR which is associated with
higher myocardial electrical heterogeneity and increased risk of arrhythmias (*47-50*). In this study, two pigs
(out of 8) experienced ventricular tachyarrhythmias during myocardial ischemia and needed to be
defibrillated. The occurrence of VT in these two pigs provides clear evidence of the risk of fatal ventricular
arrhythmias during our large animal myocardial ischemia model. Furthermore, we have shown that the
arrhythmia score has significantly increased during myocardial ischemia. The arrhythmia score is
calculated based on the number of ventricular arrhythmias, including premature ventricular contractions
and ventricular tachycardia or fibrillation episodes.

Spinal hyperexcitation during myocardial ischemia-reperfusion injury

Mechanosensitive, chemosensitive, and multimodal afferent neurons transduce myocardial ischemia. These
excitatory sensory signals are transmitted to the dorsal root ganglion and vagal nodose ganglia (*11, 51*).
The dorsal root ganglia neurons transmit this afferent excitatory signal to the spinal dorsal horn neurons
which will be processed in the spinal dorsal horn neurons and will activate the sympathetic preganglionic
neurons in the IML region. Glutamate is a critical neurotransmitter for these spinal excitatory synaptic
transmission (*13, 14*). Although the uptake mechanism makes it hard to detect the glutamate during the
normal state (*16*), it is possible to measure the extracellular glutamate concentration during the
hyperexcitation in a pathological state (*15*). In this study, we have simultaneously recorded the spinal
glutamate signaling and cardiac electrophysiological signals in-vivo to provide evidence that the spinal
glutamate signaling can be used as a biomarker for acute myocardial ischemia severity detection. We have
shown that the glutamate concentration increases significantly between 15-30 mins of the myocardial
ischemia and it stays elevated even during the reperfusion. The timing of the significant augmentation of
the spinal glutamate correlates with the second phase of ventricular arrhythmias during myocardial ischemia
between 20-30 mins after the onset of myocardial ischemia while the ischemia-induced K^+ and pH changes
are stable (*12*).

Limitation

Our study has some limitations that need to be addressed for clinical translation. First, neural activity can
be suppressed in studies performed on an anesthetized subjects. While we used alpha-chloralose as an
anesthetic agent to minimize the effect of the anesthesia on the excitation of neurons, there might still be
some suppression effects on the neural network. In this study, we have used acute implants for a proof-of-
concept study. Future studies are needed to use this technique in a chronically implanted model and evaluate
the efficacy of the probes in a chronically implanted model. We have shown that the glutamate increases
significantly during the 15-30 minutes of ischemia.

MATERIALS AND METHODS

Flexible Microelectrode Arrays Fabrication

A 4-in Si wafer with a 100 µm thick SiO_2 layer (University Wafer Inc. Boston, MA, USA) was first cleaned
with acetone, isopropanol, and DI water sequentially. The wafer was then dried with a N spray gun, heated
on a hot plate at 150°C for 5 min, and treated with O_2 plasma using a reactive ion etcher (RIE, Trion
Phantom III LT) for 2 min at 300 mTorr pressure and 150 W power. The cleaned wafer was spin-coated
with SU-8 2015 (MicroChemicals, Ulm, Germany) at 5000 rpm for 1 min and soft baked at 65°C for 3 min
and 95°C for 5 min. Then, the wafer was exposed using a direct-writing maskless aligner (MLA, MLA100
Heidelberg Instruments) with a dose of 350 mJ/cm^2 to define the bottom insulation layer. After exposure,
the wafer was first post-baked at 65°C for 3 min and 95°C for 3 min, then developed using an SU-8
developer (MicroChemicals) for 1 min and cleaned with isopropanol and DI water. The patterned SU-8 was
subsequently hard baked at 200°C, 180°C, and 150°C for 5 min each and allowed to cool down below 95°C.

After cleaning, the wafer was spin-coated with an AZ P4620 photoresist (MicroChemicals) at 5300 rpm for
1 min and baked at 105°C for 5 min, as previously described (1). After soft baking, the wafer was exposed
using MLA with a dose of 700 mJ/cm^2, then developed using an AZ400k 1:4 developer (MicroChemicals),
cleaned with water, rinsed, and dried by N_2 gas flow. A 10 nm Ti adhesion layer, 100 nm Au layer, and 40
nm Pt layer were evaporated on the wafer using an electron-beam evaporator (Plassys MEB550S), and then
the metal was lifted off in acetone to define the metal electrodes and interconnections. A top insulation
layer of SU-8 2015 was then spin-coated at 5000 rpm for 1 min, soft based at 65°C for 3 min and 95°C for
5 min, and photolithography patterned, using MLA with a dose of 350 mJ/cm^2 to expose the connection
pads and to define the top insulation layer. After post-baking and a development procedure with the SU-8
developer, the wafer was cleaned with isopropanol and DI water, hard baked at 200°C, 180°C, and 150°C
for 5 min each, and allowed to cool down below 95°C. The MEAs were lifted off from the wafer using a
buffered oxide etchant (1:7) in an acid hood for about 4 h. An anchor hole was also patterned at the shank
tip to facilitate the insertion of a 50 µm tungsten shuttle, to enable the handling and penetration of the
flexible device into the spinal cord. Figure 1B shows the schematic of the flexible MEA fabrication.

Glutamate sensor preparation

Fabricated electrodes were first characterized by electrochemical impedance spectroscopy (EIS)
and cyclic voltammetry (CV) using an Autolab potentiostat (Metrohm, Herisau, Switzerland) with Nova
2.1.4 software to determine baseline functionality. EIS was measured from 10^5 to 1 Hz, with 10 frequencies
recorded per decade using a sine wave oscillation and a 0.01 V RMS voltage. CVs were scanned between
-0.6 V and 0.8 V vs. an Ag/AgCl reference at 0.1 V/s.

Glutamate electrodes were prepared as described previously (*19*). To prepare the sensors, the Pt
electrode sites were first cleaned by immersing them in 0.05 M H_2SO_4 (Fisher Scientific, Pittsburgh, PA,
USA) and scanning from -0.35 V to 1.5 V at 1 V/s for 100 cycles. A screening layer of m-phenylenediamine
(mPD, Sigma-Aldrich) was electrodeposited onto the electrode sites by immersing the electrodes in a 10
mM solution of mPD in 1x phosphate buffered saline (PBS) and applying 0.7 V for 20 minutes. Then, 1 µL
of an enzyme solution containing 1 U glutamate oxidase (Cosmo Bio USA, Carlsbad, CA, USA), 13.7 mg
bovine serum albumin (Fisher Scientific), 6.7 µL glutaraldehyde (Sigma-Aldrich) in 1 mL DI water was
drop-casted onto 3 of the 6 electrode sites. These sites became the glutamate-sensitive sensor sites. Figure
2A shows a schematic of the electrode layers. A control solution lacking glutamate oxidase was dropped
onto the remaining 3 electrode sites; these sites became the sentinel control sites.

Glutamate was detected amperometrically at 0.7 V vs. Ag/AgCl as the difference between the
glutamate sensor sites and the sentinel control sites using a CH Instruments 1430 multichannel potentiostat
(CH Instruments, Austin, TX, USA). To evaluate sensor functionality and sensitivity, electrodes were
calibrated before and after use in standard concentrations of glutamate. In vivo, three glutamate-sensitive
sites and one sentinel site were monitored simultaneously. A calibration curve was constructed from the

post-calibration standards and used to convert detected in vivo current into concentration. To prepare
reference electrodes for in vivo use, a silver wire was coated with silver chloride by immersing it into a 3
M solution of KCl and applying 4 V for 3 min.

Animal Preparation

The study protocol was approved by the University of Pittsburgh Institutional Animal Care and Use
Committee (IACUC). All experiments were performed in compliance with the National Institution of
Health *Guide for the Care and Use of Laboratory Animals*.

Four male and four female Yorkshire pigs (44±2 kg) were used to evaluate the glutamate sensing probe
performance and investigate the glutamate release probe profile during myocardial ischemia and
reperfusion injury.

Combination of Tiletamine–Zolazepam (4 mg/kg, intramuscular) and Xylazine (2 mg/kg, intramuscular)
was used to sedate the animal. The animals were given inhaled isoflurane 3-5% via a nose cone. When the
animal was completely sedated and anesthetized, the animal was intubated and mechanically ventilated.
After intubation, the anesthesia was reduced to 2-4% of inhaled isoflurane. General anesthesia was
maintained with the isoflurane until the end of the preparation and then was switched to alpha chloralose
(50 mg/kg initial bolus followed by a 20 mg/kg/h continuous infusion). Alpha chloralose limits the impact
of anesthesia on the cardiac autonomic nervous system and cardiac myocardial excitability (*3, 4, 49, 52*).
All animals were completely anesthetized during the whole procedure and the anesthesia level was adjusted
throughout the experiment by monitoring corneal reflex, jaw tone, and hemodynamic indices. The animal
temperature was maintained using water heating pads (T/PUMP; Gaymar Industries, Orchard Park, NY).

Heart rate, blood pressure, end-tidal carbon dioxide, and blood oxygen level were monitored continuously
during the procedure. Arterial blood gas was tested hourly, or more frequently to prevent acid-base
disorders, and ventilation rate/volume adjustment, or administration of sodium bicarbonate was performed
as needed.

Electrocardiogram, systemic blood pressure, and left ventricular pressure were recorded using the Prucka
CardioLab recording system (GE Healthcare, USA) and Millar system (ADInstruments, USA).

Carotid and femoral arteries, as well as external jugular and femoral veins, were catheterized for blood
pressure monitoring and drug administration, respectively.

To expose the spinal cord, laminectomy was performed in these animals in the prone position. Upon
completion of the laminectomy, the animals were switched to the supine position to perform the sternotomy
procedure. Following sternotomy, the sternum was cauterized to avoid bleeding. The pericardial sac was
cut and secured to the sternum using sutures. Once the heart was exposed, a Prolene suture was placed
around the left anterior descending artery after its second diagonal branch. A nylon mesh epicardial sock
electrodes were placed around the heart and a Millar catheter (Millar, USA) was placed in the left ventricle
through the carotid artery.

The animals were placed in the lateral position to have access to both the heart and spinal cord to perform
the myocardial ischemia intervention and the glutamate sensing probe insertion and recording.

At the end of the data collection protocol, animals were euthanized by inducing ventricular fibrillation via
injection of potassium chloride under deep anesthesia.

Experimental Protocols

Glutamate was detected in vivo using a 3-electrode setup. The reference electrode was a silver wire coated
with silver chloride inserted into the muscle of the pig near the working electrode insertion site (*53*). A
metal retractor was utilized as a counter electrode. Following 30 mins stabilizing period after the glutamate
probe insertion, myocardial ischemia was performed for one hour by ligating the suture that was placed
around the LAD. Two animals experienced ventricular arrhythmias during the 1-hour myocardial ischemia

and the protocol could not be completed in these two animals. The suture was released after the 1-hour
myocardial ischemia. Heart rate, systemic blood pressure, left ventricular systolic pressure, left ventricular
contractility, activation recovery interval, dispersion of the repolarization, and glutamate concentration
were recorded during the baseline, myocardial ischemia, and reperfusion.

Hemodynamics Assessment

The lead II ECG was used to assess the heart rate during the protocol. Blood pressure was measured using
the pressure transducer that was connected to the femoral arterial sheath. Left ventricular pressure was
measured via a 5 French SPR-350 Millar Mikro-Tip pressure transducer catheter (Millar Instruments,
Houston, TX) was inserted into the left ventricle and connected to an MPVS Ultra Pressure-Volume Loop
System (Millar Instruments, Houston, TX). Left ventricular end-systolic pressure as well as left ventricular
contractility (dP/dt max) were calculated using the left ventricular pressure signal. The hemodynamics
parameters were analyzed using the Spike2 program (Cambridge Electronic Design) and (LabChart
software; ADInstruments, Colorado Springs, CO)

Activation Recovery Interval Analysis

A 56-electrode nylon mesh sock electrode was made using 0.2 mm silver wires and it was placed around
the heart to measure the epicardial unipolar electrograms using a Prucka CardioLab electrophysiology
mapping system (GE Healthcare, Fairfield, CT) (Fig. 4D). Unipolar electrograms were filtered (0.05-
500Hz) with the GE CardioLab System (*54*). Activation and repolarization time were detected using
customized software (iScalDyn, University of Utah, Salt Lake City, UT), and the activation recovery
intervals which is the difference between the repolarization and activation times were calculated (*55*). The
activation recovery interval is a surrogate of local action potential duration (*56, 57*). Excessive sympathetic
outflow shortens the ARIs and action potential duration.

Dispersion of Repolarization

Dispersion of repolarization is defined as the variance of ARI among all 56 leads. Greater dispersion is
associated with higher arrhythmia risk and therefore higher mortality.

Arrhythmia score

We have calculated the arrhythmia score during the baseline, myocardial ischemia, and reperfusion to
evaluate the arrhythmogenicity during ischemia-reperfusion injury. The arrhythmia score was calculated
based on the following formula:(*58*)

0: <10 Premature ventricular contractions (PVCs), 1: 10–50 PVCs or 1 episode of VT or both, 2: >50 PVCs
or >1 episode of VT or both, 3: SVF or 1 episode of NVF, 4: 2–4 episodes of NVF, 5: >4 episodes of NVF.

SVT (ventricular tachycardia) and SVF (ventricular fibrillation) denote the ventricular arrhythmias that
terminated spontaneously and NVT (ventricular tachycardia) and NVF (ventricular fibrillation) denote the
ventricular arrhythmias that did not terminate spontaneously.

Statistical Analysis

For the normal paired data, paired t-test was performed. When the data did not pass the Shapiro-Wilk
normality test, the Wilcoxon test was performed. All figures were created using GraphPad Prism software
(version 8, GraphPad Software Inc, San Diego, CA) or MATLAB (2019 version, MathWorks). A P value

≤ 0.05 was considered statistically significant. Data are presented as median (25th, 75th percentiles) or
mean ± SEM.

Conflict of Interest

The authors declare that the research was conducted in the absence of any commercial or financial
relationships that could be construed as a potential conflict of interest.

Author Contributions

S.S., E.R., X.T.C, and A.M. conceived and designed research; E.C fabricated the flexible probe. S.S, Y.K,
E.R, and E.C conducted animal experiments; S.S, E.R, and Y.K. analyzed data. S.S and E.R drafted the
manuscript and prepared figures; S.S, E.R, Y.K, E.C, X.T.C, and A.M interpreted the results of the
experiments; All authors reviewed and approved the final version of the manuscript.

Funding

The study is funded by NIH R01 HL136836, NIH R01 NS110564, and NIH R21 DA049592.

Siamak Salavatian is supported by the Competitive Medical Research Fund by University of Pittsburgh.

Elaine Robbins is supported by National Institute of Neurological Disorders and Stroke T32 NS086749
Training Grant

Xinyan Tracy Cui is supported by NIH R01 R01NS110564, R21DA049592

Aman Mahajan is supported by NIH R01 HL136836 and NIH R44 DA049630.

Acknowledgments

We thank Madison Fisher, Adrian Zalewski, and May Yoon Pwint for their technical assistance.

REFERENCE
1.   R. J. Myerburg, M. J. Junttila, Sudden cardiac death caused by coronary heart disease.
Circulation **125**, 1043-1052 (2012).
2.   J. A. Armour, Myocardial ischaemia and the cardiac nervous system. *Cardiovasc Res* **41**, 41-54
(1999).
3.   E. A. Dale *et al.*, Spinal cord neural network interactions: implications for sympathetic control of
the porcine heart. *Am J Physiol Heart Circ Physiol* **318**, H830-H839 (2020).
4.   Y. Omura *et al.*, Spinal Anesthesia Reduces Myocardial Ischemia-triggered Ventricular
Arrhythmias by Suppressing Spinal Cord Neuronal Network Interactions in Pigs. *Anesthesiology*
134, 405-420 (2021).
5.   D. V. Exner *et al.*, Electrical storm presages nonsudden death: the antiarrhythmics versus
implantable defibrillators (AVID) trial. *Circulation* **103**, 2066-2071 (2001).
6.   M. Vaseghi *et al.*, Cardiac sympathetic denervation in patients with refractory ventricular
arrhythmias or electrical storm: intermediate and long-term follow-up. *Heart Rhythm* **11**, 360-366
(2014).
7.   M. Vaseghi, K. Shivkumar, The role of the autonomic nervous system in sudden cardiac death.
Prog Cardiovasc Dis **50**, 404-419 (2008).

8.   M. J. Shen, D. P. Zipes, Role of the autonomic nervous system in modulating cardiac
arrhythmias. *Circulation research* **114**, 1004-1021 (2014).
9.   K. Fukuda, H. Kanazawa, Y. Aizawa, J. L. Ardell, K. Shivkumar, Cardiac innervation and sudden
cardiac death. *Circulation research* **116**, 2005-2019 (2015).
10. J. A. Armour, Cardiac neuronal hierarchy in health and disease. *Am J Physiol Regul Integr Comp*
Physiol **287**, R262-271 (2004).
11. S. Salavatian *et al.*, Thoracic spinal cord neuromodulation obtunds dorsal root ganglion afferent
neuronal transduction of the ischemic ventricle. *Am J Physiol Heart Circ Physiol* **317**, H1134-
H1141 (2019).
12. W. E. Cascio, H. Yang, B. J. Muller-Borer, T. A. Johnson, Ischemia-induced arrhythmia: the role
of connexins, gap junctions, and attendant changes in impulse propagation. *J Electrocardiol* **38**,
55-59 (2005).
13. M. L. Mayer, G. L. Westbrook, The physiology of excitatory amino acids in the vertebrate central
nervous system. *Prog Neurobiol* **28**, 197-276 (1987).
14. K. K. Yung, Localization of glutamate receptors in dorsal horn of rat spinal cord. *Neuroreport* **9**,
1639-1644 (1998).
15. P. Inquimbert *et al.*, Peripheral nerve injury produces a sustained shift in the balance between
glutamate release and uptake in the dorsal horn of the spinal cord. *Pain* **153**, 2422-2431 (2012).
16. N. C. Danbolt, Glutamate uptake. *Prog Neurobiol* **65**, 1-105 (2001).
17. O. D. Saether *et al.*, Microdialysis of the spinal cord during thoracic aortic cross-claming in a
porcine model. *Spinal Cord* **28**, 153-157 (2000).
18. C. J. Watson, B. J. Venton, R. T. Kennedy, In Vivo Measurements of Neurotransmitters by
Microdialysis Sampling. *Analytical Chemistry* **78**, 1391-1399 (2006).
19. J. J. Burmeister, G. A. Gerhardt, Self-Referencing Ceramic-Based Multisite Microelectrodes for
the Detection and Elimination of Interferences from the Measurement of L-Glutamate and Other
Analytes. *Analytical Chemistry* **73**, 1037-1042 (2001).
20. L. Luan *et al.*, Ultraflexible nanoelectronic probes form reliable, glial scar-free neural integration.
Science Advances **3**, 1-9 (2017).
21. B. Rexed, The cytoarchitectonic organization of the spinal cord in the cat. *J Comp Neurol* **96**,
414-495 (1952).
22. K. Howard-Quijano *et al.*, Spinal Cord Stimulation Reduces Ventricular Arrhythmias by
Attenuating Reactive Gliosis and Activation of Spinal Interneurons. *JACC Clin Electrophysiol* **7**,
1211-1225 (2021).
23. A. Weltman, J. Yoo, E. Meng, Flexible, penetrating brain probes enabled by advances in polymer
microfabrication. *Micromachines* **7**, 180 (2016).
24. K. V. Nemani, K. L. Moodie, J. B. Brennick, A. Su, B. Gimi, In vitro and in vivo evaluation of SU-8
biocompatibility. *Materials Science and Engineering: C* **33**, 4453-4459 (2013).
25. F. He, R. Lycke, M. Ganji, C. Xie, L. Luan, Ultraflexible neural electrodes for long-lasting
intracortical recording. *Iscience*, 101387 (2020).
26. Z. Zhao *et al.*, Parallel, minimally-invasive implantation of ultra-flexible neural electrode arrays.
Journal of neural engineering **16**, 035001 (2019).
27. E. Castagnola *et al.*, Flexible Glassy Carbon Multielectrode Array for In Vivo Multisite Detection of
Tonic and Phasic Dopamine Concentrations. *Biosensors* **12**, (2022).
28. Z. J. Du *et al.*, Ultrasoft microwire neural electrodes improve chronic tissue integration. *Acta*
Biomater **53**, 46-58 (2017).
29. L. Luan *et al.*, Recent Advances in Electrical Neural Interface Engineering: Minimal Invasiveness,
Longevity, and Scalability. *Neuron* **108**, 302-321 (2020).
30. M. Lotfi Marchoubeh *et al.*, Miniaturized probe on polymer SU-8 with array of individually
addressable microelectrodes for electrochemical analysis in neural and other biological tissues.
Anal Bioanal Chem **413**, 6777-6791 (2021).
31. N. Geramifard *et al.*, Insertion mechanics of amorphous SiC ultra-micro scale neural probes. *J*
Neural Eng, (2022).
32. N. Sharafkhani, A. Kouzani, S. D. Adams, J. M. Long, J. O. Orwa, A Pneumatic-based
Mechanism for Inserting a Flexible Microprobe into the Brain. *Journal of Applied Mechanics*, 1-20
(2022).

33. S. Singh *et al.*, Modeling the Insertion Mechanics of Flexible Neural Probes Coated with
Sacrificial Polymers for Optimizing Probe Design. *Sensors (Basel)* **16**, (2016).
34. T. D. Kozai, A. S. Jaquins-Gerstl, A. L. Vazquez, A. C. Michael, X. T. Cui, Brain tissue responses
to neural implants impact signal sensitivity and intervention strategies. *ACS Chem Neurosci* **6**,
48-67 (2015).
35. K. Na *et al.*, Novel diamond shuttle to deliver flexible neural probe with reduced tissue
compression. *Microsyst Nanoeng* **6**, 37 (2020).
36. T. Stieglitz, H. Beutel, J.-U. Meyer, A flexible, light-weight multichannel sieve electrode with
integrated cables for interfacing regenerating peripheral nerves. *Sensors and Actuators A:*
Physical **60**, 240-243 (1997).
37. D. P. O'Brien, T. R. Nichols, M. G. Allen, in *Technical Digest. MEMS 2001. 14th IEEE*
International Conference on Micro Electro Mechanical Systems (Cat. No. 01CH37090). (IEEE,
2001), pp. 216-219.
38. B. A. Wester, R. H. Lee, M. C. LaPlaca, Development and characterization of in vivo flexible
electrodes compatible with large tissue displacements. *J Neural Eng* **6**, 024002 (2009).
39. P. Moshayedi *et al.*, The relationship between glial cell mechanosensitivity and foreign body
reactions in the central nervous system. *Biomaterials* **35**, 3919-3925 (2014).
40. T. N. H. Nguyen *et al.*, Facile fabrication of flexible glutamate biosensor using direct writing of
platinum nanoparticle-based nanocomposite ink. *Biosens Bioelectron* **131**, 257-266 (2019).
41. H. Cao, A.-L. Li, C. M. Nguyen, Y.-B. Peng, J.-C. Chiao, An Integrated Flexible Implantable
Micro-Probe for Sensing Neurotransmitters. *IEEE Sensors Journal* **12**, 1618-1624 (2012).
42. A. Weltin *et al.*, Polymer-based, flexible glutamate and lactate microsensors for in vivo
applications. *Biosens Bioelectron* **61**, 192-199 (2014).
43. A. Weltin, B. Enderle, J. Kieninger, G. A. Urban, Multiparametric, Flexible Microsensor Platform
for Metabolic Monitoring In Vivo. *IEEE Sensors Journal* **14**, 3345-3351 (2014).
44. B. Wang *et al.*, An implantable multifunctional neural microprobe for simultaneous multi-analyte
sensing and chemical delivery. *Lab Chip* **20**, 1390-1397 (2020).
45. H. N. Schwerdt *et al.*, Cellular-scale probes enable stable chronic subsecond monitoring of
dopamine neurochemicals in a rodent model. *Commun Biol* **1**, 144 (2018).
46. Z. Zhao *et al.*, Parallel, minimally-invasive implantation of ultra-flexible neural electrode arrays. *J*
Neural Eng **16**, 035001 (2019).
47. K. Howard-Quijano *et al.*, Spinal cord stimulation reduces ventricular arrhythmias during acute
ischemia by attenuation of regional myocardial excitability. *Am J Physiol Heart Circ Physiol* **313**,
H421-H431 (2017).
48. M. Vaseghi *et al.*, Modulation of regional dispersion of repolarization and T-peak to T-end interval
by the right and left stellate ganglia. *American Journal of Physiology-Heart and Circulatory*
Physiology **305**, H1020-H1030 (2013).
49. K. Howard-Quijano *et al.*, Effect of thoracic epidural anesthesia on ventricular excitability in a
porcine model. *Anesthesiology* **126**, 1096-1106 (2017).
50. M. Vaseghi, R. L. Lux, A. Mahajan, K. Shivkumar, Sympathetic stimulation increases dispersion
of repolarization in humans with myocardial infarction. *American Journal of Physiology-Heart and*
Circulatory Physiology **302**, H1838-H1846 (2012).
51. S. Salavatian *et al.*, Thoracic spinal cord and cervical vagosympathetic neuromodulation obtund
nodose sensory transduction of myocardial ischemia. *Auton Neurosci* **208**, 57-65 (2017).
52. S. A. Batul, B. Olshansky, J. D. Fisher, R. Gopinathannair, Recent advances in the management
of ventricular tachyarrhythmias. *F1000Res* **6**, 1027 (2017).
53. E. M. Robbins, E. Castagnola, X. T. Cui, Accurate and stable chronic in vivo voltammetry enabled
by a replaceable subcutaneous reference electrode. *iScience* **25**, 104845 (2022).
54. M. Vaseghi *et al.*, Modulation of regional dispersion of repolarization and T-peak to T-end interval
by the right and left stellate ganglia. *Am J Physiol Heart Circ Physiol* **305**, H1020-1030 (2013).
55. O. A. Ajijola *et al.*, Functional differences between junctional and extrajunctional adrenergic
receptor activation in mammalian ventricle. *Am J Physiol Heart Circ Physiol* **304**, H579-588
(2013).
56. C. K. Millar, F. A. Kralios, R. L. Lux, Correlation between refractory periods and activation-
recovery intervals from electrograms: effects of rate and adrenergic interventions. *Circulation* **72**,
1372-1379 (1985).

57.   M. Chinushi *et al.*, Correlation Between the Effective Refractory Period and Activation-Recovery
656   Interval Calculated From the Intracardiac Unipolar Electrogram of Humans With and Without dl-
657   Sotalol Treatment. *JAPANESE CIRCULATION JOURNAL* **65**, 702-706 (2001).
658   58.   M. J. Curtis, M. J. Walker, Quantification of arrhythmias using scoring systems: an examination of
659   seven scores in an in vivo model of regional myocardial ischaemia. *Cardiovasc Res* **22**, 656-665
660   (1988).

692
693 **Fig. 1. Electrodes design.** (**A**)Schematic of the probe design. (**B**) Graphic of the photolithography process. (**C**)
694 Electrochemical impedance spectroscopy (EIS) and phase angle of all 6 sites on 3 probes with high
695 reproducibility within electrodes and between electrodes. (**D**) CV of an electrode

Fig. 2. Glutamate sensor performance. (**A**) Schematic of how the glutamate sensors work. (**B**) Sensors in a stirred solution of PBS. Electrodes don't respond to additions of ascorbic acid. The glutamate sites respond to glutamate but not to the addition of ascorbic acid, while the sentinel electrode does not respond to both glutamate and ascorbic acid. All sites respond to hydrogen peroxide. (**C**) Calibration curve shows a wide range of activity for the glutamate sites and no activity for the sentinel.

739
Fig. 3. Performance of flexible probe. (A) Photo demonstrating the flexibility of the probe. **(B)** A photo of
the stiff Neuronexus probe. **(C)** Left: Tip of an electrode assembled with the sharpened tungsten. Right:
polyethylene glycol (PEG) assisted probe **(D)** A photo of the electrode inserted into the pig spinal cord. **(E)**
Data were recorded during motion artifacts using a stiff acute Neuronexus probe and our flex probe, both
inserted and recorded at the same time. **(F)** The sharpened shuttle method results in significantly more detected
glutamate in vivo due to the PEG covering the electrodes' surface. **(G)** Ex vivo injections of PBS and
glutamate into a spinal cord. The electrodes do not sense the PBS but the injected glutamate is sensed by the
glutamate sensor probe.

758
Fig. 4. Simultaneous in-vivo spinal glutamate and cardiac electrophysiological recordings. (A) Following
T1-T4 laminectomy, the glutamate sensing probe was inserted in the dorsal horn region of the spinal cord at
the T2-T3 level. **(B)** Myocardial ischemia was induced by ligating the suture that was placed around the left
anterior descending (LAD) coronary artery. Myocardial ischemia was confirmed by observing the ST-elevated
electrograms (EGM) in the ischemic region. LV/RV: left/right ventricle **(C)** Number of ST elevated leads
increased during myocardial ischemia (n =6 animals Pre-LAD vs. 6 animals during LAD, P = 0.031, Wilcoxon
test) **(D)** Following sternotomy, the 56-channel sock electrode was placed around the heart to record the
electrocardiogram. The activation recovery interval (ARI) was measured by subtracting the activation time
(AT) from the recovery time (RT).

773
Fig. 5. Simultaneous in-vivo spinal glutamate and cardiac electrophysiological recordings. (A)
Myocardial ischemia-reperfusion injury caused an augmentation in the percentage change of glutamate from
baseline (Friedman test, P <0.0001). Glutamate did not change during the first 15 minutes of the left anterior
descending (LAD) coronary artery occlusion (n = 12 electrodes Pre-LAD vs. 12 electrodes during LAD15, *P* =
0.63, Dunn's multiple comparisons test). LAD between 15-30 mins (n = 12 electrodes Pre-LAD vs. 12
electrodes during LAD15, *P* = 0.032, Dunn's multiple comparisons test), LAD between 30-45 mins (n = 12
electrodes Pre-LAD vs. 12 electrodes during LAD15, *P* = 0.0002, Dunn's multiple comparisons test), LAD
between 45-60 mins (n = 12 electrodes Pre-LAD vs. 12 electrodes during LAD15, *P* <0.0001, Dunn's multiple
comparisons test) and reperfusion (n = 12 electrodes Pre-LAD vs. 12 electrodes during LAD15, *P* <0.0001,
Dunn's multiple comparisons test) caused an increase in the percentage change of glutamate from baseline. **(B)**
Representative glutamate (Glu), activation recovery interval (ARI), and dispersion of repolarization (DOR)
response during LAD ischemia. **(C)** Glutamate and DOR increased during the LAD ischemia and reperfusion,
while the ARIs decreased during the ischemia-reperfusion injury.

787
788
Fig. 6. Physiological responses to the myocardial ischemia. (A) Left anterior descending (LAD) myocardial
ischemia (n = 12 electrodes Pre-LAD vs. 12 electrodes during LAD, P =0.0085, Dunn's multiple comparisons
test) and reperfusion (Rep) (n = 12 electrodes Pre-LAD vs. 12 electrodes during reperfusion, P <0.0001,
Dunn's multiple comparisons test) caused an increase in the percent change of the glutamate concentration
from baseline. **(B)** Activation recovery interval (ARI) was shortened during the LAD ischemia (n = 6 pig Pre-
LAD vs. 6 pigs during LAD, P = 0.041, Dunn's multiple comparisons test) and reperfusion (n = 6 pig Pre-LAD
vs. 6 pigs during reperfusion, P = 0.0078, Dunn's multiple comparisons test), demonstrating the
sympathoexcitation. **(C)** Dispersion of repolarization (DOR) increased during the LAD ischemia (n = 6 pig
Pre-LAD vs. 6 pigs during LAD, P = 0.0078, Dunn's multiple comparisons test) and reperfusion (n = 6 pig
Pre-LAD vs. 6 pigs during reperfusion, P = 0.041, Dunn's multiple comparisons test), demonstrating the higher
arrhythmogenicity. **(D)** Arrhythmia score increased during the LAD ischemia (n = 6 pig Pre-LAD vs. 6 pigs
during LAD, P = 0.022, Dunnett's multiple comparisons test) and reperfusion (n = 6 pig Pre-LAD vs. 6 pigs
during reperfusion, P = 0.0049, Dunnett's multiple comparisons test) as evidence of increased ventricular
arrhythmias. **(E)** Heart rate was increased during the LAD ischemia (n = 6 pig Pre-LAD vs. 6 pigs during
LAD, P = 0.033, Dunnett's multiple comparisons test) and reperfusion (n = 6 pig Pre-LAD vs. 6 pigs during
reperfusion, P = 0.038, Dunnett's multiple comparisons test) and **(F)** Left ventricular end-systolic pressure
(LVESP) were reduced during the myocardial ischemia (n = 5 pig Pre-LAD vs. 5 pigs during LAD, P =
0.0103, Dunnett's multiple comparisons test), but not during the reperfusion (n = 6 pig Pre-LAD vs. 6 pigs
during reperfusion, P = 0.303, Dunnett's multiple comparisons test)

808
809