Decoding kinematic information from beta-band motor rhythms of speech motor cortex: A methodological/analytic approach using concurrent speech movement tracking and magnetoencephalography

Ioanna Anastasopoulou[1]*,

Douglas O. Cheyne[2,3], Pascal van Lieshout[2],

Blake W Johnson[1]*

[1]Macquarie University, School of Psychological Sciences, Sydney, New South Wales, Australia

[2]University of Toronto, Department of Speech-Language Pathology, Toronto, Ontario, Canada.

[3]Hospital for Sick Children Research Institute, Toronto, Ontario, Canada.

* Corresponding authors

Email: ioanna.anastasopoulou@hdr.mq.edu, blake.johnson@mq.edu.au

Running head: Neuroimaging of speech motor control

Keywords: magnetoencephalography (MEG), speech movement tracking, speech production, speech motor control, decoding

Abstract

Articulography and functional neuroimaging are two major tools for studying the
neurobiology of speech production. Until now, however, it has generally not been feasible to use
both in the same experimental setup because of technical incompatibilities between the two
methodologies. Here we describe results from a novel articulography system dubbed Magneto-
articulography for the Assessment of Speech Kinematics (MASK; Alves et al., 2016), which is
technically compatible with magnetoencephalography (MEG) brain scanning systems. In the
present paper we describe our methodological and analytic approach for extracting brain motor
activities related to key kinematic and coordination event parameters derived from time-registered
MASK tracking measurements (Anastasopoulou et al., 2022). Data were collected from ten
healthy adults with tracking coils on the tongue, lips, and jaw. Analyses targeted the gestural
landmarks of reiterated utterances /ipa/ and /api/, produced at normal and faster rates
(Anastasopoulou et al., 2022; Van Lieshout, 2007). The results show that (1) Speech sensorimotor
cortex can be reliably located in peri-rolandic regions of the left hemisphere; (2) mu (8-12 Hz) and
beta band (13-30 Hz) neuromotor oscillations are present in the speech signals and contain
information structures that are independent of those present in higher-frequency bands; and (3)
hypotheses concerning the information content of speech motor rhythms can be systematically
evaluated with multivariate pattern analytic techniques. These results show that MASK provides
the capability, for deriving subject-specific articulatory parameters, based on well-established and
robust motor control parameters, in the same experimental setup as the MEG brain recordings and
in temporal and spatial co-register with the brain data. The analytic approach described here
provides new capabilities for testing hypotheses concerning the types of kinematic information
that are encoded and processed within specific components of the speech neuromotor system.

60   **Introduction**

61

62   In recent years, systematic studies of speech motor control in the human brain have
63 significantly expanded our understanding of the neural foundations of expressive speech.
64 Converging evidence now points to a comprehensive re-evaluation of conventional and long-held
65 theoretical models of speech production (see recent reviews by Hickok & Venezia, 2023 and Silva
66 et al., 2022). This re-evaluation is ongoing and rapidly evolving, but there is an emerging shift
67 away from the traditional Wernicke-Geschwind model's emphasis on Broca's region in the left
68 hemisphere, and towards a greater recognition of the computational roles and network connections
69 of various premotor, motor, sensory, and insular regions of the cerebral neocortex (Hickok &
70 Venezia, 2023).

71   Much of the information that informs these new models comes from non-invasive
72 neuroimaging techniques, predominantly functional magnetic resonance imaging (fMRI)
73 (Bohland & Guenther, 2006; Peeva et al., 2010; Pang et al., 2011; Behroozmand et al., 2015; Rong
74 et al., 2018; Tourville et al., 2019; Heim & Specht, 2019) and associated techniques including
75 diffusion tensor imaging (DTI) (Catani & Forkel, 2019; Chang et al., 2020; Janssen et al., 2022).

76   Non-invasive electrophysiology methodologies using electroencephalography (EEG) and
77 magnetoencephalography (MEG) have added important detail regarding the timing of neuronal
78 processing events (Munding et al., 2016; Salmelin et al., 2019; Leckey & Federmeier, 2019).
79 Finally, recent years have provided an increasing amount of very highly detailed
80 electrophysiological evidence from invasive electrophysiological (electrocorticography; ECoG)
81 recordings of speech motor regions in neurosurgical patients (Bouchard et al., 2013; Ramsey et
82 al., 2018; Chartier et al., 2018; Silva et al., 2022).

83   Current evidence shows that spoken language processing draws on a complex set of neural
84 computations performed in a widely distributed set of brain regions (Levelt et al., 1998; Munding
85 et al., 2016; Carota et al., 2022). These computations range from abstract aspects of semantics and
86 syntactics to the low-level sensorimotor processes that directly control and modulate the overt
87 movements of speech articulators of the peripheral vocal tract (Indefrey & Levelt, 2000; Tong et
88 al., 2022). Experimental and clinical protocols for mapping of expressive speech centres employ
89 a wide variety of speech tasks according to their specific experimental or clinical aims (Salmelin
90 et al., 2019). Speech tasks can be variously deployed to emphasise different aspects of spoken
91 language processing: Story listening, object naming, rhyming, and covert word production invoke
92 relatively more abstract linguistic processes and have been shown to reliably activate distributed
93 areas of prefrontal, temporal and parietal cortex, including Broca's area in the left hemisphere
94 (Bowyer et al., 2005; Doesburg et al., 2016; Kadis et al., 2011; Youssofzadeh & Babajani-Feremi,

2019; Correia et al., 2020); while in contrast, non-word/pseudoword tasks are intended to limit the

requirements for semantic, syntactic and attentional processing and elicit neural activity that is

more restricted to brain regions associated with sensorimotor processes (Frankford et al., 2021;

Kearnery & Guenther, 2019).

The subject of the current paper is set within the context of speech motor control: the

phonological, phonetic, and sensorimotor processes that control and/or modulate the

neuromuscular output to the articulators. In this context, an important methodological limitation

of current neuroimaging research is that, with rare exceptions (Chartier et al., 2018; Mugler et al.,

2018; Ouyang et al., 2016), researchers obtain little or no information about the actual movements

of said articulators. This is a fundamental limitation in light of evidence that speech (and other

movements) is encoded in the form of kinematic movement trajectories in neurons in primary

motor cortical neurons (Chartier et al., 2018; Conant et al., 2018; Kolasinski et al., 2020). Such

essential information is technically difficult to obtain for crucially important articulators (such as

the tongue) which are located out of the line of sight within the oral cavity. Unfortunately,

specialised electromagnetic and ultrasound articulography techniques that are capable of non-line-

of-sight speech tracking are technically incompatible with the scanner environments used for

functional imaging with fMRI and MEG (Anastasopoulou et al., 2022).

In the following, we describe our method for linking speech kinematics to brain activity

using a novel MEG setup. This setup enables us to simultaneously and accurately measure speech

movements and brain function. The system, termed Magnetoencephalography for Assessment of

Speech Kinematics (MASK, Alves et al., 2016), can track the independent motion of up to 12

lightweight coils that are similar in size and shape to the tracking coils used in conventional

electromagnetic articulography (EMA). In contrast to the passive induction coils used in EMA,

MASK coils are actively energized by sinusoidal currents, and their associated magnetic fields are

measured by the MEG sensors.

In a previous paper we have described in detail movement parameters (amplitude, duration,

velocity) and interarticulator phase relationships derived from direct MASK measurements of

articulator movements (Anastasopoulou et al., 2022). We have demonstrated that MASK reliably

characterizes key kinematic and movement coordination parameters of speech motor control,

achieving a resolution comparable to standard electromagnetic articulography devices. In the

present work, we proceed to describe our methodology for establishing a mapping between

MASK-derived kinematic parameters and MEG-derived brain activities.

Methods

Participants. Ten healthy adults participated in this study (4F; mean age 32.5, range 19.7-

61.8; all right-handed as assessed by the Edinburgh Handedness Inventory). All participants were

fluent speakers of English; Nine were native English speakers, one participant's first language was

Mandarin. All procedures were approved by the Macquarie University Human Research Ethics

Committee.

MEG scans. Speech tracking data and neuromagnetic brain activity were recorded

concurrently with a KIT-Macquarie MEG160 (Model PQ1160R-N2, KIT, Kanazawa, Japan)

whole-head MEG system consisting of 160 first-order axial gradiometers with a 50-mm baseline

(Kado et al., 1999; Uehara et al., 2003). MEG data were acquired with analogue filter settings as

0.03 Hz high-pass, 1000 Hz low-pass, 1000 Hz sampling rate and 16-bit quantization precision in

a magnetically shielded room (Fujihara Co. Ltd., Tokyo, Japan). Measurements were acquired

with participants in a supine position (as the KIT MEG dewar configuration is fixed in the supine

position). This positioning is in contrast to conventional standalone articulography setups which

are used with participants in an upright seated position. We note that recent research findings have

indicated that there is no significant distinction in tongue pressure between participants in a supine

position and those in an upright position (Dietsch & Cirstea, 2013).

Structural scans. T1-weighted anatomical magnetic resonance images (MRIs) were

acquired for all participants in a separate scanning session using a 3T Siemens Magnetom Verio

scanner with a 12-channel head coil. Those anatomical images were obtained using 3D GR\IR

scanning sequence with the following acquisition parameters: repetition time, 2000 ms; echo time,

3.94 ms; flip angle, 9 degrees; slice thickness, 0.93 mm; field of view, 240 mm; image dimensions,

$512 \times 512 \times 208$.

Procedure. Five head position indicator coils (HPI) were attached on the head in an elastic

cap, and their positions were measured at the beginning and at the end of the experiment, with a

maximum displacement criterion of < 5 mm in any direction. The coils' positions with respect to

the three anatomical landmarks (nasion, right and left preauricular landmarks) were measured

using a handheld digitiser (Polhemus FastTrack; Colchester, VT).

MASK coils were placed at mid-sagittal positions on the vermilion border of the upper lip

(UL) and lower lip (LL), the tongue body (TB; 2 cm from the tongue tip) and the lower incisor

(JAW) sensor which was attached to a thin thermoplastic mould (Van Lieshout et al., 2007).

Tongue sensors were attached with surgical glue (Epiglu, MajaK Medical Brisbane; Australia),

while lip sensors were attached with surgical tape. Tracking coils were driven at frequencies higher

than 200 Hz, which allowing separate coil fields from brain activities that primarily occur at

frequencies lower than 100 Hz. Line-of-sight is not required for MASK measurement, permitting

tracking of all oral articulators, including the tongue. MASK evaluates coil positions every 33 ms

for movement tracking at rates up to 50 cm/s (Alves et al., 2016). Spatial accuracy depends on the

distance of the tracking coils from the MEG sensor array. For coils that are close to the array (like

those on the tongue), the accuracy is less than 1 mm relative position error, similar to the standard

MEG head position indicator coils. However, for coils that are more distant from the helmet sensor

array (like those on the lower lip), spatial accuracy decreases non-linearly to approximately 1-2

mm.

An experimental control computer with scripts programmed in Presentation® software

(Version 23.0, Neurobehavioral Systems, Inc., www.neurobs.com) was used to control display of

experimental instructions which were projected onto a display screen placed 100 cm above the

head of participants.

160 channel MEG data were simultaneously relayed to the MEG data acquisition

computer and to a separate MASK processing computer which calculated coil positions from the

MEG signals with an offline localisation algorithm, using a computational approach similar to

those used in conventional MEG for localising fiducial coils with respect to MEG sensors (Wilson,

2004), with modifications to optimise performance of the smaller MASK tracking coils (Alves et

al., 2016; More, 1978).

Acoustic speech signals were recorded with a directional microphone placed on the wall

of the magnetically-shielded room and were digitised in an auxiliary channel of the MEG

electronics with the same sample rate (1000 Hz) as the MEG recordings, and was relayed to both

the MEG acquisition computers and the MASK processing computer. The MASK-processed

speech tracking signals were subsequently combined with the MEG datasets stored on the

acquisition computer. Due to differences in the internal clocks of the MEG and MASK computers,

it was necessary to time-align the two datasets by applying the MATLAB *alignsignal* script to the

acoustic channels of the MEG and MASK datasets.

An additional high sample rate speech recording was obtained with an optical microphone

(Optoacoustics, Or-Yehuda, Israel) fixed on the MEG dewar at a distance of 20 cm away from the

mouth of the speaker; and digitised on the experimental control computer using a Creative sound

blaster X-Fi Titanium HD sound card (Creative, Singapore) with 48 kHz sample rate and 24-bit

quantization precision. The 48 kHz acoustic recording was aligned and integrated with the MEG

and MASK datasets as described above.

Experimental protocol. Participants performed four speech production tasks and one

manual button press task (see Figure 1). Speech productions were non-word disyllabic sequences

with a V1CV2 structure, /ipa/ and /api/, and each was produced in a reiteration fashion at normal

and faster rates. The tongue and lip gestures for /ipa/ and /api/ are reversed in phase, providing a
robust behavioural contrast in terms of interarticulator coordination (Anastasopoulou et al., 2022;
Van Lieshout et al., 2007). Variations in speech rate were used as a control variable to examine
the intrinsic stability of the coordination (Kelso 1986, Van Lieshout et al., 1996). Asking
participants to change their speaking rate (frequency of executed movements) is a typical
characteristic of studies which investigate coordination dynamics (Kelso, 1995, Van Lieshout et
al., 1996). The same reiterated stimuli have been used in previous studies investigating speech
motor control strategies in normal and in disordered populations (Van Lieshout et al. 1996; Van
Lieshout et al. 2002; Van Lieshout et al. 2007; Van Lieshout, 2017). Nonword stimuli with no
linguistic information avoid familiarity issues (Van Lieshout, 2017) and have been widely used in
the literature to investigate normal and pathological function in speech motor control (Murray et
al., 2015; Case & Grigos, 2020).

The experimental procedure for the speech task is illustrated in Figure 1A. Participants
were presented with a fixation cross (1 sec duration) on a display screen duration which they were
instructed to take a deep breath. The fixation cross was replaced with a stimulus nonword for 12
sec. Participants were required to continuously utter productions during the exhalation of the single
breath intake until the stimulus nonword disappeared from the screen. For the normal rate,
participants were instructed to produce utterances at a comfortable rate as they would do while
conversing with a friend. For the faster rate, they were instructed to produce utterances as fast as
possible while maintaining accuracy (Van Lieshout et al. 2002). Following Van Lieshout (2007),
we refer to the reiterated productions generated within the span of a single exhalation as a "trial
set". A respite of 4 seconds, referred to as the "inter trial set interval" followed each trial set. At
the end of the intertrial set interval, a fixation cross appeared for one second to cue the intake of
breath for the next trial set. Participants generated about 10 individual productions in each normal
rate trial set and about 12 individual productions in each faster rate trial set. Participants performed
10 trial sets of each utterance and each rate, for a total of 40 trial sets. A pre-experiment training
session exposed participants to recorded productions of a female native Australian speaker.
Participants repeated the modelled productions with feedback on incorrect speech productions,
rate and head or eye movements. They were allowed to blink their eyes between the trial sets but
were instructed to avoid these during trial sets.

Participants also performed manual button presses on a fibre optic response pad (Current
Designs, Philadelphia) with the index finger of their dominant hand at a self-paced rate of about 1
per 2 seconds for 180 sec (see Figure 1B) (Cheyne et al., 2008; Cheyne et al., 2014; De Nil et al.,
2021; Johnson & He, 2019).

233   ---------------------------

234   **Fig 1 about here**

235   ---------------------------

Analyses

Data analyses proceeded in four main phases:

(1) Analyses of MASK speech movement signals to characterise speech kinematic

profiles;

(2) MEG source reconstruction to identify location of speech motor cortex;

(3) Extraction of MEG-time frequency spectrograms from source-localised speech motor

cortex, followed by and multivariate pattern analysis of speech-relevant brain rhythms.

(4) Mapping of speech kinematic profiles onto source- and frequency-constrained MEG

data, via representational similarity analysis (RSA).

For the purposes of clarity, we present details of each set of analytic methods along with their

results, organised according to these four analytic phases.

Analysis of MASK-derived speech movement signals

Methods

The raw MASK position data were head motion corrected using MASK coils placed at

fiducial landmarks (nose, left and right ear) and transformed from the MEG coordinate system into

the occlusal plane frame of reference such that motion signals could be measured relative to a

midsagittal plane defined by the x (posterior-anterior) and z (inferior-superior) axes relative to the

bite plane origin. These transformed signals were then analysed using EGUANA software

(Henriques & Van Lieshout, 2013; Van Lieshout, 2021) to derive signal amplitude and phase for

selected articulators and speech gestures. Speech errors (e.g. substitutions, lengthy pauses) were

identified from examination of the tracking and acoustic signals, and subsequent analyses were

focused on accurate productions (Case & Grigos, 2020).

/ipa/ and /api/ productions involve specific movements of the lips and tongue. To create

the voiceless stop /p/ sound, a bilabial closure (BC) gesture is used. The two tongue body

constriction gestures (TB) are used to produce the sounds /i/ and /a/. The BC gesture was calculated

using the two-dimensional (x-y) Euclidian distance of the upper and lower lip positions, while the

tongue body gesture was derived from the two-dimensional (x-y) Euclidian distance of the tongue

body and the nasal reference coil, as described in Van Lieshout et al. (2007). The kinematic and

coordination parameters were computed using the methods described in (Anastasopoulou et al.,

2022; van Lieshout et al., 2002; van Lieshout et al., 2007).

The opening and closing movements of each cycle were identified using the minimum and

maximum vertical position of the gestural and articulatory signals (Van Lieshout, 2017). The

amplitude levels of the opening and closing movements at 10% and 90% were determined for each

individual cycle. The individual gestural and articulatory signals which were measured by the

MASK (see Anastasopoulou et al., 2022) were analysed with custom MATLAB scripts to

determine the times which were corresponding to the 10% and 90% amplitude levels of each

opening and closing movement. Once the individual landmarks were determined, they were

brought into time register with MEG data by aligning the acoustic signal recorded by the MASK

acquisition setup and the acoustic signal recorded in the MEG acquisition computer, as shown in

Figure 2.

282   ---------------------------
283   **Fig 2 about here**
284   ---------------------------
285

286 **Results**

288   *1B. MASK tracking signals.* Figure S1 displays acoustic recordings and tracking signals

289 of the tongue body (TB) and bilabial closure (BC) from Participant 1 for a single trial of each of

290 the four speech production tasks. The participant produced 14 utterances of /ipa/ and /api/ at a

291 normal speaking rate and 18-19 utterances at a faster rate.

292   The contrast between the mirrored positions of the tongue and lips in /ipa/ and /api/ is

clearly observed in the MASK measurements of tongue and lip gestures. Peaks and valleys in

Figure 3 indicate the high and low positions achieved by the BC and TB gestures during the

production of /api/ and /ipa/. Valleys occur during the bilabial constriction gesture and the tongue

body gesture for /i/, while peaks occur for the tongue body gesture of /a/. (We note that these

positions are Euclidean distances relative to the nasion. Within this reference frame "low a" is a

peak, and "high /i/" is a valley). In /api/, the /p/ closure occurs during the upward motion of the

TB, going from the low /a/ to the high /i/ position. On the other hand, in /ipa/, the /p/ closure occurs

during the downward motion of the TB, going from the high /i/ to low /a/ position. The gestural

movements of /ipa/ and /api/ are mirror images, with the relative timing of the motions of TB and

BC gestures reversed.

303   Overall, the TB and BC tracking signals measured with MASK are entirely comparable in

304 morphology and quality with those obtained from a conventional electromagnetic articulography

305 setup (please see Anastasopoulou et al., 2022, for a direct comparison of MASK and EMA signals

306 measured during the same utterances described here).

307   *Derived kinematic profiles.* The next stage in our analysis pipeline involves generating

308 profiles that capture the relationships between key kinematic parameters of BC and TB gestures.

309 Specifically, we examine the amplitudes, durations, velocities, and stiffnesses of gestural

310 movements, as these parameters are known to covary in highly consistent ways and reflect

311 "invariant" properties of speech kinematic movements. These invariant properties are crucial in

312 understanding the motor control of human speech (Munhall et al., 1989; Van Lieshout et al., 2007).

313   Figure S2 illustrates the covariation of these kinematic parameters for /ipa/ and /api/ for

two participants. Our analysis shows that movement peak velocity increases as a linear function

of movement amplitude, indicating that larger movement distances are associated with higher peak

speeds. Furthermore, we observe comparable amplitude/velocity relationships for opening and

closing movements, suggesting that these parameters are controlled similarly regardless of

movement direction. This roughly linear relationship between amplitude and peak velocity is a

well-established characteristic of speech kinematics, and has been described for a variety of

articulators, gestures, and utterances (Ostry et al., 1983; Ostry et al., 1985). Regarding the stiffness

vs. duration relationship, our results indicate that stiffness systematically decreases as a curvilinear

function of durations less than 200 ms, after which the relationship plateaus into a relatively flat

line (see also Munhall et al., 1989). These findings are in line with the findings reported in

Anastasopoulou et al., (2022) and consistent across the ten speakers.

MEG source reconstruction of speech motor cortex

Methods

Source reconstruction of brain activity was carried out using the synthetic aperture magnetometry (SAM) beamformer algorithms implemented in the BrainWave MATLAB toolbox (Jobst et al., 2018; cheynelab.utoronto.ca/brainwave). The raw KIT/Yokogawa data files were initially converted to CTF format and transformed to the CTF head coordinate system using the fiducial coil positions relative to the sensor array. Each participant's structural MRI was then spatially coregistered with the MEG data and normalised into standard adult MNI template space using SPM12 (Wellcome Institute of Cognitive Neurology).

The onset of each speech trial set was marked using a semi-automated peakfinding function implemented in the BrainWave MATLAB toolbox which identified peak onsets in the rectified signal of the auxiliary MEG acoustic channel. In this analysis, we use an acoustic rather than speech movement index of speech trial onsets, because the aim of localising speech motor cortex is independent of the aims of our subsequent kinematic analysis, and because the acoustic onset provides ample accuracy for the SAM beamforming analysis.

Raw data were pre-filtered using a 100 Hz low pass bidirectional zero phase-shift Butterworth filter and epoched into 15 sec segments, from 10 sec prior to speech trial onset to 5 seconds after speech trial onset. Each 15 sec segment encompassed three distinct task periods: the last five seconds of the preceding trial set (-10 to – 5 sec); the inter-trial set rest period (-5 to 0 sec); and the first five seconds of the current trial set (0 to +5 sec), thereby providing maximal contrast between active (speech) and rest periods.

The current trial set and inter-trial rest period intervals were used for the SAM pseudo-T analysis window and baseline window respectively. We used a sliding active window of 1 second duration starting from 0-1000 ms (step size 200 ms, 10 steps), and a fixed baseline window of 2 seconds duration extending from -5 to -3 seconds relative to speech movement onset and a bandpass of 18–22 Hz (centre of the beta frequency range). While beamforming analyses typically employ equal baseline and active window durations, in the present analyses we wished to use a longer baseline epoch to reduce the chance of a biased estimate of baseline power, which we reasoned is more likely to vary over time than during the active speech period (since reiterated speech is akin to a steady state). While larger order mismatches (e.g. comparing 1.0 second to 0.1 seconds) are likely to be problematic, simulation studies (Brookes et al., 2008) have shown that covariance errors are minimized, and therefore beamformer weights are stable, with at least 5 seconds of total data (a requirement that is well exceeded in the present case) and our preliminary analyses confirmed that a 2 second baseline did not affect the beamforming results relative to a 1 second baseline. The

combined active and control windows were used to compute the data covariance matrix for

beamformer weight calculations, while the full 15 second time window was used to compute data

covariance for the virtual sensor source activity calculations.

SAM pseudo-T images were volumetrically reconstructed using a 4 mm resolution grid covering

the entire brain. Group statistical analysis employed a nonparametric permutation analysis where

each permutation (total = 1024) involved randomly flipping the polarity of all voxels in the group

volumetric image, computing the mean image, and placing the maximum value in the image in the

permutation distribution (Jobst et al., 2018; Nichols and Holmes, 2002; Chau et al., 2004; Lin et

al., 2006). The value corresponding to the area under the permutation distribution for the Type I

error level (alpha = .05) was used as an omnibus threshold for the entire image. The time-course

of (group) source activity was then computed as the output of the beamformer with optimized

orientation ("virtual sensor") and plotted as time-frequency spectrograms (encompassing the entire

15 sec data epoch) to assess the temporal correspondence of beta activity with active and rest

periods. To maximise the number of trials (and consequently, the signal to noise ratio) in this

analysis we use trial sets from all four speech tasks (for a total of 40 trial sets). To examine

individual datasets, statistically significant locations were unwarped from the group template to

the same anatomical locations in the individuals and virtual sensors were computed in the same

manner as described above for the group analysis.

For the motor cortex hand region localiser analysis, trials were prefiltered with a bandpass

of 0-100 Hz and epoched with respect to the button press onset into 1.5 sec segments (-500 to

+1000 ms), encompassing the established time course of beta-band desynchronisation (several

hundred ms prior to and after the button press) and "rebound" synchronisation (several hundred

ms starting about 500 ms after the button press) (see Cheyne, 2013; Cheyne et al., 2014; Johnson

et al., 2016). Following the maximal contrast approach used for the speech analysis, the SAM

pseudo-T analysis used a sliding active window of 200 ms duration starting from 600-800 ms,

(step size 10 ms, 10 steps), a fixed baseline window from 0 to 200 ms, and bandpass of 18-22 Hz.

The full 1.5 second epoch was used to compute the data covariance matrix for beamformer weight

calculations. Volumetric reconstruction used the same grid employed for the speech analysis.

In all individuals SAM source reconstruction resulted in robust peaks centred on the hand

knob of the left precentral gyrus (Yousry et al., 1997), and a smaller mirror source centred on the

right hemisphere homologue. The left hemisphere virtual sensor source activity was then

computed and plotted as a time-frequency spectrogram (encompassing the entire 1.5 sec data

epoch) to assess the correspondence with the established time course of beta band activity

associated with the manual button press task (Cheyne, 2013; Cheyne et al., 2014; Johnson et al.,

2020).

Results

Group statistical analyses showed that a single significant SAM beamformer cluster

(Figure 3) in the left hemisphere, encompassing the middle portion of the prefrontal gyrus (mPFG)

and the immediately adjacent region of the middle frontal gyrus (MFG), both established areas of

speech motor control (Silva et al., 2022). The anatomical localisation of the mPFG is well-

supported by comparison with the SAM beamformer map for the button press task, which shows

a cluster maximum in the hand knob of the immediately dorsal region of precentral gyrus.

Physiological activities at the locations of the SAM beamformer cluster maxima are visualised in

the "virtual sensor" time frequency plots below their respective brain maps. For the button press

task the time-frequency plot shows the well-established pattern of beta-band (13-30 Hz)

desynchronisation, starting several hundred ms before the button press, persisting for several

hundred ms after, and followed by a "rebound" beta synchronisation at about 600-700 ms after the

button press.

412   ----------------------------
413   **Fig 3 about here**
414   ----------------------------
415

A comparable pattern of beta band activity is evident in the speech virtual sensor plot,

keeping in mind the different time scales (1.5 sec for button press, 15 sec for speech) and

movement requirements (a single punctate button press versus 10 seconds of steady state,

reiterated speech) of the two tasks. Beta band desynchronisation begins several hundred ms before

speech onset and persists for the duration of the speech movements. Note that in this plot the

baseline of the colour scaling (the five second inter trial set rest period) was chosen to emphasise

event-related desynchronisation. Baselining to the speaking portions of the epoch will emphasise

the event-related synchronisation during the rest period.

Taken together, the results of the localisation procedure provide a focussed and well-

grounded target for subsequent analyses that can incorporate the kinematic and coordination

parameters derived from MASK. The plausibility of the mPFG/MFG target is well-supported by

the time-frequency characteristics of the virtual sensor and its anatomic location immediately

ventral to the established landmark of the PFG hand knob, independently localised with data from

the button press task: a task that has been long established to provide highly reliable beta-band

activations located in the hand regions of the sensorimotor cortices (e.g. Cheyne et al., 2014).

Extraction and pattern analysis of source-localised MEG time-frequency spectrograms

Our aims in this analysis were twofold: (1) to perform a "time-frequency classification" to

determine if the trial-by-trial time-frequency data derived from the speech motor cortex virtual

sensor contains information that is able to discriminate between the neural activities associated

with speech and non-speaking epochs, and, if so, to determine if the discriminative information is

confined to a specific frequency range[1] (Treder, 2020); and (2) to perform a "frequency

generalization/cross decoding" analysis to assess whether speech related neural responses may be

contaminated with by non-neural artefacts associated with overt speech movements.

Methods

For each production task, continuously recorded MEG signals were pre-filtered with a

bandpass of 0-100 Hz and 50 Hz notch filter and segmented into 4 second epochs (-2 sec to +2

sec) using the onset of the BC opening movement for each speech task as time zero. For each

speech condition and participant from 75 to 250 BC opening movements were identified within

the 10 trial sets (average 175).

We note that in this analysis only activity around the single BC movement at time zero is

precisely time-locked and activations around other movements will necessarily be blurred due to

intra- and inter-individual variations in speech rates. The present analyses therefore simply rely on

the presence of task-related modulation of activity during the speech condition but not in the rest

condition. This consideration also does not affect inferences from the frequency generalisation

analysis since task-related neural modulations and artefacts due to overt movements are affected

identically.

Data epochs were subsequently truncated to 3 seconds (-1.5 sec to + 1.5 sec) to remove

edge effects from the frequency analysis. Using the speech motor cortex coordinates derived from

the speech localiser for a (single) virtual sensor, time-frequency spectrograms were generated for

each individual trial and the resulting three-dimensional (time x frequency x trial) matrix was

exported for classification analysis using the MVPA-Light MATLAB toolbox for classification

and regression of multidimensional data (Treder, 2020).

---

[1] In the case of event-related experimental designs the time-frequency classification can also determine if discrimination is confined to specific times (Treder, 2020). The reiterated speech paradigm used here is akin to a system in steady state, so the analytic question at this stage simplifies to frequency discrimination alone.

Equivalent duration non-speaking "resting" condition epochs were derived by randomly

selecting epoch-reference time-points from the inter-trial set periods of the MEG data. For each

speaking condition and participant, an equal number of resting condition trials was epoched.

We performed a searchlight analysis using a binary linear discriminant analysis (LDA)

classifier and a metric of "accuracy" (fraction of correctly predicted class labels, range = $0 - 1$),

with training parameters of five folds and five repetitions. Group level statistics were performed

using nonparametric permutation testing and cluster corrections for multiple comparisons (Maris

& Oostenveld, 2007). As implemented in the MVPA-Light toolbox (Treder, 2020), group statistics

are calculated by testing obtained accuracy values against the null value of 0.5. To create a null

distribution, data is permuted by randomly swapping the obtained value and its null value.

Results

Figure 4 shows source-localised time-frequency spectrograms for individual participant

S1119. The speech-condition spectrograms show clear speech rate related modulation of circa 20

Hz beta-band activity in all speech conditions. A clear and distinct pattern of circa 10 Hz mu band

activity is also observable for both of the /api/ productions. Both the beta and mu-band rhythms

are well-known and established rhythms of the central motor cortices (Cheyne, 2013; Cheyne et

al., 2014; Pfurtscheller et al., 2003).

Substantial movement-related broadband noise is also evident in the supra-beta frequencies

for all speaking conditions and, in this case, is especially prominent in the /api/ faster rate

condition.

In contrast to the speaking conditions, for the non-speech resting conditions mu and beta

activities are manifest as relatively continuous (unmodulated) bands of activity throughout most

of the epoch, and broadband movement-related noise patterns are absent from the resting

spectrograms.

The MVPA classification results of Figure 4 shows that the classification appears for both

the mu and beta band rhythms, with a well-defined frequency boundary between the two rhythms

that is clear and prominent in the cases of the /ipa/ faster rate and /api/ normal rate date. We note

that the classifier is also sensitive to speech-movement related noise (present in the overt speech

condition), particularly in the /api/ faster rate condition. Speech movement-related noise is evident

as high-frequency broad-band patterns extending to circa 50-60 Hz. The broadband noise in the

classification patterns is well separated in frequency from the beta/mu classifier signals and

confined to frequencies above 50 Hz.

494
495
496
497

Level 2 group analysis of the speaking/resting classifier results are shown in Figure 5. The

group results are entirely consistent with the individual results described above and provide clear

statistical support for high classification accuracy for the mu and beta motor rhythms. The >50 Hz

frequency region also shows high classification accuracy for broadband bursts associated with

overt speech movements. The mu/beta frequencies are well separated by a region of low-classifier

accuracy for circa 30-50 Hz frequencies, suggesting at least a lack of continuity between these

frequency regions, and possibly that the underlying informational structures of the lower-

frequency motor rhythms and the broadband artifact apparent at higher frequencies are

functionally independent. We consider this issue more formally in the frequency generalisation

analyses below.

513   *Frequency generalisation (cross-frequency decoding)*

514
In addition to providing an estimate of decodability for the task contrasts described above,

time/frequency series decoding can be applied to provide a picture of the continuity (or

discontinuity) of decoding estimates over time or frequency. This provides an important inferential

advantage for further interpretation of the timing or frequency specificity of experimental effects.

This "cross-decoding approach" involves training the classifier on a given time or frequency and

then testing classifier performance on different times or frequencies. The logic of this approach

relies on the classifier's ability to partition multidimensional space as a basis for discriminating

between experimental conditions: hence, where a classifier trained on a given time or frequency

can successfully discriminate experimental classes based on other time or frequency points, one

can infer that the structure of the underlying multidimensional space is similar for those two points.

Conversely, in the case where cross-point decoding is unsuccessful, one can infer that the

underlying multidimensional patterns are sufficiently different that the distinction between class

labels determined at one point are not meaningful for discrimination at the second point

(Grootswagers et al., 2017; Treder, 2020).

In the present context cross-frequency decoding enables us to more precisely address

questions about possible relations between the frequency bands identified by the basic speech/rest

classificational analyses described in Figures 7 and 8: (1) Do the beta/mu band signals rely on the

same classification information as the high frequency signals, which are visibly contaminated with

movement-related broadband signals? In this case redundancy would suggest the beta/mu signals

simply contain some level of speech movement noise that is the basis for class discrimination. On

the other hand, a lack of cross frequency generalisation supports the conclusion that classification

relies on independent structures of information. (2) In a similar fashion, it is of interest to assess

the cross-frequency generalisation between the mu and beta bands, two motor rhythms that have

been frequently observed to co-occur in electrophysiological studies and can be assumed to have

some functional inter-relationship (Cheyne et. al., 2014).

The frequency generalisation results of Figure 6 show no evidence for frequency

generalisation between mu/beta, and the high frequency region which is visibly dominated by

noise. To the contrary, frequency generalisation (observable as off-diagonal clustering) occurs

within the sub-30 Hz mu/beta frequencies, and within the supra-60 Hz frequencies (particularly

within the range of about 60-80 Hz); but the intermediate zone between mu/beta and high

frequency noise (circa 30-60 Hz) exhibits a fairly strictly diagonal trajectory (for example, see

group means for /api/ normal and faster rates). Classification of speech and resting conditions can

clearly rely on either broadband signals that are (visibly) associated with overt speech movements,

or on mu/beta modulations which show no such association: both frequency regions are prominent

in the classification plots of Figures 4-5. However, the cross-frequency coding results provide clear

support for the conclusion that the high frequency and mu/beta bands are discontinuous and rely

on distinct patterns of multidimensional structure within their data to achieve discrimination

between speech and resting data conditions.

On the second question, the group results show clear frequency generalisation between

beta frequencies at circa 15-Hz and also suggest a possibly weaker generalization for beta training

frequencies and mu test frequencies (circa 8-12 Hz; see group statistical results for /ipa/ and /api/

faster rates. Although the mu/beta clusters do not achieve statistical significance for the slower

speech rates, comparable clusters are evident in their group mean data. The individual results for

S1119 are entirely comparable to the group mean data but show a much clearer distinction between

the mu and beta bands (see especially plot for /api/ normal rate): These data show that mu training

frequencies about 8-12 Hz generalise to beta band frequencies; and that beta training frequencies

circa 20-30 Hz generalise to mu test frequencies. However, the plots also show a clear mu/beta

discontinuity, with low classification accuracy for frequencies between roughly 13-20 Hz. This

mu/beta discontinuity is not as evident in the group results, presumably due to individual

differences in the precise frequency ranges of the mu rhythm (Pfurtscheller et al., 1997).

On a final note, we emphasise that we do not wish to imply from the foregoing that the

supra-beta frequencies are simply "noise" frequencies. Gamma rhythms in the circa 60-80 Hz band

are robust and functionally important features of motor-related MEG responses (e.g. Johnson et
al., 2020; see also Cheyne, 2013; Cheyne & Ferrari, 2013); and high gamma band (> circa 80 Hz)
rhythms are key dependent measures of brain function in electrocorticographic studies (Crone et
al., 2006) including studies of speech-related brain function (e.g. Chartier et al., 2018; Conant et
al., 2018). However in the context of a reiterated speech task any potential gamma frequency
neural activity is strongly and visibly obscured by broadband movement artifact in both the time
and frequency domains. From the foregoing analyses we conclude only that the mu/beta bands are
suitable candidates for further interrogation of their functional properties, and that (within this
experimental paradigm and MEG neuroimaging setup), the gamma band is not.

577   -----------------------------
578   **Fig 6 about here**
579   -----------------------------
580

584 ***Decoding of speech kinematic parameters from source- and frequency-constrained***
585   ***MEG data***

586
Methods

In the preceding analyses we have used standard MVPA classification of speech versus
resting conditions to demonstrate that the neural signals derived from speech motor cortex contain
information that is capable of discriminating between speaking and resting conditions; and then
employed cross-frequency classification to determine that the mu-beta motor rhythms contain the
informational basis of speech-rest discrimination. Importantly, cross-frequency generalisation also
shows that the informational structure of the mu/beta rhythm is independent of the broadband
artefacts that are an inevitable confound for electrophysiological recordings during overt speech.

In subsequent analyses we attempt to derive a more detailed picture of the information
structures contained within the neural data, by performing classification between data partitions
within the speech condition, rather than between speech and rest conditions. Representational
Similarity Analysis (RSA; Kriegeskorte, 2008; Kriegeskorte & Kievit, 2013) is an MVPA
technique based on the simple logic that classes of neural data with more similar informational
(representational) structures should be more difficult to classify, relative to classes with more
distinct representational structures. Previous studies have successfully applied RSA to tracking
data of hand movements (Kolasinski et al., 2020), articulator movements during vowel production
(Carey et al., 2017), and acoustic measurements during speech production (Zhang et al., 2020).
We follow this logic to test specific hypotheses about potential representational structures in
speech motor cortex activity as follows (see Figure 7 for a summary of the computational steps):

(1) Our starting hypotheses concerning candidate representational structures within
speech motor cortex activity come from the well-behaved kinematic profiles derived
from direct MASK measurements of speech articulator movements (Figure 4): both
the strikingly linear relationship between amplitude and velocity, and the orderly
curvilinear relationship between duration and stiffness have been proposed to reflect
"control parameters" that are relatively tightly specified at some level within the
speech motor system (Munhall et al., 1989; Van Lieshout et al., 2007);

(2) Within a given kinematic profile, we divide the behavioural data points into partitions
(containing equal numbers of trials) that reflect different (Euclidean) distances
between the coordinates within each partition. Here we have used 10 partitions which
provides a good spread of inter-partition distances, each of which reflects a reasonable
number of trials of MEG data (15-30 trials/partition).

(3) Data points are averaged within each partition to provide a representation of the central
tendency of each partition.

(4) A "behavioural dissimilarity matrix" is generated based on the Euclidean distances
between averaged data points in all possible pairs of partitions.

(5) The MEG data (consisting of N trials by 3000-time points x 100 frequencies) is
similarly divided into sets of individual trials that correspond to the behavioural data
points within a partition.

(6) Classification analysis is performed for all possible pairs of MEG trial partitions.

(7) A "neural dissimilarity matrix" (for each time and frequency point) is generated based
on the Euclidean distances between the classification accuracy scores.

(8) An "RSA time-frequency plot" is generated containing the correlations between the
behavioural dissimilarity matrix and the neural matrices for each time and frequency
point.

Model evaluation is restricted in *time* to a 1 second epoch centred on the onset of the BC
opening movement, as this event is the reference for the epoching of the MEG data. Model
evaluation is further restricted to the *frequencies* of the mu and beta speech motor frequency bands
of interest defined by the analyses described in the frequency localisation sections above; and for
comparison purposes, a third high frequency region (60-80 Hz) dominated by speech movement
noise and which we therefore do not expect to contain useable information concerning the
representational structures of speech neuromotor activity.

Group data were statistically evaluated with cluster-based permutation analyses using 500
permutations, alpha < .05, and controlled for multiple comparisons using FDR.

641   ----------------------------
642   **Fig 7A about here**
643   ----------------------------
644
645
646   ----------------------------
647   **Fig 7B about here**
648   ----------------------------

Results

The statistically significant results of model evaluation are shown in Figure 8. Of the two behavioural models, four speech conditions, and three frequency bands evaluated, only the /api/ normal rate condition shows showed statistically significant correlations, for beta band and for the stiffness-duration model. Three observations are relevant from these results: (1) The group mean correlations are overall very weak, with peaks restricted to a range of less than - .2 to .2; (2) The temporal structure of the significant positive clusters is appropriate, beginning at a latency of about 100 ms prior to the onset of the BC opening movement. This timing is in good accordance with what one would expect for neural activity associated with behavioural movements. (3) The post-movement cluster of correlations is oppositely (negatively) correlated to the premovement cluster.

Figure 8 also shows comparable (though non-significant after cluster-correction) results for /ipa/ normal rate for the velocity-amplitude model. While we do not wish to over-interpret a non-significant result, the circa -90 ms timing of the peak positive correlation cluster is entirely comparable to that observed for the /api/ normal rate stiffness-duration data described above.

Fig 8 about here

Group mean behavioural-neural correlation time series are shown for all speech conditions, frequency bands, and behavioural models in Figure 9. As expected, in the gamma frequency band no significant results were obtained for any speech condition or behavioural model, and there is no discernible, consistent temporal structure in any of the plots. The mu band similarly shows no discernible or consistent temporal structure, and no significant results were obtained.

Fig 9A about here

Fig 9B about here

Fig 9C about here
----

696   In summary, the present results provide support for very weak but statistically significant

697   encoding of the stiffness-duration relationship only in the beta motor rhythm. This encoding is

698   statistically robust in only one speaking condition and is very weak in terms of magnitude of

699   correlation. However, it is well-structured in time and shows an appropriate and expected temporal

700   relationship (about -90 ms) with respect to movement onset.

Discussion

Localization of speech motor cortex

The results of our speech localiser analyses show a single statistically significant cluster in the left hemisphere, located immediately inferior to the hand motor cortex (hand knob) as identified with the independent button press localiser task. The cluster coordinates are centred on the posterior region of the middle frontal gyrus (pMFG) and extend posteriorly to encompass the middle portion of the precentral gyrus (midPrCG). This middle zone of the precentral gyrus – inferior to the precentral hand representation and superior to the ventral representations of face, mouth and larynx in the classical Penfield motor homunculus - corresponds to a functional-anatomical zone of the precentral gyrus that has been termed "dorsal laryngeal motor cortex" (dLMC; Bouchard et al., 2013; Eichart et al., 2020), a second representation of the larynx in addition to the ventral laryngeal motor cortex (vLMC) representation of the classical motor homunculus. The dorsal laryngeal representation appears to be unique to human motor cortex; this dual mode of organisation been proposed to underpin the extensive human capacity for voluntary control of vocalisation relative to non-human primates and other mammalian species (Belyk, Eichert & McGettigan, 2021).

The present results align with an emerging neuroscientific consensus which assigns novel and previously overlooked roles in speech motor planning and execution to the midPrCG and the immediately adjacent portion of the pMFG (area 55b; Glasser et al., 2016). Recent data from invasive neurosurgical and functional neuroimaging investigations have implicated the midPrCG in a variety of language and speech functions, ranging from direct laryngeal motor control to auditory-motor integration to higher level aspects of speech motor sequence planning that have previously been assigned to Broca's area in models of speech processing (see reviews by Hickok et al., 2023, and Silva et al., 2022). Invasive neurostimulation of this area evokes involuntary vocalisations (Dichter et al., 2018). The midPrCG is anatomically contiguous with and tightly functionally associated with the pMFG, an area that has recently been implicated in the production of fluent speech (Glasser et al., 2016; Silva et al., 2022). Focal surgical resection of the pMGF and midPrCG has been reported to result in a case of pure apraxia of speech (Chang et al., 2020), a speech motor planning disorder associated with problems in hitting articulatory targets (articulatory groping) and transitioning between syllables. In light of these findings two recent theoretical models of speech production have posited a critical role for these areas in coordinating complex phonological sequences into motor plans, either in and of themselves (Silva et al., 2022), or as a subsystem of a dual (dorsal and ventral) motor speech coordination system (Hickok et al., 2023). Our results are clearly supportive of these models, since fluent reiterated (nonword) speech relies heavily on the capacity to coordinate and maintain the ordering of phonological sequences.

Invasive neurosurgical studies of midPrCG/pMFG function have focussed on the left
hemisphere but there is currently little evidence to bear on the question of whether speech motor
coordination functions of these areas have a lateralised or bilateral organisation (Hickok et al.,
2023; Silva et al., 2022). The present speech localiser results showing a single significant cluster
in the left hemisphere are generally consistent with those of a recent MEG study by DeNil et al.
(2021), who (using the same analysis toolbox as the present study) compared beta-band responses
to simple (a sequence of four repetitions of individual syllables /pa/, /ta/ or /ka/) and complex
sequences (pseudo random combinations of four syllables, e.g. /patakapa/) of nonword vocal
productions. These authors reported that beta-band event-related desynchronisation for both
simple and complex verbal tasks was bilateral in premotor and motor cortical areas, but
"statistically stronger" in the left hemisphere. We are aware of a single previous neuroimaging
(fMRI) study using a continuously reiterated speech task that is overall comparable to ours. As in
our study, Reicher et al. (2000) required participants to continuously produce nonword utterances
during exhalation of a single breath intake. They used nonword items /ta/, /stra/ and /pataka/ that
were consistent with German phonotactic rules but differed in articulatory/complexity. Consistent
with our results, these authors reported highly focal activations of sensorimotor cortex for all task
items. These activations were bilateral for the single syllable tasks, while the multisyllabic /pataka/
task showed activity only in the left hemisphere. Taken together, our results and those of Reicher
et al. (2000) suggest that left lateralised speech motor function is associated with task requirements
for more complex articulatory transitions in multisyllabic relative to monosyllabic utterances. A
separate study by our group (Anastasopoulou et al., 2023 preprint) has further shown that typically
developing children exhibit *bilateral* responses to the same disyllabic utterances used in the
present study, indicating a developmental trajectory that shifts control of complex phonological
sequencing from bilateral processing in childhood to left hemispheric dominance in adults.

Decoding of speech-related brain activity

In recent years, a series of MEG studies have aimed to decode neural activity patterns
associated with speech in the context of advancing the development of brain-computer interfaces
(BCIs) (Dash et al., 2021; Dash et al., 2020; Dash, Wisler et al., 2020; Dash et al., 2019; Dash,
Ferrari, Dutta, Wang, 2020). Using advanced artificial and convolutional neural network
classifiers at the phrase level, Dash et al. (2020) have reported excellent classification accuracies
for a five-class discrimination task (80% - >95%) for both imagined and overt speech, relative to
comparable EEG studies achieving accuracies in the range of 35% (Cooney et al., 2019). A single
previous MEG study (Dash et al., 2020) has also achieved accurate (average 80%) decoding of
speech-associated jaw motion kinematics from concurrently acquired MEG signals, using a long
short term memory (LSTM) model.

The present work makes three main contributions to this emerging body of MEG speech

decoding literature. First, as discussed above, it provides a methodological and analytical approach

for spatially constraining the overall decoding approach, effectively reducing the dimensionality

of the problem from 160 MEG channels (or alternatively, thousands of source-reconstructed

voxels) to a single virtual sensor. Further, there is now substantial evidence that the brain regions

activated by our reiterated nonword speech task play a central role in in control and coordination

of integrative speech movements, providing a highly plausible functional/anatomical candidate for

more detailed interrogation of the kinematic representational structures that confer this control.

Second, the study incorporates a novel MASK technology which allows us, for the first

time, to obtain detailed movement profiles of key articulators associated with the specific speech

productions in our speech task in the same experimental setup as the MEG brain recordings and in

temporal and spatial co-register with the brain data. Third, we describe an analytic pipeline using

classification/decoding techniques that allow us to systematically query the nature the information

contained in these kinematic representations, by testing specific hypotheses derived directly from

overt movement behaviours. This analytic framework further permits strong inferences concerning

the *timing* of relevant neural activations with respect to behavioural outputs.

Recent results from invasive ECoG studies of human neurosurgical patients provide

compelling reasons to believe that concurrent neuroimaging speech tracking will be important for

future progress in understanding speech motor control. For example, Chartier et al. (2018) obtained

direct cortical recordings of human speech sensorimotor cortex together with (inferred)

articulatory kinematics derived from a recurrent neural network based articulatory inversion

technique which learned a mapping from produced speech acoustic to a speaker generic articulator

space. This study showed that articulator movements were reflected significantly better in

measured neural activity than were either acoustic or phonemic features of speech; that encoding

is more related to coordinated movements of multiple articulators than to movements of single

articulators; and that the behaviours of encoded movements were governed by damped oscillatory

dynamics. These authors concluded that these coordinative and dynamical properties align neatly

with the properties of articulatory units of speech (vocal tract gestures) as conceived within the

theoretical framework of articulatory phonology and its associated task dynamics model

(Browman & Goldstein, 1992; Goldstein & Fowler, 2003; Saltzman, 1986). As such, it seems clear

that concurrent speech movement tracking and non-invasive neuroimaging should provide richer

datasets with mutually reinforcing inferential power and precision relative to experiments that

currently are largely conducted with only one or the other measure of speech motor control.

These new technical capabilities have clear clinical relevance for advancing our

understanding and treatment of developmental and acquired disorders of speech. Speech-sound

difficulties are the most common problems encountered by paediatricians and present formidable

social, educational and employment obstacles in cases where these problems cannot be readily

treated and resolved (Morgan, 2018). Childhood apraxia of speech (CAS) is an intriguing example

of a highly debilitating and persistent disorder of speech development whose origins are

considered to lie within the brain mechanisms responsible for coordinating and sequencing speech

movements, but whose study with conventional neuroimaging approaches has so far proved highly

resistant to establishing any clear connection to any particular brain region. In such cases, the

capability to directly map speech kinematic and coordination function in speech motor control

centres within highly focal and specific brain regions promises to provide more powerful insights

into the origins of speech problems in CAS (and conversely, into why speech development

proceeds more smoothly in most other children). Similarly, acquired apraxias of speech are a

common and debilitating outcome of strokes and other brain injuries. The greater functional

specificity of MASK-MEG has a clear bearing on studies aimed at understanding the nature and

degree of functional compromise and plastic capabilities in the brain of these patients.

Limitations

While our analytic framework dramatically and effectively reduces the dimensionality of

the MEG analytic problem, there remains a large decision space concerning the selection of speech

behaviours for input to the overall analyses. Here we have fairly arbitrarily focussed on a single

articulator metric (the first opening movement of the bilabial closure gesture) and have tested 2

simple models (derived from the observed kinematic profiles) of the neural informational

structures that may underlie this movement. Our results nonetheless provide support for the

conclusion that the stiffness-duration relationship of the first opening movement of the bilabial

closure may be (very weakly) encoded in the beta-band sensorimotor rhythm, with a timing

beginning approximately 90 ms before the onset of the movement. The reason for the occurrence

of a second period of significant (but oppositely valanced) association with stiffness-duration at a

latency of about 200 ms post movement is presently unclear: one possibility is that reflects a

sensory reafference event that provides a check on the motor commands.

Overall, since we have obtained only a weak association between speech behaviour and

neural activity (and in only one of four speech conditions), it is clear that future work should more

systematically probe the sets of possible models of speech movement encoding, including models

that describe relationships between articulators that are likely required for integrative speech

behaviours (e.g., the Linguistic Gestural Model (LGM) which is a combination of Articulatory

Phonology and Task Dynamics (Saltzman & Munhall, 1989; Browman & Goldstein, 1992;

Browman & Goldstein, 1997, the speed-accuracy trade off known as Fitts' law (Fitts, 1954;
Neufeld & Van Lieshout, 2014; Gafos & van Lieshout, 2021; Kuberski & Gafos, 2021).

Finally, the present decoding framework employs a simple binary discriminant classifier
and a simple RSA correlational mapping approach, which we have chosen for their ease of use
and the straightforward inferential capabilities. At the present time artificial and convolutional
neural network classifiers are undergoing rapid development with dramatic improvements in
accuracy (see Dash et al., 2021; Dash et al., 2020; Dash, Wisler et al., 2020; Dash et al., 2019;
Dash, Ferrari, Dutta, Wang, 2020 for recent examples with application to MEG speech
decoding) and we anticipate that these improvements will be able to accordingly extend the
accuracy and scope of MASK-based studies of speech motor control.

Conclusions

MASK-MEG addresses an important gap in current neuroscientific capabilities for
studying expressive language function in the human brain. While we possess robust and well-
established methods for measuring and characterising overt movements of the speech articulators,
and highly sophisticated equipment and methods for defining the brain activities that control these
movements, the two methodologies are not readily or easily combined within a single experimental
setup. As a result, speech movement tracking and speech neuroimaging methods have largely
evolved within separate laboratories -- even separate disciplines -- and there remains no easy way
to co-register and reconcile the different types of information that are derived from them. The
advent of neuroimaging-compatible speech tracking technologies such as MASK opens a new
window for integrative studies of human speech motor control, combining precision measures of
overt speech behaviours with temporally co-registered and spatially localised measures of brain
function and new machine-learning based decoding approaches capable of interrogating the
kinematic information structures represented in speech motor cortex.

Author Contributions

IA conducted the experiment. IA and BJ analyzed the data. All authors conceived, designed the

experiment, discussed the results, wrote, and edited the manuscript.

Data Availability Statement

The raw data supporting the conclusions of this article will be made available by the authors,

without undue reservation.

Funding

This work was supported by a Child Development Fund Research Grant (Ref. no. 2532 – 4758)

and a Discovery Project Grant (DP170102407) from the Australian Research Council.

Figure Captions:

Figure 1. Experimental procedures. **A.** Speech task. Instructions were displayed for 30s, followed by an intertrial interval lasted for 15s and 5s fixation cross '+' and breath intake in preparation for the speech production trial set. During a trial set participants produced the indicated nonword in a reiterated fashion for 12s. 10 consecutive trial sets were performed for each nonword stimulus. **B.** Button press task. Instructions were displayed for about 30s followed by a fixation cross, during which participants performed self-paced button pressed with the index finger of their dominant (right) hand at a rate of about 1 per 2 seconds for a total of about 90 trials.

Figure 2: Temporal alignment of MEG and MASK signals. MASK articulatory signals are brought into register with the MEG brain data using the MATLAB *alignsignals* function on the MEG auxiliary channel acoustic channel and the high-fidelity acoustic recording (top and second rows). **Inset** shows enlargement of rectangle bounded area in main figure. 1 = onset of opening movement; 2 = offset of opening movement; 3 = onset of closing movement; 4 = offset of closing movement.

Figure 3. Localisation of speech motor cortex. *Left: Anatomical Landmarks.* 1 – Hand regions of precentral gyrus (hand knob); 2 – Hand region of postcentral gyrus; 3 – Middle precentral gyrus; 4 – Middle frontal gyrus; 5 – Rolandic fissure; 6 – precentral gyrus; 7 – postcentral gyrus. *Top right panel*: *SAM beamformer maps*. Button press task elicited activation of hand region of pre (motor) and postcentral (somatosensory) gyri. Speech task shows maximal activation in middle precentral gyrus, immediately ventral to the hand motor region of the precentral gyrus. Speech activation cluster also encompasses the middle frontal gyrus immediately adjacent to the middle precentral speech region. Bottom right panel: Time-frequency plots showing temporal evolution of oscillatory responses at virtual sensors placed at locations of cluster maxima shown above. For button press task, upward arrow indicates time of button press onset. For speech task, downward arrow shows speech trial set offset, upward arrow shows speech trial set onset.

Figure 4. Time-frequency characteristics of speech and resting conditions for an individual participant. All plots show three seconds of MEG data derived from the medial frontal gyrus voxel. *Top row*. Time-frequency spectrograms during speech. Data are epoched relative to the onset of the bilabial closure opening movement. Speech rate modulated beta-band (circa 20 Hz) activity is evident in all plots, and mu-band activity is evident in several, especially the /api/ normal rate condition. *Middle row*. Spectrograms derived from the inter-trial set rest periods. Relatively continuous beta-band ERS is evident in all plots, as well as mu-band ERS in the /api/ conditions. *Bottom row*. MVPA classification results for speech versus resting conditions. High classification accuracy is quite tightly constrained to circa 20 Hz beta band, and a well-defined mu-frequency band is evident in the /ipa/ faster rate and /api/ normal rate conditions.

Figure 5. Group analysis of classifier performance for speech versus resting conditions. All plots show three seconds of MEG data derived from the medial frontal gyrus voxel. As seen in Figure 7, classifier performance is high for both speech-related high-frequency noise and beta/mu signals.

Figure 6. Frequency generalisation. In this analysis the classifier is trained on a given frequency and decoding performance is tested on a different frequency. This is repeated for all possible frequency pairs. The classifier results show that beta frequencies generalise to each other and to some extent to mu frequencies (bottom row, /ipa/ faster and /api/ faster). Importantly, beta/mu frequencies do not generalise to the higher frequency noise band, and conversely the noise band does not generalise to the beta/mu frequencies. Permutation-based significance tests used 500

929 permutations, Wilcoxin signed rank test (alpha < .05), controlled for multiple comparisons using
930 FDR.
931

Figure 7A. **Procedure for calculation of behavioural and neural correlations**. Velocity versus
amplitude and stiffness versus duration profiles are partitioned into 10 blocks containing equal
numbers of trials. Distances between each partition based on the partition mean coordinates are
used to generate the behavioural RDMs. For each partition, the same trials of MEG data are input
to MVPA classification analysis. The resulting classification (accuracy) metric is used to generate
a neural RDM, for each time-frequency point.
938

939 **Figure 7B.** A time-frequency correlation matrix resulting from correlating the (in this case,
940 stiffness-duration) behavioural RDM with the neural RDM for each time-frequency point. Group
941 statistics/model evaluation are performed for the mean alpha, beta, and gamma frequency bands
942 within the time range of -500 to +500 ms from onset of the BC opening movement.
943

Figure 8. RSA model evaluation. Black lines show group mean correlations between behavioural
and neural RDMs; shading shows standard errors. *Left panel*: The beta-band profile for /api/
normal rate shows three significant correlational clusters against the stiffness-duration RDM. The
first positive cluster begins about 90 ms prior to onset of the first opening movement of BC. A
second positive cluster occurs beginning at time zero, and a third cluster of weak *negative*
correlations begins about 180 ms post movement-onset. *Right panel*: Beta correlation against
amplitude-velocity time profile shows a similar positive peak circa -90 ms, although the t-value
clusters do not survive cluster correction for FDR rate.
952

953 **Figure 9A, B, C. Group mean behavioural-neural correlations for all speech conditions,**
954 **frequency bands, and behavioural models.** Black lines show group mean correlations; shading
955 shows standard errors.
956
957

References

Alves, N., Jobst C., Hotze F., Ferrari P., Lalancette M., Chau T., Van Lieshout P., Cheyne D. An MEG-compatible electromagnetic-tracking system for monitoring orofacial kinematics. *IEEE Transactions on Biomedical Engineering, 63*, 1709–17. https://doi.org/10.1109/TBME.2015.2500102

Anastasopoulou, I., Cheyne, D. O.,Van Lieshout, P., Ballard, K., Wilson, P.H. & Johnson, B. W. (2023 preprint). A novel protocol for magnetoencephalographic mapping of speech motor control regions during speech production. BioRxiv preprint, https://doi.org/10.1101/2023.09.30.560288

Anastasopoulou, I., Van Lieshout, P., Cheyne, D. O., & Johnson, B. W. (2022). Speech kinematics and coordination measured with an MEG-compatible speech tracking system. *Frontiers in Neurology*, *13*, 828237. https://doi.org/10.3389/fneur.2022.828237

Belyk, M., Eichert, N., & McGettigan, C. A dual larynx motor networks hypothesis, *Philosophical Transactions B*, *376*, 20200392. https://doi.org/10.1098/rstb.2020.0392

Behroozmand, R., Shebek, R., Hansen, D. R., Oya, H., Robin, D. A., Howard, M. A., & Greenlee, J. D. W. (2015). Sensory–motor networks involved in speech production and motor control: An fMRI study. *NeuroImage*, *109*, 418–428. https://doi.org/10.1016/j.neuroimage.2015.01.040

Bohland, J. W., & Guenther, F. H. (2006). An fMRI investigation of syllable sequence production. *NeuroImage*, *32*(2), 821–841 https://doi.org/10.1016/j.neuroimage.2006.04.173

Bouchard, K. E., Mesgarani, N., Johnson, K., & Chang, E. F. (2013). Functional organization of human sensorimotor cortex for speech articulation. *Nature*, *495*(7441), 327–332. https://doi.org/10.1038/nature11911

Bowyer, S. M., Moran, J. E., Weiland, B. J., Mason, K. M., Greenwald, M. L., Smith, B. J., Barkley, G. L., & Tepley, N. (2005). Language laterality determined by MEG mapping with MR-FOCUSS. *Epilepsy & Behavior*, *6*(2), 235–241. https://doi.org/10.1016/j.yebeh.2004.12.002

Brookes, Matthew J., Jiri Vrba, Stephen E. Robinson, Claire M. Stevenson, Andrew M. Peters, Gareth R. Barnes, Arjan Hillebrand, and Peter G. Morris. Optimising experimental design for MEG beamformer imaging. *NeuroImage* 39, 1788–1802. https://doi.org/10.1016/j.neuroimage.2007.09.050.

Browman, C. P., & Goldstein, L. (1992). Articulatory phonology: An overview. Phonetica, 49(3-4), 155-180.Catani, M., & Forkel, S. J. (2019). *Diffusion imaging methods in language sciences* (pp. 212-230). Oxford University Press, Oxford, United Kingdom.

Carey, D., Miquel, M. E., Evans, B. G., Adank, P., & McGettigan, C. (2017). Vocal tract images reveal neural representations of sensorimotor transformation during speech imitation. Cerebral Cortex, 27(5), 3064–3079. https://doi.org/10.1093/cercor/bhx056

Carota, F., Schoffelen, J.-M., Oostenveld, R., & Indefrey, P. (2022). The time course of language

production as revealed by pattern classification of MEG sensor data. *The Journal of Neuroscience, 42*(29), 5745–5754. https://doi.org/10.1523/JNEUROSCI.1923-21.2022

Case, J., & Grigos, M. I. (2020). A framework of motoric complexity: An investigation in children with typical and impaired speech development. *Journal of Speech, Language, and Hearing Research, 63*(10), 3326-3348. https://doi.org/10.1044/2020_JSLHR-20-00020

Chang, E. F., Kurteff, G., Andrews, J. P., Briggs, R. G., Conner, A. K., Battiste, J. D., & Sughrue, M. E. (2020). Pure apraxia of speech after resection based in the posterior middle frontal gyrus. *Neurosurgery, 87*(3), E383–E389. https://doi.org/10.1093/neuros/nyaa002

Chau, W., McIntosh, A. R., Robinson, S. E., Schulz, M., and Pantev, C. (2004). Improving permutation test power for group analysis of spatially filtered MEG data. *Neuroimage, 23*, 983–996. doi: 10.1016/j.neuroimage.2004. 07.007

Chartier, J., Anumanchipalli, G. K., Johnson, K., & Chang, E. F. (2018). Encoding of articulatory kinematic trajectories in human speech sensorimotor cortex. *Neuron, 98*(5), 1042-1054.e4

Cheyne, D. (2008). Imaging the neural control of voluntary movement using MEG. In *Coordination: Neural, Behavioral and Social Dynamics* (pp. 137-160). Berlin, Heidelberg: Springer Berlin Heidelberg.

Cheyne, D. O. (2013). MEG studies of sensorimotor rhythms: A review. *Experimental Neurology, 245*, 27–39. https://doi.org/10.1016/j.expneurol.2012.08.030

Cheyne, D., and P. Ferrari. (2013). MEG studies of motor cortex gamma oscillations: Evidence for a gamma 'fingerprint' in the brain?" *Frontiers in Human Neurosciences, 7*. https://doi.org/Artn 575 Doi 10.3389/Fnhum.2013.00575.

Cheyne, D., Jobst, C., Tesan G., Crain, S., Johnson, BW. (2014). Movement-related neuromagnetic fields in preschool age children. *Human Brain Mapping, 35*, 4858–75. https://doi.org/10.1002/hbm.22518

Conant, D. F., Bouchard, K. E., Leonard, M. K., & Chang, E. F. (2018). Human sensorimotor cortex control of directly measured vocal tract movements during vowel production. *The Journal of Neuroscience, 38*(12), 2955–2966. https://doi.org/10.1523/JNEUROSCI.2382-17.2018

Cooney, C., Folli, R., and Coyle, D. (2019). Optimizing layers improves cnn generalization and transfer learning for imagined speech decoding from EEG, 2019 *IEEE International Conference on Systems, Man and Cybernetics* (SMC) (Bari), 1311–1316.

Correia, J. M., Caballero-Gaudes, C., Guediche, S., & Carreiras, M. (2020). Phonatory and articulatory representations of speech production in cortical and subcortical fMRI responses. *Scientific Reports, 10*(1), 4529. https://doi.org/10.1038/s41598-020-61435-y

Crone, N.E., Sinai, A., Korzeniewska, A. (2006). High-frequency gamma oscillations and human brain mapping with electrocorticography. *Progress in Brain Research, 159*, 275-295. https://doi-org.simsrad.net.ocs.mq.edu.au/10.1016/S0079-6123(06)59019-3

Dash, D., Ferrari, P., Berstis, K., & Wang, J. (2021). Imagined, Intended, and Spoken Speech Envelope Synthesis from Neuromagnetic Signals. In A. Karpov & R. Potapova (Eds.), *Speech and Computer* (Vol. 12997, pp. 134–145). Springer International Publishing. https://doi.org/10.1007/978-3-030-87802-3_13

Dash, D., Ferrari, P., Heitzman, D., & Wang, J. (2019). Decoding Speech from Single Trial MEG Signals Using Convolutional Neural Networks and Transfer Learning. *2019 41st Annual International Conference of the IEEE Engineering in Medicine and Biology Society (EMBC)*, 5531–5535. https://doi.org/10.1109/EMBC.2019.8857874

Dash, D., Ferrari, P., Malik, S., & Wang, J. (2018). Overt speech retrieval from neuromagnetic signals using wavelets and artificial neural networks. *2018 IEEE Global Conference on Signal and Information Processing (GlobalSIP)*, 489–493. https://doi.org/10.1109/GlobalSIP.2018.8646401

Dash, D., Ferrari, P., & Wang, J. (2020). Decoding Speech Evoked Jaw Motion from Non-invasive Neuromagnetic Oscillations. *2020 International Joint Conference on Neural Networks (IJCNN)*, 1–8. https://doi.org/10.1109/IJCNN48605.2020.9207448

Dash, D., Wisler, A., Ferrari, P., Davenport, E. M., Maldjian, J., & Wang, J. (2020). MEG Sensor Selection for Neural Speech Decoding. *IEEE Access*, *8*, 182320–182337. https://doi.org/10.1109/ACCESS.2020.3028831

De Nil, L., Isabella, S., Jobst, C., Kwon, S., Mollaei, F., & Cheyne, D. (2021). Complexity-dependent modulations of beta oscillations for verbal and nonverbal movements. *Journal of Speech, Language, and Hearing Research*, *64*(6S), 2248-2260.

Dichter BK, Breshears JD, Leonard MK, Chang EF (2018) The control of vocal pitch in human laryngeal motor cortex. Cell, *174*:21–31.e9. https://doi-org.simsrad.net.ocs.mq.edu.au/10.1016/j.cell.2018.05.016

Doesburg, S. M., Tingling, K., MacDonald, M. J., & Pang, E. W. (2016). Development of network synchronization predicts language abilities. *Journal of Cognitive Neuroscience*, *28*(1), 55–68. https://doi.org/10.1162/jocn_a_00879

Eichert, N., Papp, D., Mars, R.B. & Watkins K.E. (2020). Mapping human laryngeal motor cortex during vocalization. *Cerebral Cortex*, *30*, 6254–69. https://doi.org/10.1093/cercor/bhaa182.

Frankford, S. A., Nieto-Castañón, A., Tourville, J. A., & Guenther, F. H. (2021). Reliability of single-subject neural activation patterns in speech production tasks. *Brain and Language*, *212*, 104881. https://doi.org/10.1016/j.bandl.2020.104881

Fitts, P. M. (1954). The information capacity of the human motor system in controlling the amplitude of movement. *Journal of Experimental Psychology*, 47(6), 381–391. https://doi.org/10.1037/h0055392

Glasser, M. F., Coalson, T. S., Robinson, E. C., Hacker, C. D., Harwell, J., Yacoub, E., Ugurbil, K., Andersson, J., Beckmann, C. F., Jenkinson, M., Smith, S. M., & Essen, D. C. V. (2016). A multi-modal parcellation of human cerebral cortex. *Nature*, *536*(7615), 171–178. https://doi.org/10.1038/nature18933

Goldstein, L., & Fowler, C. A. (2003). Articulatory phonology: A phonology for public language use. *Phonetics and phonology in language comprehension and production: Differences and similarities*, 159-207.

Grootswagers, T., Wardle, S. G., & Carlson, T. A. (2017). Decoding dynamic brain patterns from evoked responses: a tutorial on multivariate pattern analysis applied to time series neuroimaging data. *Journal of cognitive neuroscience*, *29*(4), 677-697.

Heim, S., & Specht, K. (2019). Studying language with functional magnetic resonance imaging (fMRI). In G. I. de Zubicaray & N. O. Schiller (Eds.), *The Oxford Handbook of Neurolinguistics* (pp. 71–93). Oxford University Press. https://doi.org/10.1093/oxfordhb/9780190672027.013.4

Henriques, R., Van Lieshout P. (2013). A comparison of methods for decoupling tongue and lower lip from jaw movements in 3D articulography. *Journal of Speech, Language, and Hearing Research, 56*, 1503–16. https://doi.org/10.1044/1092-4388(2013/12-0016)

Hickok, G., Venezia, J., & Teghipco, A. (2023). Beyond Broca: neural architecture and evolution of a dual motor speech coordination system. *Brain*, awac454. https://doi.org/10.1093/brain/awac454

Indefrey, P., & Levelt, W. J. (2000). The neural correlates of language production. *The new Cognitive Neurosciences; 2nd ed.*, 845-865.

Janssen, N., Kessels, R. P. C., Mars, R. B., Llera, A., Beckmann, C. F., & Roelofs, A. (2022). Dissociating the functional roles of arcuate fasciculus subtracts in speech production. *Cerebral Cortex*, bhac224. https://doi.org/10.1093/cercor/bhac224

Johnson, B. W., & He, W. (2019). MEG studies on the connectivity of brain networks in children. *Magnetoencephalography: From signals to dynamic cortical networks*, 733-756.

Johnson, B.W., Jobst, C., Al - Loos, R., He, W., Cheyne, D. (2020). Individual differences in movement related brain activity in early childhood: An MEG study." Developmental Science, 23, e12935. https://doi-org.simsrad.net.ocs.mq.edu.au/10.1111/desc.12935

Jobst, Cecilia, Paul Ferrari, Silvia Isabella, and Douglas Cheyne. BrainWave: A Matlab Toolbox for beamformer source analysis of MEG data (2018). *Frontiers in Neuroscience, 12* (August 22, 2018). https://doi.org/10.3389/fnins.2018.00587

Kadis, D. S., Pang, E. W., Mills, T., Taylor, M. J., McAndrews, M. P., & Smith, M. L. (2011). Characterizing the normal developmental trajectory of expressive language lateralization using magnetoencephalography. *Journal of the International Neuropsychological Society*, *17*(05), 896–904. https://doi.org/10.1017/S1355617711000932

Kado, H., Higuchi, M., Shimogawara, M., Haruta, Y., Adachi, Y., Kawai, J., Ogata, H., & Uehara, G. (1999). Magnetoencephalogram systems developed at KIT. *IEEE Transactions on Applied Superconductivity*, *9*(2), 4057–4062. https://doi.org/10.1109/77.783918

Kearney, E., & Guenther, F.H. (2019). Articulating: The neural mechanisms of speech production." *Language, Cognition and Neuroscience*, *34*, 1214–29. https://doi.org/10.1080/23273798.2019.1589541.

Kelso, J. A., Saltzman, E. L., & Tuller, B. (1986). The dynamical perspective on speech production: Data and theory. *Journal of Phonetics*, *14*(1), 29-59.

Kelso, J. S. (1995). *Dynamic patterns: The self-organization of brain and behavior*. MIT press Boston.

Kolasinski, J., Dima, D. C., Mehler, D. M. A., Stephenson, A., Valadan, S., Kusmia, S., & Rossiter, H. E. (2020). Spatially and temporally distinct encoding of muscle and kinematic information in rostral and caudal primary motor cortex. *Cerebral Cortex Communications*, *1*(1), tgaa009. https://doi.org/10.1093/texcom/tgaa009

Kriegeskorte, N. (2008). Representational similarity analysis – connecting the branches of systems neuroscience. Frontiers in Systems Neuroscience. https://doi.org/10.3389/neuro.06.004.2008

Kriegeskorte, N., & Kievit, R. A. (2013). Representational geometry: Integrating cognition, computation, and the brain. Trends in Cognitive Sciences, 17(8), 401–412. https://doi.org/10.1016/j.tics.2013.06.007

Kuberski, S. R., & Gafos, A. I. (2021). Fitts' law in tongue movements of repetitive speech. *Phonetica*, *78*(1), 3-27.

Leckey, M., & Federmeier, K. D. (2019). Electrophysiological methods in the study of language processing. In G. I. de Zubicaray & N. O. Schiller (Eds.), *The Oxford Handbook of Neurolinguistics* (pp. 41–71). Oxford University Press. https://doi.org/10.1093/oxfordhb/9780190672027.013.3

Levelt, W. J. M., Praamstra, P., Meyer, A. S., Helenius, P., & Salmelin, R. (1998). An MEG study of picture naming. *Journal of Cognitive Neuroscience*, *10*(5), 553–567. https://doi.org/10.1162/089892998562960

Lin, F.-H., Belliveau, J. W., Dale, A. M., and Hämäläinen, M. S. (2006). Distributed current estimates using cortical orientation constraints. Hum. Brain. Mapp. 27, 1–13. doi: 10.1002/hbm.20155

Maris, E., & Oostenveld, R. (2007). Nonparametric statistical testing of EEG- and MEG-data. Journal of Neuroscience Methods, 164(1), 177–190. https://doi.org/10.1016/j.jneumeth.2007.03.024

Morgan, A. T., & Webster, R. (2018). Aetiology of childhood apraxia of speech: A clinical practice update for paediatricians. *Journal of paediatrics and child health*, *54*(10), 1090-1095.

Mugler, E. M., Tate, M. C., Livescu, K., Templer, J. W., Goldrick, M. A., & Slutzky, M. W. (2018). Differential representation of articulatory gestures and phonemes in precentral

and inferior frontal gyri. *The Journal of Neuroscience*, *38*(46), 9803–9813. https://doi.org/10.1523/JNEUROSCI.1206-18.2018

Munding, D., Dubarry, A.-S., & Alario, F.X. (2016). On the cortical dynamics of word production: A review of the MEG evidence. *Language, Cognition and Neuroscience*, *31*(4), 441–462. https://doi.org/10.1080/23273798.2015.1071857

Murray, E., McCabe, P., & Ballard, K. J. (2015). A randomized controlled trial for children with childhood apraxia of speech comparing rapid syllable transition treatment and the Nuffield Dyspraxia Programme–Third Edition. *Journal of Speech, Language, and Hearing Research*, *58*(3), 669–686. https://doi.org/10.1044/2015_JSLHR-S-13-0179

Neufeld, C., & van Lieshout, P. (2014). Tongue kinematics in palate relative coordinate spaces for electro-magnetic articulography. *The Journal of the Acoustical Society of America*, *135*(1), 352-361.

Nichols, T. E., and Holmes, A. P. (2002). Nonparametric permutation tests for functional neuroimaging: a primer with examples. Hum. Brain Mapp. 15, 1–25. doi: 10.1002/hbm.1058

Ouyang, G., Sommer W., Zhou C., Aristei S., Pinkpank T., Rahman, R.A. (2016). Articulation artifacts during overt language production in event-related brain potentials: Description and correction." *Brain Topography*, *29*, 791–813. https://doi.org/10.1007/s10548-016-0515-1.

Pang, E. W., Wang, F., Malone, M., Kadis, D. S., & Donner, E. J. (2011). Localization of Broca's area using verb generation tasks in the MEG: Validation against fMRI. *Neuroscience Letters*, *490*(3), 215–219. https://doi.org/10.1016/j.neulet.2010.12.055

Peeva, M. G., Guenther, F. H., Tourville, J. A., Nieto-Castanon, A., Anton, J. L., Nazarian, B., & Alario, F. X. (2010). Distinct representations of phonemes, syllables, and supra-syllabic sequences in the speech production network. *Neuroimage*, *50*(2), 626-638.

Pfurtscheller, G., Neuper Ch., Andrew, C., Edlinger, G. (1997). Foot and hand area mu rhythms. *International Journal of Psychophysiology*, *26*, 121-135.

Pfurtscheller, G., Graimann, B., Huggins, J.E., Levine, S.P. and Schuh, L.A. Spatiotemporal patterns of beta desynchronization and gamma synchronization in corticographic data during self-paced movement. *Clinical Neurophysiology, 114*, 1226–36. https://doi.org/10.1016/S1388-2457(03)00067-1.

Ramsey, N. F., Salari, E., Aarnoutse, E. J., Vansteensel, M. J., Bleichner, M. G., & Freudenburg, Z. V. (2018). Decoding spoken phonemes from sensorimotor cortex with high-density ECoG grids. *NeuroImage*, *180*, 301–311. https://doi.org/10.1016/j.neuroimage.2017.10.011

Rong, F., Isenberg, A. L., Sun, E., & Hickok, G. (2018). The neuroanatomy of speech sequencing at the syllable level. *PloS one*, *13*(10), e0196381.

Salmelin, R., Kujala, J., & Liljeström, M. (2019). Magnetoencephalography and the cortical dynamics of language processing. In G. I. de Zubicaray & N. O. Schiller (Eds.), *The*

1263   *Oxford Handbook of Neurolinguistics* (pp. 114–153). Oxford University Press.
1264   https://doi.org/10.1093/oxfordhb/9780190672027.013.6

1266 Saltzman, E. (1986). Task dynamic coordination of the speech articulators: A preliminary
1267   model. *Experimental Brain Research Series*, *15*, 129-144.

1269 Silva, A. B., Liu, J. R., Zhao, L., Levy, D. F., Scott, T. L., & Chang, E. F. (2022). A neurosurgical
1270   functional dissection of the middle precentral gyrus during speech production. *Journal of*
1271   *Neuroscience*, *42*(45), 8416–8426. https://doi.org/10.1523/JNEUROSCI.1614-22.2022

1273 Tong, J., Binder, J. R., Humphries, C., Mazurchuk, S., Conant, L. L., & Fernandino, L. (2022). A
1274   distributed network for multimodal experiential representation of concepts. *The Journal*
1275   *of Neuroscience*, *42*(37), 7121–7130. https://doi.org/10.1523/JNEUROSCI.1243-21.2022

1277 Tourville, J. A., Nieto-Castañón, A., Heyne, M., & Guenther, F. H. (2019). Functional
1278   parcellation of the speech production cortex. *Journal of Speech, Language, and Hearing*
1279   *Research*, *62*(8S), 3055–3070. https://doi.org/10.1044/2019_JSLHR-S-CSMC7-18-0442

1281 Treder, M. S. (2020). MVPA-Light: A classification and regression toolbox for multi-dimensional
1282   data. *Frontiers in Neuroscience*, *14*, 289. https://doi.org/10.3389/fnins.2020.00289

1284 Uehara, G., Adachi, Y., Kawai, J., Shimogawara, M., Higuchi, M., Haruta, Y., ... & Kado, H.
1285   (2003). Multi-channel SQUID systems for biomagnetic measurement. *IEICE transactions*
1286   *on electronics*, *86*(1), 43-54.

1288 Van Lieshout, P. (2021). Electromagnetic articulography. *Manual of Clinical Phonetics*, pp. 356-
1289   74. Routledge. https://doi-org.simsrad.net.ocs.mq.edu.au/10.4324/9780429320903

1291 Van Lieshout, P. H. H. M. (2017). Coupling dynamics in speech gestures: Amplitude and rate
1292   influences. *Experimental Brain Research*, *235*(8), 2495–2510.
1293   https://doi.org/10.1007/s00221-017-4983-7

1295 Van Lieshout, P. H. H. M., Bose, A., Square, P. A., & Steele, C. M. (2007). Speech motor
1296   control in fluent and dysfluent speech production of an individual with apraxia of speech
1297   and Broca's aphasia. *Clinical Linguistics & Phonetics*, *21*(3), 159–188.
1298   https://doi.org/10.1080/02699200600812331

1300 Van Lieshout, P. H., Hulstijn, W., Alfonso, P. J., & Peters, H. F. (1996). Higher and lower order
1301   influences on the stability of the dynamic coupling between articulators.

1303 Van Lieshout, P. H. H. M., Rutjens, C. A. W., & Spauwen, P. H. M. (2002). The dynamics of
1304   interlip coupling in speakers with a repaired unilateral cleft-Lip history. *Journal of*
1305   *Speech, Language, and Hearing Research*, *45*(1), 5–19. https://doi.org/10.1044/1092-
1306   4388(2002/001)

1308 Youssofzadeh, V., & Babajani-Feremi, A. (2019). Mapping critical hubs of receptive and
1309   expressive language using MEG: A comparison against fMRI. *NeuroImage*, *201*, 116029.
1310   https://doi.org/10.1016/j.neuroimage.2019.116029

1311

1312   Zhang, W., Liu, Y., Wang, X., & Tian, X. (2020). The dynamic and task dependent
1313   representational transformation between the motor and sensory systems during speech
1314   production. Cognitive Neuroscience, 11(4), 194–204.
1315   https://doi.org/10.1080/17588928.2020.1792868

1330   Supplementary Materials
1331
1332

Figure S1. Representative acoustic and kinematic measurements from MASK. Data are shown for
two participants for a single /ipa/ trial set at normal and faster speaking rates. Shown are (from top
to bottom) waveforms for the audio signal, tongue body (TB) gesture, and bilabial constriction
(BC) gesture.

Figure S2. Covariation of kinematic parameters of speech movements for two participants.
Left columns: Velocity versus amplitude. Right columns: Stiffness versus duration. BC = bilabial
closure. TB = tongue body.
1340

Acoustic signal
MEG computer

Acoustic signal
MASK computer

Spectrogram

5 kHz

0 kHz

Tongue body

Open

Closed

Bilabial closure

Open

Closed

Time (sec)

1 2 3 4

1 2 3 4

A

Speech Instructions	Fixation and breath intake	Trial Set 1	Inter Trial Set Interval	Fixation and breath intake	Trial Set 2	....	Trial Set 10
30 sec	1 sec	12 sec	4 sec	1 sec	12 sec		12 sec

B

Button Press Instructions	Fixation	Self paced button press
30 sec	5 sec	180 sec

Mu-band

Beta-band

Gamma-band

/api/ normal rate

Correlations with behavioural
dissimilarity matrix
based on *stiffness-duration*
profile for first opening
movement of bilabial closure

/ipa/ normal rate

Correlations with behavioural
dissimilarity matrix
based on *amplitude-velocity*
profile for first opening
movement of bilabial closure

A

Behavioural RDM

Neural RDM

S1133 /ipa/ normal rate

acoustic

TB

BC

time (s)

S1133 /api/ normal rate

time (s)

S1133 /ipa/ faster rate

acoustic

TB

BC

time (s)

S1133 /api/ faster rate

time (s)