TESSELLATION OF ARTIFICIAL TOUCH VIA MICROSTIMULATION OF HUMAN SOMATOSENSORY CORTEX

Charles M. Greenspon[1], Natalya D. Shelchkova[2], Giacomo Valle[1], Taylor G. Hobbs[3,4], Ev I. Berger-Wolf[1], Brianna C. Hutchison[5], Efe Dogruoz[1], , Ceci Verbarschott[3], Thierri Callier[1], Anton R. Sobinov[1], Elizaveta V. Okorokova[2], Patrick M. Jordan[1], Dillan Prasad[1], Qinpu He[2], Fang Liu[3,6], Jonathan P. Miller[7,8,9] , Ray C. Lee[10], David Satzer[11], Jorge Gonzalez-Martinez[12], Peter C. Warnke[11], Lee E. Miller[13,14,15,16], Michael L. Boninger[3,6,4], Abidemi B. Ajiboye[5,7,9], Emily L. Graczyk[5,7,9], John E. Downey[1], Jennifer L. Collinger[3,6,4,17], Nicholas G. Hatsopoulos[1,2,18], Robert A. Gaunt[3,6,4,17], and Sliman J. Bensmaia[1,2,18]

[1] Department of Organismal Biology and Anatomy, University of Chicago, Chicago, IL
[2] Committee on Computational Neuroscience, University of Chicago, Chicago, IL
[3] Rehab Neural Engineering Labs, University of Pittsburgh, Pittsburgh, PA
[4] Department of Bioengineering, University of Pittsburgh, Pittsburgh, PA
[5] Department of Biomedical Engineering, Case Western Reserve University, Cleveland, OH
[6] Department of Physical Medicine and Rehabilitation, University of Pittsburgh, Pittsburgh, PA
[7] School of Medicine, Case Western Reserve University, Cleveland, OH
[8] The Neurological Institute, University Hospitals Cleveland Medical Center, Cleveland, OH
[9] Louis Stokes Cleveland VA Medical Center, Cleveland, OH
[10] Schwab Rehabilitation Hospital, Chicago, IL
[11] Department of Neurological Surgery, University of Chicago, Chicago, IL
[12] Department of Neurosurgery, University of Pittsburgh, Pittsburgh, PA
[13] Department of Neuroscience, Northwestern University, Chicago, IL
[14] Department of Biomedical Engineering, Northwestern University, Evanston, IL
[15] Department of Physical Medicine and Rehabilitation, Northwestern University, Chicago, IL
[16] Shirley Ryan Ability Lab, Chicago, IL
[17] Department of Biomedical Engineering, Carnegie Mellon University, Pittsburgh, PA
[18] Neuroscience Institute, University of Chicago, Chicago, IL

ACKNOWLEDGMENTS
We would like to thank the participants for their generous contribution to the advancement of science. This work was supported by NINDS grants UH3 NS107714, R35 NS122333 and RO1 NS119160.

DISCLOSURES
NH and RG serve as consultants for Blackrock Neurotech, Inc. RG is also on the scientific advisory boards of Braingrade GmbH and Neurowired LLC. MB, JC, RG, NH, and SB receive research funding from Blackrock Neurotech, Inc. though that funding did not support the work presented here.

ABSTRACT

When we interact with objects, signals from the hand convey information about the objects and our interactions with them. A basic feature of these interactions, the locations of contacts between the hand and object, is often only available via the sense of touch. Information about locations of contact between a brain-controlled bionic hand and an object can in principle be signaled via intracortical microstimulation (ICMS) of somatosensory cortex (S1), which evokes touch sensations that are localized to a specific patch of skin. To provide intuitive location information, tactile sensors on the robotic hand drive ICMS through electrodes that evoke sensations at skin locations matching sensor locations. This approach requires that ICMS-evoked sensations be focal, stable, and distributed over the hand. To systematically investigate the localization of ICMS-evoked sensations, we analyzed the projected fields (PFs) of ICMS-evoked sensations – their spatial extent – from reports obtained over multiple years from three participants implanted with micro-electrode arrays in S1. First, we found that PFs vary widely in their size, are highly stable, and are distributed over large swaths of each participant's hand. Second, PFs increase in size as the amplitude and frequency of ICMS increases. Third, leveraging participants with residual sensation, we found that PF locations match the locations of the receptive fields (RFs) of the neurons near the stimulating electrode. Furthermore, PFs tended to be subsumed by the corresponding RFs. Fourth, multi-channel stimulation yielded a PF that reflected an approximately additive combination of the PFs of the component channels. By stimulating through electrodes with largely overlapping PFs, then, we could evoke more focal sensations, experienced primarily at the intersection of the component PFs. To assess the functional consequence of this phenomenon, we implemented multi-channel ICMS-based feedback in a bionic hand and demonstrated that the resulting sensations are more localizable than are those evoked via single-channel ICMS.

INTRODUCTION

When we interact with objects, signals from the hand convey information about the objects and about our interactions with them (Johansson and Flanagan, 2009). A basic feature of object interactions, the location on the hand of contacts with objects, is often only available via the sense of touch because some contacts are visually occluded and visual feedback, even when available, is a poor substitute for touch to guide object interactions (Cabibihan et al., 2021). Efforts are underway to restore tactile feedback via bionic hands by electrically activating touch neurons along the neuraxis (Bensmaia et al., 2020) . Indeed, electrical activation of tactile nerve fibers evokes sensations experienced at a specific location on the skin, known as the projected field (PF) (Ochoa and Torebjörk, 1983; Ortiz-Catalan et al., 2020b; Overstreet et al., 2019; Petrini et al., 2019; Tan et al., 2014; Wendelken et al., 2017). Similarly, delivering intracortical microstimulation (ICMS) to somatosensory cortex (S1) typically evokes a sensation restricted to a specific patch of skin (Fifer et al., 2020; Flesher et al., 2016; Salas et al., 2018; Tabot et al., 2013). Thus, force sensors on the bionic hand can be used to drive stimulation through electrodes in the nerve or in the brain that evoke sensations on the corresponding location on the phantom or deafferented hand, thereby intuitively conveying information about contact location.

The representation of the body in S1 is systematically organized, such that nearby body parts are encoded by the activity recorded from neighboring neuronal populations, with some discontinuities reflecting those in the body (Delhaye et al., 2018; Penfield and Boldrey, 1937). Stimulating through nearby electrodes has been shown to evoke sensations in nearby hand regions following the expected

somatotopic organization (Fifer et al., 2020; Flesher et al., 2016). Furthermore, the organization of S1 is consistent across individuals – with the hand representation featuring a systematic progression from the thumb to the little finger as one progresses in the medial posterior direction along the central sulcus. This organization facilitates electrode array placement because locating the respective S1 representations of a subset of digits informs where the representations of the other digits lie. Pre-operative fMRI, MEG, or ECOG can be used to identify the digit representations and thus guide the placement of arrays of stimulating electrodes (Flesher et al., 2016; Foldes et al., 2021). Critically, studies involving limited numbers of patients and electrodes have shown that PFs are relatively stable over time (Flesher et al., 2016; Ortiz-Catalan et al., 2020a), suggesting that the somatotopic map is stable, even after deafferentation caused by spinal cord injury or amputation (Kikkert et al., 2021, 2016; Makin and Bensmaia, 2017).

Though electrical activation of S1 neurons has been shown to evoke focal sensations, these observations have been largely qualitative. The spatial extent, distribution, and stability of the evoked PFs have not been systematically evaluated (Bjånes et al., 2022; Flesher et al., 2016; Salas et al., 2018). To fill this gap, we quantitatively characterized the PFs of ICMS-evoked sensations in three human participants with cervical spinal cord injury and gauged the degree to which they remained stable over a period of years. In an additional series of experiments with participants endowed with residual sensation, we also assessed the degree to which the PF of an electrode coincided with its receptive field (RF), defined as the patch of skin that, when touched, activates neurons around the electrode tip. First, we found that PFs were

Figure 1. Array implant locations and sensation maps for all subjects. Each row shows the anatomical MRI with (subsequently implanted) arrays superimposed based on intra-operative photos for each participant (C1, P2, or P3). M1 and S1 denote primary motor cortex and somatosensory cortex (Brodmann's area 1), respectively. The central sulcus is indicated by the dashed line. The areas on the hand in which each subject feels sensations when ICMS is performed are shown in the middle column and the corresponding electrodes that evoke those sensations are shown in the array maps on the right.

highly stable over time and covered large swaths of the hand (across two arrays in S1). Second, the locations of the PFs followed the expected somatotopic organization of the sensory homunculus. Third, at the current levels tested, the PF of an electrode tended to be smaller than but largely subsumed by its RF. Fourth, ICMS delivered through multiple electrodes yielded a PF reflecting a conjunction of the PFs of the individual electrodes; any overlapping regions of the PFs were thus more salient. Accordingly, stimulating through multiple electrodes with overlapping PFs evokes more localizable sensations than does stimulating through individual channels facilitating better localization of touches on a bionic hand. We discuss the implications of our findings in the development of sensitized brain-controlled bionic hands.

RESULTS

Three participants were implanted with arrays of electrodes in the hand representation of S1 (Brodmann's area 1, **Figure 1**, **Supplementary Figure 1**), localized based on pre-operative functional Magnetic Resonance Imaging or Magnetoencephalography. In participant C1, most of the sensations were experienced on the fingertips, in participant P2, on the palm, and in participant P3, on the medial phalanges and palm. To quantitatively characterize the PF of each electrode, we repeatedly delivered through it a 1-sec long ICMS pulse train (100 Hz, 60 µA), which was intense enough to reliably elicit a sensation for most electrodes (**Supplementary Figure 2A**, **Supplementary Figure 2B**). After each stimulation bout, the participant drew the spatial extent of the PF on a digital representation of his hand (**Figure 2A**). From these images, we computed, for each electrode on each testing day, the area of skin over which the PF extended and its center of mass (centroid) (**Figure 2B**). We also computed an aggregate PF for each stimulating channel by weighting each pixel on the hand by the proportion of times it was included in the reported PF over the duration of the study (**Figure 2C**). This allowed us to estimate the probability of a sensation being evoked on different parts of the hand for each channel and revealed that most electrodes had a core region in which sensations were reliably evoked and a diffuse shell over which sensations were less consistent. With this in mind, we applied a reliability criterion (33%) on the aggregate PFs and removed pixels that did not meet this criterion (See **Supplementary Figure 3** for the justification of the threshold level). PFs for which no pixels met this threshold criterion were deemed too unreliable and excluded from further analysis, totaling around 25% for Participants C1 & P2 and ~60% for Participant P3.

Next, we examined how the PFs tiled the hands for each participant. While all participants reported a sensation on most of the hand on at least one occasion (**Figure 2D**, light shade), participant C1 predominantly experienced sensations on the tip of the digits, participant P2 on the pads and thumb, and participant P3 on both. Examining individual electrodes, we found that PF size varied widely (median = 25.1 mm^2; 5th/95th percentiles = 8.3 / 52.2 mm^2) across electrodes (**Figure 2E**) and participants, with C1 reporting the smallest PFs and P2 the largest. Overall, as many of the PFs overlap, the total area over which sensations were evoked was less than the sum of the individual PF, with total area (the union of all reported pixels for each participant) ranging between 70 and 140 mm^2. C1 had the most distal PFs and P2 had the most proximal ones, suggesting that PFs decrease in size as one progresses distally from the palm to the digit tips but confounded by the small sample of participants. Note that receptive fields of neurons in S1 generally follow an analogous trend, where distal RFs are smaller than proximal ones (Sur et al., 1980). In parallel, also the ICMS-evoked phosphene size depend on the location of the stimulated site in the visual cortex, with size increasing with distance from the foveal representation (Bosking et al., 2017).

Figure 2. Projected field locations systematically vary in size and location across participants. A| Example projected fields from one session from each participant. Crosses denote the respective centroids. **B|** The same projected fields as in panel A but across all sessions. **C|** The density function computed for the same electrodes across all sessions. **D|** Parts of the hand upon which each participant reported a session. The lighter shade indicates pixels selected on <33% of sessions while the darker shade indicates pixels selected on >33% of sessions. **E|** The distribution of the size of the sensations evoked for each electrode (after thresholding) for each participant. **F|** The area of the hand over which a sensation can be evoked, given by the union of projected fields of across electrodes, for each participant (after thresholding).

Projected fields are highly stable over time

While PF field location has been reported to be stable over time (Flesher et al., 2016), stability was not been systematically quantified. To fill this gap, we compared the location of the PFs at regular intervals across 2 to 7 years (for C1/P3 and P2, respectively; **Figure 2B,C**). First, we computed the degree to which PFs reported for an electrode on any given session matched the first ever reported PF on that electrode. We found that centroid distance between the initial PF and subsequent ones for a given electrode remained stable, with no significant change over the lifetime of the arrays for two of the three participants (C1 and P3, r = -0.03 and 0.12, p = 0.99 and 0.34, respectively), and a slight but significant increase in the third (P2, r = 0.23, p < 0.01, **Supplementary Figure 4A**). At the single electrode level, some electrodes yielded positive and others negative slopes, distributed evenly around 0 for two participants (C1 and P3, t = 0.56 and 2.39, p = 0.99 and 0.09 respectively) and shifted positively for the third (P2, t = 3.35, p < 0.01, **Supplementary Figure 4B**) but always very shallow (median = 0.00 mm/day; Q_1, Q_3 = 0.00, 0.01 respectively). Second, we computed the distance between each single-day centroid and its corresponding aggregate centroid (**Figure 3A**) to determine how representative the aggregate PF was of any individual PF for a given electrode. Across all recording sessions, we found that the mean variation in centroid placement ranged from 3.5 to 8.7 mm (depending on the participant). Note, however, that larger PFs tended to yield more variable centroids (**Figure 3C**, r = 0.34, p < 0.01), as might be expected. Furthermore, centroid distance was stable over time for one of the subjects (P3, r = -0.1, p = 0.77) and *decreased* over time for the other two (C1 and P2, r = -0.17 for both, p < 0.01 for both), suggesting that the latter converged onto a more stable reporting of their PFs (over the years that these measurements were obtained).

Figure 3. Sensation locations are stable over time. A| The distribution of distances from the aggregate centroid across electrodes for each subject over time is stable. **B|** Mean centroid distance when reports were collected within a single day compared to that computed across years for a subset of matched electrodes. **C|** The variance in reporting location is dependent upon the size of the evoked sensation.

Next, we assessed whether the fluctuations in reported PF reflected true changes in position over time or simply variability in the participants' reports. To this end, ICMS pulse trains were delivered through a subset of electrodes (n = 12 and 11 for C1 and P2, respectively), interleaved randomly, and the participant reported the PF of each. This procedure was then repeated multiple times throughout the day (6 times for subject C1 and 5 times for subject P2), each time in a different order to reduce biases. We then assessed the degree to which the centroids of the reported PFs coincided. First, PFs were consistent between repeated reports for the two participants tested (centroid distance: median = 3.5 mm, Q_1-Q_3, 1.6 – 4.8 mm). Second, the within- vs. across-day centroid distances for each electrode were highly correlated (r = 0.68, p < 0.01) and statistically equivalent (paired t-test, t = 0.1, p = 0.93, **Figure 3B**). In other words, the variability in the PFs reported within a session was equivalent to the variability in the PFs reported over years of testing. We conclude that the bulk of the variability in PFs over time reflects variability in the reports rather than variability in the PFs themselves (assuming that PFs are stable within a day). PFs are thus highly stable over time. Furthermore, the aggregate PF provides a reliable estimate of the PF.

Projected fields progress systematically with location along the cortical surface

According to the canonical homunculus, the representations of digits and hand segments proceed systematically along an axis parallel to the central sulcus. Examination of the PF maps (**Supplementary Figure 1**) suggests that, within each array, the dominant digit or hand segment – where the PFs are predominantly located – changes systematically along one axis but not along its perpendicular axis, consistent with the geometry of the homunculus. To test this quantitatively, we projected the location of each electrode on each array onto a single axis and assessed the degree to which the identity of the digit could be inferred from the electrode's location on that axis (**Figure 4A**). By computing classification accuracy across a range of axes (spanning 180 degrees), we identified the axis along which the digit/hand segment gradients were most pronounced. We found that, for each array, a single axis could account for digit or hand segment dominance as well as if both coordinates were included and that this axis was approximately parallel to the central sulcus for 5 out of the 6 arrays (**Figure 4B**), consistent with the canonical homunculus. In the array that did not show this pattern, the axis was nearly perpendicular to

Figure 4. PFs progress systematically across electrodes. A| The ability to classify digit identify based on position along a single axis depends on the angle of that axis. Rotation of the projected axis is relative to the rotation at which minimum performance was achieved. Zero degrees corresponds to the short axis of the array. **B|** Each participant's sensory implants and the optimal digit discrimination axis shown superimposed on the array (dotted line). The central sulcus is shown as a dashed line. **C|** Within digit, the distance between two projected fields is correlated to the distance between the electrodes (n = 5892 pairs, r = 0.69, p < 0.01). When computed on individual arrays correlations are significant for all (r > 0.4, p < 0.01).

the central sulcus, but the dominance gradient was weak, largely because the reported PFs were so large and overlapping. Next, we examined whether the distance between PFs increased as the distance between electrodes increased, restricting the analysis to pairs of electrodes with PFs on the same digit. We found that, as expected, centroid distance increased systematically with cortical distance (**Figure 4C**). A 2-mm shift in cortex corresponded to a ~10-mm shift in the PF on the skin, on average. The systematic relationship between cortical location and PF location are thus consistent with the canonical homunculus, in which S1 is characterized by strips that encode individual digits or palmar whorls.

The projected field is determined by the receptive field of the activated neurons

To further examine the relationship between homunculus location and PF location, we leveraged the residual sensation in two of our participants (C1 and P3) and compared the receptive field (RF) and PF of each electrode. To map RFs, we applied gentle touches to the skin and monitored the multiunit activity through speakers. As for the PFs, RFs were measured over multiple days with the experimenter blinded to electrode identity. Repeated mapping sessions yielded nearly identical RFs. We then examined the spatial correspondence of the PF and RF of each electrode (**Figure 5A**). First, we found that, across electrodes and participants, RFs were on average twice larger than the PFs (**Figure 5B**). However, there was no relationship between the size of the PF and the size of its corresponding RF (r = 0.13 and 0.36, p =

Figure 5. The projected field of an electrode is smaller than and circumscribed by its receptive field. A| Aggregate PF (red) and measured RF (blue) for two example electrodes from participant C1 and P3, respectively. **B|** Size of the RF vs. size of the PF for electrodes from which both were obtained in participants C1 and P3. Receptive fields were larger for both subjects (paired t-test, p < 0.01 for both). **C|** Proportion of the PF that fell within the RF for all tested electrodes. The median proportion was 1 for both with 25th percentiles of 0.83 and 0.72 for C1 and P3, respectively, suggesting that PFs tended to be completed subsumed in the RF. **D|** The number of regions (digits plus palm) encapsulated by each electrodes RF minus its PF for 3 participants. Multiple electrodes are shown for each participant with pairs connected by dotted lines. RFs spanned more hand regions than PFs in all 3 subjects (Ranksum test, p < 0.01, Holm-Bonferroni corrected).

0.37 and 0.15, for participant C1 and P3, respectively). Secondly, PFs were typically subsumed by the RF: On average, 80% of the reported PF fell within the measured RF (**Figure 5C**). In both participants, the RF included more hand segments than did the PF. We verified that this phenomenon was not an artifact of our approach by examining the RFs and PFs characterized independently by another group in a third partially sensate participant (**Figure 5D**, see Methods). We conclude that the PF of an electrode is determined by the RFs of the neurons around the electrode tip. Furthermore, the spatial extent of PFs tended to scale with that of the corresponding RF, but this relationship was only significant for one of the two participants (r = 0.15 and 0.76, p = 0.35 and 0.011 for C1 and P3, respectively).

Projected fields grow larger with more intense ICMS

Next, we examined the degree to which PFs were dependent on ICMS amplitude and frequency. First, we found that the size of the PF increased threefold as amplitude increased from 40 to 80 μA, with ICMS frequency fixed at 100 Hz (**Figure 6A**, median (Q_1-Q_3)= 170% (142-330%), 2-way ANOVA (2,11), F = 6.26, p

Figure 6. PF size and sensory magnitude increase with ICMS amplitude and frequency. A| Normalized ratings of sensory magnitude and PF size vs. ICMS amplitude (at 100 Hz). **B|** Normalized ratings of sensory magnitude and PF size vs. ICMS frequency (with amplitude fixed at 60 µA). Both frequency and amplitude significantly impacted perceived size and intensity (2-way ANOVA, p< 0.01 for all). **C|** PF size and sensory magnitude are strongly correlated (r = 0.77, p < 0.01). Data from participant C1.

< 0.01). Second, PFs grew systematically as frequency increased from 50 to 200 Hz, with amplitude fixed at 60 µA (**Figure 6B**, median (Q_1-Q_3)= 129% (121-185%), 2-way ANOVA (2,11), F = 7.43, p < 0.01). Because the perceived magnitude increases with both ICMS frequency and amplitude for the electrodes tested (3-way ANOVA (2,2,11), F = 19.61 and 42.35 respectively, p < 0.01 for both), we assessed the relationship between PF size and sensation magnitude. We found that the size of the reported PF could be accurately predicted from the reported magnitude of the evoked sensation, across ICMS frequencies and amplitudes (**Figure 6C**, r = 0.77, p < 0.01). The relationship between ICMS intensity and PF size is a predictable consequence of the somatosensory homunculus. Each volume of cortex maps onto a patch of skin; the greater the volume of cortex activated (amplitude modulation) or the number of activated neurons in that cortex volume (frequency modulation), the greater the corresponding swath of skin.

Projected fields are superimposed with multielectrode stimulation

We then examined the impact of stimulating through multiple electrodes on reported PFs. To this end, we simultaneously delivered ICMS through pairs of electrodes and compared the reported PFs to those when ICMS was delivered to the individual electrodes that formed the pairs (**Figure 7A,B**). In some cases, the electrodes in the pair had PFs that largely overlapped, so we could assess how the two sensations were integrated. In other cases, the electrodes in the pair had non-overlapping PFs, so we could investigate whether the two sensations would interfere or interact with one another. Single and multi-electrode trials were interleaved to limit biases in the PF reports. Examination of the single-electrode and multi-electrode PFs suggests that the latter reflect a superimposition of the former. We tested this by computing the pixel-wise correlation between the sum of the component PFs and the multi-electrode PF. We found the summed PFs of the component electrodes were highly predictive of the resulting multi-electrode PF (mean r = 0.61) (**Figure 7C**). We conclude that PFs combine approximately additively when ICMS is delivered through multiple electrodes.

Multielectrode ICMS evokes more localizable sensations than does single-electrode ICMS

Figure 7. Projected fields with multi-channel stimulation are additive. A, B| Two example projected fields predicted from the union of two individual channels versus the reported field when the two channels were stimulated simultaneously. **C|** Correlation between the additive model and observed projected field versus a null model where two random channels were chosen. The additive model significantly outperformed the null model (2-sample Kolmogorov-Smirnov test, D = 0.86, p < 0.01).

As discussed above, the circumscription and systematic localization of PFs can be exploited to convey information about (bionic) hand locations at which contact with an object is established (Flesher et al., 2021; Valle et al., 2018). Given that multi-electrode PFs reflect a superimposition of their component PFs, we reasoned that more focal and thus more easily localizable sensations might be evoked via multielectrode stimulation. To test this possibility, we mapped force sensors on the bionic hand to electrodes with matching PFs. For example, sensors on the prosthetic thumb tip drove stimulation through electrodes with PFs on the thumb. In some cases, each sensor drove stimulation through a single electrode; in other cases, sensor output drove a quartet of electrodes (at 60 µA) whose PFs largely overlapped. For these, the overlapping component matched the sensor location. We then randomly touched different digits and had the (blindfolded) participant report which finger was touched (**Figure 8A**). In some experimental blocks, we only touched one (prosthetic) digit at a time; in others, we touched one or two digits. The participant (C1) was warned when more than one finger might be touched in a given experimental block. We also repeated the same experiment, except that digit(s) were selected by the experimenter on the experimental computer (rather than by physically touching the bionic hand). Results from these two paradigms – one with and one without the bionic hand – were similar and thus combined. In all conditions (single vs. multi electrode and/or digit), the participant reported the digit(s) with the PF overlap on the majority of trials. Single-electrode stimulation more often failed to elicit a sensation (30% vs 0%) and more often elicited a sensation reported on another digit than did multi-electrode stimulation (42 vs. 7%, respectively) (**Figure 8A, Supplementary Figure 5A**). The difference in performance for single- vs. multi-electrode stimulation was more pronounced on blocks in which single digits and multiple digits were touched. Multi-channel stimulation thus gives rise to more readily localizable sensations than does its single-electrode counterpart.

Figure 8 Multi-channel stimulation more reliably evokes localizable sensations. A| Task setup for robotic digit localization task. The subject was blindfolded while an experimenter randomly squeezed individual or pairs of fingers. **B|** Consolidated performance of robotic and open loop localization tasks. Note that trials where the subject failed to detect stimulation are excluded here to reduce confounding localization performance with detectability.

DISCUSSION

Stimulation through individual electrodes evokes sensations that are localized to a specific patch of skin (their PF), the size and location of which is electrode dependent. PFs are highly stable over time and are determined by the location of the electrode within the somatosensory homunculus. PFs increase in size with increases in amplitude or frequency, an effect that can be predicted from the concomitant increase in perceived magnitude. ICMS delivered through multiple electrodes results in a PF that is a superimposition of the individual component electrodes. Accordingly, stimulation through multiple electrodes with overlapping PFs evokes sensations that are more readily localized to the overlapping region of the component PFs.

PFs are highly stable over time

PFs remained stable over the testing period, which spanned ~2 years for participants C1 and P3 and ~7 years for participant P2. Indeed, the variability in the PF overlap and centroid distance across repeated tests on the same electrode were equivalent within and across sessions. Given that the PF location largely coincides with RF location, this stability suggests that the somatosensory homunculus is highly stable, consistent with fMRI studies with amputees (Kikkert et al., 2016) and people with tetraplegia (Andersen and Aflalo, 2022). What's more, the different participants varied widely in their degrees of residual sensation, where participants C1 and P3 retain sensation over large swaths of skin whereas P2 was completely insensate across half of his hand. For the latter, the PFs were indistinguishable in their size and relative locations whether these were on sensate or insensate patches, suggesting that the homunculus remains stable regardless of the degree of residual sensation. Furthermore, recent results with intraneural electrodes implanted in the human nerves suggested that the PF changes observed over time are most likely caused by the foreign body reactions (Valle et al., 2022). Indeed, deliberate attempts

to modify the PFs of electrodes implanted in the nerves – which leverage any subcortical plasticity – have failed to systematically change the PF location (Ortiz-Catalan et al., 2020a), consistent with the theory that body maps are rigid in adulthood (Makin and Bensmaia, 2017).

The projected field of an electrode is subsumed by its receptive field

Since the PF of an electrode is determined by its location on the somatosensory homunculus, the spatial extent of the PF is expected to be determined by the spatial extent of activation across the cortical surface. Consistent with this, increases in ICMS amplitude or frequency lead to increases in the volume of activated neurons (Dadarlat et al., 2022; Kumaravelu et al., 2022; Stoney et al., 1968) and concomitant increases in PF area. Furthermore, the PF of an electrode is, on average, half the size of its RF. If we assume that the spatial extent of a PF is determined by the activated cortical area, ICMS at 60 µA activates the somata of neurons over a span of around 1 mm (Kumaravelu et al., 2022) (**Supplementary Figure 6A**). The RF size is determined by (1) the area over which neurons contribute to the multiunit activity on a given electrode (~150 µm radius) and (2) the area of cortex that is activated by a touch (**Supplementary Figure 6B**). Regarding the latter, a punctate indentation applied to the skin evokes neuronal activity on two spatial scales (**Supplementary Figure 6C**). Contact initiation evokes a transient response over a wide swath of cortex (spanning ~15 electrodes on the array), with RFs spanning multiple digits. Contact maintenance is associated with a much more spatially restricted sustained response (spanning ~2 electrodes). RFs, mapped by touching the skin lightly and repetitively, reflect the transient response. If responses to contact transients determined the spatial extent of a tactile experience, a touch on a single digit would evoke a sensation on multiple digits. Accordingly, the spatial extent of a tactile sensation is more likely to be driven by the cortical population that remains active during maintained contact, the so-called hotzone (Callier et al., 2019). For a punctate indentation, the hotzone spans 1 to 2 mm. At a first approximation, then, the area of cortex activated by ICMS is on the same order of magnitude as the hotzone, but systematically smaller than the transiently activated cortical area (**Supplementary Figure 6D**). Note, however, that the spatial extent of a sensation is not only determined by the spatial extent of the activated cortex but also by the spatial pattern of that activation. A punctate indentation produces a response that is spatially graded, peaking at the hotzone and dropping off smoothly around it (Callier et al., 2019). While the ICMS-evoked activation also decreases with distance from the electrode tip (Merrill et al., 2005), the pattern is different. This difference likely underlies the fact that ICMS-evoked sensations have more diffuse borders than do their natural tactile counterparts. The relationship between the spatial pattern of cortical activation and the evoked sensation remains to be conclusively elucidated.

Multielectrode stimulation evokes more localizable sensations

Mapping sensors on the bionic hand to somatotopically matched electrodes in S1 yields intuitive feedback about the locations on the bionic hands at which contact with an object occurs. Indeed, contact with the prosthetic thumb, for example, leads to a sensation experienced on the thumb. Here, we show that this mapping is even more effective if the sensor output drives ICMS through multiple electrodes, whose common PF matches the sensor location. For example, if multiple electrodes have PFs that include the thumb, their aggregate PF will be dominated by the thumb. Multi-electrode ICMS results in sensations that not only are more tangible but also more readily localizable to the hand regions corresponding to the PF overlap. Not only does multi-channel ICMS evoke more localizable sensations, it also leads to more accurate force feedback. Indeed, a greater number of discriminable steps of force can be signaled via multi-electrode ICMS than via single-electrode ICMS (Greenspon et al., 2023). Moreover, multi-channel

ICMS robustly evokes somatosensory sensations at significantly shorter latencies than does single-electrode ICMS (Bjånes et al., 2022; Sombeck and Miller, 2019). The disadvantage of multi-electrode stimulation of S1 is that it evokes more activity in M1, thereby disrupting the decoding of motor intent (Shelchkova et al., 2022). This disruption, however, can be minimized by implementing biomimetic feedback – which emphasizes contact transients at the expense of maintained contact. The present findings thus constitute further evidence that multi-electrode stimulation leads to more effective tactile feedback for bionic hands.

Implanted arrays should consist of distributed quads of electrodes

As the majority of our interactions with objects involve the digit tips (Christel, M.I. et al., 2020), ICMS-tactile feedback should emphasize fingertip sensations over more proximal ones. Implants in S1 often consist of 6x10 arrays of electrodes with every other electrode wired in a checkerboard pattern (**Figure 1**), a design that has failed to cover all the fingertips in any participant. The placement of the arrays is based on the identification of distinct digit-specific patches of activity using functional magnetic resonance imaging or magnetoencephalography. Individual arrays are then placed near the border of two digits to maximize coverage. While implanting larger arrays may improve the coverage, implanting more arrays rather than larger ones might improve the chances that all digits are represented.

The location of the S1 representation of the digit tips is unclear. In humans and monkeys, RFs progress from tip to base as one progresses caudally through Brodmann's area 3b (Blankenburg et al., 2003; Delhaye et al., 2018; Rosa M. Sanchez-Panchuelo et al., 2012; Roux et al., 2018). The RF progression reverses at the border with area 1, proceeding from base to tip, then reverses again at the border with area 2. Given that the border between areas 3b and 1 is located in the posterior bank of the central sulcus, the digit tip representations at the area 1/2 border are the only ones that may be accessible with the arrays currently approved for human use. Much of area 2 is in the anterior bank of the intraparietal sulcus (IPS) in humans (Geyer et al., 1999), so the digit tip representations tend to be near the IPS, though this is not always the case. Note that, while imaging yields reliable localization of the individual digit representations, localization of the digit tips is far less clear. Ideally, quads of electrodes would be implanted in the center of the presumptive digit tip representations, near the IPS. With a spacing of 500 μm, the quads would activate populations of neurons with largely overlapping RFs yet different electrodes would activate largely non-overlapping neuronal populations as the electric fields at each electrode would be largely nonoverlapping. This configuration can scale up as the robotics, sensorization, and algorithms improve, with each quad matched to a sensor on the hand.

METHODS

Participants

This study was conducted under an Investigational Device Exemption from the U.S. Food and Drug Administration and approved by the Institutional Review Boards at the Universities of Pittsburgh and Chicago. The clinical trial is registered at ClinicalTrials.gov (NCT01894802). Informed consent was obtained before any study procedures were conducted. Participant C1 (m), 57 years old at the time of implant, presented with a C4-level ASIA D spinal cord injury (SCI) that occurred 35 years prior to implant. Participant P2 (m), 28 years old at the time of implant, presented with a C5 motor/C6 sensory ASIA B SCI that occurred

10 years prior to implant. Participant P3 (m), 28 years old at the time of implant, presented with a C6 ASIA B SCI that occurred 12 years prior to implant.

Cortical implants

We implanted four microelectrode arrays (Blackrock Neurotech, Salt Lake City, UT, USA) in each participant. The two arrays (one medial and one lateral array) in Brodmann's area 1 of somatosensory cortex were 2.4 mm x 4 mm with sixty 1.5-mm long electrode shanks wired in a checkerboard pattern such that 32 electrodes could be stimulated. The two arrays in primary motor cortex were 4 mm x 4 mm with one-hundred 1.5-mm long electrode shanks wired such that 96 (C1 and P3) or 88 (P2) electrodes could be used to monitor neural activity. The inactive shanks were located at the corners of these arrays. Two percutaneous connectors, each connected to one sensory array and one motor array, were fixed to the participant's skull. We targeted array placement during surgery based on functional neuroimaging (fMRI) or magnetoencephalography (MEG) of the participants attempting to make movements of the hand and arm (all participants) and imagining feeling sensations on their fingertips (participant P2), within the constraints of anatomical features such as blood vessels and cortical topography.

Intracortical microstimulation

ICMS was delivered via a CereStim 96 (Blackrock Neurotech). Each stimulating pulse consisted of a 200-µs cathodic phase followed by a half-amplitude 400-µs anodic phase (to maintain charge balance), the two phases separated by 100 µs. For multi-channel stimulation, the same pulse train was delivered to all channels simultaneously and synchronously.

Projected field mapping and quantification

To map a PF, ICMS was delivered through one or more electrodes (60 µA, 100 Hz, 1 second unless otherwise specified), and the participant reported whether a sensation was evoked. The participant could request as many repetitions of the stimulus as desired. During or after the stimulation, the participants drew the spatial extent of the sensation on a digital representation of the hand using a stylus.

Periodically (every 1-3 months), this procedure was repeated for every electrode on both sensory arrays, with electrodes interleaved in random order, across a span of approximately 800, 2750, and 750 days for participants C1, P2, and P3, respectively. From these digital images, we counted the number of pixels subsumed by the PF, computed its area and centroid (center of mass). To gauge the validity of the computed center of mass, one participant also marked, on a subset of electrodes in one session, the center of the PF on the picture of their hand. We found that the estimated centroids matched the reported centroids with sub-millimeter accuracy (median = 0.71 mm, Q_1, Q_3 = 0.52, 1.33 mm).

In fourth participant (R3), the PF mapping procedure differed slightly. On each experimental block, a group of 5 electrodes were randomly selected, and each electrode was stimulated approximately 5 times (n = 4-7 times, mean = 5.12) in a randomized order within the block. The participant verbally reported the hand segments on which the sensation was experienced (distal and medial finger pads, e.g.), each segment numbered on digital representation of the hand [3]. ICMS pulse amplitude was 80 µA, pulses were symmetric and 200 µs wide, and pulse frequency was 100 Hz [3]. Skin locations included in the reported PF on at least 60% of trials with a given electrode were considered to be within the projected field of that electrode.

Aggregate projected fields

Having established that day to day variation in PF location was essentially random and primarily reflected noise in the reports, we constructed an estimate of each PF that weighted skin regions according to the frequency with which these were included in the single-day PF reports. Specifically, we computed the proportion of times a given pixel was included in the single-day PF. We then eliminated pixels that were included on fewer than 25% of single-day reports and normalized the remaining proportions such that they summed to one. For some electrodes, this criterion eliminated all of the pixels. These electrodes were not included in subsequent analysis and are reported as having no reliable PF. In the computation of the aggregate centroid, each pixel was weighted according to its value (normalized proportion). When aggregate centroids spanned multiple hand segments, the one with the largest summed pixel values was identified as the dominant one. The size of the aggregate field was the total number of pixels that exceeded the threshold. The size of the aggregate field was the total number of pixels that exceeded the thresholds. Aggregate receptive fields were characterized in a similar way as projected fields. Note, however, that measured RFs were nearly identical across sessions in the one participant for whom these were measured repeatedly over multiple sessions.

Projected field stability

We gauged projected field stability in three ways. First, we computed the distance between each single-day PF centroid and the centroid of the first reported PFs. Because this measure was susceptible to an anomalous report on the first session, we also computed the distance between the PF centroid on any given session and the centroid of the aggregate PF. Third, we measured the proportion of all unique pixels reported for a given electrode that exceeded each of several thresholds, reasoning that stable PFs would be consistent across a wide range of thresholds.

PF progression over the cortical surface

To test the degree to which PF progressions followed the canonical homunculus, we assessed how well we could identify the dominant hand segment for an electrode given that electrode's location. In brief, we used the row and column coordinates of the array as the X and Y coordinates in Cartesian space, whose origin was the center of the array. We then projected the coordinates onto each of 72 axes, spanning the range from 0 to 360 degrees in increments of 5 degrees. For example, for the 0-degree axis, the coordinate would be identical to the X coordinate (row). For each axis, we then applied a linear discriminant classifier with the projected coordinates as inputs and the dominant hand segments as output classes (MATLAB's *fitcdiscr*). To further test the degree to which PFs progress somatotopically, we computed for each pair of electrode the distance between their respective aggregate centroids and assessed the relationship between PF centroid distance and the physical distance between the electrodes over the cortical surface.

Receptive field mapping

To map the extent of the receptive fields of the multi-unit around each electrode, we lightly brushed the skin of the hand using cotton swabs or Von Frey hairs while monitoring the multi-unit response using a speaker. One experimenter stimulated the hand while the other experimenter selected the electrode to be mapped (unknown to the first). In the case of subject C1, where 3 sessions were completed, the electrode order was randomized across sessions. The RF was reported on the same tablet interface used for PFs so that the same analytical protocols could be applied to both types of fields. An aggregate RF was

produced for subject C1 with a cutoff of 33% (the pixel must have been present on 2/3 of observations) using the method described above for PFs.

For participant R1, a trapezoidal indentation was delivered in succession to the skin using a tactile linear actuator (LCA25-025-6MSD6, SMAC, Carlsbad, California, USA) while recording the neuronal activity evoked in S1. The indentation tip was positioned near the distal tip of the distal pad. Each indentation was presented 60 times at a constant amplitude. Because the neuronal signal was weak, we computed spike band power – the root mean square of the filtered signal in 1 ms bins – to quantify the strength of the neural response. The spike band power was normalized within trials by z-scoring the signal during the 2 second stimulus by the 2 second pre-stimulus interval, then the normalized metric was trial averaged for each indenter location. Electrodes with peak normalized spike band power greater than 1.5 standard deviations above baseline were considered responsive to indentation at the specific location. While this RF mapping approach involved a much more controlled and systematic mechanical stimulus than that used in the other three participants (P2, P3, C1), it suffers from the poor coverage, able only to detect neuronal responses evoked by stimulation of the distal digit tips.

Localization task

To assess the degree to which ICMS conveys information about the location of contact between bionic hand and objects, we implemented a sensory encoding algorithm that linked sensors on the robotic hand (Ability Hand, Psyonic, CA, USA) and somatotopically matched electrodes in S1. For example, the output of a sensor on the index fingertip triggered ICMS delivered through one or more electrodes with PFs on the index fingertip. Then, on each trial, the experimenter squeezed one or more digits and the participants task was to report which digits were squeezed. In some experimental blocks, the hand segment was selected by the experimenter on a custom tablet interface instead of squeezing the digit. In some experimental blocks, only one digit was squeezed (or selected on the tablet). On others, the experimenter would squeeze or selected either one or two. Furthermore, sensor output (or digit selection) would trigger ICMS through a single electrode with a PF on the corresponding digit or through multiple electrodes (2 or 4), all with PFs that were predominantly on that digit. We could then compare the participant's performance with single vs. multi-channel stimulation on the single- vs. multi-digit task. The participant reported the location of the sensation (individual digits, combinations of digits, or no sensation) at the end of the stimulus. On single-digit trials, the subjects were given full credit if they correctly identified the stimulated digit; on multi-digit trials, they were given half credit for each correctly identified digit (the digit where the aggregate PF of the electrode(s) was located).

REFERENCES

Andersen, R.A., Aflalo, T., 2022. Preserved cortical somatotopic and motor representations in tetraplegic humans. Current Opinion in Neurobiology 74, 102547. https://doi.org/10.1016/j.conb.2022.102547

Bensmaia, S.J., Tyler, D.J., Micera, S., 2020. Restoration of sensory information via bionic hands. Nature Biomedical Engineering 1–13. https://doi.org/10.1038/s41551-020-00630-8

Bjånes, D.A., Bashford, L., Pejsa, K., Lee, B., Liu, C.Y., Andersen, R.A., 2022. Multi-channel intra-cortical micro-stimulation yields quick reaction times and evokes natural somatosensations in a human participant. https://doi.org/10.1101/2022.08.08.22278389

Blankenburg, F., Ruben, J., Meyer, R., Schwiemann, J., Villringer, A., 2003. Evidence for a Rostral-to-Caudal Somatotopic Organization in Human Primary Somatosensory Cortex with Mirror-reversal in Areas 3b and 1. Cerebral Cortex 13, 987–993. https://doi.org/10.1093/cercor/13.9.987

Bosking, W.H., Sun, P., Ozker, M., Pei, X., Foster, B.L., Beauchamp, M.S., Yoshor, D., 2017. Saturation in Phosphene Size with Increasing Current Levels Delivered to Human Visual Cortex. J. Neurosci. 37, 7188–7197. https://doi.org/10.1523/JNEUROSCI.2896-16.2017

Cabibihan, J.-J., Alhaddad, A.Y., Gulrez, T., Yoon, W.J., 2021. Influence of Visual and Haptic Feedback on the Detection of Threshold Forces in a Surgical Grasping Task. IEEE Robotics and Automation Letters 6, 5525–5532. https://doi.org/10.1109/LRA.2021.3068934

Callier, T., Suresh, A.K., Bensmaia, S.J., 2019. Neural Coding of Contact Events in Somatosensory Cortex. Cerebral cortex (New York, N.Y. : 1991) 1–15. https://doi.org/10.1093/cercor/bhy337

Christel, M.I., Ktizel, S., Niemitz, C., 2020. How Precisely Do Bonobos (Pan paniscus) Grasp Small Objects? International journal of primatology 19, 165–194.

Dadarlat, M.C., Sun, Y.J., Stryker, M.P., 2022. Spatiotemporal recruitment of inhibition and excitation in the mammalian cortex during electrical stimulation. bioRxiv 2022.06.03.494729. https://doi.org/10.1101/2022.06.03.494729

Delhaye, B.P., Long, K.H., Bensmaia, S.J., 2018. Neural Basis of Touch and Proprioception in Primate Cortex. Comprehensive Physiology 8, 1575–1602. https://doi.org/10.1002/cphy.c170033

Fifer, M.S., McMullen, D.P., Thomas, T.M., Osborn, L.E., Nickl, R.W., Candrea, D.N., Pohlmeyer, E.A., Thompson, M.C., Anaya, M., Schellekens, W., Ramsey, N.F., Bensmaia, S.J., Anderson, W.S., Wester, B.A., Crone, N.E., Celnik, P.A., Cantarero, G.L., Tenore, F.V., 2020. Intracortical Microstimulation Elicits Human Fingertip Sensations. medRxiv 2020.05.29.20117374. https://doi.org/10.1101/2020.05.29.20117374

Flesher, S.N., Collinger, J.L., Foldes, S.T., Weiss, J.M., Downey, J.E., Tyler-Kabara, E.C., Bensmaia, S.J., Schwartz, A.B., Boninger, M.L., Gaunt, R.A., 2016. Intracortical microstimulation of human somatosensory cortex. Science translational medicine 8, 361ra141. https://doi.org/10.1126/scitranslmed.aaf8083

Flesher, S.N., Downey, J.E., Weiss, J.M., Hughes, C.L., Herrera, A.J., Tyler-Kabara, E.C., Boninger, M.L., Collinger, J.L., Gaunt, R.A., 2021. A brain-computer interface that evokes tactile sensations improves robotic arm control. Science 372, 831–836. https://doi.org/10.1126/science.abd0380

Foldes, S.T., Chandrasekaran, S., Camerone, J., Lowe, J., Ramdeo, R., Ebersole, J., Bouton, C.E., 2021. Case Study: Mapping Evoked Fields in Primary Motor and Sensory Areas via Magnetoencephalography in Tetraplegia. Frontiers in Neurology 12.

Geyer, S., Schleicher, A., Zilles, K., 1999. Areas 3a, 3b, and 1 of Human Primary Somatosensory Cortex: 1. Microstructural Organization and Interindividual Variability. NeuroImage 10, 63–83. https://doi.org/10.1006/nimg.1999.0440

Greenspon, C.M., Valle, G., Hobbs, T.G., Verbaarschot, C., Callier, T., Shelchkova, N.D., Sobinov, A.R., Jordan, P.M., Weiss, J.M., Fitzgerald, E.E., Prasad, D., van Driesche, A., Lee, R.C., Satzer, D.,

Gonzalez-Martinez, J., Warnke, P.C., Miller, L.E., Boninger, M.L., Collinger, J.L., Gaunt, R.A., Downey, J.E., Hatsopoulos, N.G., Bensmaia, S.J., 2023. Biomimetic Multi-channel Microstimulation of Somatosensory Cortex Conveys High Resolution Force Feedback for Bionic Hands (preprint). Neuroscience. https://doi.org/10.1101/2023.02.18.528972

Johansson, R.S., Flanagan, J.R., 2009. Coding and use of tactile signals from the fingertips in object manipulation tasks. Nature Reviews Neuroscience 10, 345–359. https://doi.org/10.1038/nrn2621

Kikkert, S., Kolasinski, J., Jbabdi, S., Tracey, I., Beckmann, C.F., Johansen-Berg, H., Makin, T.R., 2016. Revealing the neural fingerprints of a missing hand. eLife 5, 1–19. https://doi.org/10.7554/eLife.15292

Kikkert, S., Pfyffer, D., Verling, M., Freund, P., Wenderoth, N., 2021. Finger somatotopy is preserved after tetraplegia but deteriorates over time. eLife 10, e67713. https://doi.org/10.7554/eLife.67713

Kumaravelu, K., Sombeck, J., Miller, L.E., Bensmaia, S.J., Grill, W.M., 2022. Stoney vs. Histed: Quantifying the spatial effects of intracortical microstimulation. Brain Stimulation 15, 141–151. https://doi.org/10.1016/j.brs.2021.11.015

Makin, T.R., Bensmaia, S.J., 2017. Stability of Sensory Topographies in Adult Cortex. Trends in cognitive sciences 21, 195–204. https://doi.org/10.1016/j.tics.2017.01.002

Merrill, D.R., Bikson, M., Jefferys, J.G.R., 2005. Electrical stimulation of excitable tissue: design of efficacious and safe protocols. Journal of Neuroscience Methods 141, 171–198. https://doi.org/10.1016/j.jneumeth.2004.10.020

Ochoa, J., Torebjörk, E., 1983. Sensations evoked by intraneural microstimulation of single mechanoreceptor units innervating the human hand. The Journal of Physiology 342, 633–654. https://doi.org/10.1113/jphysiol.1983.sp014873

Ortiz-Catalan, M., Mastinu, E., Greenspon, C., Bensmaia, S., 2020a. Chronic use of a sensitized bionic hand does not remap the sense of touch. Cell Reports.

Ortiz-Catalan, M., Mastinu, E., Sassu, P., Aszmann, O., Brånemark, R., 2020b. Self-Contained Neuromusculoskeletal Arm Prostheses. New England Journal of Medicine 382, 1732–1738. https://doi.org/10.1056/NEJMoa1917537

Overstreet, C.K., Cheng, J., Keefer, E., 2019. Fascicle specific targeting for selective peripheral nerve stimulation. J. Neural Eng. https://doi.org/10.1088/1741-2552/ab4370

Penfield, W., Boldrey, E., 1937. SOMATIC MOTOR AND SENSORY REPRESENTATION IN THE CEREBRAL CORTEX OF MAN AS STUDIED BY ELECTRICAL STIMULATION. Brain 60, 389–443. https://doi.org/10.1093/brain/60.4.389

Petrini, F.M., Valle, G., Strauss, I., Granata, G., Di Iorio, R., D'Anna, E., Čvančara, P., Mueller, M., Carpaneto, J., Clemente, F., Controzzi, M., Bisoni, L., Carboni, C., Barbaro, M., Iodice, F., Andreu, D., Hiairrassary, A., Divoux, J.-L., Cipriani, C., Guiraud, D., Raffo, L., Fernandez, E., Stieglitz, T., Raspopovic, S., Rossini, P.M., Micera, S., 2019. Six-Month Assessment of a Hand Prosthesis with Intraneural Tactile Feedback. Annals of Neurology 85, 137–154. https://doi.org/10.1002/ana.25384

Rosa M. Sanchez-Panchuelo, Julien Besle, Alex Beckett, Richard Bowtell, Denis Schluppeck, Susan Francis, 2012. Within-Digit Functional Parcellation of Brodmann Areas of the Human Primary Somatosensory Cortex Using Functional Magnetic Resonance Imaging at 7 Tesla. J. Neurosci. 32, 15815. https://doi.org/10.1523/JNEUROSCI.2501-12.2012

Roux, F.-E., Djidjeli, I., Durand, J.-B., 2018. Functional architecture of the somatosensory homunculus detected by electrostimulation. J Physiol 596, 941–956. https://doi.org/10.1113/JP275243

Salas, M.A., Bashford, L., Kellis, S., Jafari, M., Jo, H., Kramer, D., Shanfield, K., Pejsa, K., Lee, B., Liu, C.Y., Andersen, R.A., 2018. Proprioceptive and cutaneous sensations in humans elicited by intracortical microstimulation. eLife Sciences 7, e32904. https://doi.org/10.7554/eLife.32904

Shelchkova, N.D., Downey, J.E., Greenspon, C.M., Okorokova, E.V., Sobinov, A.R., Verbaarschot, C., He, Q., Sponheim, C., Tortolani, A.F., Moore, D.D., Kaufman, M.T., Lee, R.C., Satzer, D., Gonzalez-Martinez, J., Warnke, P.C., Miller, L.E., Boninger, M.L., Gaunt, R.A., Collinger, J.L., Hatsopoulos, N.G., Bensmaia, S.J., 2022. Microstimulation of human somatosensory cortex evokes task-dependent, spatially patterned responses in motor cortex. https://doi.org/10.1101/2022.08.10.503543

Sombeck, J.T., Miller, L.E., 2019. Short reaction times in response to multi-electrode intracortical microstimulation may provide a basis for rapid movement-related feedback. J. Neural Eng. 17, 016013. https://doi.org/10.1088/1741-2552/ab5cf3

Stoney, S.D., Thompson, W.D., Asanuma, H., 1968. Excitation of pyramidal tract cells by intracortical microstimulation: effective extent of stimulating current. Journal of Neurophysiology 31, 659–669. https://doi.org/10.1152/jn.1968.31.5.659

Sur, M., Merzenich, M.M., Kaas, J.H., 1980. Magnification, receptive-field area, and "hypercolumn" size in areas 3b and 1 of somatosensory cortex in owl monkeys. Journal of Neurophysiology 44, 295–311.

Tabot, G.A., Dammann, J.F., Berg, J.A., Tenore, F.V., Boback, J.L., Vogelstein, R.J., Bensmaia, S.J., 2013. Restoring the sense of touch with a prosthetic hand through a brain interface. Proceedings of the National Academy of Sciences 110, 18279–18284. https://doi.org/10.1073/pnas.1221113110

Tan, D.W., Schiefer, M.A., Keith, M.W., Anderson, J.R., Tyler, J., Tyler, D.J., 2014. A neural interface provides long-term stable natural touch perception. Science Translational Medicine 6, 257ra138-257ra138. https://doi.org/10.1126/scitranslmed.3008669

Valle, G., Aiello, G., Ciotti, F., Cvancara, P., Martinovic, T., Kravic, T., Navarro, X., Stieglitz, T., Bumbasirevic, M., Raspopovic, S., 2022. Multifaceted understanding of human nerve implants to design optimized electrodes for bioelectronics. Biomaterials 291, 121874. https://doi.org/10.1016/j.biomaterials.2022.121874

Valle, G., Petrini, F.M., Strauss, I., Iberite, F., D'Anna, E., Granata, G., Controzzi, M., Cipriani, C., Stieglitz, T., Rossini, P.M., Mazzoni, A., Raspopovic, S., Micera, S., 2018. Comparison of linear frequency and amplitude modulation for intraneural sensory feedback in bidirectional hand prostheses. Scientific Reports 8, 16666. https://doi.org/10.1038/s41598-018-34910-w

Wendelken, S., Page, D.M., Davis, T., Wark, H.A.C., Kluger, D.T., Duncan, C., Warren, D.J., Hutchinson, D.T., Clark, G.A., 2017. Restoration of motor control and proprioceptive and cutaneous sensation in humans with prior upper-limb amputation via multiple Utah Slanted Electrode Arrays (USEAs) implanted in residual peripheral arm nerves. J NeuroEngineering Rehabil 14, 121. https://doi.org/10.1186/s12984-017-0320-4

Supplementary Figure 1. Palmar and dorsum projected field maps for all participants. The hand diagrams show the distributions of the locations of the sensations evoked by ICMS any electrode on the volar (left) and dorsal (right) surface of the hand. The array diagrams show the dominant hand segment for each electrode. All array rotations are approximately aligned such that up is medial and anterior is left.

Supplementary Figure 2. Incidence of evoked sensations. A| Proportion of times that ICMS (at 100 Hz, 60 μA) through a given electrode evoked a sensation in the three participants. **B|** The probability of evoking a sensation by delivering ICMS through a given electrode is strongly related to the detection threshold on that electrode (r = -0.82, -0.56, and -0.58, for C1, P2, and P3, respectively, p < 0.01).

Supplementary Figure 3. Thresholding the aggregate PFs to assess stability. A| The proportion of electrodes for which any pixel exceeds the criterion decreases as the threshold increases. **B|** The area of the aggregate PF drops dramatically as the threshold increases to 0.25 and then decrease more slowly. **C|** The variability in the PF (Euclidean distance of each observation's centroid from the aggregate centroid) changes only marginally as threshold increases.

Supplementary Figure 4. Sensations are stable over time. A| The mean distance between the first centroid and subsequent ones is stable. **B|** The distribution of slopes computed from the data shown in panel A for individual electrodes grouped by participant.

Supplementary Figure 5. Multi-channel ICMS leads to improved localization. A| Performance on the localization task when classifying single or multi-digit stimulation while being stimulated through individual or quads of channels. Hashing indicates testing with the robotic hand, with single channels or quads of channels. Single channel performance was not improved in the closed loop task (permutation test, p = 0.55), though there was a substantial improvement in the open loop task (p < 0.01). However, when comparing single-channel to multi-channel ICMS when multiple digits were liable to be touched, the performance differential was much greater regardless of whether the task was performed with a robotic hand or a tablet (p <0.01). **B|** Confusion matrices for single and multi (**C**) channel stimulation. Data from participant C1.

Supplementary Figure 6 Cortical activation during natural touch and ICMS. A| Illustration of cortical activation by ICMS and **B|** during RF mapping for a given electrode. The cortical activation by touch is much wider than that by ICMS. **C|** Considering the differences in cortical activation during transient and sustained phases of contact, the area of cortex activated by ICMS (A_{ICMS}) is on the same order of magnitude as the hotzone (cortical activation during sustained contact - A_S), but systematically smaller than the transiently activated cortical area (- A_T), at a first approximation.