1

Role of spinal sensorimotor circuits in triphasic command: a simulation approach using Goal Exploration Process.

Daniel Cattaert[1], Matthieu Guemann[1], Florent Paclet[1], Bryce Chung[2], Pierre-Yves Oudeyer[3], Aymar de Rugy[1]

[1] Institut de Neurosciences Cognitives et Intégratives d'Aquitaine,

UMR 5287 CNRS & Univ. Bordeaux, Bordeaux, France

[2] Neuroscience Institute, Georgia State University, Atlanta, GA 30302

[3] Inria Bordeaux Sud-Ouest, Talence, France ;

Corresponding author: Daniel Cattaert

INCIA UMR 5287 – 146 rue Léo Saignat, 33076 BORDEAUX CEDEX, France

Manuscript type: Research article

Word count: 12 379

Abstract

During rapid voluntary limb movement about a single joint, a stereotyped triphasic pattern is typically observed in the electromyograms (EMGs) of antagonistic muscles acting at this joint. To explain the origin of such triphasic commands, two types of theories have been proposed. Peripheral theories consider that triphasic commands result from sensorimotor spinal networks, either through a combination of reflexes or through a spinal central pattern generator. Central theories consider that the triphasic command is elaborated in the brain. Although both theories were partially supported by physiological data, there is still no consensus about how exactly triphasic commands are elaborated. Moreover, capacities of simple spinal sensorimotor circuits to elaborate triphasic commands on their own have not been tested yet. In order to test this, we modelled arm musculoskeletal system, muscle activation dynamics, proprioceptive spindle and Golgi afferent activities and spinal sensorimotor circuits. Descending step commands were designed to modify the activity of spinal neurons and the strength of their synapses, either to prepare (SET) the network before movement onset, or to launch the movement (GO). Since these step commands do not contain any dynamics, changes in muscle activities responsible for arm movement rest entirely upon interactions between the spinal network and the musculo-skeletal system. Critically, we selected descending step commands using a Goal Exploration Process inspired from baby babbling during development. In this task, the Goal Exploration Process proved to be very efficient. It proficiently discovered step commands that enabled spinal circuits to handle a broad spectrum of functional behaviors. Notably, this accomplishment was predominantly realized while eliciting natural triphasic commands, thereby substantiating the inherent capacity of the spinal network.

Author Summary

In this study, we tested the capacities of sensorimotor spinal networks and musculo-

skeletal dynamics to produce triphasic commands for single joint arm flexion. Spinal

networks only received step commands from the brain consisting in preparatory (SET) and

launch (GO) controls. In the absence of dynamics in these descending commands, the arm

movements result solely from sensorimotor interactions and processing in the spinal circuits.

Descending commands were elaborated in a Goal Exploration Process (GEP) inspired from

baby babbling during development. We show that in this configuration, sensorimotor spinal

networks spontaneously produce triphasic commands for most arm flexion movements in a

large range of amplitudes and speeds.

Introduction

During rapid voluntary limb movement about a single joint, a stereotyped triphasic pattern is observed in the electromyograms (EMGs) of antagonistic muscles commanding this joint (Hallett et al. 1975). Prior to limb displacement, the agonist muscle is briefly active (AG1). After the limb begins to move, a burst of muscle activity occurs in the antagonist muscle (ANT) while the agonist is silenced, and then a second burst is observed in the agonist (AG2). The precise organization of this triphasic pattern ensures the softness of the movement.

What is the origin of this triphasic command? Two possibilities have been proposed; either a **spinal origin** via sensorimotor circuits (Barnett and Harding 1955; Ghez and Martin 1982; Terzuolo et al. 1974) or a **central origin** elaborated in brain networks and transmitted to the spinal cord via descending commands. The **central hypothesis** was supported by observations on humans with severe, though not complete, sensory neuropathy, who could still produce triphasic patterns **(Hallett et al. 1975; Rothwell et al. 1982**). Although these studies highlight the capacities of the motor cortex and other higher centers that can learn how to control limb movements after partial or total deafferentation, the deep reorganization of motor commands following such deafferentation prevents firm conclusion about how triphasic commands are produced in healthy subjects. Other studies used reversible transient deafferentation using ischemic process of the muscles controlling the joint and their afferent nerves Ia and Ib, the diameter of which are more sensitive to ischemia that axons of alpha motoneurons (**Sanes and Jennings 1984**). During such reversible ischemia, the triphasic pattern persists, although passive movements fail to elicit stretch reflexes.

Other experiments indicate that triphasic motor command is also present in the primary motor cortex (M1), and that neural activities in M1 are correlated with output kinematics and kinetics during isometric-force and arm-reaching tasks (**Sergio et al. 2005**).

Physiological model describing the transformation from the neural activity in M1, through

the muscle control signal, into joint torques and down to endpoint forces and movements

(**Trainin et al. 2007**), show that optimized solutions for M1 activities display triphasic

changes in temporal pattern and instantaneous directionality similar to that found in the

EMG (**Trainin et al. 2007**). Other studies have also suggested that optimal control models

can predict EMG patterns in step-tracking wrist movement (**Haruno and Wolpert 2005**), and

even triphasic pattern of muscle activation (**Ueyama 2021**). Interestingly, such optimal

control models also predict neural representation in M1 (**Ueyama 2021**).

In opposition with the arguments in favor of a central origin of triphasic commands, it

was shown that procedures that modify discharge of muscle spindle afferents during

movement alter the duration and amplitude of these bursts (**Brown and Cooke 1981; Hallett**

and Marsden 1979). In addition, simulation studies concerning the central origin of triphasic

commands, although aiming toward physiological models, often lack spinal sensorimotor

loops (**Trainin et al. 2007**). Therefore, if we cannot doubt that M1 neurons and populations

of neurons present activities correlated with kinetic, kinematic and dynamic cues of the

performed movements, there is still questions about the possible role of spinal sensorimotor

circuits in the elaboration of triphasic commands. More precisely, if the first EMG activity

(AG1) can be attributed to a central command from the brain (at least for its onset), there is

still debate about ANT and AG2.

The first aim of this paper was to explore the capacities of the spinal sensorimotor

circuits in shaping triphasic commands, using a modeling approach based on the

neuromechanical environment AnimatLab (https://www.animatlab.com/). We modelled the

movement of the forearm around the elbow joint, involving two muscles (biceps and

triceps). Movements consisted in elbow flexion starting from a fully extended position. Our

approach was based on spinal like regulator (SLR) work (**Raphael et al. 2010**). Spinal

interneurons and synapses of sensorimotor circuits were controlled by simple descending

SET and GO step commands. The SET commands shape the sensorimotor circuits (synaptic gains, level of activity of neurons) without producing any movement, and the GO commands trigger and elicit the movement. These signals, deprived from any dynamic content, were chosen in order to give the spinal sensorimotor circuit the complete responsibility in the shaping of the dynamics of the commands, and in particular the production of the triphasic commands.

We also wanted the neuromechanical system to self-organize its commands as a function of the produced movements, as would do a child exploring the commands of its own arm. Recent advances in developmental machine learning **(Baranes and Oudeyer 2013; Forestier et al. 2017**) have shown that a novel form of exploration algorithms, called *Goal Exploration Processes* (**GEP**), can be used to automatically define target behaviors and efficiently discover a map of reachable behaviors, thereby solving problems of unreachable behaviors and local minima encountered by alternative, state-of-the-art optimization methods **(Colas et al. 2018; Forestier et al. 2017; Oudeyer and Kaplan 2007) ;** (for related methods using diversity search to solve problems with local minima or sparse rewards, see also **Eysenbach et al. 2019; Lehman and Stanley 2011; Mouret and Doncieux 2012; Pathak et al. 2017)**. Moreover, self-conducted exploration of high-dimensional, continuous parameter systems have the advantage to be sample efficient, i.e., they enable the discovery of diverse behavioral domains with a limited number of experiments. So far, such algorithms have been used to discover diverse behaviors in robotics **(Forestier et al. 2017; Péré et al. 2018)** as well as in complex systems such as cellular automata, morphogenetic models **(Etcheverry et al. 2020; Reinke et al. 2019**) and chemical systems (**Grizou et al. 2020**), implementing a form of discovery assistant that can leverage interactively guidance of users (**Etcheverry et al. 2020**).

The second aim of the present work was to extend the application domain of such algorithms by studying their efficacy when applied to neuromechanical systems. We used a

simple GEP protocol inspired from **Forestier et al (2017)**. These algorithms use two work

spaces: (i) one for the behaviors: here we used a two dimensions space (movement

amplitude and movement speed), and (ii) one for the parameters that determine the motor

commands from the brain: here we used a series of step commands that modify synaptic

strength and neuron activity in spinal cord circuits either in the preparatory phase (SET) or to

launch the movement). The GEP finds new valid behaviors by repeating 4 stages:

1- Choose a goal (a goal is a targeted behavior)

2- Find the parameters that produced a behavior close to the aim in the data base of

140   preceding successes and modify slightly these parameters in a random way

141   3- Run the model with these parameters

142   4- Observe the result and if acceptable, store behavior and parameters in the

143   database.

Several modelling approaches have proposed that the CNS employs a minimum jerk

strategy when planning any given movement (**Flash and Hogan 1985**). This proposal was

refined later **(Nakano et al. 1999)** showing that minimum angle jerk predicts the actual arm

trajectory curvature better than the minimum jerk model. Therefore, we used it here. Once

valid behaviors were found, the GEP searched new ones by modifying preexisting valid

behaviors. Valid behaviors, the parameter sets of which were altered to elaborate new

commands, were chosen on the periphery of the behavior domain in order to extend it.

Because the policy was random, we called this process rGEP. Here, the rGEP proved efficient

at discovering step commands that enabled spinal circuits to handle a broad spectrum of

functional behaviors while predominantly eliciting natural triphasic commands.

Results

A. Goal exploration process explores the capacity of spinal sensorimotor circuits and their descending commands to produce behaviors.

In this section, we provide a brief overview of the neuromechanical models and the process (rGEP) used to explore their behavioral capabilities.

1. Example of a simple Neuromechanical model

Neuromechanical model of musculoskeletal apparatus and spinal sensorimotor networks were modelled on the AnimatLab platform (see Methods). All neurons modelled in this study were non-spiking (NS) neurons (i.e., neurons that do not produce spikes but transmit activity to postsynaptic neurons in a continuous manner when their potential is over a threshold value - see Methods for more explanations). Such neurons present the advantage to avoid discontinuity of spikes and spiking synaptic transmission. This is specially critic in small neuron networks, when the level of activity is low.

To illustrate how rGEP works and progresses along time, we have chosen the simplest network, which contained only 6 neurons and 6 synapses, and is controlled by 14 descending commands (Figure 1B). Using this model, we will see how rGEP progressively builds a behavior map (i.e., the collection of all valid behavior found) and parameter maps (i.e., the collection of their associated 14 parameters' sets).

In this study, one of the objectives was to demonstrate how a highly simplified sensorimotor system (Figure 1B) could proficiently manage movement control, as previously shown by **Raphael et al. (2010)** in the context of more complex spinal networks. The specific aim here was to generate minimum jerk movements. Therefore, we used the same principles for descending commands as **Raphael et al. (2010)**. Descending commands were represented as step functions starting at t=1s (SET command) and at t=5s (GO command) (Figure 1C). The SET commands were responsible for the state of readiness of the network.

This first stimulation should activate the network without releasing any movement

(**Eliasmith and Anderson 2003**); (**Prut & Fetz, 1999**).

Figure 1: Simplified neuromechanical model and GEP principles.
A, Musculoskeletal system.
B, Simplified sensorimotor system comprising αMNs, γMNs, propriospinal interneurons and Ia afferents from
muscle spindles, with SET ad GO commands. In this study, more complex sensorimotor networks have been
associated to the same musculo-skeletal system (see Figs 3-9).
C, SET and GO commands used to control the sensorimotor network. The SET commands adjust all neuron
activity levels at 1 sec to bring the network in a state ready to trigger the movement (without producing the
movement by itself). The GO commands launch the movement. SET and GO commands are the parameters of
parameter space.
D, Example of Behavior space obtained with rGEP algorithm after 91794 iterations. Valid behaviors are
indicated by red dots, and corresponding movement durations are indicated by doted lines.
E, In this work the **behavior space** was defined by the amplitude of elbow movement (abscissa) and its maximal
speed (ordinate).
F, Schematic diagram of the GEP exploration algorithm. **F1**: Process starts from an existing **parameter space**
(black filled squares in *Parameter space* – for simplicity reduced to two parameters), which is associated with a
behavior space (black filled circles in *Behavior space*), a new *goal* is given in the periphery of the known
behavioral space (red cross). The algorithm searches for the closest behavior (closest neighbor), it will retrieve
the parameters associated with this behavior and replay its parameters including additional noise ("*New*
parameters"). This new set of parameters generates a "*New behavior*" in the space of behaviors that is kept or
not, depending on its *Cost* value). **F2**: The movement that was closest to the goal (red circle in behavior space,
and red movement trace in right diagram) is a valid movement. However, when its parameters are changed

randomly different issues are possible: i) the obtained new movement is invalid, either because there are
oscillations (1) or because it is performed in the wrong direction (2); ii) the new movement is valid and may be
close or far from its parent.

The SET command targeted all the elements of the network (neurons and synapses)

and their control was maintained constant during all the time of the simulation (up to t=10s).

The GO commands were responsible for movement initiation and were maintained constant

until the end of the simulation. In this example GO commands modulated the level of

activity of propriospinal interneurons (see Figure 1B). Note that at t = 5 seconds, the

transient changes induced by the SET command had stabilized before the GO command was

issued.

2.   Brief overview of rGEP

To assess behavior capabilities associated with a given neuromechanical model (i.e.,

the variety of movements that can be produced (Figure 1D) and meeting some criteria like

minimum jerk - see methods for the cost function), we have developed a rGEP algorithm

that uses two spaces (the parameter space and the related behavior space). The movements

contained in the behavior space are defined by their amplitude and their maximal speed

(Figure 1E). At each iteration, goals (i.e., movements of given amplitude and speed) are self-

produced by the algorithm. Goals are disposed either on the periphery of (extend strategy)

or inside (fill strategy) the known behavior space. In the illustration of Figure 1F1, the

example goal is on the periphery of the behavior domain (see red cross). The closest

behavior is then searched and its associated parameters are slightly modified (**random**

function) to produce a new parameter set (*New parameters*). We choose a random policy in

order not to introduce bias in the setting of new values for parameters. Because the policy

used by GEP for parameter changes was a random function, this GEP was named **rGEP.** After

a simulation is run (Figure 1F2), if the produced movement fulfils the **acceptance criteria**, it

is stored in the behavior domain (see trace (3) in Figure 1F2), otherwise, it is rejected (traces

(1) and (2)). Acceptance criteria were as follows: (i) the produced movement should fit a **minimum jerk angular kinetics** (**Friedman and Flash, 2009**); (ii) there should be no oscillations in preparatory and post movement phases; (iii) the movement amplitude should be in the range (10-110°); (iv) no co-contraction should be present in the preparatory phase (controlled by SET commands, see below). A **cost function** ensured valid behaviors fulfill acceptance criteria (see methods)

Because rGEP needs valid behaviors to progress, the first step, was to find initial valid behaviors. In order not to interfere with the design of the commands, these initial behaviors (termed **seeds**) were found via optimization methods (covariance matrix association evolution strategy (CMAes) or variable step coordinate descent (VSCD) – see methods). Briefly, a desired behavior (a movement template) was given to the optimization method that worked on the parameters of the SET and GO commands to find the result that best fitted the desired movement template. During this process of optimization, any valid movement produced was stored and could be used as a seed.

3. Time course of the rGEP algorithm

An example of rGEP time course is presented in Figure 2, on the same simple model presented in Figure 1 (see also inset network diagram in Figure 2). Before rGEP starts, **valid behaviors (seeds)** must be given to the algorithm (see below). In the example presented in figure 2, six seeds were given (see blue crosses in Figure 2A1-4).

Four pictures of the behavior domain extension are presented for 100, 500, 1000 and 4000 valid behaviors (Figure 2A1-4), corresponding to 239, 1232, 2440 and 9922 runs of simulation, respectively. As the rGEP progresses, the behavior domain extends (Figure 2B, violet trace, *behavior domain area*). The behavior domain area was quantified as the number of cases of a grid, defined in the behavior work space (see Methods), which contain at least one valid behavior (see green grids in Figure 2A1-4).

While the borders of the behavior domain get more and more precise, there were still some empty central zones when the process was stopped after 1000 "extend" rounds and 50 "fill" rounds (totalizing #150000 runs). Note that there is no direct relationship between the number of extend rounds and the number of runs, because the number of runs in a given round depends on the size of the behavioral domain at the time the round is launched. Note also that the empty zones were still being progressively explored when rGEP was stopped. Indeed, , the process was not complete in this example as the behavior domain area was still increasing, and did not reach a steady state (Figure2B).

We can also see that the progression of rGEP is not linear. Indeed, several transient plateaus were observed (see filled arrow heads in Figure 2B) on the behavior domain area curve (violet trace). During such blockage of exploration, valid results were found in the already discovered behavior domain, resulting in a transient increase of the mean density (see methods) of valid behaviors (green curve in Figure 2B). The situation unblocks when an original valid behavior is found that extends the behavior domain, and allows new behaviors to be found from its parameter set, resulting sometimes in an abrupt increase of the behavior domain area (see open arrow heads in Figure 2B) while the mean density decreases (see green trace, in Figure 2B). As the behavior domain extends (Figure 2A-B), the parameter domain also evolves, and the final parameter domain is presented in Figure 2C1-7. In this figure, all valid values of the 14 parameters are presented in 7 graphs, each displaying a pair of parameters: GO stim: [*Triceps PN, Biceps PN*] (Figure 2C1); SET stim: [*Triceps PN, Biceps PN*] (Figure 2C2), [*Triceps Alpha, Triceps Alpha*] (Figure 2C3), [*Triceps Gamma, Biceps Gamma*] (Figure 2C4); SET syn: [*Triceps 1a-> Alpha, Biceps 1a->Alpha*] (Figure 2C5), [*Triceps PN->Alpha, Biceps PN->Alpha*] (Figure 2C6), [*Triceps 1a- >PN, Biceps 1a- >PN*] (Figure 2C7) in which *stim* = stimulus sent to a neuron, and *syn* = strength setting of a synapse between a presynaptic and a post synaptic neuron separated by "->" (see Figure2 legend for more explanations).

Figure 2: Temporal evolution of rGEP. **A**, Progression of the behavior domain uncovered by rGEP after 100 (A1), 500 (A2), 1000 (A3) and 4000 (A4) valid behavior were found. **B**, Time course of behavior domain area expansion (i.e., number of squares containing at least one valid behavior in the green grids presented in A1-4) presented in violet trace. The mean density of behaviors in the behavior domain area is presented in green trace. The numbers 1, 2, 3 and 4 correspond to the behavior domains representations shown in (A). **C**, Parameter domain. The 14 parameters are represented in 7 graphs displaying 2 parameters each: 4 stimulus graphs (C1-4) and 3 synapse strength graphs (C5-7) obtained after 91794 runs. Axis names: stimulus graphs represent intensity of stimulus sent to a neuron in the GO (C1) and SET (C2,3,4) commands; synapse strength graphs represent strength setting of a synapse between a presynaptic and a post synaptic neuron separated by "->". Since in this example the Triceps and the Biceps networks are separated, for simplification the name of the network is given first followed by pre- and post-synaptic elements (for example Biceps 1a->Alpha SET indicate the SET command for synaptic strength between 1a spindle afferent and alpha MN both belonging to the Biceps network). The six seeds used to launch the rGEP are indicated with blue cross in the behavior map A1. **Inset**: Diagram of the neuron network model used in this rGEP.

4. Behavior domain of the complete (50-parameters) model with both Ia and Ib

afferents and associated networks

We started the exploration with a system receiving proprioceptive feedback from

muscle spindles (Ia) and Golgi Tendon Organ (GTO). The associated sensorimotor circuits

were inspired from Raphael et al (2010), and contained 12 neurons (2 alpha motoneurons

(MNs), 2 gamma MNs, 2 propriospinal interneurons (INs), 2 Ia INs, 2 Ib INs, and 2 Renshaw

INs), and 30 synapses. GO commands targeted the 8 INs, SET commands targeted the 12

neurons and adjusted the 30 synapses' gains (Figure 3A).

The behavior domain found for this 50 parameters model by the rGEP is presented in

Figure 3B after 1500 rounds of "extend" and 100 rounds of "fills" totalizing 107315 runs, in

which 36152 behaviors were valid. The behavior domain is defined by two parameters of the

produced movements: maximal speed (ordinate) and movement amplitude (abscissa). A

third characteristic of movements (movement duration) is presented on the graphs by

oblique lines labelled with the represented duration (in ms). Only physiologically plausible

movements have been retained (slow movements the duration of which was > 2s have been

rejected – see gray area). Only movements with an amplitude in the range [10°, 110°] have

been retained, to avoid too small movements and too large movements that could reach the

flexion limits. With both Ia and Ib sensorimotor circuits complete, this model could perform

large movement (>80°) at a rapid speed (>400°/s) with movement durations < 400ms. Note

for each amplitude, a great variety of speeds was found.

A representative example of a large movement (amplitude 90.23°) is given in Figure

3C1. Note the profile of the movement that fitted a minimum jerk profile with small MSE

value (0.59). Several other variables are also presented for this example: Force, Membrane

potentials of MNs, and sensory neurons. At the initiation of the movement, the force

recorded in the Biceps was large (reaching 150 N) and decayed slowly during 200 ms, and

more rapidly during the next 200 ms (Figure 3C2). The force recorded in the triceps

increased during the rapid decrease of biceps force, and reached 102 N at t=540ms, and

then decreased in the last part of flexion movement. After movement stopped, triceps force

slowly increased again, while biceps force slightly increased, resulting in a stable global

torque that maintained the forearm in a stable position.

Figure 3: Movements produced by rGEP with the 50-parameters model. **A**, Sensorimotor spinal network of the 50-parameters model. **B**, Behavior domain uncovered by rGEP on this model. The perimeter of the domain is outlined with a blue dashed line. **C**, Representative example of one valid movement in the behavior domain.

The activity of alpha MNs present transient activities during the movement phase: the biceps MN (*FlxαMN*) presents two peaks of depolarization, the second being hardly visible, and an abrupt decrease of activity between the two peaks, during which the triceps MN (*ExtαMN*) presents a peak of activity (Figure 3C3). Once the flexed position is reached, the activity of both alpha MNs remain stable. During the movement phase, the proprioceptive feedback from Ib afferents was much larger than that of the Ia afferents (Figure 3C4). The shape of Ib activations was also different from that of Ia afferents: during the rapid flexion movement, the Ib activity of the flexor muscle (*Flx1b*) present a large peak during the acceleration of the flexion movement, in accordance with its role in sustaining the flexion movement via the Flexor PN excitatory circuit (see Figure 3A); this initial *Flx1b* peak is followed by a smaller peak of the extensor 1a activity (*Ext1a*) that contributes to slow down the flexion movement due to its excitatory effect on the extensor αMN (see Figure 3A); this slowing effect is prolonged by the delayed increase of *Ext1b* activity that activates the extensor αMN via the PN interneuron of the extensor circuit (see Figure 3A), with a small peak just before movement's end; Ext1b activity is maintained after the end of the flexion movement. Note that during the flexion movement, the activity of the Flx1a presents a trough.

The time course of 1a and 1b afferent activities (larger Flx1b peak followed by a smaller Ext1a peak, and by a delayed step-like increase of the Ext1b activity, concomitant with the recovery of Flx1a trough) were regularly observed in the 50-parameter model, with some small variations all along its behavior domain. However, in the same domain regions, other profiles coexisted, with more irregularities similar to that observed in the absence of 1a afferent feedback (see below, §7). This first study will serve to compare the capacities of other models issued from this one, but lacking some neural elements. To facilitate comparison, the perimeter of the behavior domain of the 50-parameter model (see dashed blue line in Figure 3B) will be superimposed on their behavior domains.

338   *5.   Behavioral domain produced in the absence of Ib feedback (with central cross*

339   *connections).*

340   In order to study what proprioceptive feedback was necessary to produce valid

341   movements, in a first step, we suppressed the Ib input, the Ib INs and their synapses (Figure

342   4A). When rGEP was run on this model, the resulting behavior domain was close to the one

Figure 4: Movements produced by rGEP with the 36 parameters model. A, Sensorimotor spinal network of the 36 parameters model. **B**, Behavior domain uncovered by rGEP on this model. For comparison, the perimeter of the domain of the 50-parameter domain is represented with blue dashed line. **C**, Representative example of one valid movement in the behavior domain.

obtained with the complete spinal network (compare Figure 3B and Figure 4B), although maximal speed for large movements was slightly reduced, and all movement durations were longer than 420 ms.

Forces, MN activities and muscle spindles feedback (Figure 4C) were very similar to that of the complete model (Figure 3C) for comparable movements. A representative example of a large movement (amplitude 78.72°) is given in Figure 4C1, with a maximal speed of 295.78°/s, the amount of force developed by the Biceps muscle (Figure 4C2) was in the same range (#150 N) as that observed for the complete model. This is also true for MN and 1a activities (Figure 4C3-4).

6.   *Behavioral domain produced in the absence of Ib feedback (without central cross connections).*

To go further in the analysis of the involvement of Ia proprioceptive feedback in the production of minimum jerk movements, we drastically reduced the sensorimotor network, by suppressing all relationships between extensor and flexor parts of the network, as well as all interneurons except propriospinal INs. The resulting spinal network was the 14-parameters simplified network presented in Figure 1B, and redrawn in Figure 5A with the same design as other models presented in Result section. Interestingly, this extremely simplified spinal network, reduced to Ia proprioceptive inputs connecting their homonymous MN either directly or via their propriospinal IN (PN), was capable of producing a great variety of valid behaviors (Figure 5B). The resulting behavior domain was, however much smaller than the one of the 36-parameters mode (no movement shorter than 500 ms were produced and maximal speed was under 370°/s). A representative example of a large movement (amplitude 80.58°) is given in Figure 5C1.

Figure 5: Movements produced by rGEP with the 14-parameters model. **A**, Sensorimotor spinal network of the 14 parameters model. **B**, Behavior domain uncovered by rGEP on this model. For comparison, the perimeter of the domain of the 50-parameter domain is represented with blue dashed line. **C**, Representative example of one valid movement in the behavior domain.

7.   Behavioral domain produced in the absence of Ia feedback with central cross-

connections.

We then applied the same method to test Ib afferents involvement in the production

of valid movements via rGEP. Starting from the complete (50-parameters model), we

suppressed Ia afferents, Ia INs and their synapses (Figure 6A). This Ib network could produce

a variety of valid behaviors (Figure 6B), with fast movements of great amplitude (maximal

speed > 400°/s and movement duration < 450 ms. However, the behavioral domain was

significantly smaller than that of the 50-parameter model: for each amplitude, the maximal

speed observed in valid behaviors were always smaller than that of the 50-parameters

model (Figure 6B).

Figure 6: Movements produced by rGEP with the 34-parameters model. **A**, Sensorimotor spinal network of the 34 parameters model. **B**, Behavior domain uncovered by rGEP on this model. For comparison, the perimeter of the domain of the 50-parameter domain is represented with blue dashed line. **C**, Representative example of one valid movement in the behavior domain.

The limitations of the 34-parameters model were likely linked with the difficulty to get

stable control of neurons and forces when the only proprioceptive feedback comes from

Golgi Tendon Organs, as can be observed in Figure 6C. Note, in particular, the complex shape

of the force time course (Figure 6C2), with rapid increase at t=5s and rapid decrease at

t=5.3s, and in between an evolution that presents several changes. In other recordings,

these rapid changes correspond to oscillations that are also visible in the αMNs activity, and

in the Flexor Ib afferent activity although to a lesser degree (not shown). A characteristic of

this network is also visible in the activity of the αMNs (Figure 6C3) with the presence of

constant activity between t=5s and t=5.3s. We never found this type of activity in the models

with muscle spindles.

8.   Behavioral domain produced in the absence of Ia feedback with central cross-

connections limited to IbINs.

We went further in the suppression of Ib sensorimotor elements (no Renshaw, no

cross connections from propriospinal INs), and we tested a spinal network in which Ib INs

were kept with their reciprocal connections (Figure 7A). The behavior domain found by rGEP

with this reduced Ib network was smaller than that of the 34-parameters. For each

movement amplitude, the maximum speed was more reduced than that of the 34-

parameters model, with a straight-line upper border (Figure 7B). It seems also that slow

movements were difficult to produce: there is no slow movements with amplitude larger

than 40 degrees in Figure 7B. An example of large movement (amplitude 81.08°) is given in

Figure 7C. Again, as was the case when 1a afferent were absent, the activity profiles of MNs

were complex, with peaks and plateaus. The initial Biceps force peak is very short and

followed by a plateau (Figure 7C2). Note that the same profile is also found in the flexor

alpha MN (*FlxαMN*) (Figure 7C3). The plateau-like αMN activity was also observed in Figure

6C3. Note also that large forces were observed: the Biceps displayed an initial 120 N short

peak; and the Triceps reached 90 N.

Figure 7: Movements produced by rGEP with the 20-parameters model. A, Sensorimotor spinal network of the 20-parameters model. **B**, Behavior domain uncovered by rGEP on this model. For comparison, the perimeter of the domain of the 50-parameter domain is represented with blue dashed line. **C**, Representative example of one valid movement in the behavior domain.

407   *9. Behavioral domain produced in the absence of Ia feedback without central cross-*

408   *connections.*

409   We also tried a simpler model with Golgi Tendon Organ feedback, in which no cross

410   relationship was present (Figure 8A). This model that was equivalent to the 14-paramaters

411   model for spindles (see Figure 5A), did not produce any valid behavior.

Figure 8: Absence of Valid Movements produced by rGEP with the 16-parameters model. **A**, Sensorimotor spinal network of the 16-parameters model. **B**, Absence of any valid behavior in the behavior domain uncovered by rGEP on this model

Figure 9: Absence of Valid Movements produced by rGEP with a complete model deprived of proprioceptive feedback. **A**, Sensorimotor spinal network of the 38-parameters model. **B**, Absence of any valid behavior in the behavior domain uncovered by rGEP on this model

10. Behavioral domain produced in the absence of any feedback but with all INs.

Because reciprocal connections seemed important to perform valid behaviors, we

tested if complete spinal network deprived of any proprioceptive feedback (Figure 9) could

produce valid behaviors. However, no valid behaviors were found with this model (Figure

9B).

B.   Analysis of triphasic patterns in the various models.

By design, valid behaviors found by rGEP followed the minimum jerk rule. However,

as we will see, this rule does not imply conformity with a triphasic command. Triphasic

command is defined from the EMG recordings of two antagonistic muscles that were

involved in a rapid movement around a joint (**Wachholder 1928; Angel 1974; Wadman et al.**

1979). Typically, the agonist muscle produced two bursts of activity: one (AG1) at the onset

of movement and one (AG2) at end of the movement. The amplitude of the initial agonist

burst (AG1) was larger than that of the second (AG2) (**Bullock and Grosberg, 1992**). In

between the two agonist bursts, an antagonist burst (ANT) is present (**Sanes and Jennings,**

1984), the role of which is to slow down the movement speed so that, ideally, the speed is 0

when target angle is reached. However, in rapid movements, the activity of the antagonistic

muscle is too large and the movement goes back. This effect is counteracted by AG2. This

excess of ANT activity and the second burst of the agonist (AG2) produce a small oscillation

of the joint angle. Such small oscillations at the movement end were accepted as long as the

error (SEM) calculated between the movement and its minimum-jerk profile was less than 1.

Movements with too large end oscillation (see Figure 1F, right, profile (1)) were rejected.

In order to apply the definition of the triphasic command, we have used the electrical

activity of muscles. However, since all models used in this study were based on non-spiking

neurons (and hence non-spiking muscle), we used the non-spiking muscle activity to analyze

triphasic command occurrences. In order to illustrate EMG profiles, for each model, we give

examples of EMGs produced during two small movements (#40°) (one rapid and one slow), during a medium amplitude movement (#60°), and during a large movement (#80°) (see Figure 10B1-4). In addition, given the variety of activity profiles recorded from muscles, we needed to get a measurement of the quality of triphasic pattern. To do this, we defined 3 criteria to quantify EMG profiles:

- **Criterium 1**: Existence of two agonist (flexor) peaks (AG1, AG2). This was a binary criterium

- **Criterium 2**: Existence of antagonist (extensor) peak (ANT) in between AG1 and AG2. This was a binary criterium.

- **Criterium 3**: Stop of agonist activity between the two peaks. This criterium (name *stopAgonistIndex*) is continuous between 0 (no activity stop) to 1 (total stop of activity between the two peaks).

    We used the following formula for this calculation:

    StopAgonistIndex = 1 - (ANT trough amplitude) / (AG1 peak amplitude)

    Each time ANT falls down to -60mV (resting potential), *StopAgonistIndex* takes the value 1. If the relative decrease of the ANT activity between AG1 and AG2 (trough) is small (say tending to 0), then *StopAgonistIndex* tends to 0.

1. *Triphasic commands with the complete (50-parameters) model*

The occurrence of triphasic commands with AG1, ANT, AG2 peaks of activity with the **50-parameters model** (Figure 10A) consisted in the following characteristics: the first AG1 flexor peak was generally very prominent (starting at resting potential and reaching a high level of activity (Figure 10B2-4). EMGs were indicated using an arbitrary unit system scale from minimum (0 corresponding to rest) to maximum activity. Its intensity was smaller in slow and small movements (Figure 10B1) compared to fast and large movements (Figure 10B2-4). Note however, that the second (AG2) flexor peak was also present but much

smaller (zooming the recording was often needed to make it visible – see Supplementary

Figure 1 for more examples with magnification of Flexor activity). The extensor peak of

activity (ANT) was regularly present in between the two flexor peaks, although its shape

could be complex (see Figure 10B1,3). Note that when the final angle is reached and stable,

extensor and flexor activities are maintained at a constant level (that can be different for

various movements of the same amplitude, i.e., the equilibrium of torques could be

Figure 10: Analysis of triphasic commands occurring in the complete model (50-parameters) with Ia and Ib feedbacks and IN cross-connections. A, Sensorimotor spinal network of the 50-parameters model. **B**, Four representative movements (pink dashed lines) and their corresponding EMG recordings (orange and blue lines for Biceps and Triceps EMGs, respectively). **C**: Estimation of the goodness of the triphasic EMG Command using the three criteria defined in the text. **C1**, Mean value for criteria 1 (Crit 1 - presence of two agonist peaks) and criteria 2 (Crit 2 - presence of antagonist peak), over all valid behaviors of the 50-parameters model. **C2**, Frequency histogram of criterion 3 (AG activity stop between the two AG peaks; crit 3 gives values between 0 (no reduction of AG activity) and 1 (total stop of AG activity) over all valid behaviors, with a majority of total stop (74.93%). **C3**, Distribution of Crit 3 values in the behavior domain (red = total AG block; see color scale).

established with various stiffnesses). In between the two flexor peaks (AG1, AG2), the

activity of the flexor was totally stopped in most of the valid behaviors obtained with the 50-

parameters model (Figure 10B1-4).

Based on the criteria define above for triphasic EMG, it appears that the valid

behaviors produced by the **compete model** (**50-parameters model**) consisted of a majority

of t*riphasic pattern commands* (Figure 10C1). Criterium 1 (presence of two agonist peaks in

muscle EMG - AG1 and AG2) and criterium 2 (presence of an antagonist peak ANT in

between AG1 and AG2) were satisfied in most of the behaviors (crit1 = 0.936 ± 0.009; crit2 =

0.885 ± 0.012; 1 corresponding to 100%, Mean + SEM) (Figure 10C1). The proportion of total

stop of the agonist activity (criterium 3) was also very high (74.93% - Figure 10C2), and

behaviors displaying this total stop were distributed all over the behavior domain (Figure

10C3).

2.   Triphasic commands with the with Ia feedback only and cross connections (36-

parameters model).

Removing the GTO feedback (**36-parameters model**, Figure 11A) did not change

fundamentally the occurrence of triphasic commands. It consisted in the presence of the

two flexor peaks (AG1, AG2) with a total stop of flexor activity between the two peaks

(Figure 11B2-4) and a nice simple extensor peak (ANT) (Figure 11B1-4). Note that the

complex shapes of extensor peak observed in Figure 10B1,2,4, were never observed in the

36-parameters model (model without GTO feedback).

The valid behaviors produced by the compete model deprived of GTO feedback (**36-**

parameters model) consisted also of a majority of t*riphasic pattern commands* (Figure 11C).

Criterium 1 and criterium 3 were satisfied in most of the produced valid behaviors (crit1 =

0.981 ± 0.006; crit3 = 0.971 ± 0.008; Mean + SEM) (Figure 11C1). The proportion of total

stop of the agonist activity during the antagonist peak (criterium 2) was 53.1% (Figure 11C2),

and behaviors displaying this total stop were distributed all over the behavior domain
(Figure 11C3).

Figure 11: Analysis of triphasic commands occurring in the complex model with Ia feedbacks only and IN cross-connections (36-parameters). A, Sensorimotor spinal network of the 36-parameters model. **B**, Four representative movements and corresponding EMG recordings. **C**: Triphasic criteria (same disposition as in Figure 10).

3. *Triphasic commands with only Ia feedback without cross connections (14-parameters model).*

In the simplest sensorimotor model, without GTO feedback and deprived of Interneurons except PNs (Figure 12A), GEP still produced valid behaviors in a behavior domain almost as large as that of the complete model (compare Figures 6B with Figure 3B). However, the muscle activation patterns (Figure 12B) were more deeply modified compared to that of the complete model. In particular, although the two flexor peaks (AG1, AG2) were

present, the activities did not come back to rest (=0 activity) in between (Figure 12B1-4). This was constantly observed whatever the amplitude or speed of the movement (Figure 12B1 4).

Figure 12: Analysis of triphasic commands occurring in the simple model (14-parameters) with Ia feedbacks only and no IN cross-connections. A, Sensorimotor spinal network of the 50-parameters model. B, Four representative movements and corresponding EMG recordings. C: Triphasic criteria (same disposition as in Figures 10-11).

In this simplest model with Ia feedback only (**14-parameters model**), the presence and disposition of AG1, AG2 and ANT peaks were largely dominant in valid behaviors (Figure 12C1). Criterium 1 and criterium 2 were satisfied in most of the produced valid behaviors (crit1 = 0.969 $\pm$ 0.009; crit2 = 0.969 $\pm$ 0.009; Mean + SEM) (Figure 12C1) (see also Supplementary Figure 2 for more examples with magnification of Flexor activity). The proportion of total stop of the agonist activity during the antagonist peak (criterium 3) was, however, much lower (2.83% - Figure 12C2), with a mean value for Stop_Agonist_Index of 0.462 and a median of 0.492. Consequently, it was not possible to estimate the distribution

of total agonist stop behaviors in the behavior domain. However, it seems that the

distribution of the behaviors with a Stop_Agonist_Index of 1 concerns only small movements

(amplitude < 50°); the behaviors with almost total stop (crit3 in range [0.8, 1]) concerns

movements < 70°; behaviors with crit3 in the range [0.5, 0.8] (yellow circles) concern

movements with an amplitude < 80°. In contrast behaviors with crit3 in the range [0.2, 0.5]

(green circles) were distributed all over the behavior domain (Figure 12C3); finally, behaviors

with small crit3 values in the range [0.05, 0.2] (blue circles) concern only large movements

(amplitude > 60°).

4.   Triphasic commands with Ib feedback only and cross connections (34-parameters

model).

The most complete sensorimotor network deprived from Ia proprioceptive feedback

(**34-parameters model**) (Figure 13A) produced a large variety of valid behavior with a

behavior domain slightly reduced compared to that of the complete (50-parameters) model

(compare Figure 6B with Figure 3B). However, the EMG profile differed from that of the

complete 50-parameters model (Figure 13B). In particular, EMG profiles were generally

more complex for the flexor activity, with a sharp AG1 peak followed by a plateau of reduced

activity (rarely falling down to rest = 0), followed by a second increase of activity with a

complex profile (abrupt trough in Figure 13B1; multi stage increase in Figure 13B2). The

activity of the Extensor was also deeply modified, with most of the time no clear peak of

activity occurring in between the two flexor peaks (Figure 13B1,3), although some behavior

presented an increased ANT plateau activity (Figure 13B2. In most cases, the level of activity

of the extensor muscle stayed high (close to maximum), or presented a high plateau activity

followed by an abrupt decrease before increasing again in a short peak occurring at the

same time as AG2 (Figure 13B4).

For this most complete model with Ib feedback only (**34-parameters model**) the

mean value of criterium 1 (presence of AG1 and AG2 peaks) was crit1 = **0.639** ± 0.009 (Mean

+ SEM) (Figure 13C1) against 0.94, 098 and 0.97 for 50-parameters, 36-parameters and 14-

parameters models, respectively. Criterium 2 (presence of ANT peak) was greater (Figure

13C1) (crit3=0.854 ± 0.007; Mean + SEM) against 0.885, 0.971 and 0.969 for 50-parameters,

36-parameters and 14-parameters models, respectively. Moreover, for criterium 3, only

2.17% of the valid behaviors displayed a total stop of agonist activity during the ANT peak

(Figure 13C2).

Figure 13: Analysis of triphasic commands occurring in model with Ib afferents only and IN cross-connections. A, Sensorimotor spinal network of the 34-parameters model. **B**, Four representative movements and corresponding EMG recordings. **C:** Triphasic criteria (same disposition as in Figures 10-12).

545   In addition, the behaviors presenting this total stop of agonist activity were restricted

546   on the highest velocity movements for amplitudes in the range 30-80° (red circles in Figure

13C3), while behaviors with a marked trough of agonist activity (crit3 in the range [0.5-0.8])
were distributed all over the behavior domain (yellow circles in Figure 13C3), which indicates
that less frequent, degraded triphasic pattern can also be produced by the **34-parameters
model** all over the behavior domain. However, the behaviors with small to absent trough in
agonist activity were preponderant all over the behavior domain (blue circles in Figure
13C3).

5. *Triphasic commands with 1b feedback only and Ib INs cross connections (20-*
   parameters model).

In the presence of Ib proprioceptive feedback only, and with Ib INs central cross
connections (Figure 14A), the behavior domain was very reduced (Figure 7B) compared to
that of the 50-parameters model (Figure 3B). Valid behaviors presented the same
characteristics as that of the 34-parameters model (Figure 14B), with a marked brief peak of
activity (AG1) (Figure 14B1-4) followed by a reduced plateau activity and a last increase in
activity (sometimes with a small AG2 peak– Figure 14B2). The activity of the extensor muscle
was generally maintained very high (close to max), sometimes starting at the onset of the
SET command (Figure 14B2-3) or starting with the onset of the GO command (Figure 14B1).
Nevertheless, there were also behaviors with a peak of activity corresponding to ANT (Figure
14B4) .

For this simplified **20-parameter model** (with only GTO feedback) (Figure 14A),
statistics on triphasic command were close to that of the 14-parameters model. The mean
value of criterium 1 (presence of AG1 and AG2 peaks) was crit1 = **0.997** $\pm$ 0.002 (Mean +
SEM) (Figure 14C1). Criterium 2 (presence of ANT peak) (Figure 14C1) was crit2=**0.855** $\pm$
0.011 (Mean + SEM). However, the criterium 3 (stop of agonist discharge during ANT peak)
was never encountered (Figure 14C2), the mean value of the Stop Agonist Index being
0.316$\pm$ 0.004 (Mean + SEM). The behavior domain the 20-parameters model (Figure 14C3) is

572   covered mainly by behaviors with a Stop_Agonist_Index in the range [0.2, 0.5] (Figure 14C3),

573   Behaviors with higher crit3 values are restricted to the smallest movements (see orange and

574   yellow circles).

Figure 14: Analysis of triphasic commands occurring in model with Ib afferents only and Ib PN cross connections. A, Sensorimotor spinal network of the 20-parameters model. B, Four representative movements and corresponding EMG recordings. C: Triphasic criteria (same disposition as in Figures 10-13).

Discussion

In the present modelling work, we explored the capacities of spinal sensorimotor networks to produce triphasic EMG pattern when activated by simple descending SET and GO step commands. We observed spontaneously occurring triphasic pattern EMGs produced by spinal sensorimotor circuits (50-parameters model) during the goal exploration process used to establish the behavioral capabilities of the system. Critically, the timing of such triphasic patterns were not predetermined in the descending commands consisting of simple step functions. Particularly, the GO command, initiated the movement (t=5s) but did not give any indication for the observed triphasic EMG patterns. Since the 50-parameters model involved both Ia spindle and GTO afferent feedback, we have used a dissecting out approach to evaluate the role of Ia and Ib afferents and their respective sensorimotor circuits in the elaboration of the triphasic commands.

A. Role of spindle feedback in triphasic pattern.

In the 50-parameters model, most of the valid movements uncovered by the random Goal Exploration Process (rGEP) were triphasic commands (Figure 12A). Removing Ib sensory feedback and Ib sensorimotor circuits did not change much this result (Figure 12B), and indicates that Ia feedback and Ia sensorimotor spinal circuits can handle the elaboration of triphasic commands when descending commands are deprived of such dynamic contains. Moreover, such triphasic commands issued from Ia spindle afferent feedback and Ia sensorimotor spinal circuits are spontaneously produced all over the behavior domain uncovered using the rGEP (Figure 12B3). Note, however, that spinal sensorimotor circuits, and especially reciprocal connections, seem to be important for fast and large valid movements to be produced (compare Figure 5B with Figure 4B). Indeed, the behavior domain is reduced in the absence of these reciprocal connections, but it is still covered by triphasic commands (Figure 12C3) (if we accept only partial stop of agonist discharge

between AG1 and AG2 peaks). Yet, it is important to stress that reciprocal connections via

spinal interneurons (Renshaw, Ia, Ib, PN) are not sufficient on their own to produce valid

movements, i.e., in the absence of proprioceptive feedback (Figure 9). Therefore, this study

demonstrates that spindle signals and the associated sensorimotor spinal networks have the

capacity to handle the production of triphasic command pattern. It is then highly likely that

they participate in the elaboration of this triphasic command in animals and human. But if

this conclusion is true, how to explain the finding that triphasic patterns were still produced

in transient deafferentation experiments **(Sanes and Jennings 1984)**? In fact, this experiment

do not totally invalidate the **participation of sensorimotor circuits** in the shaping of the

triphasic command, because the ischemic block affected the afferent activity of the muscles

below the elbow, leaving intact both the efferent copy of their motoneurons via Renshaw's

interneurons and all proprioceptive feedbacks from all proximal muscles. The widespread

extent of these feedback circuits **(Cavallari et al. 1992),** and the strong modulation of

proximal muscles to stabilize posture during distal phasic movements, were not fully

appreciated until later **(Massion 1992)**.

B.   Role of GTO feedback in triphasic pattern

In the absence of Ia feedback, and in the presence of Ib feedback with all Ib

sensorimotor circuits, triphasic commands were found all over the corresponding behavior

domain (Figure 12D3) which was almost the same as that of the 50-parameters model

(compare Figure 6 with Figure 3). However, only 2.17% of movements displayed a total

agonist activity block between AG1 and AG2 peaks (see an example of such activity in Figure

13B4 and stop agonist index in Figure 13C2). However, the pattern of agonist and antagonist

activity was clearly dissimilar from that of the 50-parameters model (i.e., complete model –

Figure 10B) and the 36-parameters model (i.e., complete model deprived of Ib feedback –

Figure 11B). Indeed, in most valid movements, antagonist activity (Ext EMG) displayed an

increased activity at the beginning of the movement (when the GO command starts), and

when the ANT peak was present, it occurred at the same time as AG2 (Figure 13B1,B2,B4).

This pattern of activity is far from the typical AG1, ANT, AG2 peaks sequence described in

Hallett et al. (**1975**), in which, even though ANT activity may overlap AG1 or AG2, ANT peak

always occurred after AG1 peak and before AG2 peak. For all these reasons, Ib GTO feedback

and Ib sensorimotor circuits does not seem to play a central role in the organization of the

classical Triphasic command. Note also that the instability resulting from Ib positive feedback

onto their MNs is certainly responsible for the complex profiles of EMGs. If we compare the

EMG profiles of the 50 parameters model (complete model with Ia and Ib – Figure 10B) with

the EMG profiles of the 36-parameters model (complete model deprived from Ib – Figure

11B), we note that the instability present in the complete model has disappeared when Ib

feedback and sensorimotor circuits have been removed. Nevertheless, Ib GTO feedback

seems to play a role in boosting movement initiation, because when Ib feedback is

suppressed, Maximal speed is reduced (compare Figure 4B with Figure 3B). This involvement

in force enhancement was also described in physiological conditions in cat **(Donelan and**

Pearson 2004).

C.   Role of descending commands and spinal networks in triphasic pattern.

The fact that Ia spindle feedback and their spinal sensorimotor circuits are capable of

handling triphasic commands all over the behavior domain, does not exclude, however, that

in physiological conditions, descending command also participate in the elaboration of

triphasic commands. Recordings from M1 motor cortex indicate that unit and global

activities can be correlated either with static and dynamic forces and torques around single

joints **(Cabel et al. 2001)**, or with muscle synergies **(Holdefer and Miller 2002)**. Therefore, it

is likely that such precise descending command may interact with spinal sensorimotor

networks. In the present report, we used simple step commands to control spinal

sensorimotor circuits. Some authors have argued that because EMGs are organized in

triphasic pattern with silent periods, this indicated that descending commands did not

operate in a smooth and continuous manner **(Leib et al. 2020)**. Indeed, the simple model

(bang-bang optimal control model) proposed by these authors is more structured in time

than the simple step functions we used here. In the bang-bang control, the control signal

abruptly switches between a maximum and a minimum value at certain sparse points in

time. The control function is made of three constant segments (with two transitions). The

bang-bang model explains both abrupt changes in muscles activity (triphasic command) and

the smooth reaching trajectory. Interestingly, rGEP was capable of uncovering a set of valid

behaviors (minimum jerk movements) relying incidentally on triphasic commands (with

abrupt changes in activity), although this triphasic command was not explicitly searched for

nor included in the process with simple step commands. Therefore, it is possible that spinal

network properties (and the associated biomechanical effector system) possess the

capacities of handling such complex dynamic commands just by giving the correct level of

stimulation of target spinal neurons and precise synaptic gain settings. In a more general

perspective, these spinal sensorimotor circuits could be considered as the physiological

support of movement primitives proposed by **Degallier and Ijspeert (2010)** that can be

handled by simple step commands from the brain. In this case, the motor primitives not only

encompass movement' start dynamics but also movement' stop dynamics with a unique

step command.

D.   Triphasic pattern and minimum jerk.

Simulation studies have suggested that minimum-jerk models **(Flash and Hogan**

1985) and minimum torque-change models **(Uno et al. 1989)** were likely not capable to

predict muscle actions **(Osu et al. 2004)** and thus triphasic pattern. Here, we used a different

approach that involved a musculoskeletal model associated to spinal sensorimotor

networks, and a search method (rGEP) to revisit the capability of spinal sensorimotor circuits

to produce triphasic pattern of muscle activation.

Indeed, rGEP uncovered a great diversity of parameters associated with a given valid

movement. Among these parameters, some will result in triphasic commands. This solution

was found all over the behavior domain of the model. But other parameter sets do not fit

the definition of triphasic command. For example, although the silence of the agonist

between the two agonist peaks (AG1 and AG2) was found in most of the 50-parameters

model valid movements (Figure 10B), there were also rare solutions with virtually no

reduction in agonist activity (criterion 3<0.05; see violet symbol in Figure 10C3) all over the

behavior domain of this complete model. Yet, it seems that triphasic pattern is the natural

solution issued from the spinal sensorimotor networks during random Goal Exploration

Process (rGEP).

The fact that we imposed a minimum jerk profile for movements had consequences

on the type of triphasic command retained by rGEP. Indeed, when we consider fast

movements that were retained to define the triphasic pattern (**Hallett et al. 1975**), we note

the presence of a small oscillation at the end of the movement. The origin of this final

oscillation comes from ANT peak that was slightly too strong, resulting in a final oscillation

that required the second agonist peak (AG2) to be damped **(Berardelli et al. 1996)**. The

minimum jerk profile virtually imposes the absence of such oscillation at the end of the

movement, and thereby reduces dramatically the amplitude of AG2 (see blue traces in

Figure 10B1-4).

E.   Limits of the study.

No separate Static and Dynamic gamma MNs. All models of the present study used a

mixed type of gamma MN (one for the biceps and one for the triceps). Ideally, we should

have used two types of gamma MNs for each muscle: a static gamma MN and a dynamic

gamma MN, as was the case in the model of spinal-like regulator **(Raphael et al. 2010)**.

However, the activation of the gamma MN of our model increased spindle sensitivity to both

position and velocity, and this single type of gamma MN was enough to produce the desired

behavior of the model under rGEP. Certainly, the possibility for the descending step

commands to act differently on spindle length coding and speed/acceleration coding

feedbacks could benefit to the possibilities of control, and likely extend the behavior domain

of the model. This point will need future work to estimate the changes brought by the two

gamma MN types.

Absence of gravity. We presented here the results of movements conducted in the

absence of gravity. The presence of gravity during elbow flexion exerts an increasing torque

that opposes the action of the biceps and could potentially obscure the role of the triceps in

slowing down the movement, particularly when the movements are not sufficiently fast. It

will be interesting in future investigations to add gravity to see how triphasic pattern evolve,

depending on movement trajectory, and how spinal network can handle it. Such studies

should show smaller ANT burst when gravity is present and tend to slow down the

movement as the forearm becomes more horizontal during flexion movements. Inversely, if

movements start from a flexed position (say 110° in our model), and stops at 90°, ANT burst

should be dramatically increased.

Simple flexion movement. In the present study, we used a single joint (elbow) and

movement consisted in elbow flexion. This was made because minimum jerk is more

adapted to this situation **(Nakano et al. 1999).** It would be interesting to generalize the

results of the present study by using more complex models including two joints, and mono-

and bi-articular muscles, and considering endpoint reaching movements.

Methods

A.   Software's used in simulations.

During this work, we have used several models of sensorimotor systems controlling the same musculo-skeletal apparatus. All models were developed with the **AnimatLab software** (https://animatlab.com) (**Cofer et al. 2010)**, a neuromechanical environment based on user-friendly graphic interface that can be downloaded from https://www.animatlab.com. Execution of AnimatLab models can be controlled by **Python scripts**, which were used to command execution of model movements by **descending cues** targeting spinal neurons and synapses (see below). All scripts used in the present work are written in Python3.8 language. For a quick overview of GEP principles, see pseudo script in Supplementary materials. Python scripts for GEP and all simulations included in this study can be downloaded from GitHub, with an installation procedure for all software package involved:

(https://github.com/Cattaert/rGEP/tree/main).

B.   Musculoskeletal system

The musculoskeletal model consisted of an upper limb involving an elbow actuated by two antagonistic muscles (biceps and triceps) (Figure 1A). This single musculoskeletal model was used in all simulations, with various spinal sensorimotor circuits and their descending commands (see below). Information about this musculoskeletal model is given in table 1.

745   All movements were produced **in the absence of gravity** in order to avoid natural

746   slowdown of movement speed as the forearm is flexed.

Segments	Length (mm)	density	mass
Humerus	337.0911395	8000 Kg/m3	1.164 Kg
Forearm	283.1808226	8000 Kg/m3	0.802 Kg
Hand	193.21	8000 Kg/m3	0.966 Kg
Joints (coordinates world positions)	**Z_coord (deepness)**	**Y_coord (up-down)**	**X_coord (left-right)**
Elbow	-4.586	-144.65	-5.372
wrist	14.883	-427.07	1.789
Muscle insertions (world positions)			
Biceps origin	0	150.69	26.509
Biceps insertion	-0.578	-188.28	24.146
Triceps origin	0	151.13	-21.51
Triceps insertion	0.934	-103.64	-16.507
Biceps insertion/Forearm elbow axis	52.82947367		
Triceps insertion/forearm elbow axis	42.85182289		

Table 1: musculo-skeletal model data. Coordinates and dimensions are given in mm. The origin of coordinates (0,0,0) is the center of the Humerus, that is in vertical position at rest (see Fig. 1A).

C.   Modelling coding properties of muscle spindle

Muscle spindles were added to each muscle. In AnimatLab (see Methods), muscle

spindles have the same "attachments" as the muscles. Their tension-length ratio, maximum

force capacity, and viscoelasticity are based on the Hill muscle model **(Scovil and Ronsky**

2006). To assess the quality of this neuro-musculoskeletal model, imposed movements of

flexion and extension were simulated, while muscle spindle activity was recorded (Figure

15A). Our first work was to adjust by hand the muscle spindle parameters that controlled

their coding of movements so that their response were comparable to electrophysiological

 data from the literature **(Boyd et al. 1977)** (Figure 15B), in the absence and in the presence

756 of activation of a Gamma MN.

Figure 15. Muscle spindle coding properties

A. Modeled extensor muscle spindle activity during stretch (S) and release (R) ramps, without (left), and with (right) activation of the gamma motoneuron (I γMN). **B.** Electrophysiological recording of the Ia fiber during the same imposed movements as in **A** modified from (**Boyd et al. 1977**)

Note that, in both simulation and physiological recording, the first release of the spindle does not give any response (see *) due to lack of tension of the spindle. However, the activation of the γMN allows the spindle to give an answer during the second release (see **). Note also that in **A**, the "acceleration" component produced by the serial spring velocity (in the Hill model) is responsible for the transient activation at each movement change (arrows), while the "tonic" component (produced by the tension of the spindle (in the Hill model) produces an exponential decay shape. Transients are also produced at onset and offset of the γMN stimulation. These features are present in **B** except for transients at the end of stretch movements.

      D.   Type of neurons used in the present work

Non-spiking (NS) neurons were used to simulate neurons in spinal sensorimotor

networks. NS neurons allow a continuous synaptic activation that depends only on

presynaptic threshold potential, presynaptic saturation potential, equilibrium potential for

post-synaptic effect and synaptic gain (maximal synaptic conductance). The change in

postsynaptic conductance increases from 0 (at presynaptic threshold potential) to the

maximal synaptic conductance (for presynaptic saturating potential and over). Between

these presynaptic threshold and saturation potentials, the postsynaptic conductance

increases linearly. Using NS neurons can also be considered as representing population

neurons instead of single neurons.

E.   Cost function used to select valid behaviors.

For each movement produced, a **cost function** estimated the proximity of

movements produced by the simulation to human movement. As normal human movements

follow a template based on the minimum jerk model (**Flash and Hogan 1985**), the **cost**

function calculates the distance (mean square error) between the produced movement and

this template (see Figure 1C), with the addition of the penalty for the co-contraction

(*Equation 1*). This term was added after a first exploration of the method, which led to

systematic co-contraction during the preparation period (result of the SET command). The

result was considered valid when the *Loss* value was less than 1.

$Cost = \sum_{t=2}^{t=10} (T_{desired}(t) - T_{actual}(t))^2 + Penalty\_Prep + Penalty\_Main$ **Equation 1**,

with t representing the different sampled times of the simulation (dt=10ms).

In order to avoid solutions in which co-contraction occurred during the preparatory

phase (or after movement stabilization), co-contraction penalty was added in each of these

phases. *Penalty_Prep* was calculated during the preparatory phase (start=2s, end=5s), and

Penalty_Main during the maintained position phase (start=7s, end=10s). The movement

phase was not included because complex interactions may occur due to the dynamics of

sensorimotor interactions. The penalty for co-contraction was calculated as indicated in

Equation 2.

$Penalty\_i = \frac{1}{end-start} * \left(\int_{t=start}^{t=end} (VMN_{flex} - Vthr) * (VMN_{ext} - Vthr) * dt\right) * coeff\_i$ **Equation 2**,

in which VMN_{flex} and VMN_{ext} are the membrane potential of the flexor and extensor MNs,

respectively, and V_{thr}=-60mV, is a threshold voltage under which penalty = 0.

The coefficient (*coeff_i*) was set to 100 during the preparatory phase to make sure

coactivation would be rejected in this phase, and *coeff_i* was set to 0 during the maintained

position after movement to allow coactivation in this last phase.

F.   Optimization methods used to get first behaviors (seeds).

1.   Variable step coordinate descent (VSCD)

The original method developed by Gerald Loeb's group **(Raphael et al. 2010)** was a

classical coordinate descent method, in which all parameters are successively improved

individually. The value of each parameter is modified by a given amount (delta) to get a

value slightly above and another slightly below the previous setting. A cost value (see cost

function above) is calculated for three simulation runs (value above, value below and

previous value). The parameter value that elicited the lowest cost value is saved for the next

simulation. Then, the process is repeated for the next variable. This method is iterated until

the *Loss* value is stable and reaches a minimal value. However, in order to accelerate the

optimization process the method was modified : several iterations were performed on each

variable before passing to the next one, using an **adaptable delta** inspired from the resilient

propagation (Rprop) algorithm **(Igel and Husken 2003).** When iteration improves the loss

function, delta value was multiplied by 2.5, and when no improvement was obtained, the

delta value was divided by 2 and applied to the previous best iteration to re-center the

exploration. We used up to 5 iterations for each parameter. At the end of a round

(optimization of all parameters), the order of these variables was shuffled to avoid any order

effect that could limit the optimization procedure. For all optimizations, the starting delta

was equal to 0.01 which means a variability of 1% of the parameter for the first iteration.

2. Covariance Matrix Adaptation evolution strategy (CMAes)

The second type of optimization algorithm (CMAes) is an evolution algorithm developed

by Hansen **(Hansen, 2006)**. It works with a gradient descent with the aim to minimize a cost

function. This evolution algorithm is based on the principle of biological evolution. This

means that for each generation (iteration), new individuals are generated from variation, in

a stochastic way, of the current generation. To initiate the next generation, individuals with

the best scores (minimal value of the cost function) are selected to become the parents of

the next generation. Following this rule, individuals of the successive generations get closer

to the best results.

In the evolution algorithm, the solutions that represent the new generations are issued

from multivariate-normal distribution based on a variance value (*sigma*) and the covariance

matrix of the preceding best solutions. This allows the stochastic changes made to the

parameters to be oriented in the direction of the solution. Moreover, from one generation

to the next, the *sigma* value is adapted: increased when two generations are in the same

direction, and decreased if not. This allows accelerating the progress of optimization.

In the CMAes optimization procedure, some parameters have to be given before the

simulation was launched including the *limits* of exploration and the *sigma* value. If the *limits*

of exploration were too large, new individuals could be generated too far from each other

and the optimal solution might not be reached. A small *sigma* will create a new generation

not so different from the previous one and a large one will bring more changes. All

optimization series were initiated with a small *sigma* (0.005) and *limits* of exploration

covering 100% (i.e., between 0 and 1 for all normalized parameter values). *Sigma* and *limits*

were given to CMAes at initiation of optimization process.

Author Contributions

Conceptualization: Daniel Cattaert, Aymar de Rugy, Pierre-Yves Oudeyer.

Funding acquisition:

Methodology: Daniel Cattaert, Bryce Chung, Florent Paclet, Pierre-Yves Oudeyer,

Aymar de Rugy.

Project administration: Aymar de Rugy.

Investigation: Daniel Cattaert, Matthieu Guemann.

Software: Daniel Cattaert, Bryce Chung, Florent Paclet.

Supervision: Aymar de Rugy.

Validation: Daniel Cattaert, Aymar de Rugy, Pierre-Yves Oudeyer.

Writing – original draft: Daniel Cattaert.

Writing – review & editing: Daniel Cattaert, Matthieu Guemann, Florent Paclet,

Bryce Chung, Pierre-Yves Oudeyer, Aymar de Rugy

Acknowledgments

850 This work was supported by The Centre National de la Recherche Scientifique

851 (CNRS) and the University of Bordeaux.

References

References

Baranes A, and Oudeyer PY. Active learning of inverse models with intrinsically motivated

goal xploration in robots. *Robotics and Autonomous Systems* 61: 2013.

Barnett CH, and Harding D. The activity of antagonist muscles during voluntary movement.

Ann Phys Med 2: 290-293, 1955.

Berardelli A, Hallett M, Rothwell JC, Agostino R, Manfredi M, Thompson PD, and Marsden

CD. Single-joint rapid arm movements in normal subjects and in patients with

motor disorders. *Brain* 119 (Pt 2): 661-674, 1996.

Boyd IA, Gladden MH, McWilliam PN, and Ward J. Control of dynamic and static nuclear bag

fibres and nuclear chain fibres by gamma and beta axons in isolated cat muscle

spindels. *J Physiol* 265: 133-162, 1977.

Brown SH, and Cooke JD. Amplitude- and instruction-dependent modulation of movement-

related electromyogram activity in humans. *J Physiol* 316: 97-107, 1981.

Cabel DW, Cisek P, and Scott SH. Neural activity in primary motor cortex related to

mechanical loads applied to the shoulder and elbow during a postural task. *J*

Neurophysiol 86: 2102-2108, 2001.

Cavallari P, Katz R, and Penicaud A. Pattern of projections of group I afferents from elbow

muscles to motoneurones supplying wrist muscles in man. *Exp Brain Res* 91: 311-

319, 1992.

Cofer D, Cymbalyuk G, Reid J, Zhu Y, Heitler WJ, and Edwards DH. AnimatLab: a 3D graphics

environment for neuromechanical simulations. *J Neurosci Methods* 187: 280-288,

2010.

Colas C, Sigaud O, and Oudeyer P-Y. GEP-PG: Decoupling Exploration and Exploita- tion in

Deep Reinforcement Learning Algorithms. In: *International Conference on*

Machine Learning (ICML). Stockholm, Sweden: 2018.

Degallier S, and Ijspeert A. Modeling discrete and rhythmic movements through motor

primitives: a review. *Biol Cybern* 103: 319-338, 2010.

Donelan JM, and Pearson KG. Contribution of force feedback to ankle extensor activity in

decerebrate walking cats. *JNeurophysiol* 92: 2093-2104, 2004.

Eliasmith C, and Anderson CH. *Neural engineering : Computation, representation, and*

dynamics in neurobiological systems. . MIT press., 2003.

Etcheverry M, Moulin-Frier C, and Oudeyer PY. Hierarchically Organized Latent Modules for

Exploratory Search in Morphogenetic Systems. *Advances in Neural Information*

Processing Systems 2020.

Eysenbach B, Gupta A, Ibarz J, and Levine S. Diversity is all you need: Learning skills without

a reward function. In: *7th Internarional Conference on Learning Representations*.

New Orleans, LA, USA, : 2019.

Flash T, and Hogan N. The coordination of arm movements: an experimentally confirmed

mathematical model. *J Neurosci* 5: 1688-1703, 1985.

Forestier S, Mollard Y, and Oudeyer P-Y. Intrinsically Motivated Goal Exploration Processes

with Automatic Curriculum Learning. arXiv preprint 2017.

Ghez C, and Martin JH. The control of rapid limb movement in the cat. III. Agonist -

antagonist coupling. *Exp Brain Res* 45: 115-125, 1982.

Grizou J, Points LJ, Sharma A, and Cronin L. A curious formulation robot enables the

discovery of a novel protocell behavior. . *Science advances* 6: 2020.

Hallett M, and Marsden CD. Ballistic flexion movements of the human thumb. *J Physiol* 294:

33-50, 1979.

Hallett M, Shahani BT, and Young RR. EMG analysis of stereotyped voluntary movements in

man. *J Neurol Neurosurg Psychiatry* 38: 1154-1162, 1975.

Haruno M, and Wolpert DM. Optimal control of redundant muscles in step-tracking wrist

movements. *J Neurophysiol* 94: 4244-4255, 2005.

Holdefer RN, and Miller LE. Primary motor cortical neurons encode functional muscle
synergies. *Exp Brain Res* 146: 233-243, 2002.

Igel C, and Husken MH. Empirical evaluation of the improved rprop learning algorithms.
Neurocomputing 50: 105-123, 2003.

Lehman J, and Stanley KO. Abandoning objectives: evolution through the search for novelty
alone. *Evol Comput* 19: 189-223, 2011.

Leib R, Russo M, d'Avella A, and Nisky I. A bang-bang control model predicts the triphasic
muscles activity during hand reaching. *J Neurophysiol* 124: 295-304, 2020.

Massion J. Movement, posture and equilibrium: interaction and coordination. *Prog*
Neurobiol 38: 35-56, 1992.

Mouret JB, and Doncieux S. Encouraging behavioral diversity in evolutionary robotics: an
empirical study. *Evol Comput* 20: 91-133, 2012.

Nakano E, Imamizu H, Osu R, Uno Y, Gomi H, Yoshioka T, and Kawato M. Quantitative
examinations of internal representations for arm trajectory planning: minimum
commanded torque change model. *J Neurophysiol* 81: 2140-2155, 1999.

Osu R, Kamimura N, Iwasaki H, Nakano E, Harris CM, Wada Y, and Kawato M. Optimal
impedance control for task achievement in the presence of signal-dependent
noise. *J Neurophysiol* 92: 1199-1215, 2004.

Oudeyer PY, and Kaplan F. What is Intrinsic Motivation? A Typology of Computational
Approaches. *Front Neurorobot* 1: 6, 2007.

Pathak D, Agrawal P, Efros AA, and Darrell T. Curiosity-driven exploration by self-supervised
prediction. In: *IEEE Conference on Computer Vision and Pattern Recognition*
Workshops Honolulu, HI, USA: IEEE, 2017, p. 16-17.

Péré A, Forestier S, Sigaud O, and Oudeyer PY. Unsupervised learning of goal spaces for
intrinsically motivated goal exploration. In: *ICLR 2018*2018.

Raphael G, Tsianos GA, and Loeb GE. Spinal-like regulator facilitates control of a two-

degree-of-freedom wrist. *J Neurosci* 30: 9431-9444, 2010.

Reinke C, Etcheverry M, and Oudeyer PY. Intrinsically Motivated Discovery of Diverse

Patterns in Self-Organizing Systems. In: *ICLR 2019*2019.

Rothwell JC, Traub MM, Day BL, Obeso JA, Thomas PK, and Marsden CD. Manual motor

performance in a deafferented man. *Brain* 105 (Pt 3): 515-542, 1982.

Sanes JN, and Jennings VA. Centrally programmed patterns of muscle activity in voluntary

motor behavior of humans. *Exp Brain Res* 54: 23-32, 1984.

Scovil CY, and Ronsky JL. Sensitivity of a Hill-based muscle model to perturbations in model

parameters. *J Biomech* 39: 2055-2063, 2006.

Sergio LE, Hamel-Paquet C, and Kalaska JF. Motor cortex neural correlates of output

kinematics and kinetics during isometric-force and arm-reaching tasks. *J

Neurophysiol* 94: 2353-2378, 2005.

Terzuolo CA, Soechting JF, and Ranish NA. Studies on the control of some simple motor

tasks. V. Changes in motor output following dorsal root section in squirrel

monkey. *Brain Res* 70: 521-526, 1974.

Trainin E, Meir R, and Karniel A. Explaining patterns of neural activity in the primary motor

cortex using spinal cord and limb biomechanics models. *J Neurophysiol* 97: 3736-

3750, 2007.

Ueyama Y. Costs of position, velocity, and force requirements in optimal control induce

triphasic muscle activation during reaching movement. *Sci Rep* 11: 16815, 2021.

Uno Y, Kawato M, and Suzuki R. Formation and control of optimal trajectory in human

multijoint arm movement. Minimum torque-change model. *Biol Cybern* 61: 89-

101, 1989.

Figure01

Figure02

A NS26NG_36par

20 SET on synapses
10 SET on Neurons
6 GO on IN Neurons

Renshaw   Renshaw

Biceps γ MN   Triceps γ MN

Biceps α MN   IaIN   IaIN   Triceps α MN

PN   PN

Spindle   Spindle

Ia   Ia

Biceps   Triceps

B **No gravity** NS26NG_36par

50109 valid bhv   **132261 runs**

Duration (ms)
- - - 300
- - - 400
- - - 500
- - - 600
- - - 700
- - - 850
- - - 1000
- - - 1150
- - - 1300
- - - 1600
- - - 1900
- - - 2200

movements with a duration of 300 ms

max speed (°/s)

mvt amplitude (°)

C₁

maxSpeed: 295.78 °/s
amplitude: 78.72 °
duration: 470 ms   mse: 0.311

Elbow Mvt(deg.)

— Elbow
— Template

C₂

Force (N)

— Triceps
— Biceps

C₃

Mb Potential (mV)

— ExtαMN
— FlxαMN

C₄

Mb Potential (mV)

— ExtIa
— FlxIa

Time (s)

Chart04 (seeds00)

Figure04

A NS25NG_50par

30 SET on synapses
12 SET on Neurons
8 GO on IN Neurons

B No gravity NS25NG_50par
36152 valid bhv   107315 runs

Figure03

C₁
maxSpeed: 324.24 °/s
amplitude: 90.23 °
duration: 480 ms   mse: 0.591

Chart06 (seeds00)

Figure05

A NS25NG_34par

20 SET on synapses
8 SET on Neurons
6 GO on IN Neurons

Renshaw   Renshaw

Biceps α MN   Triceps α MN

PN   IbIN   IbIN   PN

Biceps   Triceps

Golgi   Ib   Ib   Golgi

B No gravity NS25NG_34par

66794 valid bhv   216892 runs

Duration (ms)
- - - 300
- - - 400
- - - 500
- - - 600
- - - 700
- - - 850
- - - 1000
- - - 1150
- - - 1300
- - - 1600
- - - 1900
- - - 2200

max speed (°/s)

movements with a duration of 300 ms

mvt amplitude (°)

Chart01 (seeds02)

C1

maxSpeed: 284.43 °/s
amplitude: 76.43 °
duration: 470 ms   mse: 0.92

Elbow Mvt(deg.)

Elbow
Template

C2

Force (N)

Triceps
Biceps

C3

Membrane Potential (mV)

ExtαMN
FlxαMN

C4

Membrane Potential (mV)

Ext1b
Flx1b

Time (s)

Figure06

Figure07

Figure08

A NS25NG_38par

20 SET on synapses
10 SET on Neurons
8 GO on IN Neurons

Renshaw Renshaw

Biceps α MN IaIN IaIN Triceps α MN

PN IbIN IbIN PN

Biceps Triceps

B No gravity NS25NG_38par

3621 valid bhv 35629 runs

max speed (°/s)

Duration (ms)
- - - 300
- - - 400
- - - 500
- - - 600
- - - 700
- - - 850
- - - 1000
- - - 1150
- - - 1300
- - - 1600
- - - 1900
- - - 2200

No valid behavior

mvt amplitude (°)

Figure09

Figure10

Figure11

Figure12

Figure13

Figure14

Figure15

Model 50 param

figure Sup02