Segmentation-free measurement of locomotor frequency in *Caenorhabditis*

***elegans* using image invariants**

Hongfei Ji[a,b,1], Dian Chen[a,1], and Christopher Fang-Yen[a,b]

[a]Department of Biomedical Engineering, College of Engineering, The Ohio State University,
Columbus, OH 43210, USA

[b]Department of Bioengineering, School of Engineering and Applied Science, University of
Pennsylvania, Philadelphia, OH 19104, USA

[1]These authors contributed equally to this work.

ABSTRACT

An animal's locomotor rate is an important indicator of its motility. In studies of the nematode

C. elegans, assays of the frequency of body bending waves have often been used to discern

the effects of mutations, drugs, or aging. Traditional manual methods for measuring

locomotor frequency are low in throughput and subject to human error. Most current

automated methods depend on image segmentation, which requires high image quality and

is prone to errors. Here, we describe an algorithm for automated estimation of *C. elegans*

locomotor frequency using image invariants, i.e., shape-based parameters that are

independent of object translation, rotation, and scaling. For each video frame, the method

calculates a combination of 8 Hu's moment invariants and a set of Maximally Stable

Extremal Regions (MSER) invariants. The algorithm then calculates the locomotor frequency

by computing the autocorrelation of the time sequence of the invariant ensemble. Results of

our method show excellent agreement with manual or segmentation-based results over a

wide range of frequencies. We show that compared to the segmentation method that

analyzes a worm's shape, our method is more robust to low image quality. We demonstrate

the system's capabilities by testing the effects of serotonin and serotonin pathway mutants

on locomotor frequency.

INTRODUCTION

Locomotion is an important parameter in behavioral genetics. Changes in motor behavior can reflect the effects of genetic mutations, modulations of neurochemical compounds, and variations in the physiological states of animals (1). For *C. elegans*, a variety of studies investigating changes or defects in its locomotor frequency have given insights into complex biological processes, including neurochemical modulation, neuromuscular coordination, and neural circuit development (2–8).

Current methods for quantifying locomotor frequency include manual scoring and machine vision approaches. Traditional manual scoring is performed by counting the number of body bending movements of worms placed in a solid or liquid environment (9). Manual measurements are technically simple but low in throughput and subject to observer error.

To address these limitations, progress has been made in machine vision systems for automating the analysis of *C. elegans* locomotor movements. Most automated methods rely on analyses of animal morphometry. In these methods, each image undergoes filtering and thresholding to yield a binary image, from which features such as centroid position, body centerline, curvature, and posture can be determined. Extracting these features from image sequences enables further determination of behavioral dynamics, including moving speed, amplitude, reorientations, and locomotor frequency (7, 10–14). These methods are highly susceptible to recording conditions and are vulnerable to image noise, low image quality, and behavioral fluctuations. These methods often require some degree of manual intervention, such as for identifying key points (head and tail) and performing additional noise reduction steps (5, 10).

An alternative automated strategy computes the covariance matrix of video frames, inferring locomotor frequency by measuring the time intervals between frames that exhibit statistical similarity (15). This method is capable of automatically measuring worm locomotor

frequency without using morphometry. However, this direct covariance between video

frames is degraded by translation or rotation of the animal over time.

Here, we introduce a method we call Imaginera (Image Invariant Ensemble for

Rhythmicity Analysis), which uses an image invariant ensemble to conduct rhythmicity

analysis in freely behaving *C. elegans*. Our method extracts several affine-invariant image

features from video frames and computes the autocorrelation of the time sequence of the

invariant ensemble to infer frequency. We evaluated the robustness and speed of our

method by testing its performance in analyzing videos of moving animals under varied

spatiotemporal resolutions and comparing outcomes to those of alternative methods. We

applied our method to a multi-array experimental setup to analyze the locomotion of

hundreds of wild-type and mutant individuals under controlled environmental conditions,

demonstrating Imaginera as a reliable, high throughput method for measurement of *C.*

elegans locomotor frequency.

RESULTS

Implementation and performance of automated frequency tracking

Our analysis consists of three modules, each carrying out a sequence of image analysis

operations on each video frame. The first module provides an initial background reduction of

a video frame by subtracting the video background derived from the first principal

component of the original video (15) (Fig. 1A).

The subsequent module calculates a set of 8 Hu's moment invariants from each

background-subtracted frame (16) (Fig. 1B; see *Methods*). Each Hu's moment invariant

constitutes a specific weighted average (moment) of image pixel intensities or their positive-

integer powers. These moments are invariant with respect to image translation, scale, and

rotation (16).

The third module, termed the MSER (Maximally Stable Extremal Regions) detector,

extracts a series of co-variant regions from an image, which are a sequence of stable

connected components from certain gray-level sets of the image (17) (see *Methods*). This

operation is executed by first sorting all pixels by gray value, then adding pixels

incrementally to each connected component as the gray value threshold decreases (Fig. 1C;

method valid for dark-field images). While monitoring the pixel area, regions that display

minimal variation with respect to the threshold are designated Maximally Stable Extremal

Regions, or MSERs. Elliptical frames are then marked by fitting minimal circumscribed

ellipses to the regions, whence orientation angles (Ψ) are computed as feature invariants

(Figs. 1 C and D; see *Methods*).

Lastly, the software standardizes the time sequences of the invariants extracted from the

previous modules using z-score normalization (Fig. 1F) and computes the autocorrelation of

the invariant ensemble (Fig. 1G; see *Methods*). Displayed within the autocorrelation curve is

an alternating series of peaks ($\mathcal{P}_M$) and troughs ($\mathcal{T}_N$) reflecting periodicity of the object in the

video (Fig. 1G). The frequency value is computed as the reciprocal of the mean of all

intervals between consecutive peaks and troughs within the autocorrelation (Fig. 1G; see

Methods).

To validate the accuracy of Imaginera in quantifying animals' moving frequency, we

acquired a testing dataset consisting of 153 videos of individual freely swimming worms,

each at least 10 s in duration, recorded at 30 frames per second (fps) and a 6.7-μm pixel

resolution (see *Methods*). We compared automated frequency measurements from

Imaginera with ground-truth results from manual scoring within these videos and found an R-

squared value of 0.93 (Fig. 1H). These results show that our system provides an accurate

estimate of *C. elegans* locomotor frequency.

Figure 1. Implementation and performance of Imaginera. (A) Video images undergo background subtraction.

(B) Calculation of Hu's moment invariants from a background-removed video image. Hu's moment invariants,

$H = (h_1, h_2, ..., h_8)$, are a series of 8 image moments derived from the normalized central image moments of

order from 0 to 3. (C) The MSER detector incrementally thresholds a background-removed video image through

the intensity range of the image to determine MSER regions. Each MSER region can be represented by an

ellipse with identified orientation angle (ψ). (D) Orientation angles (Ψ) of the detected MSER regions. (E)

Invariants from Hu's moments and MSER regions are extracted from a sequence of video frames (representative

frames shown on *Top*). Curves are representative examples of Hu's moments 1-4 (*Panel 1*), Hu's moments 5-8

(*Panel 2*), and orientation angles (*Panel 3*) of 4 MSER regions. (F) Invariants over time are combined to form the

invariant ensemble matrix ($F(t)$). Colored rectangles indicate behavioral patterns. Constrained movement was

observed from a worm confined by a microfluidic channel (5). (G) Autocorrelation of the invariant ensemble.

$\mathcal{P}_1, \mathcal{P}_2, ..., \mathcal{P}_M$ denote local maxima and $\mathcal{T}_1, \mathcal{T}_2, ..., \mathcal{T}_N$ denote local minima. (H) Comparison between the

frequencies calculated by the automated method vs. manual observation of recorded videos.

Performance under spatial or temporal downsampling

The spatial and temporal resolution of behavioral recordings can be limited by several

factors including equipment constraints, data storage constraints, field of view, number of

animals being imaged, and computational time. We investigated the extent to which the

software could estimate frequency with imaging at lower spatial and/or temporal resolution.

We downsampled our testing dataset in time and space to emulate image sequences with

lower frame rates or lower pixel resolution (Figs. 2 A and B).

We first investigated the effect of changing temporal resolution while keeping spatial

resolution fixed. We found that accuracy exhibited a mild decline as the temporal resolution

decreased within a range in which the acquisition frequency (f_s) was at least triple the

animals' average locomotor frequency ($f_0 \approx 1.7\ Hz$ and $f_s/f_0 \geq 2.94$) (Fig. 2A). The accuracy

markedly plummeted when temporal resolution was around or below the Nyquist-limit critical

point, twice the average locomotor frequency of the animal ($f_0 \approx 1.7\ Hz$) (Fig. 2A).

Next, we asked how well the algorithm worked with lowered spatial resolution (Fig. 2A),

keeping temporal resolution constant. The accuracy of frequency measurements remained

stable as the spatial resolution reduced from 60 to 6 pixels per worm length ($L \approx 1\ mm$) (Fig.

2B). The accuracy dropped markedly when the spatial resolution decreased to 4 pixels per

worm length.

We used Imaginera to analyze the testing dataset under different combinations of

temporal and spatial resolutions. The algorithm showed excellent agreement with ground

truth data (R^2 = 0.93) when analyzing videos with a 30-fps temporal resolution ($f_s/f_0 = $

17.65) and a 6.7-µm spatial resolution (60 pixels per worm length) (Fig. 2C). The

performance remained passable under relatively poor recording conditions where temporal

resolution was 5 fps ($f_s/f_0 = 2.94$) and spatial resolution was 20 µm (20 pixels per worm

length) or even 67 µm (6 pixels per worm length), yielding R-squared values of 0.84 and

0.76, respectively.

Figure 2. Robustness analysis of Imaginera. (A) Accuracy of the Imaginera method in measuring frequency

under various recording conditions, emulated by computationally downsampling the spatiotemporal resolutions of

the original videos. R^2 shown as a function of the ratio of the video acquisition frequency (f_s) and average

locomotor frequency ($f_0 \approx 1.7 \, Hz$). Line colors indicate different spatial resolutions denoted by the number of

pixels to resolve an average worm length L. The gray dashed line indicates the Nyquist limit for the average

frequency. (B) Worm images under different spatial resolutions. (C-E) Comparison between results of the

Imaginera method and manual observation for measuring locomotor frequency under indicated spatiotemporal

resolutions. (F and G) Comparison of the coefficient of determination for frequency estimation between our

method and a method based on worm segmentation, under indicated spatiotemporal resolutions.

Performance comparison with alternative method

We compared the performance of the Imaginera software with that of a widely used

approach based on a segmentation-based algorithm to analyze the worm morphometric

skeleton (10) (see *Methods*).

We used the two methods to analyze the testing dataset across various spatiotemporal

resolutions. When analyzing mildly pixelated videos (20 pixels per worm length), Imaginera

delivered accuracies similar to or slightly better than the segmentation-based method under

varied temporal resolutions (Fig. 2F). When analyzing videos that are more coarsely

pixelated (6 pixels per worm length), our method outperformed the segmentation-based

method (Fig. 2G). These results demonstrate that our method is robust to a wide spectrum

of image recording conditions and suggests it is a better option for analyzing video data with

limited spatial resolution.

To assess computational efficiency, we measured the time each method took to analyze

10,000 video frames (120 x 160 pixel resolution) and found that Imaginera executed

analyses under 40 sec, approximately 3 times faster than the segmentation-based method.

While the implementations of these algorithms have yet to be optimized for speed, these

results suggest that our method is faster than the segmentation-based method.

Automated frequency analysis facilitates large-screen behavioral assays

Having demonstrated the accuracy and robustness of Imaginera under computationally

emulated recording conditions (Fig. 2A), we evaluated its proficiency in practical applications

by applying it to a multi-array imaging setup intended for large-scale phenotypic assays (Ji et

al., *in preparation*).

During data acquisition, we employed a standard 96-well microtiter plate, with individual

animals situated in wells filled with liquid NGM under defined external conditions. The

imaging setup captured details at approximately one-sixtieth the length of an adult *C.*

elegans, with a pixel resolution of 18 μm for a field of view that included all 96 wells (Figs. 3

A and B). In each experiment, up to 96 1-day adult animals were monitored for a duration of

5 hr. Every 2 minutes during this period, a 20-s-long image sequence was captured at 5 fps.

We used Imaginera to analyze the movements of each animal in a well during each 20 s

recording window.

The biogenic amine serotonin is an important neuromodulator that regulates *C. elegans*

behavior in response to changing environmental cues (18). Exogenous serotonin at

sufficiently high concentrations can cause inhibition of locomotion (19, 20). We tracked the

frequency dynamics of wild-type and mutant *C. elegans* individuals in liquids with controlled

serotonin (5-HT) concentrations. The mutant strains under examination included *ser-1*, *ser-*

7, and *ser-1; ser-7* double mutants, each carrying loss-of-function mutations in the G protein-

coupled metabotropic receptors SER-1 and/or SER-7.

We computed each animal's level of behavioral quiescence by calculating the fraction of

time the frequency equaled zero (Figs. 3 E and F). Generally, both wild-type and mutant

animals exhibited normal locomotor frequency and low quiescence under serotonin-free

conditions (Figs. 3 E and F). With the incremental addition of exogenous serotonin, wild-type

animals exhibited a decline in the average locomotor frequency and increased quiescence

(Figs. 3 E and F). Conversely, *ser-1* and *ser-7* mutants exhibited milder serotonin-induced

effects on locomotor frequency and quiescent fraction, while *ser-1; ser-7* double mutants

showed frequency slowing responses or quiescence to an intermediate level of exogenous

serotonin and stronger responses to a high level of serotonin (Figs. 3 E and F). Our

behavioral data align qualitatively with previously reported results for each respective strain

regarding the effects of exogenous serotonin on *C. elegans* locomotion (3, 19, 21–24).

We evaluated the accuracy of our method in this multi-array setup by comparing

automated measurements to manual counts of head bends in 480 video clips (each 6 s long)

of individual wild-type worms across all 96 wells. Our method demonstrated excellent

agreement with results from manual counting (Fig. 3D).

These results show that our method is suitable for measuring frequency in 96 animals

simultaneously.

Figure 3. Automated frequency analysis facilitates large-screen behavioral assays. (A) Worms in a 96-well

assay plate under dark field illumination (FOV 108 mm x 73 mm). (B) Individual wells are cropped and

background-subtracted before analysis (FOV 6 mm x 6 mm). (C) Locomotor frequency dynamics of two individual

animals calculated from a 5 h video sequence by the Imaginera method. (D) Locomotor frequency values

evaluated by human observation (ground truth) compared with those from automated frequency assessment. (E)

Locomotor frequency of wild-type and mutant individuals. (F) Quiescent fraction of wild-type and mutant

individuals. In E and F, each point represents an animal, point colors indicate groups in the respective serotonin

conditions, black bars represent population mean ± SEM.

DISCUSSION

The Imaginera software provides a measurement of frequency in the locomotion of *C.*

elegans, incorporating both non-morphometric invariants drawn from image profiles via Hu's

moments and morphometric invariants derived from object conformations via MSER regions.

Our method thus complements other behavioral output metrics utilized in large-scale

phenotypic assays, such as pixel differences between successive frames (2, 25).

In this study, we applied Imaginera for analyzing *C. elegans* locomotion; however, its

utility may go beyond this specific application, adapting to broader image analysis contexts

that require quantifications of periodic behaviors or phenomena. This potentially includes

locomotor dynamics in other animals, as well as breathing, cardiac rhythms, neuronal

calcium activity, microbial oscillations, fluid dynamics, and collective organismal behaviors.

We anticipate that our method will aid in identifying subtle behavioral phenotypes and

facilitating studies of periodic dynamics.

METHODS

***C. elegans* strains and maintenance**

C. elegans strains were cultivated on *Escherichia coli* strain OP50 at 20 °C following

standard methods (26). The strains used in this study include wild-type strain (Bristol N2),

egl-1(n487), *ser-1(ok345)*, *ser-7(tm1325)*, and *ser-7(tm1325); ser-1(ok345)* mutant strains,

all obtained from the NIH *Caenorhabditis* Genetics Center. All experiments were conducted

with 1-day-old adult worms. To synchronize worm populations, we used a timed egg lay

approach (27).

Behavioral data acquisition

To capture the locomotion of freely moving worms, we placed animals in NGM buffer within

a chamber formed by a glass slide and a coverslip, separated by 125-µm-thick polyester

shims (McMaster-Carr 9513K42). This NGM buffer mirrors the composition of solid NGM,

excluding agar, peptone, and cholesterol (28). The NGM buffer was supplemented with

0.1% (by weight) bovine serum albumin (BSA) to deter worms from sticking to chamber

walls.

Behavioral footage of each worm within the field of view was recorded for approximately

1 min using a 5-megapixel CMOS camera (DMK33GP031, The Imaging Source, Inc.) paired

with a C-mount lens (Nippon Kogaku NIKKOR-H; effective focal length 28 mm). Video

sequences, captured at 30 fps with a 6.7-µm pixel resolution, were acquired using IC

Capture software (The Imaging Source) under dark-field illumination provided by a red LED

ring (outer diameter 80 mm; Qasim).

Multi-well plate assays

For multi-worm imaging, we picked a single worm into each well of a standard 96-well

microtiter assay plate (Corning 3795, round bottom), containing 60 µL of NGM buffer or

NGM buffer containing serotonin.

The assay plate was positioned on a stage inside a custom-built imaging apparatus.

Dark-field lighting was provided by an LED light ring (outer diameter 12 inches; Sunpak)

above the platform. Videos were recorded with a CMOS camera (DMK 33UX183, 20

megapixels, The Imaging Source) coupled with a C-mount lens (HF12.5SA-1, Fujinon),

recording at 5 fps for a duration of 20 s using the IC Capture software (The Imaging Source).

The behavioral assay involved obtaining a sequence of these 20 s videos, taken every 2

minutes until a cumulative recording time of 5 h was reached. The system's field of view was

calibrated to encompass all 96 wells on the plate, yielding a pixel resolution of 18 µm.

Mathematical formulae of Hu's moment invariants

The Hu's image invariants (16) with respect to translation, scale, and rotation are defined as:

261
$$h_1 = \eta_{20} + \eta_{02}$$

262
$$h_2 = (\eta_{20} - \eta_{02})^2 + 4\eta_{11}^2$$

263
$$h_3 = (\eta_{30} - 3\eta_{12})^2 + (3\eta_{21} - \eta_{03})^2$$

264
$$h_4 = (\eta_{30} + \eta_{12})^2 + (\eta_{21} + \eta_{03})^2$$

265
$$h_5 = (\eta_{30} - 3\eta_{12})(\eta_{30} + \eta_{12})((\eta_{30} + \eta_{12})^2 - 3(\eta_{21} + \eta_{03})^2) + (3\eta_{21} - \eta_{03})(\eta_{21}$$

266
$$+ \eta_{03})(3(\eta_{30} + \eta_{12})^2 - (\eta_{21} + \eta_{03})^2)$$

267
$$h_6 = (\eta_{20} - \eta_{02})((\eta_{30} + \eta_{12})^2 - (\eta_{21} + \eta_{03})^2) + 4\eta_{11}(\eta_{30} + \eta_{12})(\eta_{21} + \eta_{03})$$

$$h_7 = (3\eta_{21} - \eta_{03})(\eta_{30} + \eta_{12})((\eta_{30} + \eta_{12})^2 - 3(\eta_{21} + \eta_{03})^2) - (\eta_{30} - 3\eta_{12})(\eta_{21}$$

$$+ \eta_{03})(3(\eta_{30} + \eta_{12})^2 - (\eta_{21} + \eta_{03})^2)$$

$$h_8 = \mu_{11}((\eta_{30} + \eta_{12})^2 - (\eta_{03} + \eta_{21})^2) - (\eta_{20} - \eta_{02})(\eta_{30} + \eta_{12})(\eta_{03} + \eta_{21}),$$ [1]

where $\eta_{pq} = \mu_{pq}/\mu_{00}^{1+\frac{p+q}{2}}$ is the scaled central moment of order $(p + q)$ and $\mu_{pq} =$

$\sum_x \sum_y (x - x_c)^p (y - y_c)^q f(x, y)$ is the central moment of image intensity $f(x, y)$ with the

image centroid defined as $\{x_c, y_c\} = \{\frac{\Sigma_{x,y} x f(x,y)}{\Sigma_{x,y} f(x,y)}, \frac{\Sigma_{x,y} y f(x,y)}{\Sigma_{x,y} f(x,y)}\}$.

Out of the 8 Hu's moments, h_1 through h_6 are reflection-symmetric, meaning they remain

unchanged with respect to image reflection, whereas h_7 and h_8 are reflection-antisymmetric,

in that they invert their signs when the image is reflected.

Extraction of MSER regions and features

The Maximally Stable Extremal Regions (MSER) are characterized by connected pixel

components that depicted areas with a consistent intensity over a range of pixel values in

the image (17). We constructed the minimal circumscribed ellipses that enclosed these

regions, with the largest ellipse covering the entire worm and the smallest one covering the

worm's brightest segment. For each video frame, we calculated the orientations of the

ellipses, resulting in a sequence of orientation values (termed feature invariants).

Given that the MSER method operates based on image intensity levels, the count of

extracted ellipses may vary between frames due to variations in pixel intensity. To ensure

uniformity in the number of feature invariants (N by default) across all frames, we computed

N orientation values represented as $\boldsymbol{\Psi} = (\psi_1, \psi_2, \ldots, \psi_N)$ in radians for every frame, using

bilinear interpolation and extrapolation methods with respect to N evenly spaced query

values of connected component areas (in pixels) defined between predefined maximum and

minimum values. To achieve rotational invariance in orientation values, the $\boldsymbol{\Psi}$ vector was

recentered by deducting its circular mean, $\overline{\Psi} = arg\left(\sum_{n=1}^{N} exp\left(i \cdot \psi_n\right)\right)$, leading to the

adjusted value $\widetilde{\boldsymbol{\Psi}} = \boldsymbol{\Psi} - \overline{\Psi}$.

Ensemble feature invariants for determining locomotor frequency

We define an ensemble vector combining the 8 Hu's Moment invariants ($\boldsymbol{H}$) with the N

MSER-derived invariants ($\widetilde{\boldsymbol{\Psi}}$), forming a vector with $P = 8 + N$ elements:

$$\boldsymbol{F} = \left(\boldsymbol{H}, \widetilde{\boldsymbol{\Psi}}\right) = [f_1, f_2, \ldots, f_P].$$ [2]

Next, we create an invariant ensemble matrix $\boldsymbol{F}(t)$ that includes the time dependence of

the vector sequence:

$$\boldsymbol{F}(t) \coloneqq [f_1(t), f_2(t), \ldots, f_P(t)].$$ [3]

Each component variable $f_i(t)$ was measured on different scales and with widely

different ranges in magnitude. We thus standardized them via z-score normalization:

$$\tilde{f}_i(t) = \frac{f_i(t) - \frac{\Sigma_\tau f_i(\tau)}{T}}{\sqrt{\frac{\Sigma_\tau f_i^2(\tau)}{T} - \left(\frac{\Sigma_\tau f_i(\tau)}{T}\right)^2}},$$ [4]

where T denotes the number of video frames.

Following the standardization of the invariant ensemble time sequence, we computed its

autocorrelation $\widehat{\boldsymbol{R}}(\tau)$, defined by:

$$\widehat{\boldsymbol{R}}(\tau) = \frac{1}{T-\tau} \sum_{t=1}^{T-\tau} \frac{\widetilde{\boldsymbol{F}}(t) \cdot \widetilde{\boldsymbol{F}}(t+\tau)}{\|\widetilde{\boldsymbol{F}}(t)\|\|\widetilde{\boldsymbol{F}}(t+\tau)\|},$$ [5]

where $\widetilde{\boldsymbol{F}}(t) \cdot \widetilde{\boldsymbol{F}}(t+\tau) = \sum_{i=1}^{P} \tilde{f}_i(t)\tilde{f}_i(t+\tau)$ and $\|\widetilde{\boldsymbol{F}}(t)\| = \sqrt{\sum_{i=1}^{P} \tilde{f}_i^2(t)}$.

We used the following peak-finding method to determine the locomotor period: 1. In

$\widehat{\boldsymbol{R}}(\tau)$, identify local maxima (peaks), $\{\mathcal{P}_1, \mathcal{P}_2, \ldots\}$, and local minima (troughs), $\{\mathcal{T}_1, \mathcal{T}_2, \ldots\}$,

excluding the peak at zero. 2. Compute all the identified local extrema's topographic

prominence, a measure of how much the peak or trough stands out relative to other peaks

or troughs (29). 3. From the peak list, generate a sub-list, $\{\mathcal{P}_1, \mathcal{P}_2, \ldots, \mathcal{P}_k\}$, by first choosing

the initial element $\mathcal{P}_1$ and then iteratively picking the successive element until the query

element's prominence is smaller than 0.25 (this element is not included). If the initial element

$\mathcal{P}_1$ has a prominence less than 0.25, then the sub-list is defined as empty. 4. For the

troughs, the corresponding sub-list, $\{\mathcal{T}_1, \mathcal{T}_2, \ldots, \mathcal{T}_l\}$, is generated by using the same rule as

step 3. 5. The worm's locomotor frequency in the targeted video is computed as the

reciprocal of the mean of all consecutive extrema intervals within the identified sub-lists of

peaks and troughs:

320
$$f_{worm} = \frac{k + l - 1/2}{\tau(\mathcal{P}_k) + \tau(\mathcal{T}_l)},\qquad\qquad [6]$$

where $\tau(\cdot)$ denotes the time value of lag. If both the peak and trough sub-list are empty, then

the worm's locomotion is regarded as non-periodic, and the frequency is set to 0.

Segmentation-based approach for frequency analysis

In order to compare with our method, we used image thresholding and segmentation to

extract the morphometric skeleton of worm images from videos (10, 12, 30). For each video

frame, we filtered and thresholded the image to give a binary image that identifies the

boundary of the worm. The head and tail of the worm were identified as the points of local

maximal convex curvature of the worm boundary. A worm centerline extending from the

head to the tail was calculated as points equidistant to the two sides of the worm boundary

(7). and identified the worm's boundary and centerline from the binary image. Next, we

smoothed the worm's centerline using a cubic spline fit and computed the curvature of the

body centerline as the dot product between the unit normal vector to the centerline and the

derivative of the unit tangent vector to the centerline with respect to the body coordinate.

To infer the animal's movement frequency from the curvature dynamics, we defined

anterior curvature as the average of the whole-body curvature across body coordinates 0.1-

0.3 (fractional distance from the head). This specific range was chosen to exclude the high-

frequency movements of the animal's anterior tip (12). Lastly, we determined the local

extrema from the anterior curvature and the frequency during the examined video period

was defined as the product of the acquisition frequency and the reciprocal of the mean of all

peak intervals in the anterior curvature.

ACKNOWLEDGMENTS. We thank Niels Ringstad, Yen-Chih Chen, and Zihao (John) Li for

providing reagents and helpful discussions. Some strains were provided by the *C. elegans*

Genetics Center, funded by the NIH Office of Research Infrastructure Programs (P40

OD010440). This work was supported by the National Institutes of Health (R01DA056358).

345
REFERENCES

1.   A. Biewener, S. Patek, *Animal locomotion* (Oxford University Press, 2018).

2.   D. M. Raizen, *et al.*, Lethargus is a Caenorhabditis elegans sleep-like state. *Nature*
451, 569–572 (2008).

3.   S. Stern, C. Kirst, C. I. Bargmann, Neuromodulatory control of long-term behavioral
patterns and individuality across development. *Cell* **171**, 1649–1662 (2017).

4.   E. Yemini, T. Jucikas, L. J. Grundy, A. E. Brown, W. R. Schafer, A database of
Caenorhabditis elegans behavioral phenotypes. *Nature methods* **10**, 877–879 (2013).

5.   H. Ji, A. D. Fouad, Z. Li, A. Ruba, C. Fang-Yen, A proprioceptive feedback circuit
drives Caenorhabditis elegans locomotor adaptation through dopamine signaling.
Proceedings of the National Academy of Sciences **120**, e2219341120 (2023).

6.   G. Haspel, *et al.*, Resilience of neural networks for locomotion. *The Journal of*
Physiology **599**, 3825–3840 (2021).

7.   C. Fang-Yen, *et al.*, Biomechanical analysis of gait adaptation in the nematode
Caenorhabditis elegans. *Proceedings of the National Academy of Sciences* **107**,
20323–20328 (2010).

8.   S. Brenner, The genetics of Caenorhabditis elegans. *Genetics* **77**, 71–94 (1974).

9.   A. Hart, Behavior. *WormBook* (2006) https:/doi.org/10.1895/wormbook.1.87.1
(December 5, 2023).

10. A. M. Leifer, C. Fang-Yen, M. Gershow, M. J. Alkema, A. D. Samuel, Optogenetic
manipulation of neural activity in freely moving Caenorhabditis elegans. *Nature*
methods **8**, 147–152 (2011).

11. L. Luo, *et al.*, Bidirectional thermotaxis in Caenorhabditis elegans is mediated by
distinct sensorimotor strategies driven by the AFD thermosensory neurons.
Proceedings of the National Academy of Sciences **111**, 2776–2781 (2014).

12. H. Ji, *et al.*, Phase response analyses support a relaxation oscillator model of
locomotor rhythm generation in Caenorhabditis elegans. *Elife* **10**, e69905 (2021).

13.   Q. Wen, *et al.*, Proprioceptive coupling within motor neurons drives C. elegans forward
locomotion. *Neuron* **76**, 750–761 (2012).

14.   N. Cermak, *et al.*, Whole-organism behavioral profiling reveals a role for dopamine in
state-dependent motor program coupling in C. elegans. *Elife* **9**, e57093 (2020).

15.   S. D. Buckingham, D. B. Sattelle, Fast, automated measurement of nematode
swimming (thrashing) without morphometry. *BMC neuroscience* **10**, 1–6 (2009).

16.   M.-K. Hu, Visual pattern recognition by moment invariants. *IRE Transactions on
Information Theory* **8**, 179–187 (1962).

17.   J. Matas, O. Chum, M. Urban, T. Pajdla, Robust wide-baseline stereo from maximally
stable extremal regions. *Image and Vision Computing* **22**, 761–767 (2004).

18.   D. Chase, Biogenic amine neurotransmitters in C. elegans. *WormBook* (2007)
https:/doi.org/10.1895/wormbook.1.132.1 (December 6, 2023).

19.   H. R. Horvitz, M. Chalfie, C. Trent, J. E. Sulston, P. D. Evans, Serotonin and
octopamine in the nematode Caenorhabditis elegans. *Science* **216**, 1012–1014 (1982).

20.   R. J. McCloskey, A. D. Fouad, M. A. Churgin, C. Fang-Yen, Food responsiveness
regulates episodic behavioral states in Caenorhabditis elegans. *Journal of
Neurophysiology* **117**, 1911–1934 (2017).

21.   Y.-C. Chen, M. R. Seyedsayamdost, N. Ringstad, A microbial metabolite synergizes
with endogenous serotonin to trigger C. elegans reproductive behavior. *Proc Natl Acad
Sci U S A* **117**, 30589–30598 (2020).

22.   L. A. Hardaker, E. Singer, R. Kerr, G. Zhou, W. R. Schafer, Serotonin modulates
locomotory behavior and coordinates egg-laying and movement inCaenorhabditis
elegans. *J. Neurobiol.* **49**, 303–313 (2001).

23.   M. A. Churgin, R. J. McCloskey, E. Peters, C. Fang-Yen, Antagonistic serotonergic and
octopaminergic neural circuits mediate food-dependent locomotory behavior in
Caenorhabditis elegans. *Journal of Neuroscience* **37**, 7811–7823 (2017).

24.   R. J. Hobson, *et al.*, SER-7, a Caenorhabditis elegans 5-HT7-like receptor, is essential
for the 5-HT stimulation of pharyngeal pumping and egg laying. *Genetics* **172**, 159–169
(2006).

25.   M. A. Churgin, *et al.*, Longitudinal imaging of Caenorhabditis elegans in a
microfabricated device reveals variation in behavioral decline during aging. *Elife* **6**,
e26652 (2017).

26.   M. Chalfie, J. White, W. B. Wood, *The nematode Caenorhabditis elegans* (New York:
Cold Spring Harbor Laboratory Press, 1988).

27.   S. Gandhi, J. Santelli, D. H. Mitchell, J. W. Stiles, D. R. Sanadi, A simple method for
maintaining large, aging populations of Caenorhabditis elegans. *Mechanisms of ageing
and development* **12**, 137–150 (1980).

28.   T. Stiernagle, *Maintenance of C. elegans (February 11, 2006), WormBook, ed. The C.
elegans Research Community, WormBook, doi/10.1895/wormbook. 1.101. 1* (2006).

29.   Prominence - MATLAB & Simulink.
413   *https://www.mathworks.com/help/signal/ug/prominence.html* (November 25, 2023).

414   30.   A. D. Fouad, *et al.*, Distributed rhythm generators underlie Caenorhabditis elegans
415   forward locomotion. *Elife* **7**, e29913 (2018).

416