Disentangling signal and noise in neural responses through generative modeling

Kendrick Kay*[1], Jacob S. Prince[2], Thomas Gebhart[3], Greta Tuckute[4,5],
Jingyang Zhou[6], Thomas Naselaris[1,7], Heiko Schutt[8]

[1]Center for Magnetic Resonance Research (CMRR), Department of Radiology, University of Minnesota
[2]Department of Psychology, Harvard University
[3]Department of Computer Science, University of Minnesota
[4]Department of Brain and Cognitive Sciences, Massachusetts Institute of Technology
[5]McGovern Institute for Brain Research, Massachusetts Institute of Technology
[6]Center for Computational Neuroscience (CCN), Flatiron Institute
[7]Department of Neuroscience, University of Minnesota
[8]Department of Behavioural and Cognitive Sciences, Université du Luxembourg
*Corresponding author (kay@umn.edu)

Abstract

Measurements of neural responses to identically repeated experimental events often exhibit large amounts of variability. This *noise* is distinct from *signal*, operationally defined as the average expected response across repeated trials for each given event. Accurately distinguishing signal from noise is important, as each is a target that is worthy of study (many believe noise reflects important aspects of brain function) and it is important not to confuse one for the other. Here, we introduce a principled modeling approach in which response measurements are explicitly modeled as the sum of samples from multivariate signal and noise distributions. In our proposed method—termed Generative Modeling of Signal and Noise (GSN)—the signal distribution is estimated by subtracting the estimated noise distribution from the estimated data distribution. We validate GSN using ground-truth simulations and demonstrate the application of GSN to empirical fMRI data. In doing so, we illustrate a simple consequence of GSN: by disentangling signal and noise components in neural responses, GSN denoises principal components analysis and improves estimates of dimensionality. We end by discussing other situations that may benefit from GSN's characterization of signal and noise, such as estimation of noise ceilings for computational models of neural activity. A code toolbox for GSN is provided with both MATLAB and Python implementations.

Introduction

Nominally identical sensory, cognitive, and/or motor events often result in highly variable neural activity measurements (Goris et al., 2014; Ito et al., 2020; Rabinowitz et al., 2015; Tolhurst et al., 1981). Such variability is termed *noise*, and manifests in all techniques for measuring brain activity, including electrophysiology, optical imaging, electroencephalography, magnetoencephalography, and functional magnetic resonance imaging (fMRI). Noise may originate from multiple sources. Noise can arise for instrumental reasons (e.g., electrical noise, head motion) or physiological reasons (e.g., cardiac noise), but can also reflect genuine variability in neural activity. Another important aspect of noise is its complex multivariate nature: variability in activity is not independent across units (e.g., neurons, voxels, channels) but typically exhibits structured correlations (Biswal et al., 1995; Cohen and Kohn, 2011; Hazon et al., 2022; Kanitscheider et al., 2015; Mell et al., 2021; Moreno-Bote et al., 2014). To mitigate the effects of noise, neuroscientists usually average neural responses across repeated trials associated with the same event. The underlying premise is that the object of interest, the *signal*, is not the neural response observed on any single trial but the average expected neural response across a large (infinite) number of trials.

Many research programs in systems, cognitive, and computational neuroscience focus on studying signal. For example, one might seek to characterize the tuning of sensory neurons by averaging responses across several trials measured for each stimulus condition. But there are also scientific motivations for characterizing and understanding noise, which may play an important role in neural computation (Panzeri et al., 2022; Ringach, 2009; Uddin, 2020). One example approach, originating in computational neuroscience, investigates the correlational structure of noise in the responses of individual neurons and explores how these noise correlations affect the information capacity of a neural population code (Averbeck et al., 2006; Azeredo da Silveira and Rieke, 2021; Cafaro and Rieke, 2010; Zylberberg et al., 2016). Another approach, commonly referred to as resting-state functional connectivity, leverages spontaneous activity fluctuations to parcellate brain areas and networks (Eickhoff et al., 2018) and to develop biomarkers for individuals (Gratton et al., 2020) or populations (Zhang et al., 2021). Perhaps the deepest potential interpretation of noise is that it reflects critical latent cognitive processes that are not directly controlled by the experimental paradigm. One example of this view is the theory that noise reflects statistical priors and/or probabilistic neural computations (Ma et al., 2006; Orbán et al., 2016; van Bergen et al., 2015).

Given that both signal and noise are of potential interest, a challenge faced by neuroscientists is that signal and noise are entangled in neural activity measurements, and it is not immediately obvious how to separate the two components. The standard approach is to average responses across trials and assume that the result adequately isolates signal from noise. However, while simple and straightforward, the approach of trial averaging does not necessarily produce perfectly accurate signal measures, a point that has been previously recognized (Pospisil and Bair, 2021a; Pospisil and Pillow, 2024; Stringer et al., 2019). To illustrate, we perform a simple simulation in which two units exhibit positive noise correlation but no signal correlation (**Figure 1**). When the number of trials per condition is large, trial averaging indeed suppresses the noise, but noise correlation is still observed in the trial-averaged results (panel A). When the number of trials per condition is small, noise correlation in the trial-averaged results is even more substantial (panel B). Finally, to further accentuate the point, we simulate a situation where there is no signal at all (panel C): this case clearly shows how noise structure seeps into the trial-averaged results. The residual influence of noise on trial-averaged results is a problem as it may lead to inaccurate estimates of signal correlation (Pospisil and Bair, 2021a), and inaccurate interpretations of commonly performed multivariate analyses, such as principal components analysis, representational similarity analysis, and analysis of neural dimensionality. In short, what is thought to be due to signal might actually be due to noise. Indeed, there

81 has been recent interest in methods for identifying and isolating signal and noise components in high-
82 dimensional neural data (Pospisil and Pillow, 2024; Stringer et al., 2019; Williams and Linderman, 2021).
83

Figure 1. Trial averaging is insufficient for removing the effects of noise. Here we perform simulations to illustrate how noise correlations persist after trial averaging (code available at https://osf.io/7shc4). *A*, In this simulation, responses to 9 conditions are measured from 2 units. The left shows the signal, i.e. responses in the absence of noise. The middle shows the noise, i.e. trial-to-trial response variability for a fixed condition; the noise is drawn from a zero-mean multivariate Gaussian distribution (ellipse indicates a Mahalanobis distance of 2). The right shows responses averaged across 40 trials for each condition (black lines join the trial average to the corresponding signal). *B*, Same as panel A except that 4 trials per condition are used. *C*, Same as panel B except that the signals associated with the 9 conditions are all set to zero.

In this paper, we propose an analysis technique for disentangling signal and noise covariance in neural
response measurements. Our approach, termed generative modeling of signal and noise (GSN), builds and
fits a model of the signal and noise components of measured multivariate neural responses. The model is

generative in the sense that the process by which measurements are generated is explicitly modeled. First,
we lay out the principles underlying GSN and validate GSN through a series of simulations with a known
ground truth. Next, we demonstrate the application of GSN to visually evoked functional magnetic
resonance imaging (fMRI) responses in the publicly available Natural Scenes Dataset (Allen et al., 2022).
This provides intuition for how GSN fares on empirical brain data and highlight ways in which GSN can be
leveraged within computational neuroscience. Finally, we use the example data to illustrate how GSN can
be used to improve the results of principal components analysis. Specifically, by disentangling signal and
noise, GSN provides a cleaner estimate of the signal in the data and its properties (eigenspectra and
dimensionality). Code used in this paper is available at https://osf.io/wkyxn/, and a code toolbox
implementing GSN is available at https://github.com/cvnlab/GSN/.
108

Results

Generative signal and noise modeling approach

Consider the general situation where responses are measured from a set of units (e.g., voxels, neurons, channels) to several experimental conditions (e.g. stimuli) and several trials are collected for each condition. The core idea of the generative signal and noise (GSN) approach is to model each response as reflecting the sum of a sample drawn from a multivariate distribution associated with signal (defined as the response to different conditions in the absence of noise) and a sample drawn from a multivariate distribution associated with noise (defined as trial-to-trial response variability for a fixed condition). We assume the noise distribution is zero-mean and assume the noise is independent of the signal. We allow the signal and noise distributions to have potentially different means and covariances.

A schematic illustrating GSN is shown in **Figure 2**. This schematic depicts a situation in which responses are measured from two units to 40 conditions with three trials per condition. Panel A shows the ground-truth signal distribution. Red dots are samples from the distribution and indicate noiseless responses to the 40 conditions. One of the dots is highlighted in blue, marking an example condition. Panel B shows the ground-truth noise distribution. Blue x's indicate three samples from the distribution; these are noise samples associated with the example condition. Panel C shows the data distribution, whose mean and covariance are equal to the sum of the means of the signal and noise distributions and the sum of the covariances of the signal and noise distributions, respectively. The red x's indicate the measured responses (obtained as the sum of signal and noise), with the blue x's highlighting the responses associated with the example condition. Overall, panels A–C illustrate how signal and noise distributions give rise to observed measurements.

The core challenge in GSN is estimating the unknown signal and noise distributions given a set of measurements. The basic procedure that we propose is illustrated in panels D–F. Responses are averaged across trials and the mean and covariance of the trial-averaged responses are computed, as shown in panel D (red diamonds indicate trial-averaged responses; the blue diamond corresponds to the example condition). This procedure yields the estimate of the data distribution. After subtracting the mean response from the original non-trial-averaged responses to each condition, the covariance of the residuals is computed and then averaged across conditions, as shown in panel E (red x's indicate the residuals; blue x's indicate the residuals associated with the example condition). This yields the estimate of the noise distribution. Finally, the parameters associated with the noise distribution are subtracted from the parameters associated with the data distribution, as shown in panel F. This is the key step that corrects for the noise that persists after trial averaging (see **Figure 1**), and yields the estimate of the signal distribution. (Note that in order to ensure positive semi-definite covariance estimates, the full procedure is slightly more complicated than what is presented here; please see Methods for details.)

Figure 2. Schematic of GSN. Here we depict an example involving n = 2 units, c = 40 conditions, and t = 3 trials per condition (code available at https://osf.io/46zxk). In each plot, the black cross and black ellipse indicate the mean and spread (Mahalanobis distance of 2) of a multivariate Gaussian distribution. For definitions of symbols, please see Methods. *A*, Signal. The signal indicates responses to different conditions in the absence of noise and is modeled as a multivariate distribution. *B*, Noise. The noise indicates trial-to-trial variability for a given condition and is modeled as a zero-mean multivariate distribution. *C*, Data. The data are modeled as the sum of a sample from the signal distribution and a sample from the noise distribution. *D*, Estimate of data distribution. Given a set of measured responses, we compute trial-averaged responses and estimate the mean and covariance of these responses, yielding the estimate of the data distribution. *E*, Estimate of noise distribution. We compute the covariance of responses to each condition and average across conditions, yielding the estimate of the noise distribution. *F*, Estimate of signal distribution. We subtract the estimated parameters of the noise distribution from the estimated parameters of the data distribution, yielding the estimate of the signal distribution.

Validation of GSN through ground-truth simulations

GSN attempts to determine the signal and noise distributions that underlie a set of measured responses. To validate GSN, we performed a series of ground-truth simulations involving 10 units whose ground-truth signal and noise distributions have specific structure (**Figure 3**). For the signal distribution, each unit was set to have a variance of 1, and units 1 through 5 were given positive correlation (r = 0.5; covariance = 0.5). For the noise distribution, each unit was set to have a variance of 2, and units 4 through 8 were given positive correlation (r = 0.5; covariance = 1).

Figure 3. Estimation of signal and noise distributions. Here we show results of simulations that assess how well GSN estimates the signal and noise distributions that underlie a set of measurements (code available at https://osf.io/qc5d7). All simulations involve 10 units whose responses are generated as the sum of a sample from a signal distribution and a sample from a noise distribution. Both distributions are multivariate Gaussian with zero mean but have different covariances (as depicted). For different combinations of number of conditions (samples from the signal distribution) and number of trials (samples from the noise distribution for each condition), we perform 1,000 simulations. In each simulation, we generate responses and analyze the resulting data using three different methods: 'Naive' refers to simple heuristic methods for estimating signal and noise covariance (see main text), 'No shrinkage' is the GSN method with standard covariance estimation, and 'Shrinkage' is the GSN method with shrinkage-based covariance estimation. We quantify how well each method recovers ground truth using coefficient of determination (R^2). Blue number labels (1–8) highlight specific aspects of the results that are discussed in the main text. *A–C*, Detailed inspection of results for specific condition and trial numbers. In the scatter plots, purple and brown dots indicate diagonal and off-diagonal elements of the covariance matrix, respectively, and error bars indicate standard deviation across simulations. At the far right are plots of the eigenspectra (mean across simulations) produced by the three methods, as well as the ground-truth eigenspectra. *D*, Overall performance as a function of number of trials (number of conditions fixed at 50). Markers indicate mean across simulations. *E*, Overall performance as a function of number of conditions (number of trials fixed at 5). Same format as panel D.

To gain insight, we plot detailed inspections of the performance of different methods for recovering ground-truth signal and noise distributions (**Figure 3A–C**). First, consider the performance of naive methods for

signal and noise estimation ('Naive'). For signal estimation, the naive method is to simply average
responses across trials and compute the sample covariance of the trial-averaged data. We see that this
method incurs upward bias in the estimated signal covariance values; this can be observed in the qualitative
image plots as the seeping of the noise covariance into the signal estimate (panel C, location 3) and in the
quantitative scatter plots as dots lying above the line of unity (panel C, location 4). The bias is due to the
fact that although trial averaging reduces noise, the trial-averaged data are still influenced by noise (Pospisil
and Pillow, 2024). Thus, it is critical for an estimation procedure to account for this persistent noise. For
noise estimation, the naive method is to simply remove the mean response for each condition, aggregate
the residuals across conditions, and then proceed to covariance estimation. We see that the naive method
for noise estimation incurs downward bias in the estimated noise covariance values; this can be observed
in the image plots (panel A, location 5) and the scatter plots (panel A, location 6). The reason for this bias
is that in aggregating de-meaned responses across conditions, the naive method fails to account for the
reduced degrees of freedom in the de-meaned responses.

We now proceed to the GSN method for signal and noise estimation. One version of GSN is coupled with
standard covariance estimation ('No shrinkage'). This version provides unbiased estimates of covariance
(dots in the scatter plots lie on the line of unity) but these estimates suffer from high variance (error bars
indicating standard deviation across simulations are large). A second version of GSN is coupled with
shrinkage-based covariance estimation ('Shrinkage'). This version provides estimates with reduced
variance (brown dots indicating off-diagonal elements have smaller error bars), though these estimates are
biased (the brown dots lie below the line of unity). Notice that the amount of bias is larger in scenarios with
low amounts of data (e.g., panel A, location 1) than in scenarios with high amounts of data (e.g., panel C,
location 2).

We summarize the overall performance of the different methods by plotting ground-truth recovery of
covariance as a function of number of trials (**Figure 3D**) and number of conditions (**Figure 3E**). We find
that in general, the noise distribution is easier to estimate than the signal distribution. This makes sense
since all samples contribute to estimating the noise distribution, whereas only the mean of the samples
associated with a condition contribute to estimating the signal distribution. We also see that across the
board, the shrinkage method performs better than or as well as the other methods, with larger
improvements in low-data regimes. This is consistent with the idea that although the 'No shrinkage' method
converges to the correct covariance when results are averaged across an large (infinite) number of
simulations (i.e. it is unbiased), in individual simulations the 'Shrinkage' method produces more accurate
results than the 'No shrinkage' method. Finally, we observe that the limiting factor for accurate estimation
appears to be the number of conditions available. If we fix the number of conditions at 50, even if we greatly
increase the number of trials, ground-truth recovery of the signal reaches a plateau that is lower than 100%
(panel D, location 7). In contrast, if we fix the number of trials to 5, as we increase the number of conditions,
ground-truth recovery of the signal approaches 100% (panel E, location 8). In other words, even if the
number of trials per condition is low, we can achieve accurate recovery of signal and noise distributions as
long as we sample a sufficient number of conditions. This means that when designing an experiment in
which we can either sample more trials per condition or sample more conditions, it is more important to
sample many conditions for GSN outcomes than to sample many trials per condition.

Besides assessing how well the different methods estimate covariance, we can also assess how well the
different methods estimate eigenspectra. We observe that the sample covariance tends to underestimate
dimensionality. This is most visible in the estimation of signal covariance when the number of conditions is
small (panel A, location 9, red +'s). By incorporating shrinkage (panel A, location 9, red circles), the match
to the ground-truth eigenspectrum is improved (panel A, location 9, red dashed line). Notice that the
difference between the two methods diminishes in situations where a relatively large number of samples is

available, such as estimation of noise covariance (panel A, location 10) or when the number of conditions
is increased (panel A, location 11). Finally, consistent with earlier observations, we see that naive signal
estimation produces eigenvalues that are too high (pink x's; reflecting the seeping of the noise covariance
into the signal covariance estimate) and that naive noise estimation produces eigenvalues that are too low
(gray x's; reflecting the lack of compensation for the reduced degrees of freedom).
249
Application of GSN to empirical data
250
251
Signal and noise covariance estimates
252
253
We demonstrate the application of GSN to empirical data taken from the 7T fMRI Natural Scenes Dataset
(NSD) (Allen et al., 2022). NSD consists of human brain responses to over 70,000 visually presented natural
scenes distributed across eight participants. Each image is presented up to three times to a given
participant. This limited number of presentations reflects the prioritization of sampling a large number of
distinct images over sampling a large number of trials per image (see also (Stringer et al., 2019)). As such,
NSD can be viewed as an especially challenging dataset for methods that seek to accurately disentangle
signal from noise.
261

262
263
Figure 4. Application of GSN to example fMRI data. Here we demonstrate the application of GSN to example
data (330 vertices × 10,000 images × 3 trials) (code available at https://osf.io/kebh8). *A*, Signal and noise
covariance estimates. In addition to GSN outputs (first and second columns), we show results from naive
estimation of signal covariance which involves simply calculating the covariance of trial-averaged data (third
column). *B*, Results for shuffled data. As a control, we shuffled responses across all images and trials and re-
analyzed the data. *C*, Conversion to correlation units. The results of panel A are re-plotted after converting

As an illustrative example, we extracted responses from right hemisphere fusiform face area subdivision 1
(FFA-1) in one participant (Participant 1), yielding 330 vertices × 10,000 images × 3 trials. As a pre-
processing step, we normalized the responses associated with each vertex to have zero mean and unit
variance. We then performed GSN on these data, yielding estimates of signal and noise covariance (**Figure**
4).

A number of observations can be made from the results. First, notice that the magnitude of the noise is
generally larger than the magnitude of the signal (panel A, compare diagonal of noise covariance with
diagonal of signal covariance). The fact that response measurements contain large trial-to-trial variability
even when holding the experimental manipulation (stimulus) constant is typical in fMRI and many other
measurement techniques. Second, we observe that the covariance structure of the noise is different from
that of the signal, though there are some similarities (panel A, compare middle image with left image). A
naive method that averages responses across trials yields covariance structure (panel A, right image) that
is a mixture of signal covariance and noise covariance, since trial averaging reduces but does not eliminate
noise. Third, as a control, if we fully shuffle responses across images and trials, we see that values in GSN's
estimated signal covariance become very low (panel B, left image). This makes sense since after shuffling,
we do not expect to find reliable differences in responses across images. In contrast, the naive method fails
to produce a good signal covariance estimate: even though there are no reliable differences in responses
across images, trial averaging does not fully suppress the noise and the noise covariance seeps into the
signal covariance estimate (panel B, right image).

For visual comparison, we show covariance estimates after conversion to correlation units (panel C). One
motivation for this conversion is to ensure that each unit contributes equally to subsequent analyses of the
covariance estimates. Prominent differences between covariance and correlation are observed, reflecting
the fact that there are substantial variations in signal-to-noise ratio across vertices (vertices with low signal
strength are only weakly visible in the covariance matrices and become more visible in the correlation
matrices). Finally, by applying GSN to different subsets of the data (panel D), we see that signal and noise
can be reliably estimated in this dataset. For example, compare the signal and noise correlation estimates
obtained using 1/4th of the data to those obtained using 1/16th of the data (these reflect two mutually
exclusive subsets of the data). Reliable estimation is especially notable given that the dataset involved only
three trials for each stimulus. Of course, in the limit of very low amounts of data (panel D, rightmost
columns), estimation quality starts to suffer and we start to see strong influence of the shrinkage bias pulling
off-diagonal elements towards zero.

Although GSN does not require nor assume Gaussian distributions, if the signal and noise distributions are
indeed Gaussian, then the mean and covariance parameters estimated by GSN are sufficient for a full
characterization of a given dataset. Curious about the nature of the distributions in NSD, we performed
inspections of the example data shown in **Figure 4**. These inspections reveal that the signal and noise
indeed have Gaussian-like distributions and that a synthesized dataset that uses the parameters of the
GSN model and assumes Gaussian distributions looks highly similar to the empirical data (**S1 Figure**).

Eigenspectra of signal and noise

Principal components analysis (PCA) is a widely used method for dimensionality reduction and data
visualization (Greenacre et al., 2022). Using the empirical data, we conducted several analyses that

demonstrate the benefits of GSN for PCA. The first analysis (**Figure 5A**) pertains to eigenspectra, which are important as they indicate the amount of variance explained by different principal components. For each of the eight NSD participants, we computed the eigenspectrum of the covariance of the data after trial averaging (cyan lines); this represents a naive analysis in which responses are averaged across trials to reduce noise. We also computed the eigenspectrum of the signal covariance (red lines) and noise covariance (black lines) as estimated by GSN. To make the results directly comparable to the results of the naive analysis, we scaled the noise covariance by 1/3 (since trial averaging is expected to reduce the variance of the noise by a factor equal to the number of trials). Finally, we calculated the effective dimensionality associated with each of the three eigenspectra (numbers above each plot).

Figure 5. GSN disentangles signal and noise in principal components analysis (PCA). Here we use PCA to analyze the results of GSN (code available at https://osf.io/guchw). *A*, Eigenspectra. For each of the eight participants (P1–P8), we plot the eigenspectra of the signal and noise as estimated by GSN ('Signal (GSN)', 'Noise (GSN)'), as well as the eigenspectrum of the trial-averaged data ('Naive'). The main plots show results on a linear scale for up to the first 10 dimensions; the insets show results on a base-10 log-log scale for up to the first 100 dimensions. Numbers above each main plot indicate the effective dimensionality of the three eigenspectra. *B*, Split-half reliability of principal components. The cosine similarity between corresponding principal components from two split-halves of the data from each participant is plotted for up to the first 100 dimensions. The thick black line indicates the mean across participants. *C*, Across-participant consistency. A common set of 515 images were viewed three times each by all participants. For each participant, we computed

We find that the three eigenspectra exhibit distinct patterns. In terms of overall magnitudes, eigenvalues are slightly higher for the signal than they are for the noise and are highest for the naive analysis. This is consistent with the interpretation that after averaging across 3 trials, the total variance contributed by signal is slightly higher than the total variance contributed by noise, and that the trial-averaged data have high total variance due to contributions from both signal and noise. In terms of how quickly eigenvalues fall off (independent of their magnitudes), we see that the eigenspectrum of the signal falls off relatively quickly and has low effective dimensionality (between 2–4). This indicates that the coding of natural scenes in FFA-1 is low-dimensional (at least as measured in NSD). In contrast, we find that the eigenspectrum of the noise falls off more slowly and has higher effective dimensionality than the signal (between 9–18). This is most evident in the inset log-log plots, which show more clearly what occurs at high numbers of dimensions. Finally, we find that the eigenspectrum of the trial-averaged data falls somewhere in the middle, with a moderate effective dimensionality (between 4–10). Overall, these results illustrate how GSN separates signal and noise components in a set of data and enables the researcher to study their separate properties. The separation of noise from signal is important, as it compensates for the fact that in empirical data, noise corrupts the dimensionality of the measured signal (Del Giudice, 2021).

Reliability of principal components

A second analysis pertains to the reliability of the principal components derived from the data. We randomly split the images from each participant into halves, performed PCA separately on the two split-halves, and then computed the cosine similarity of principal components across the split-halves. Results are shown both for the signal and noise as estimated by GSN as well as for the naive trial-averaged data (**Figure 5B**). We find that the principal components of the signal are highly reliable across split-halves for approximately the first 4 dimensions, and that the principal components of the noise are highly reliable for approximately the first 12 dimensions (see labeled points). Beyond these numbers of dimensions, reliability levels are substantially lower, which makes sense given that the amount of variance associated with the higher dimensions is very small (see **Figure 5A**). The principal components of the trial-averaged data also exhibit reasonably high levels of reliability. However, the reliability levels decrease gradually, making it difficult to decide the number of highly reliable dimensions.

One peculiar observation is that reliability values for the noise and the trial-averaged data fluctuate, but on average stay elevated, over a large range of dimensions (20–100). We suggest that this could be due to the fact that the eigenvalues in these higher dimensions are roughly equal in magnitude, making the ordering of the principal components somewhat arbitrary and subject to estimation error. In such a scenario, corresponding principal components across split-halves are not likely to match but might incidentally match on occasion. Finally, notice that the reliability pattern for the trial-averaged data looks approximately like a mixture of the reliability patterns for the signal and the noise. This is consistent with the interpretation that the data is a mixture of signal and noise and that GSN successfully decomposes the data into these constituent components.

Denoising of PCA results

The third and final analysis seeks to validate the signal and noise identification provided by GSN. In short, how do we know that GSN is successfully estimating and removing the influence of noise? Here, we can

leverage the notion that signal, not noise, is expected to generalize across participants (Charest et al.,
2018). We reasoned that if GSN successfully separates signal from noise in each participant, then signal
properties—specifically, the coding of natural scenes—should exhibit improved consistency across
participants compared to the trial-averaged data. This is because the trial-averaged data is expected to
contain the residual effects of noise, and many types of noise are expected to be idiosyncratic to each
participant (e.g., the effects of head motion on fMRI responses is likely unrelated to the coding of natural
scenes). But how can we compare participants? Given the variability of the size and shape of FFA-1 across
participants (the number of vertices is not even the same), comparing principal components across
participants is not straightforward. However, we can compute the projections of responses to natural scenes
onto principal components, and these projections should be comparable across participants insofar that
there is some degree of commonality in the representation of natural scenes across participants.
401
In accordance with our approach for assessing across-participant consistency, we computed trial-averaged
responses for a common set of 515 images that were viewed by all participants, and then projected these
responses onto the top principal component of the signal covariance estimated by GSN. For comparison,
we also projected the responses onto the top principal component of the trial-averaged data. The results
show that the projections for GSN are substantially more consistent across participants than the standard
analysis (**Figure 5C**). This implies that GSN is successfully reducing the influence of noise on principal
components derived from the data, and that the principal components derived by GSN better reflect the
underlying coding dimensions in the brain that are shared across humans. As a sanity check, we visually
inspected the stimulus images that drive variance along the direction of the top principal component (**S2**
Figure); this reveals that the presence of faces appears to be the dominant factor, consistent with prior
studies (Grill-Spector et al., 2017; Kanwisher et al., 1997).
413

Discussion

In this paper, we have described a simple generative model that characterizes the contributions of signal and noise to a set of neural response measurements. We developed a method for fitting this model, implemented this method in a code toolbox, and demonstrated the method on ground-truth simulations and empirical data. We showed three main results. First, we showed that naive approaches to estimating signal covariance (i.e. trial averaging) and estimating noise covariance (i.e. aggregating residuals) are inaccurate (**Figures 3–4**). A key insight is that simply computing trial-averaged responses is insufficient to eliminate noise: the result will invariably contain a mixture of both signal and noise covariance. Second, we confirmed that the GSN method works as expected, with ground-truth recovery performance improving with larger numbers of trials and conditions (**Figure 3**). Third, we showed how GSN can be exploited to improve principal components analysis (PCA). Specifically, GSN decomposes a set of data into signal and noise distributions, each of which has its own eigenspectrum and eigenvectors. These distributions can be analyzed separately, for example, with respect to dimensionality (**Figure 5A**) and reliability (**Figure 5B**). Furthermore, isolating the signal distribution leads to principal components that have improved generalizability across participants (**Figure 5C**).

Relationship to other approaches

From a statistical perspective, GSN bears some similarity to probabilistic principal components analysis (PPCA) (Ghojogh et al., 2021; Roweis, 1997; Tipping and Bishop, 1999). PPCA is a special case of factor analysis, and models the data as the sum of the combination of latent factors and a noise term. However, a key difference between PPCA and GSN is that PPCA assumes that the noise is isotropic (i.e., the noise has the same variance and is uncorrelated across units), whereas GSN does not make this assumption. Instead, GSN exploits the fact that neural response measurements usually involve multiple trials per condition, and estimates the noise structure instead of assuming it to be isotropic. Another difference is that PPCA typically comes with the presumption that the latent variables have lower dimensionality than the original data, whereas GSN does not necessarily involve dimensionality reduction.

Signal and noise correlations have been studied in the computational neuroscience literature using a variety of approaches. Here, we discuss a few approaches closely related to GSN. The approach used in (Triplett et al., 2020) involves building a model of calcium imaging data that simultaneously characterizes both evoked activity (signal) and spontaneous activity (noise). The model is generative in nature, similar to GSN. A difference is that the approach involves a number of modeling choices that are specific to the signal and noise characteristics present in calcium imaging data. Incorporating modality-specific details may enhance statistical efficiency and interpretability. In contrast, GSN has a different philosophical goal of providing a general-purpose framework for signal and noise estimation that rests on minimal assumptions. Another generative modeling approach, TAFKAP, was introduced by (van Bergen and Jehee, 2021, 2018) in the context of developing improved decoding methods for fMRI data. This approach, like GSN, estimates both signal covariance and noise covariance. However, the modeling of signal proceeds quite differently in TAFKAP than GSN. In TAFKAP, the response of each unit to the experimental conditions is fit using a specific tuning curve model—for example, in (van Bergen and Jehee, 2021), a weighted sum of basis functions is used to model the orientation tuning of each unit. GSN takes a different approach: instead of attempting to estimate the signal (noiseless response) to each condition, GSN attempts to estimate only the distribution of the signal across conditions. An advantage of the GSN approach is that it avoids the need to specify (and thus does not depend on) a tuning curve model, thereby providing more generality. Moreover, if a tuning curve model is used, there is a risk that model failures (either due to model

misspecification or imperfections in model fitting) may corrupt estimates of the noise (assuming noise is
estimated from model residuals) (Wilson and Gardner, 2023).

A recent paper (Stringer et al., 2019) proposed a method termed 'cross-validated PCA' (cvPCA) that seeks
to quantify signal (stimulus-related variance) in neural response measurements, similar to GSN. The
method involves splitting a dataset into halves (where the halves contain different trials for the same set of
conditions), performing PCA on one half, projecting the responses in each half onto the estimated PCs, and
then computing covariance across the projections from each half as an estimate of signal variance. The
underlying logic is that noise is not expected to covary across halves, whereas the signal is expected to do
so. Similar to GSN, the cvPCA method leverages repeated trials to infer what is related to the experimental
manipulations (signal) and relies on a model in which the total variance in a dataset is equal to the sum of
signal variance and noise variance. However, the two models differ substantially in the method by which
estimates are obtained. In particular, cvPCA estimates signal variance (using the procedure described
above) and subtracts signal variance from total variance to infer noise variance, whereas GSN estimates
noise variance (using shrinkage-based covariance estimation) and subtracts noise variance from total
variance to infer signal variance.

Recent work (Pospisil and Pillow, 2024) has pointed out that the PCs estimated in cvPCA are influenced
by noise and are therefore not identical to the true underlying signal PCs. This fact degrades the accuracy
of the signal components estimated by cvPCA, and leads to biased estimates of the signal eigenspectrum
(Pospisil and Pillow, 2024). Indeed, this observation mirrors our demonstrations that trial-averaged results
still suffer from the effects of noise (see **Figures 1 and 4**). Motivated by these concerns, the authors
propose an MEME (minimize eigenmoment error) method to deliver improved estimates of the signal
eigenspectrum. Specifically, MEME first calculates unbiased estimates of the moments of the signal
eigenspectrum, assumes a parametric model for the signal eigenspectrum, and then optimizes parameters
of the model to minimize the error between the eigenspectrum moments achieved by the model and the
estimated moments of the signal eigenspectrum.

Overall, the cvPCA and MEME methods are similar in spirit to GSN in the sense of attempting to separate
signal and noise in neural response measurements. The former two methods, however, are primarily
focused on estimation of signal eigenspectra, whereas GSN takes a broader view in which the goal is to
estimate a full generative model including both the eigenspectrum and eigenvectors of the signal and noise
distributions. As such, GSN designed to facilitate subsequent analyses of signal and noise covariance
structure. Further work towards comparing and contrasting the various methods in terms of their
assumptions and their performance characteristics would be valuable. It may turn out that different methods
are optimal for different outcome measures, and if so, the choice of method may depend on the goals of
the researcher. For example, although the sample covariance provides unbiased estimates of covariance
values, it yields biased dimensionality estimates (see **S4 Appendix**); hence, whether one should use the
sample covariance depends on whether one is primarily interested in covariance values or dimensionality.
As another example, if one's goal is to optimize out-of-sample generalization performance for a covariance
estimate, one should be willing to accept some bias (e.g. through shrinkage) in order to achieve that goal.

Other applications of GSN

Besides improving PCA and dimensionality estimation (as illustrated in **Figure 5**), GSN may aid in other
applications not specifically covered in this paper. One important application is the estimation of noise
ceilings for computational models (Lage-Castellanos et al., 2019; Pospisil and Bair, 2021b). Since noise
imposes limits on the maximum amount of variance that can in theory be predicted on the basis of
experimental events (e.g. sensory stimuli), obtaining accurate estimates of the noise ceiling is critical for

assessing model performance. GSN provides explicit models of the distributions of signal and noise, and
can be used to estimate noise ceilings for the responses of individual units (see Methods in (Allen et al.,
2022)) as well as noise ceilings for multivariate measures, such as representational dissimilarity matrices
(see Methods in (Conwell et al., 2022)). Having principled methods to compute univariate and multivariate
noise ceilings is critical in efforts to compare deep neural network models of brain data at scale (Cichy et
al., 2019; Conwell et al., 2022; Schrimpf et al., 2020; Willeke et al., 2022).

Another application relates to research programs where noise itself is of intrinsic interest, often
hypothesized to perform functions relevant to neural computation (e.g., (Bays, 2014; Dinstein et al., 2015;
Ecker et al., 2014; Keeley et al., 2020; Ma et al., 2006; Orbán et al., 2016; Stein et al., 2005; van Bergen
et al., 2015)). The GSN approach facilitates the study of noise by decomposing datasets into signal and
noise, providing researchers with two distinct entities that can be separately measured, characterized,
manipulated, compared with one another, and related to brain function. Isolating the separate contributions
of signal and noise to response measurements may help enrich our understanding of how response
variability contributes to the function of neural systems and whether and how noise and signal interact.

Limitations of GSN and future directions

GSN rests on the assumption that noise is additive and independent of the signal. The assumption of
independence simplifies estimation and enables efficient use of data: even though the example dataset in
this paper included only three trials per image, pooling estimates of noise covariance across images
enabled robust noise covariance estimates (see **Figure 4D**). The extent to which the additive and
independence assumptions accurately characterize fMRI responses is an important open question. For
example, a recent study provided evidence that noise magnitude and noise correlations in fMRI data
decrease during task states (Ito et al., 2020). However, it is clear that the additive and independence
assumptions do not strictly hold for spiking data. Spike trains exhibit Poisson-like proportionality between
the mean firing rate and the variance of firing rate across trials (Tolhurst et al., 1983), and this proportionality
may depend upon stimulus statistics (Festa et al., 2021). Moreover, multiplicative-type noise has been
observed in which firing rates in neural populations are collectively scaled (Goris et al., 2014; Lin et al.,
2015; Liska et al., 2022). Finally, evidence that noise depends on the stimulus has been shown for neurons
in the retina (Franke et al., 2016; Zylberberg et al., 2016). A direction for future work would be to relax the
assumptions of GSN to accommodate a larger range of settings.

Another potential limitation of GSN is that it may require a large number of samples for accurate estimation
of signal and noise distributions. We observed that a relatively large number of conditions is required to
accurately estimate the signal covariance (see **Figure 3E**). In addition, although pooling of noise covariance
estimates across conditions can achieve robust estimation of noise (see **Figure 4B**), if one wishes to
explore the possibility that the noise distribution may depend on the experimental condition, large numbers
of trials for each condition may be required. Future research might investigate practical data requirements
for a diverse range of experimental scenarios.

Our proposed method for estimating covariance incorporates shrinkage to improve estimation accuracy.
This is a mild prior and is expected to improve out-of-sample generalization compared to an unbiased
estimator. If one is willing to make stronger assumptions, there are other approaches that could achieve
more efficient covariance estimates. Such approaches include banding and tapering (Bickel and Levina,
2008a), thresholding (Bickel and Levina, 2008b), and methods that impose low-rank structure (Pourahmadi,
2013; Yatsenko et al., 2015). In addition, one could seek to model covariance in terms of one or more
structured covariance components (Pourahmadi, 2013; Triplett et al., 2020; van Bergen and Jehee, 2021;

Yatsenko et al., 2015). This type of approach can improve estimation efficiency, but its utility depends on
the accuracy of the assumed covariance components.
560
Finally, an important direction for future research is to devise methods for distinguishing different sources
of noise. Neural noise (true variability in neural activity) is fundamentally distinct from instrumental noise
(e.g. electrical noise), physiological noise (e.g. noise related to respiration and the cardiac cycle), and
motion-related noise (e.g. motion of the head). Without specific modeling of these various noise sources, it
remains unknown how much of the noise observed in a set of measurements is due to neural noise.
Developing methods to identify non-neural noise and isolate neural noise will presumably lead to improved
insights into the nature of noise and how it may support brain function.
568

Methods

The GSN method

Basic framework

GSN is a multivariate generalization of the univariate framework that we previously proposed for modeling signal and noise in responses of individual units (Allen et al., 2022). Consider the general situation in which responses are measured from a set of n units (e.g., voxels, neurons, channels) to c conditions (e.g., different stimuli) and this process is repeated for t trials per condition (we assume $t > 1$). In this scenario, response measurements have a dimensionality of n units $\times$ c conditions $\times$ t trials. The scenario is multivariate in the sense that there exist multiple units and we are attempting to model the joint distribution across all units. Our broad goal is to formally characterize the distribution of signal, i.e., the average expected response to each given condition, and the distribution of noise, i.e., trial-to-trial variability in the response to each given condition.

For the purposes of modeling, we assume that the signal and the noise are independent and additive and that each is characterized by some underlying multivariate distribution. We propose the following model:

$$D \sim X_{signal} + X_{noise}$$
$$\mathrm{E}[X_{signal}] = \mu_{signal}$$
$$\mathrm{Cov}[X_{signal}] = \Sigma_{signal}$$
$$\mathrm{E}[X_{noise}] = \mu_{noise} = \mathbf{0}$$
$$\mathrm{Cov}[X_{noise}] = \Sigma_{noise}$$
$$\mathrm{Cov}(X_{signal}, X_{noise}) = \mathbf{0}$$

where D is an n-dimensional random variable indicating the responses of the n units on each trial ($1 \times n$), X_{signal} is the signal component of the data with mean μ_{signal} ($1 \times n$) and covariance Σ_{signal} ($n \times n$), X_{noise} is the noise component of the data with mean μ_{noise} ($1 \times n$) and covariance Σ_{noise} ($n \times n$), and $\mathbf{0}$ indicates a matrix of zeros. In other words, the response on each trial is modeled as the sum of a random sample drawn from a signal distribution (which represents the noiseless response to some condition) and a random sample drawn from a noise distribution (which represents the noise that accompanies the response). The noise is further assumed to be zero-mean. See **Figure 2A–C** for a visual illustration.

The modeling approach we describe is generative in the sense that we are characterizing the process by which measurements are generated (specifically, the data for each trial are modeled as a random draw from the multivariate distribution associated with D). We therefore refer to the approach as *generative modeling of signal and noise (GSN)*.

Algorithm for estimating model parameters

The core challenge in GSN is estimating the parameters of the signal and noise distributions. We propose a method based on the observation that the sum of two independent random variables has a mean that is equal to the sum of the means of the distributions associated with the variables and a covariance that is equal to the sum of the covariances of the two distributions. Hence, we can write:

$$\mu_{data} = \mu_{signal} + \mu_{noise}$$
$$\Sigma_{data} = \Sigma_{signal} + \Sigma_{noise}$$

where μ_{data} and Σ_{data} indicate, respectively, the mean ($1 \times n$) and the covariance ($n \times n$) of the measurement variable D. For simplicity, we have used notation that acts as if each trial involves a fresh

616 draw from the signal distribution. However, in typical practice, several trials are measured for each condition
617 and the draw from the signal distribution is the same for each of these trials. In other words, the signal is
618 deterministic when conditioned on the condition, but the noise is not. To properly account for this, we
619 average responses across the available t trials before estimating the data distribution, and this has the
620 consequence that the covariance of the noise is reduced by a factor of t:

621
$$\mu_{data[t]} = \mu_{signal} + \mu_{noise}$$

622
$$\Sigma_{data[t]} = \Sigma_{signal} + \Sigma_{noise}/t$$

where $\mu_{data[t]}$ indicates the mean of the multivariate distribution that describes trial-averaged data ($1 \times n$)
and $\Sigma_{data[t]}$ indicates the covariance of this distribution ($n \times n$).

Our basic strategy for parameter estimation is to (i) estimate the mean and covariance of the noise and
then scale this distribution by $1/t$, (ii) estimate the mean and covariance of the trial-averaged data, and then
(iii) subtract the first set of parameters from the second to obtain an estimate of the mean and covariance
of the signal (**Figure 2D–F**).

The algorithm is as follows (*performgsn.{m,py}*):
1. Start with a set of neural response measurements X (n units $\times$ c conditions $\times$ t trials). Let X_j
denote the responses measured for condition j, arranged as a 2D matrix (t trials $\times$ n units). Let $\overline{X}$
denote trial-averaged responses, arranged as a 2D matrix (c conditions $\times$ n units).
2. To estimate the noise distribution, calculate the covariance of responses separately for each
condition, average the covariances across conditions, and then shrink the result. This yields an
initial estimate of the noise covariance, which we refer to as $\hat{\Sigma}_{noiseORIG}$ ($n \times n$):

647
$$\hat{\Sigma}_{noiseORIG} = s\left(\sum_{j=1}^{c} \text{cov}(X_j)/c\right)$$

where $\text{cov}(A) = \dot{A}^{\text{T}}\dot{A}/(d-1)$ computes sample covariance using Bessel's correction, $\dot{A}$ indicates
A with its columns centered around zero, d is the number of rows in A, and $s()$ is a shrinkage
procedure (see *Shrinkage-based regularization of covariance* below). Intuitively, we are
quantifying unit-to-unit covariation around the mean response to each condition, pooling
covariance estimates across conditions to improve accuracy, and then using shrinkage to further
improve accuracy. Since we might update our estimate of the noise covariance later in the
algorithm, we use $\hat{\Sigma}_{noise}$ ($n \times n$) to refer to our current estimate of the noise covariance:

648
$$\hat{\Sigma}_{noise} = \hat{\Sigma}_{noiseORIG}$$

645   We assume that the noise distribution is zero-mean (i.e., the expected value of the noise for each
646   unit is zero):

649
$$\hat{\mu}_{noise} = \mathbf{0}$$

650   where $\hat{\mu}_{noise}$ is the estimated noise mean ($1 \times n$).
651   3. To estimate the data distribution (i.e., the distribution that characterizes the measured data), take
652   the trial-averaged responses and then estimate mean and covariance, again applying shrinkage
653   to improve accuracy of covariance estimation:

654
$$\hat{\mu}_{data[t]} = \text{mean}(\overline{X})$$

655
$$\hat{\Sigma}_{data[t]} = s(\text{cov}(\overline{X}))$$

where $\text{mean}()$ indicates column-wise mean, $\hat{\mu}_{data[t]}$ is the estimated data mean for the case of
averaging across t trials ($1 \times n$), and $\hat{\Sigma}_{data[t]}$ is the estimated data covariance for the case of
averaging across t trials ($n \times n$). Notice that $\text{cov}(\overline{X})$ is the naive estimate of signal covariance that
is obtained after simply trial averaging.

4.   Repeat until convergence of $\hat{\Sigma}_{signal}$ and $\hat{\Sigma}_{noise}$:
4.1. To estimate the signal distribution, subtract the current estimate of the noise distribution
662   scaled by 1/t from the estimated data distribution:

$$\hat{\Sigma}_{signal} = \hat{\Sigma}_{data[t]} - \hat{\Sigma}_{noise}/t$$

663   where $\hat{\Sigma}_{signal}$ is the estimated signal covariance ($n \times n$). Additionally:

$$\hat{\mu}_{signal} = \hat{\mu}_{data[t]} - \hat{\mu}_{noise}$$

665   where $\hat{\mu}_{signal}$ is the estimated signal mean ($1 \times n$).
667   4.2. Ensure the signal covariance estimate obtained in Step 4.1 is positive semi-definite by
668   calculating the nearest positive semi-definite matrix:

$$\hat{\Sigma}_{signal} = \text{PSD}(\hat{\Sigma}_{signal})$$

669   where $\text{PSD}()$ is a method for finding the nearest symmetric positive semi-definite matrix to a
670   given square matrix (details below).
672   4.3. Calculate an updated estimate of the noise covariance:

$$\hat{\Sigma}_{noise} = \frac{ct^2(t-1)}{ct^2(t-1)+c-1}\hat{\Sigma}_{noiseORIG} + \frac{c-1}{ct^2(t-1)+c-1}t(\hat{\Sigma}_{data[t]} - \hat{\Sigma}_{signal})$$

673   This calculates a weighted average of two possible estimates of the noise covariance: the
674   first is the estimate based on the covariance of the mean-subtracted residuals (as calculated
675   in Step 2), while the second is the estimate based on the subtraction of the signal
676   distribution from the data distribution. The weights reflect the amount of data that inform
677   each of the two estimates (for details, see **S3 Appendix**).
679   4.4. Ensure the noise covariance estimate obtained in Step 4.3 is positive semi-definite by
680   calculating the nearest positive semi-definite matrix:

$$\hat{\Sigma}_{noise} = \text{PSD}(\hat{\Sigma}_{noise})$$

In many situations, Steps 1 through 4.1 are sufficient for determining the final signal and noise covariance
estimates. Specifically, if the estimated signal covariance generated by Step 4.1 is positive semi-definite,
then Steps 4.2 through 4.4 will not have any effect. However, in some cases (such as scenarios with limited
data or low signal-to-noise ratio), the estimated signal covariance generated by Step 4.1 may not be positive
semi-definite and therefore may not be a valid covariance matrix. To address this issue, we developed a
mathematical formalism that demonstrates how to optimally estimate signal and noise covariance under
the constraint that the covariance estimates are positive semi-definite. The procedure involves iterative
biconvex optimization as laid out in Steps 4.1 through 4.4. Convergence of $\hat{\Sigma}_{signal}$ and $\hat{\Sigma}_{noise}$ typically takes
just a few iterations, and convergence is guaranteed given that the problem is convex. Details of the
formalism are provided in **S3 Appendix**.

Shrinkage-based regularization of covariance

An appealing feature of computing sample covariance using Bessel's correction is that the covariance
values are unbiased estimates of the true covariance values. However, when the number of observations
is small relative to the number of variables (in our case, when the number of trials or conditions is small
relative to the number of units), the sample covariance is unstable and hence inaccurate. Moreover, the
sample covariance may have an eigenspectrum that suffers from bias. To improve accuracy of covariance
estimation, the GSN algorithm incorporates shrinkage (in Steps 2 and 3), a well-established method for
regularizing covariance estimates (Chen et al., 2010; Daniels and Kass, 2001; Ledoit and Wolf, 2004;
Schäfer and Strimmer, 2005). Specifically, the off-diagonal elements of the sample covariance are scaled
towards zero, reflecting the prior that variables are generally expected to be uncorrelated. The goal of
shrinkage is to introduce some amount of bias in order to reduce estimation variance and achieve a

covariance estimate that is closer to the ground-truth covariance. Note that shrinking towards a diagonal
matrix tends to increase the rank (dimensionality) of the covariance estimate. Also, note that shrinkage is
not a requirement of the GSN approach and can be omitted if desired (using the flag <wantshrinkage>).
709
710 To perform shrinkage, we calculate:
711
$$\Sigma_{shrunk} = s(\Sigma) = \lambda\Sigma + (1 - \lambda)\Sigma_{diag}$$
where Σ is the sample covariance ($n \times n$), λ is a shrinkage fraction in the range [0,1], Σ_{diag} is Σ with off-
diagonal elements set to zero ($n \times n$), and Σ_{shrunk} is the shrinkage-based covariance estimate ($n \times n$). When
the shrinkage fraction is 1, the sample covariance is preserved and no shrinkage is applied; when the
shrinkage fraction is 0, full shrinkage is applied. Notice that in our formulation, the target towards which
estimates are shrunk (Σ_{diag}) contains the original sample variance estimates on the diagonal. This choice
of target is referred to as Target D "diagonal, unequal variance" in (Schäfer and Strimmer, 2005). The
reason for this choice of target is to avoid imposing bias on the variances associated with the variables.
719
To determine the amount of shrinkage to apply, we use a cross-validation approach (similar to that used in
(van Bergen and Jehee, 2021; Yatsenko et al., 2015)) in which held-out data are used to evaluate
likelihoods corresponding to covariance estimates at different levels of shrinkage. We opt for this
computational approach, as opposed to analytical methods for setting the shrinkage level (Ledoit and Wolf,
2004; Schäfer and Strimmer, 2005), for increased transparency and to avoid reliance on assumptions. In
our implementation (*calcshrunkencovariance.{m,py}*), we randomly split the available data into an 80%
training set and a 20% testing set. In the case of noise estimation (Step 2), the data are split with respect
to trials; in the case of data estimation (Step 3), the data are split with respect to conditions. The sample
covariance of the training set is then calculated, different shrinkage fractions ranging from 0 to 1 in
increments of 0.02 are applied, the average negative log likelihood of observations in the testing set is
calculated for each shrinkage fraction, and the shrinkage fraction yielding the minimum negative log
likelihood is selected. Note that in the case of estimating the noise distribution, the mean response to each
condition in the testing set is subtracted before evaluating likelihoods (in order to remove the signal). Our
implementation includes flexible options that allow the user to control the training/testing split (<leaveout>)
as well as the specific shrinkage fractions evaluated (<shrinklevels>). In addition, the implementation
includes an optional flag (<wantfull>) that enables a final step in which the selected shrinkage fraction is
applied to the sample covariance of the full dataset (combining both the training and testing sets). This
option improves estimation quality (since more data are used) at the expense of imposing slightly more
shrinkage than is optimal (in theory, if more training data are available, then less shrinkage should be
necessary).
740
741 We conducted simulations to confirm the validity of our shrinkage-based method for covariance estimation
742 (**S4 Appendix**). These simulations also confirm that shrinkage reduces the bias present in the
743 eigenspectrum of the sample covariance.
744
745 *Method for finding the nearest positive semi-definite matrix*
746
To ensure valid covariance matrices, the GSN algorithm involves finding the nearest (in the sense of the
Frobenius norm) symmetric positive semi-definite matrix to a given matrix (see $\mathrm{PSD}()$ in Steps 5 and 7).
This is accomplished using the method proposed by Higham (Higham, 1988). Our implementation is as
follows (*constructnearestpsdcovariance.{m,py}*):
1.   Start with a given square matrix $\boldsymbol{C}$.
2.   Ensure symmetry by updating $\boldsymbol{C} = (\boldsymbol{C} + \boldsymbol{C}^{\mathrm{T}})/2$.
3.   Perform singular value decomposition to obtain $\boldsymbol{C} = \boldsymbol{USV}^{\mathrm{T}}$.

4. Compute the approximating matrix $\widetilde{C} = (C + VSV^{\mathrm{T}})/2$.
5. If $\widetilde{C}$ is not positive semi-definite (due to numerical precision issues), add a small multiple of the
identity matrix (εI) to $\widetilde{C}$ and restart the procedure starting from Step 3. We use $\varepsilon = 10^{-10}$.
Note that this method is equivalent to performing an eigendecomposition of C and setting negative
eigenvalues to zero.
759
Additional analyses related to GSN

Conversion of covariance to correlation

When interpreting covariance matrices, it is often useful to convert the values to correlation units.
Correlation is simply a version of covariance where the variances of each of the two variables have been
normalized to one. We provide a function to convert covariance matrices to correlation units
(*convertcovariancetocorrelation.{m,py}*). Our implementation divides each element of a given covariance
matrix by the square root of its associated row-wise diagonal element and by the square root of its
associated column-wise diagonal element. This conversion procedure is used in **Figure 4**.

Principal components analysis

773   The present study uses principal components analysis (PCA) as a means for interpreting the results of
774   GSN. We perform PCA through eigendecomposition of a given covariance matrix:

$$C = VSV^{\mathrm{T}}$$

776
$$S = \begin{bmatrix} \lambda_1 & \cdots & 0 \\ \vdots & \ddots & \vdots \\ 0 & \cdots & \lambda_n \end{bmatrix}$$

where C is a covariance matrix ($n \times n$) associated with data in n dimensions, V is an orthonormal matrix (n
$\times n$) with unit-length eigenvectors in the columns, and S is a diagonal matrix ($n \times n$) with eigenvalues along
the diagonal in descending order ($\lambda_1 \geq \lambda_2 \geq \cdots \geq \lambda_n \geq 0$). The eigenvectors are referred to as *principal*
components; the sizes of the eigenvalues indicate the importance of the principal components; and the full
set of eigenvalues is referred to as the *eigenspectrum*. A given data point ($1 \times n$), expressed relative to the
centroid of the data, can be projected onto the principal components, producing *scores* ($1 \times n$). These
scores are simply the coordinates of the data point in the rotated space defined by the principal components.
Finally, a useful metric that summarizes the distribution of eigenvalues is effective dimensionality (ED) (Del
Giudice, 2021):

786
$$\mathrm{ED} = \frac{(\sum_{i=1}^{n} \lambda_i)^2}{\sum_{i=1}^{n} (\lambda_i{}^2)}$$

This metric ranges continuously from 1 to *n* and indicates the number of underlying dimensions in the data
(specifically, the number of dimensions that results in an equivalent amount of entropy). Note that the metric
shown above is just one of several possible metrics for ED (Del Giudice, 2021).

Depending on one's goals, one might want to convert a covariance matrix to correlation units before
computing the eigendecomposition. The motivation for this would be to ensure that all dimensions have
equal influence (otherwise, dimensions with larger variances would tend to dominate the principal
components). Indeed, in standard usage of PCA, it is generally recommended to *z*-score each dimension
as a pre-processing step; this has the consequence that the covariance matrix will be in correlation units.

Empirical data

Data preparation

We demonstrate GSN on example data taken from the Natural Scenes Dataset (NSD) (Allen et al., 2022).
NSD consists of 7T fMRI measurements (1.8-mm resolution) from 8 healthy young adults who each viewed
9,000–10,000 distinct natural scenes up to 3 times each over the course of 30–40 scan sessions. Images
were presented for 3 s with 1-s gaps in between images. Participants fixated centrally and performed a
long-term continuous recognition task on the images. The fMRI data in NSD come already pre-processed
and analyzed using a general linear model as implemented in GLMsingle (Prince et al., 2022). This general
linear model produces single-trial beta weights representing the amplitude of the fMRI response on each
trial in units of percent signal change. Note that GLMsingle denoises the signal-trial beta weights (i.e.
removes some unwanted sources of variance); hence, the analyses in this paper assess the noise that
remains after the GLMsingle procedure.

For the purposes of this paper, we took the betas_fithrf version of the single-trial betas in the fsaverage
preparation of NSD (the betas_fithrf version reflects a general linear model that accounts for voxel-to-voxel
variation in the hemodynamic response function). From the single-trial betas, we extracted responses from
right hemisphere fusiform face area (FFA-1 subdivision), a brain region that was functionally localized in
each participant. We normalized the data by *z*-scoring the responses of each vertex in each session, and
then extracted responses for all images that were shown all three times to the participant. (The term 'vertex'
refers to a point that belongs to a cortical surface representation; for all practical purposes, 'vertex' can be
treated as synonymous with 'voxel' in this paper.) This procedure yielded, for each participant, a set of
response measurements with dimensionality n vertices $\times$ c images $\times$ 3 trials. Across participants, the value
of n ranged from 167 to 1,231 and the value of c ranged from 5,445 to 10,000.

Application of GSN

We performed GSN on the response measurements from each participant. For the example participant
shown in **Figure 4** and **S1 Figure**, GSN was applied to the full dataset as well as data subsets of varying
sizes in order to examine the impact of amount of data on estimation quality. This was accomplished by
varying the fraction of images used: 1 (10,000 images), 1/4 (2,500 images), 1/16 (625 images), 1/64 (156
images), and 1/256 (39 images). The images in the data subsets were randomly selected and mutually
exclusive across subsets. For the full set of participants shown in **Figure 5**, GSN was applied to the full
dataset as well as split-halves of the data from each participant. Splitting was performed such that a random
half of the images were used for one split and the remaining images were used for the other split.

To aid visual inspection of covariance matrices, we used a particular vertex ordering for the rows and
columns of the covariance matrices in **Figure 4**. Specifically, we performed hierarchical clustering
(MATLAB's Statistics Toolbox's *linkage.m*) on trial-averaged responses using a distance metric of one
minus correlation and the linkage algorithm of unweighted average distance. This procedure yielded a
vertex ordering where similar vertices tend to be close to one another. The same vertex ordering is used
for all depicted covariance matrices.

Application of PCA

We performed PCA on the results of GSN ('GSN PCA'). This involved performing PCA separately on the
covariance of the signal distribution and on the covariance of the noise distribution. For comparison, we
also conducted a naive application of PCA by simply performing PCA on the covariance of the trial-
averaged data ('Standard PCA').

To compare PCA results across participants, we isolated the set of 515 images that were viewed by all 8
participants 3 times each during the NSD experiment. For each participant, we computed trial-averaged
responses for the 515 images and projected these responses onto (i) the principal components associated
with the signal distribution in the case of GSN PCA, or (ii) the principal components of the trial-averaged
data in the case of Standard PCA. The resulting scores were then compared across participants using the
metric of cosine similarity (i.e., the dot product of unit-length-normalized vectors).
854
One characteristic of PCA is that the sign of each principal component is arbitrary. We performed several
sign adjustments to facilitate comparison of PCA results across data splits and participants. First, for every
principal component, we flipped the sign of the principal component if necessary to ensure that the mean
of the values in the principal component is positive. This incurs no loss of generality and establishes a
reasonable starting point for the determination of signs. Second, for corresponding principal components
in the split-half analysis for each participant (e.g., PC1 from one half and PC1 from the other half), we
flipped the sign of one of the principal components if necessary to ensure that the cosine similarity between
the two principal components is non-negative. This flipping procedure ensures that the reliability of results
across split halves is not penalized for incidental variation in signs. Third, when comparing scores across
participants, we performed a simple iterative algorithm in which scores are sign-flipped if necessary to
ensure that the cosine similarity between the scores from a given participant and the average of the scores
from the other seven participants is non-negative. This procedure compensates for the sign ambiguity of
the principal components derived from each participant.
868

869 ## Data and code availability statement

870
871 The code used in this study is provided at https://osf.io/wkyxn/. The empirical fMRI data used is available
872 at http://naturalscenesdataset.org. The GSN code toolbox is available at https://github.com/cvnlab/GSN/.
873

Author Contributions

K.K. developed methods and performed data analysis. K.K. and J.S.P. wrote the paper. J.S.P. and G.T. aided in code implementation. T.G. developed concepts and performed data analysis. H.S. developed methods. All authors discussed and edited the manuscript.

Acknowledgements

We thank B. Pig for comments on the manuscript. This work was supported by NIH grant R01EY034118 (K.K.). Collection of the NSD dataset was supported by NSF IIS-1822683 (K.K.) and NSF IIS-1822929 (T.N.).

Competing Interests

The authors confirm that there are no competing interests.

References

Allen, E.J., St-Yves, G., Wu, Y., Breedlove, J.L., Prince, J.S., Dowdle, L.T., Nau, M., Caron, B., Pestilli, F., Charest, I., Hutchinson, J.B., Naselaris, T., Kay, K., 2022. A massive 7T fMRI dataset to bridge cognitive neuroscience and artificial intelligence. Nat. Neurosci. 25, 116–126.

Averbeck, B.B., Latham, P.E., Pouget, A., 2006. Neural correlations, population coding and computation. Nat. Rev. Neurosci. 7, 358–366.

Azeredo da Silveira, R., Rieke, F., 2021. The geometry of information coding in correlated neural populations. Annu. Rev. Neurosci. 44, 403–424.

Bays, P.M., 2014. Noise in neural populations accounts for errors in working memory. J. Neurosci. 34, 3632–3645.

Bickel, P.J., Levina, E., 2008a. Regularized estimation of large covariance matrices. Ann. Stat. 36, 199–227.

Bickel, P.J., Levina, E., 2008b. Covariance regularization by thresholding. The Annals of Statistics 36, 2577–2604.

Biswal, B., Yetkin, F.Z., Haughton, V.M., Hyde, J.S., 1995. Functional connectivity in the motor cortex of resting human brain using echo-planar MRI. Magn. Reson. Med. 34, 537–541.

Cafaro, J., Rieke, F., 2010. Noise correlations improve response fidelity and stimulus encoding. Nature 468, 964–967.

Charest, I., Kriegeskorte, N., Kay, K.N., 2018. GLMdenoise improves multivariate pattern analysis of fMRI data. Neuroimage 183, 606–616.

Chen, Y., Wiesel, A., Eldar, Y.C., Hero, A.O., 2010. Shrinkage Algorithms for MMSE Covariance Estimation. IEEE Trans. Signal Process. 58, 5016–5029.

Cichy, R.M., Roig, G., Andonian, A., Dwivedi, K., Lahner, B., Lascelles, A., Mohsenzadeh, Y., Ramakrishnan, K., Oliva, A., 2019. The Algonauts Project: A platform for communication between the sciences of biological and artificial intelligence. arXiv [cs.CV].

Cohen, M.R., Kohn, A., 2011. Measuring and interpreting neuronal correlations. Nat. Neurosci. 14, 811–819.

Conwell, C., Prince, J.S., Kay, K.N., Alvarez, G.A., Konkle, T., 2022. What can 1.8 billion regressions tell us about the pressures shaping high-level visual representation in brains and machines? bioRxiv. https://doi.org/10.1101/2022.03.28.485868

Daniels, M.J., Kass, R.E., 2001. Shrinkage estimators for covariance matrices. Biometrics 57, 1173–1184.

Del Giudice, M., 2021. Effective dimensionality: A tutorial. Multivariate Behav. Res. 56, 527–542.

Dinstein, I., Heeger, D.J., Behrmann, M., 2015. Neural variability: friend or foe? Trends Cogn. Sci. 19, 322–328.

Ecker, A.S., Berens, P., Cotton, R.J., Subramaniyan, M., Denfield, G.H., Cadwell, C.R., Smirnakis, S.M., Bethge, M., Tolias, A.S., 2014. State dependence of noise correlations in macaque primary visual cortex. Neuron 82, 235–248.

Eickhoff, S.B., Yeo, B.T.T., Genon, S., 2018. Imaging-based parcellations of the human brain. Nat. Rev. Neurosci. 19, 672–686.

Festa, D., Aschner, A., Davila, A., Kohn, A., Coen-Cagli, R., 2021. Neuronal variability reflects probabilistic inference tuned to natural image statistics. Nat. Commun. 12, 3635.

Franke, F., Fiscella, M., Sevelev, M., Roska, B., Hierlemann, A., da Silveira, R.A., 2016. Structures of neural correlation and how they favor coding. Neuron 89, 409–422.

Ghojogh, B., Ghodsi, A., Karray, F., Crowley, M., 2021. Factor analysis, probabilistic Principal Component Analysis, variational inference, and Variational Autoencoder: Tutorial and survey. arXiv [stat.ML].

Goris, R.L.T., Movshon, J.A., Simoncelli, E.P., 2014. Partitioning neuronal variability. Nat. Neurosci. 17, 858–865.

Gratton, C., Kraus, B.T., Greene, D.J., Gordon, E.M., Laumann, T.O., Nelson, S.M., Dosenbach, N.U.F., Petersen, S.E., 2020. Defining individual-specific functional neuroanatomy for precision psychiatry. Biol. Psychiatry 88, 28–39.

Greenacre, M., Groenen, P.J.F., Hastie, T., D'Enza, A.I., Markos, A., Tuzhilina, E., 2022. Principal component analysis. Nat. Rev. Methods Primers 2. https://doi.org/10.1038/s43586-022-00184-w

Grill-Spector, K., Weiner, K.S., Kay, K., Gomez, J., 2017. The Functional Neuroanatomy of Human Face Perception. Annu Rev Vis Sci 3, 167–196.

Hazon, O., Minces, V.H., Tomàs, D.P., Ganguli, S., Schnitzer, M.J., Jercog, P.E., 2022. Noise correlations in neural ensemble activity limit the accuracy of hippocampal spatial representations. Nat. Commun. 13, 4276.

Higham, N.J., 1988. Computing a nearest symmetric positive semidefinite matrix. Linear Algebra Appl. 103, 103–118.

Ito, T., Brincat, S.L., Siegel, M., Mill, R.D., He, B.J., Miller, E.K., Rotstein, H.G., Cole, M.W., 2020. Task-evoked activity quenches neural correlations and variability across cortical areas. PLoS Comput. Biol. 16, e1007983.

Kanitscheider, I., Coen-Cagli, R., Pouget, A., 2015. Origin of information-limiting noise correlations. Proc. Natl. Acad. Sci. U. S. A. 112, E6973-82.

Kanwisher, N., McDermott, J., Chun, M.M., 1997. The fusiform face area: a module in human extrastriate cortex specialized for face perception. J. Neurosci. 17, 4302–4311.

Keeley, S.L., Aoi, M.C., Yu, Y., Smith, S.L., Pillow, J.W., 2020. Identifying signal and noise structure in neural population activity with Gaussian process factor models. bioRxiv. https://doi.org/10.1101/2020.07.23.217984

Lage-Castellanos, A., Valente, G., Formisano, E., De Martino, F., 2019. Methods for computing the maximum performance of computational models of fMRI responses. PLoS Comput. Biol. 15, e1006397.

Ledoit, O., Wolf, M., 2004. A well-conditioned estimator for large-dimensional covariance matrices. J. Multivar. Anal. 88, 365–411.

Lin, I.-C., Okun, M., Carandini, M., Harris, K.D., 2015. The nature of shared cortical variability. Neuron 87, 644–656.

Liska, J.P., Rowley, D.P., Nguyen, T.T.K., Muthmann, J.-O., Butts, D.A., Yates, J.L., Huk, A.C., 2022. Running modulates primate and rodent visual cortex via common mechanism but quantitatively distinct implementation. bioRxiv. https://doi.org/10.1101/2022.06.13.495712

Ma, W.J., Beck, J.M., Latham, P.E., Pouget, A., 2006. Bayesian inference with probabilistic population codes. Nat. Neurosci. 9, 1432–1438.

Mell, M.M., St-Yves, G., Naselaris, T., 2021. Voxel-to-voxel predictive models reveal unexpected structure in unexplained variance. Neuroimage 238, 118266.

Moreno-Bote, R., Beck, J., Kanitscheider, I., Pitkow, X., Latham, P., Pouget, A., 2014. Information-limiting correlations. Nat. Neurosci. 17, 1410–1417.

Orbán, G., Berkes, P., Fiser, J., Lengyel, M., 2016. Neural variability and sampling-based probabilistic representations in the visual cortex. Neuron 92, 530–543.

Panzeri, S., Moroni, M., Safaai, H., Harvey, C.D., 2022. The structures and functions of correlations in neural population codes. Nat. Rev. Neurosci. 23, 551–567.

Pospisil, D.A., Bair, W., 2021a. Accounting for biases in the estimation of neuronal signal correlation. J. Neurosci. 41, 5638–5651.

Pospisil, D.A., Bair, W., 2021b. The unbiased estimation of the fraction of variance explained by a model. PLoS Comput. Biol. 17, e1009212.

Pospisil, D.A., Pillow, J.W., 2024. Revisiting the high-dimensional geometry of population responses in visual cortex. bioRxiv. https://doi.org/10.1101/2024.02.16.580726

Pourahmadi, M., 2013. High-dimensional covariance estimation, 1st ed, Wiley Series in Probability and Statistics. John Wiley & Sons, Nashville, TN.

Prince, J.S., Charest, I., Kurzawski, J.W., Pyles, J.A., Tarr, M.J., Kay, K.N., 2022. Improving the accuracy of single-trial fMRI response estimates using GLMsingle. Elife 11. https://doi.org/10.7554/eLife.77599

Rabinowitz, N.C., Goris, R.L., Cohen, M., Simoncelli, E.P., 2015. Attention stabilizes the shared gain of V4 populations. Elife 4, e08998.

Ringach, D.L., 2009. Spontaneous and driven cortical activity: implications for computation. Curr. Opin. Neurobiol. 19, 439–444.

Roweis, S., 1997. EM algorithms for PCA and SPCA. Adv. Neural Inf. Process. Syst. 626–632.

Schäfer, J., Strimmer, K., 2005. A shrinkage approach to large-scale covariance matrix estimation and implications for functional genomics. Stat. Appl. Genet. Mol. Biol. 4, Article32.

Schrimpf, M., Kubilius, J., Lee, M.J., Ratan Murty, N.A., Ajemian, R., DiCarlo, J.J., 2020. Integrative
Benchmarking to Advance Neurally Mechanistic Models of Human Intelligence. Neuron 108, 413–
423.
Stein, R.B., Gossen, E.R., Jones, K.E., 2005. Neuronal variability: noise or part of the signal? Nat. Rev.
Neurosci. 6, 389–397.
Stringer, C., Pachitariu, M., Steinmetz, N., Carandini, M., Harris, K.D., 2019. High-dimensional geometry
of population responses in visual cortex. Nature 571, 361–365.
Tipping, M.E., Bishop, C.M., 1999. Probabilistic principal component analysis. J. R. Stat. Soc. Series B
Stat. Methodol. 61, 611–622.
Tolhurst, D.J., Movshon, J.A., Dean, A.F., 1983. The statistical reliability of signals in single neurons in cat
and monkey visual cortex. Vision Res. 23, 775–785.
Tolhurst, D.J., Movshon, J.A., Thompson, I.D., 1981. The dependence of response amplitude and
variance of cat visual cortical neurones on stimulus contrast. Exp. Brain Res. 41, 414–419.
Triplett, M.A., Pujic, Z., Sun, B., Avitan, L., Goodhill, G.J., 2020. Model-based decoupling of evoked and
spontaneous neural activity in calcium imaging data. PLoS Comput. Biol. 16, e1008330.
Uddin, L.Q., 2020. Bring the noise: Reconceptualizing spontaneous neural activity. Trends Cogn. Sci. 24,
734–746.
van Bergen, R.S., Jehee, J.F.M., 2021. TAFKAP: An improved method for probabilistic decoding of
cortical activity. bioRxiv. https://doi.org/10.1101/2021.03.04.433946
van Bergen, R.S., Jehee, J.F.M., 2018. Modeling correlated noise is necessary to decode uncertainty.
Neuroimage 180, 78–87.
van Bergen, R.S., Ma, W.J., Pratte, M.S., Jehee, J.F.M., 2015. Sensory uncertainty decoded from visual
cortex predicts behavior. Nat. Neurosci. 18, 1728–1730.
Willeke, K.F., Fahey, P.G., Bashiri, M., Pede, L., Burg, M.F., Blessing, C., Cadena, S.A., Ding, Z., Lurz,
K.-K., Ponder, K., Muhammad, T., Patel, S.S., Ecker, A.S., Tolias, A.S., Sinz, F.H., 2022. The
Sensorium competition on predicting large-scale mouse primary visual cortex activity. arXiv [q-
bio.NC].
Williams, A.H., Linderman, S.W., 2021. Statistical neuroscience in the single trial limit. Curr. Opin.
Neurobiol. 70, 193–205.
Wilson, J., Gardner, J., 2023. Covariance between similarly tuned populations in human visual cortex is
model-dependent. J. Vis. 23, 5802–5802.
Yatsenko, D., Josić, K., Ecker, A.S., Froudarakis, E., Cotton, R.J., Tolias, A.S., 2015. Improved estimation
and interpretation of correlations in neural circuits. PLoS Comput. Biol. 11, e1004083.
Zhang, J., Kucyi, A., Raya, J., Nielsen, A.N., Nomi, J.S., Damoiseaux, J.S., Greene, D.J., Horovitz, S.G.,
Uddin, L.Q., Whitfield-Gabrieli, S., 2021. What have we really learned from functional connectivity
in clinical populations? Neuroimage 242, 118466.
Zylberberg, J., Cafaro, J., Turner, M.H., Shea-Brown, E., Rieke, F., 2016. Direction-selective circuits
shape noise to ensure a precise population code. Neuron 89, 369–383.

S1 Figure. Assessment of data distributions. As an instructive exercise, we take the empirical brain data illustrated in **Figure 4** and perform an inspection of the signal and noise components of the data (code available at https://osf.io/kebh8). We inspect two different distributions. One is the distribution of trial-averaged responses. Since trial averaging reduces noise, inspecting trial-averaged responses helps us assess properties of the signal. The second is the distribution of mean-subtracted residuals (in which trial-averaged responses have been removed). This allows us to focus our assessment on properties of the noise. We compute the first several principal components (PCs) of the covariance of the trial-averaged responses and then visualize the two distributions of interest in the low-dimensional space defined by these PCs. We also generate, for comparison, a synthesized dataset based on the parameters of the GSN model as fit to the empirical data. In order to generate responses for this synthesized dataset, we assume that both the signal and noise are Gaussian-distributed. We visualize the synthesized data in exactly the same manner as the real data (including using the same low-dimensional space). Examining the distributions associated with the real data (top row), we see that both the distribution of trial-averaged responses and the distribution of mean-subtracted residuals are Gaussian-like in their shape. We also see that the structure of the mean-subtracted residuals differs from that of the trial-averaged responses (top row, compare first and second images). This indicates that the noise structure is not identical to the signal structure, consistent with the inspections in **Figure 4A**. Next, we compare the distributions associated with the real data (top row) with those obtained from the synthesized data (bottom row). The distributions obtained from the synthesized data look very similar to those from the real data, suggesting that both the signal and the noise in the real data have Gaussian-like distributions and that the generative model learned by GSN accurately characterizes the real data.

S2 Figure. Inspection of stimuli in PCA results. Here we visually inspect stimulus images from the PCA analysis (code available at https://osf.io/guchw). The projections of responses to the common 515 images onto PC1 (see **Figure 5C**) were unit-length-normalized, averaged across participants, and then unit-length-normalized again. This figure compares the results obtained using Standard PCA (*x*-axis) against the results obtained using GSN PCA (*y*-axis). Red dots indicate images that were judged by human raters to have at least one prominent face present; black dots indicate all other images. (The human raters were blind to the results in this paper.) The actual images corresponding to the highest five and lowest five projection values (based on the average of the two methods) are shown. The presence of faces appears to be the dominant factor governing the response projections. (Note: Faces have been grayed out due to privacy reasons.)

S3 Appendix: GSN estimation of signal and noise covariance

Problem setting

As described in the main text, GSN calculates two covariance estimates from the data: $\hat{\Sigma}_{noiseORIG}$ and $\hat{\Sigma}_{data[t]}$. The former is an estimate of the noise covariance based on the trial-to-trial variability around the mean response to each condition (see Step 2). The latter is an estimate of the data covariance based on the data after averaging across t trials (see Step 3).

We believe that these two covariance estimates reflect unknown covariance matrices Σ_{signal} and Σ_{noise} such that $\hat{\Sigma}_{noiseORIG}$ is a noisy version of Σ_{noise} based on $c(t-1)$ samples and $\hat{\Sigma}_{data[t]}$ is a noisy version of $\Sigma_{data[t]} = \Sigma_{signal} + \Sigma_{noise}/t$ based on $c-1$ samples.

We wish to determine estimates $\hat{\Sigma}_{signal}$ and $\hat{\Sigma}_{noise}$ under the constraint that these estimates are positive semi-definite matrices. To do so, we define the following loss that quantifies errors from the data-derived covariances scaled by the number of samples they are based on:

$$L\left(\hat{\Sigma}_{signal}, \hat{\Sigma}_{noise}\right) = c(t-1)\left\|\hat{\Sigma}_{noiseORIG} - \hat{\Sigma}_{noise}\right\|_2^2 + (c-1)\left\|\left(\hat{\Sigma}_{data[t]} - \hat{\Sigma}_{noise}/t\right) - \hat{\Sigma}_{signal}\right\|_2^2$$

where $\|\ \|_2$ indicates the Frobenius norm. Intuitively, the noise estimate $\hat{\Sigma}_{noise}$ is allowed to deviate to some degree from the data-derived $\hat{\Sigma}_{noiseORIG}$, and the signal estimate $\hat{\Sigma}_{signal}$ is allowed to deviate to some degree from the subtraction-based estimate of the signal covariance $\hat{\Sigma}_{data[t]} - \hat{\Sigma}_{noise}/t$.

Notice $\hat{\Sigma}_{noiseORIG}$ is positive semi-definite, as it is a covariance matrix computed from data. If $\hat{\Sigma}_{data[t]} - \hat{\Sigma}_{noise}/t$ is also positive semi-definite, setting $\hat{\Sigma}_{noise} = \hat{\Sigma}_{noiseORIG}$ and $\hat{\Sigma}_{signal} = \hat{\Sigma}_{data[t]} - \hat{\Sigma}_{noise}/t$ is the optimal solution for the problem (since the loss equals zero). If not, we can solve the optimization problem using the method described below.

Solution

To solve the optimization problem in the general case, we note that it is a convex optimization problem, as it is a sum of squares and the cone of semi-definite matrices is a convex set (Boyd and Vandenberghe, 2016). Thus, this problem has a single optimum. For solving this problem efficiently, we split the problem into optimizing $\hat{\Sigma}_{signal}$ and $\hat{\Sigma}_{noise}$ separately, as we can compute an analytic solution for each matrix if the other is fixed. Since each of these separate optimizations is guaranteed to improve the loss, this approach is guaranteed to converge.

Lemma: solution pattern

Consider the following problem. Given B, find A that minimizes $\|B - A\|_2^2$ (or equivalently $\|A - B\|_2^2$) subject to the constraint that A is positive semi-definite. We can solve this problem as $A = \text{PSD}(B)$ where $\text{PSD}()$ is the method for finding the nearest positive semi-definite matrix described in the main text. We will use this solution pattern in solving the individual optimizations for $\hat{\Sigma}_{signal}$ and $\hat{\Sigma}_{noise}$.

Optimizing $\hat{\Sigma}_{signal}$

Since $c(t-1)\left\|\hat{\Sigma}_{noiseORIG} - \hat{\Sigma}_{noise}\right\|_2^2$ is independent of $\hat{\Sigma}_{signal}$, we are left with minimizing

$$(c-1)\left\|\left(\hat{\Sigma}_{data[t]} - \hat{\Sigma}_{noise}/t\right) - \hat{\Sigma}_{signal}\right\|_2^2$$

subject to $\hat{\Sigma}_{signal}$ being positive semi-definite. To do this, we use our solution pattern where $A = \hat{\Sigma}_{signal}$ and $B = \hat{\Sigma}_{data[t]} - \hat{\Sigma}_{noise}/t$.

Optimizing $\hat{\Sigma}_{noise}$

In this case, we apply a quadratic extension to turn the sum of squares into a single one:

$$L\left(\hat{\Sigma}_{signal}, \hat{\Sigma}_{noise}\right) = \sum_{ij}\left[c(t-1)\left(\hat{\Sigma}_{noiseORIG}^{(ij)} - \hat{\Sigma}_{noise}^{(ij)}\right)^2 + (c-1)\left(\hat{\Sigma}_{data[t]}^{(ij)} - \hat{\Sigma}_{signal}^{(ij)} - \frac{\hat{\Sigma}_{noise}^{(ij)}}{t}\right)^2\right]$$

$$= \sum_{ij}\left[c(t-1)\left(\left(\hat{\Sigma}_{noiseORIG}^{(ij)}\right)^2 - 2\hat{\Sigma}_{noiseORIG}^{(ij)}\hat{\Sigma}_{noise}^{(ij)} + \left(\hat{\Sigma}_{noise}^{(ij)}\right)^2\right)\right.$$

$$\left. + \frac{c-1}{t^2}\left(\left(t^2\left(\hat{\Sigma}_{data[t]}^{(ij)} - \hat{\Sigma}_{signal}^{(ij)}\right)^2\right) - 2t\left(\hat{\Sigma}_{data[t]}^{(ij)} - \hat{\Sigma}_{signal}^{(ij)}\right)\hat{\Sigma}_{noise}^{(ij)} + \left(\hat{\Sigma}_{noise}^{(ij)}\right)^2\right)\right]$$

$$= \sum_{ij}\left[\frac{ct^2(t-1) + c - 1}{t^2}\left(\hat{\Sigma}_{noise}^{(ij)}\right)^2 - 2\hat{\Sigma}_{noise}^{(ij)}\left(c(t-1)\hat{\Sigma}_{noiseORIG}^{(ij)} + \frac{c-1}{t}\left(\hat{\Sigma}_{data[t]}^{(ij)} - \hat{\Sigma}_{signal}^{(ij)}\right)\right)\right] + C_0$$

where C_0 is a term that is independent of $\hat{\Sigma}_{noise}$. Simplifying, we obtain:

$$L\left(\hat{\Sigma}_{signal}, \hat{\Sigma}_{noise}\right) \propto \sum_{ij}\left[\hat{\Sigma}_{noise}^{(ij)} - \frac{ct^2(t-1)}{ct^2(t-1) + c - 1}\hat{\Sigma}_{noiseORIG}^{(ij)} - \frac{c-1}{ct^2(t-1) + c - 1}t\left(\hat{\Sigma}_{data[t]}^{(ij)} - \hat{\Sigma}_{signal}^{(ij)}\right)\right]^2 + C_1$$

where C_1 is a term that is independent of $\hat{\Sigma}_{noise}$. To minimize this loss, we use our solution pattern where $A = \hat{\Sigma}_{noise}$ and $B = \frac{ct^2(t-1)}{ct^2(t-1)+c-1}\hat{\Sigma}_{noiseORIG} + \frac{c-1}{ct^2(t-1)+c-1}t\left(\hat{\Sigma}_{data[t]} - \hat{\Sigma}_{signal}\right)$.

Notice that the calculation of B is a weighted average of two possible estimates of the noise covariance. The first estimate, $\hat{\Sigma}_{noiseORIG}$, reflects the covariance of mean-subtracted residuals, while the second estimate, $t\left(\hat{\Sigma}_{data[t]} - \hat{\Sigma}_{signal}\right)$, reflects the subtraction of the signal distribution from the data distribution. The weights in the weighted average reflect the amount of data that inform each of the two estimates.

Algorithm

The overall algorithm for optimizing signal and noise covariance estimates is described in the main text. Holding $\hat{\Sigma}_{noise}$ fixed, the algorithm optimizes $\hat{\Sigma}_{signal}$ in Steps 4.1 and 4.2. Holding $\hat{\Sigma}_{signal}$ fixed, the algorithm optimizes $\hat{\Sigma}_{noise}$ in Steps 4.3 and 4.4. This process of biconvex optimization is iterated until convergence.

References

Boyd, S., Vandenberghe, L., 2016. Convex Optimization. Cambridge University Press, Cambridge, England.

S4 Appendix: Shrinkage-based covariance estimation

A core component of GSN is estimation of covariance (this is performed for the estimated noise covariance in Step 2 and the estimated data covariance in Step 3). However, in high-dimensional datasets involving a large number of units but only a limited number of samples (e.g. trials), the standard method of computing sample covariance may yield inaccurate estimates of covariance. To improve accuracy of covariance estimation, GSN incorporates shrinkage (Ledoit and Wolf, 2004; Schäfer and Strimmer, 2005) of off-diagonal elements of covariance matrices towards zero. This reflects the prior that units are generally expected to be uncorrelated. The specific amount of shrinkage is tailored to optimally match the data using a cross-validation procedure in which likelihoods are evaluated on held-out data (see *Methods*).

We tested our shrinkage-based method for covariance estimation. We performed a set of simulations in which we assessed, as a function of the number of samples, how well the shrinkage method recovers a ground-truth covariance, compared to the standard method in which shrinkage is omitted (**Figure S4.1**). In one set of simulations, we used a ground-truth covariance equal to the identity matrix, corresponding to a scenario of uncorrelated units (panel A). In a second set of simulations, we re-used the previous ground-truth covariance but introduced positive correlations ($r = 0.5$) amongst the first five units (panel B). For additional comparison, in a third set of simulations, we used a ground-truth covariance equal to the covariance of a fixed set of random numbers drawn from the standard normal distribution (20 observations, 10 variables) (panel C).

The results show that the shrinkage method works well. In each scenario, the introduction of shrinkage improves ground-truth covariance recovery and this occurs regardless of the number of samples (panels A–C, lower left). Note that the size of the improvement varies across scenarios, with larger improvements when the ground truth is consistent with the prior of uncorrelated units (e.g. panel A) than when this is less the case (e.g. panel C). This makes sense: the cross-validation procedure should, in theory, correctly determine that shrinkage should be applied more strongly in situations where the underlying ground-truth covariance involves uncorrelated variables. Indeed, if we examine cross-validation results across different shrinkage levels, we see that in the scenario of uncorrelated variables, the shrinkage fractions yielding the highest likelihood on held-out data are close to 0, indicating large amounts of shrinkage (panel A, vertical red line in rightmost column), whereas in scenarios of correlated variables, the optimal shrinkage levels are closer to 1, indicating small amounts of shrinkage (panels B–C, vertical red lines in rightmost column).

The simulations also reveal insights into how ground-truth recovery performance varies as a function of the amount of data. As the number of samples increases, the induced shrinkage becomes weaker (compare 5 samples to 100 samples in panel C). This makes sense because at small sample sizes, the unregularized (non-shrunken) covariance is so inaccurate that inducing heavy bias improves the estimate. Furthermore, we see that as the number of samples increases, the difference in results between the shrinkage method and the standard method becomes smaller. Thus, shrinkage provides the most benefit when the amount of available data is small. It is important to keep in mind, however, that the covariance estimates produced by shrinkage are by no means perfect and that they contain bias. This can be seen intuitively by visually comparing the shrinkage-based covariance estimates at low number of samples to the ground-truth covariance. While shrinkage increases the overall similarity of covariance estimates to the underlying ground-truth covariance, it does so at the expense of biasing the magnitudes of off-diagonal elements towards zero. The introduction of bias is not necessarily a problem, as it depends on the goals of the researcher.

Figure S4.1. Shrinkage-based covariance estimation. Here we show results of simulations that assess the performance of the shrinkage-based method we use for covariance estimation (code available at https://osf.io/9nrq6). Panels A–C depict three different scenarios. Each scenario involves 10 units whose responses are distributed according to a ground-truth multivariate Gaussian (whose covariance is shown at the upper left). We vary the number of samples (e.g., trials, conditions) drawn from the distribution, performing 50 simulations for each number of samples. In each simulation, we estimate covariance from the samples using two different methods. One method ('No shrinkage') is to simply compute the sample covariance with Bessel's correction. The second method ('Shrinkage') involves additionally shrinking the off-diagonal elements of the sample covariance, using cross-validation to determine the optimal shrinkage level. In each panel, the ground-truth covariance is shown at the upper left. Cross-validation results for different numbers of samples are shown at the upper right, where colored lines indicate different simulations, black dots indicate the minimum negative log likelihood achieved, and the vertical red line indicates the median selected shrinkage level across simulations. Below each cross-validation plot, covariance estimates from one simulation are shown (we choose the simulation in which the selected shrinkage level is closest to the median). At the bottom are plots of the eigenspectra (mean across simulations) produced by the two methods (red and pink lines) as well as the ground-truth eigenspectrum (black dotted line). Finally, the ground-truth recovery performance quantified using coefficient of determination (R^2) is shown at the lower left (mean across simulations).

A clear benefit of the bias induced by shrinkage can be seen in the eigenspectra of the covariance estimates (panels A–C, bottom right). Even though the sample covariance provides an unbiased estimate of covariance, it produces biased eigenspectra that are lower in dimension than the ground-truth eigenspectra (see steep fall-off of the eigenspectra in the case of 5 samples). In other words, the sample covariance tends to underestimate the true dimensionality of the data. Shrinkage, to an extent, alleviates this issue, as it increases dimensionality (eigenvalues become more spread out) and produces eigenspectra that more closely resemble the ground-truth eigenspectra. These results are consistent with prior results from the literature (see Figure 1 in (Schäfer and Strimmer, 2005)).