Concurrent multimodal imaging demonstrates that EEG-based excitation/inhibition balance reflects glutamate and GABA concentrations

Aaron Cochrane[1], Luke Rosedahl[1], Masako Tamaki[2], Takeo Watanabe[1], Yuka Sasaki[1]

[1] Brown University, Rhode Island, United States

[2] RIKEN, Saitama, Japan

Abstract

Neural excitation/inhibition (E/I) ratio is dynamically regulated on multiple timescales. Adaptive changes in E/I

ratio can support healthy development, learning, and cognition, while disordered E/I ratio has been implicated in

neurodevelopmental disorders, neurodegenerative disorders, and states of impaired vigilance. There has been

growing interest in inferring E/I ratio from efficient and noninvasive measurements such as electroencephalography

(EEG), and several algorithms have been proposed to estimate E/I ratio from EEG. Despite promising results, there

has been a lack of validation studies testing the underlying neurochemical changes leading to increased or decreased

EEG-based E/I ratio. Here, using concurrent EEG and magnetic resonance spectroscopy (MRS) for over an hour,

we assessed which algorithm of EEG-based E/I ratio best matched with MRS-based E/I ratio in humans of both

sexes. The MRS-based E/I ratio was obtained by the ratio of glutamate concentration to GABA concentration. We

applied 10 candidate indices of EEG-based E/I ratio using four approaches in several spontaneous frequency bands.

Uniquely, we quantified the associations between the EEG-based E/I ratio and MRS-based E/I ratio separately for

between-subjects and within-subjects variations. We found that each EEG-based E/I algorithm showed reliable and

positive associations with MRS-based E/I, and especially EEG-based E/I ratio in alpha band with a criticality theory

based approach showed the best association to the MRS-based E/I ratio. While these associations were evident for

between-subjects comparisons, they were quite weak for within-subjects comparisons. These results suggest that

EEG-based E/I algorithms are likely to reflect, at least in part, relative concentrations of glutamate and GABA.

Introduction

Brain functioning is largely regulated through a dynamically changing balance of excitatory and inhibitory (E/I) activities (Hensch et al. 1998; Shew et al. 2011). Such dynamics are closely linked to a variety of phenomena including neural plasticity (Bavelier et al. 2010; Hensch et al. 1998; Vogels et al. 2011), brain development (Hensch 2004; Takesian and Hensch 2013) disordered functioning (Bruining et al. 2020; Geertjens et al. 2022; Nifterick et al. 2023), and cognition-related phenomena (Hellyer et al. 2016; Yang et al. 2023; Amil and Verschure 2021). Reflecting the fact that E/I ratio varies on multiple spatial and temporal scales, and is difficult to measure non-invasively (Ahmad et al. 2022; Craven et al. 2022), a variety of methods are used to assess E/I in humans. These include the use of electrophysiological (EEG) signatures and magnetic resonance spectroscopy (MRS). Each of these approaches holds great promise and yet faces serious limitations.

EEG-based approaches to quantifying E/I ratio (i.e., EEG-E/I) come from several theoretical and computational sources, including scale-free dynamics (Gao, Peterson, and Voytek 2017), criticality theory (Poil et al. 2012), and neural mass modeling (Yokoyama and Kitajo 2023), and have been used to investigate physiological underpinnings of phenomena ranging from vigilance (Yang et al. 2023) to Alzheimer's disease (Nifterick et al. 2023). Each of these has proposed mechanistic bases for the links between a scalp-based electrical signal and cortical excitation or inhibition, but empirical data tracking brain regions' neurochemistry to EEG measures has been largely lacking (Ahmad et al. 2022; Geertjens et al. 2022). In contrast, EEG-based E/I ratio measures have relative advantages include their wide availability, inexpensive and efficient implementation, and providing data from multiple brain regions simultaneously.

The use of MRS to study E/I ratio (i.e., MRS-E/I) ratio presents a different and complementary set of trade-offs. Studies of E/I ratio using MRS have been conducted to study brain plasticity, including that involved in perceptual learning (Shibata et al., 2017; Tamaki et al., 2020). While MRS-based E/I has the distinct benefit of having a clear biological basis, namely, excitatory (glutamate) and inhibitory (gamma-aminobutyric acid; GABA) neurotransmitter concentrations, it is limited to a single cortical location with fairly low temporal resolution and restricts the measurement only inside an MRI scanner, thereby precluding measurement in certain populations or during certain behaviors, and is relatively expensive.

There have been efforts to link EEG measures and MRS data. There have been multiple reports of associations between MRS-measured GABA concentrations with electrophysiological frequency bands (e.g., Balz et al., 2016; Edden et al., 2009), but each of these studies measured electrophysiology and MRS in separate sessions and were therefore limited to stable inter-individual correlations and were insensitive to rapid or functional changes that may occur on short timescales. However, functional changes in varying E/I ratio would be necessary to investigate in many fields, including neuroplasticity, pharmacological interventions, and cognition.

There remains a clear need for multimodal investigations of EEG-E/I ratio in conjunction with MRS-E/I ratio. Only

simultaneously measuring the two forms of E/I ratio can allow assessment of both within-subject and between-

subject variations in each of the two measures. For example, it is possible that the two forms of E/I ratio are

empirically distinct from each other, if EEG-based E/I ratio reflects specific neural subpopulations generating

oscillatory signatures (Scheeringa and Fries 2019; Shafiei et al. 2023), while MRS-based EI ratio reflects the

aggregate concentration of certain molecules in a large voxel. In contrast, it is possible that the two forms of E/I are

indexing the same underlying biological processes, that is, the relative concentrations of the primary excitatory

vs. inhibitory neurotransmitters in a broad region of cortex. Here we addressed these questions by comparing MRS-

based E/I ratio with EEG-based E/I ratio using several approaches in participants in simultaneous measurements of

MRS and EEG in healthy young participants.

Materials and Methods

Experimental Design

We re-analyzed data from Study 1 of Tamaki et al. (2020), which consists of 18 subjects who slept for between 60

and 90 minutes following a perceptual learning task. Simultaneous polysomnography including EEG and MRS

were recorded throughout the sleep session. To assess the extent to which candidate EEG-based measures of E/I

ratio were reflecting the changes in neurotransmitter concentrations measured by MRS-based E/I ratio, we estimated

a single E/I value using each method for each 5-minute period of the recorded data (see sections *MRS-based E/I*

ratio and *EEG-based measures of E/I ratio*). We then used Bayesian multivariate linear mixed-effects modeling

and cross-validation to quantify the ability to predict MRS-based E/I using EEG-based estimates (see section

Statistical Analysis). We separated these estimates into between-subjects and within-subjects analyses; while much

previous work has focused on the relatively stable differences between individuals' levels of excitation and

inhibition (e.g., Balz et al., 2016; Edden et al., 2009), within-subjects variation in E/I ratio are central to many

research domains such as vigilance (Yang et al. 2023) and learning-related neuroplasticity (Bavelier et al. 2010;

Tamaki et al. 2020) because these topics are inherently concerned with intra-individual changes. Separating these

results helps identify both the overall associations between MRS-E/I ratio and EEG-E/I ratio as well as their relative

isomorphism in the context of different applications.

MRS-based E/I ratio

MRS-based E/I ratio is typically estimated by identifying a brain region of interest (e.g., early visual areas) and

placing a single voxel in that region. Using magnetic resonance, the spectroscopic signal is then measured in that

voxel over the course of several minutes and the relative concentrations of excitatory and inhibitory

neurotransmitters are estimated (Provencher, 1993). These concentrations can then be examined separately or

combined into a single measure of E/I ratio. Using such methods with a 3 Tesla MRI it would conventionally be

considered high spatial resolution to have a single voxel that is 15mm per side and a high temporal resolution to

have one measurement every 2 minutes. The relative trade-offs of MRS measures of E/I ratio are clear, then: While

MRS-based E/I ratio is a relatively direct measure of actual molecules of interest within the brain, this measurement

technique is resource-intensive, spatially and temporally imprecise, and the measured spectrum is itself a noisy

measure. Indeed, the estimation of neurotransmitter concentrations has no consensus standard and results from a

single MR sequence may vary depending on the estimation algorithm (e.g., inter-algorithm correlations between

GABA concentration estimates ranging from below .1 to above .8; Craven et al., 2022).

Our primary results used the originally-published MRS data (Tamaki et al. 2020; Study 1), wherein a MEGA-

PRESS sequence was used (1.25s TR; 2.2 × 2.2 × 2.2 cm voxel, placed on midline in early visual cortices; 3 Tesla

Siemens scanner). We made two modifications to the data reported in the previous publication, namely, partial

volume correction (PVC) to account for relative proportions of grey matter (i.e., to mitigate the influence of grey

matter proportion on associations with EEG measures) and separation into 5-minute sections of time instead of 10-

minute time sections (mean number of 5-minute windows per participant = 13.1, sd = 3.6). As with the originally-

published work, we used LCModel software (Provencher, 1993) to identify Glx (Glutamate + Glutamine) and

GABA+ (GABA + residual molecules) concentrations normalized to NAA. We then estimate MRS-based E/I ratio

by dividing Glx by GABA+. We chose to continue using LCModel to estimate Glx and GABA+, rather than other

candidate softwares for several reasons. First, we needed to maintain congruence with the original findings because

reliable results in the original paper indicate that E/I from LCModel reflects true underlying cortical changes

(Tamaki et al., 2020). Second, LCModel has been found to provide the most typical estimates of neurotransmitter

concentrations, as it shows the highest correlation of GABA estimates with the median of estimates from other

software (Craven et al., 2022).

EEG-based measures of E/I ratio

We assessed four approaches to quantifying electrophysiological activity from EEG. Three of these approaches

were calculated separately for three canonical frequency bands (see below), leading to a total of 10 total EEG-based

measures to test associations with MRS-E/I. The first measure, overall amplitude, is not a measure of E/I *per se*,

but associations between MRS-E/I within specific frequency bands have been observed previously (e.g., theta and

low beta; Tamaki et al. 2020). Next, we assessed EEG-based E/I ratio derived from scale-free dynamics reflected

by the 1/f power slope (Gao, Peterson, and Voytek 2017), then an extension of this scale-free perspective that

derives from criticality theory (Bruining et al. 2020), and a set of estimates utilizing a neural mass model of

excitatory and inhibitory dynamics (Yokoyama and Kitajo 2023).

For details of EEG preprocessing steps, such as MR artifact rejection, see Methods in Tamaki et al. (2020; Study

1). In all analyses we report EEG measures estimated from the closest 7 electrodes (Oz, O1, O2, PO3, PO4, & PO7)

to the MRS voxel, since the MRS voxel was placed over early visual areas (Tamaki et al., 2020). We show the

detailed information for each approach below.

Frequency band amplitude

As one of the most basic measures identifiable within EEG signals, we included simple amplitude (i.e., square root

of power) measures from several frequency bands. We used finite impulse response (FIR) bandpass filtering in

EEGLAB (Delorme & Makeig, 2004) to isolate theta (5-8Hz), alpha (8-12Hz), and low beta (12-20Hz) bands,

estimated the amplitude in 5-second windows, and then calculated the trimmed mean amplitude for each 5-minute

measurement period (i.e., for robustness to outliers, after removing the 5% lowest and 5% highest amplitude

windows, calculating the arithmetic mean of the amplitudes within the remaining windows). These three frequency

bands were examined due to previous work finding links between MRS-based E/I ratio and theta as well as low

beta power (Tamaki et al., 2020), and the use of alpha amplitude envelopes in the implementation of the criticality-

based E/I ratio (Bruining et al., 2020).

While there have been some indications of links between frequency bands and E/I ratio (Balz et al., 2016; Duncan

et al., 2014; Porjesz et al., 2002), we include amplitude here primarily as a baseline approach against which to assess

the more algorithmically complex approaches to estimating EEG-based E/I ratio. That is, as an algorithmically

simple derivation from resting-state EEG, we consider amplitudes to be valuable measures to assess overall data

reliability (e.g., see Supplement *Across-channel correlations*; we would expect amplitude measures to have high

cross-channel correlations and a lack of such correlations would indicate poor data quality), test the divergence of

EEG-E/I measures from amplitudes (see Supplement *Associations among EEG measures*), as well as providing

parsimonious reflections of MRS measures if the relevant correlations were to be found (Edden et al., 2009; Tamaki

et al., 2020).

EEG-E/I from 1/f slope ("1/f")

The next approach to derives E/I ratio from EEG signals is based on the widespread observation that neural activity,

in temporal, spatial, and frequency domains, displays scale-free dynamics (power-law, or "1/f" when in the

frequency domain; Hahn et al., 2017; He, 2014; Linkenkaer-Hansen et al., 2001). Computational derivations of the

slopes of these 1/f distributions have been linked to cortical E/I ratio due to the relative timescales of excitatory and

inhibitory interneurons' firing rates (Gao et al., 2017; Lendner et al., 2020). As with previous work (Gao, Peterson,

and Voytek 2017; Yokoyama and Kitajo 2023) we estimated the 1/f slope coefficient between 30Hz and 50Hz

(bandpass filtered) for each 5-minute window of interest, which avoids contamination of the 1/f slope with

deviations from this slope associated with alpha and beta frequencies; we implemented this approach with Python

scripts available in conjunction with Yokoyama and Kitajo (2023). Unlike the other approaches, 1/f slope does not

consider discrete frequency bands, but instead the change in power across a wide range of frequencies. The

following approach, based in criticality theory, is an elaboration of these principles of scale-free dynamics.

EEG-E/I from criticality theory ("fE/I")

A recently-developed algorithm for identifying E/I ratio from EEG data is grounded in the computational biology

framework of criticality, which characterizes the nature of many biological systems as existing at the cusp of state

transitions (Bak 1999; Márton et al. 2014; Poil et al. 2012). One application of this theoretical approach is to neural

criticality, which proposes that neural activity exists approximately at a ratio between excitation and inhibition in

order to maximize the flexibility of macro-scale neural computations (Avramiea et al. 2022; Cocchi et al. 2017;

Shew et al. 2011). To estimate this type of EEG-based E/I ratio (Ahmad et al., 2022; Juarez Martinez et al., 2019),

we used an algorithm which is based in criticality theory and has been validated in computational, pharmacological

(Bruining et al. 2020), and animal models (Kat et al., 2024); the developers of this algorithm label it "functional E/I

ratio" (fE/I). We do not know of any previous work linking fE/I to MRS measures.

We applied this approach to the same three bandpass-filtered frequency bands we considered when examining

simple amplitude measures. In brief, this algorithm first determines the degree of *criticality* (here, linked to the

exponent of Detrended Fluctuation Analysis (DFA) Long-Range Temporal Correlations (LRTC)). This uses links

between the window size of an analyzed signal and the variability in its cumulative detrended amplitude profile.

Second, this degree of criticality is linked to the signal amplitude; in inhibitory-dominant regimes these two values

should be positively correlated, while in excitation-dominant regimes they should be anticorrelated (Bruining et al.,

2020). Using code published in conjunction with Bruining et al. (2020), fE/I values were estimated for each of the

above-defined three frequency bands (theta, alpha, and low beta) and then within- and between-subject correlations

with MRS-E/I were estimated. As in the publication establishing the method, estimation of fE/I used a window size

of 5 seconds with an inter-window overlap of .8 (Bruining et al. 2020); we also tested the effects of increasing the

window sizes to 15 seconds and found minimal changes, and here report only 5-second window sizes for simplicity.

For each 5-minute measurement period we also estimated the DFA coefficient and excluded measurement periods

with DFA below .6, as recommended by the developers of this approach (Bruining et al. 2020; Diachenko et al.

2024).

EEG-E/I from neural mass model ("NMM-E/I")

A fourth approach comes from a body of work instantiating neural mass models, that is, computational models of

neural circuitry such as cortical columns; such models can be scaled up and can simulate complex dynamics and

characterize dynamic and nonlinear features of neural activity (Cooray, Rosch, and Friston 2023; Jansen and Rit

1995). Yokoyama and Kitajo (2023) extended earlier neural mass models (Jansen and Rit 1995), which had been

developed for purposes such as modeling epileptic dynamics, with a key insight: such models can include estimates

of the relative activity of circuits' excitatory and inhibitory neural populations. Following this, and so they could

compare to the 1/f approach described above, Yokoyama and Kitajo (2023) showed that the E/I ratio derived from

such models could capture the fluctuating activity of humans' electrophysiological activity during sleep. This

approach to estimating E/I ratio is quite new, however, and to our knowledge has not been widely assessed. We

estimated this NMM-E/I using Python code available in conjunction with Yokoyama and Kitajo (2023) for each 5-

minute measurement period, and for each of the canonical frequency bands described above (i.e., theta, alpha, &

low beta). Unlike the fE/I algorithm, the NMM-E/I ratio algorithm does not involve separation into 5-second

segments. We also tested the NMM-E/I on a single wider set of frequencies, more similar to the approach

implemented in Yokoyama and Kitajo (2023), on bandpass-filtered data between 5Hz and 20Hz (i.e., the lower and

upper limits of the three frequency bands considered in the above analyses). The resulting NMM-E/I values did not

improve correspondence to MRS-E/I relative to the values estimated from distinct canonical frequency bands.

Statistical Analysis

For both within-subjects and between-subjects analyses we used two separate statistical approaches which were

complementary to one another. In the first approach, in order to best estimate the effect size (i.e., correlation

coefficient) between each EEG measure and MRS-based E/I ratio, we fit a Bayesian multivariate linear mixed-

effects model using **brms** in R (Bürkner 2017). Using this approach we specified each of the measures as variables

to predict (i.e., "response" variables). Each response variable was fit with an overall intercept, a random-effects by-

participant intercept, and a fixed-effect autoregressive term with an order of one to account for non-independence

of temporally proximal measurements. Within the multivariate model the correlations across the response variables

of the by-participant intercepts were estimated (in brms "Wilkensen" notation the formula for each E/I measure was

`response ~ 1 + ar(time, order = 1) + (1 | subjectR | subjectID)`; for full schematic see Figure

S1). In this way we estimated simultaneously the between-subjects effects, in the form of the correlations between

different response variables' by-participant intercepts, as well as within-subjects effects, in the form of the residual

correlations remaining after accounting for the autoregressive and by-subject terms. We report these two

correlations, both between-subjects and within-subjects, as the best empirical estimate of the links between each

measure. In addition, this model included an estimation of the remainder of the correlation matrix (e.g., between all

EEG-E/I measures as well as estimates of Glx and GABA+); we report these correlations to determine the extent to

which our EEG measures are isomorphic and are potentially more reflective of Glx or GABA+ variations (see

Figure S2).

As tests of the reliability of associations between EEG measures and MRS-based E/I ratio, and in consideration of

the possibility of overfitting our data, we augmented our Bayesian multivariate linear mixed-effects model with a

maximum-likelihood cross-validation approach. This approach involved iteratively and randomly partitioning the

data into "training" and "test" sets, fitting a maximum-likelihood linear regression model predicting MRS-based

E/I ratio to the training set, and assessing the R-squared (i.e., proportional reduction in sum of squared error; out-

of-sample delta R-squared dRsq$_{oos}$) on the test set (Dale et al., 2021; Scott et al., 2023). Between-subjects and

within-subjects analyses were necessarily implemented somewhat differently. Between-subjects cross-validation

involved first calculating the subject-level means for each measure, and then using simple random partitioning of

this aggregated dataset into 80%/20% subsets, with data being fit with a bivariate robust linear model to 80% of the

data and dRsq$_{oos}$ assessed on the remaining 20%. The null model in this case was an intercept-only linear regression.

In contrast, within-subjects cross-validation involved randomly selecting a single observation (i.e., 5-minute time

period) from each participant to keep as a test set, fitting a linear model including a by-participant covariate (i.e., to

control for participant-level means in MRS-E/I ratio) to the remaining training set, and then assessing the

proportional change in out-of-sample squared error (dRsq$_{oos}$) when compared to a model with only the participant

covariate as a predictor. To control for between-subjects variations in the predictor EEG-based measures, for each

of these within-subjects cross-validation models the EEG-E/I measure was first normalized within participants, after

using a Yeo-Johnson transformation to minimize univariate skew, and then z-scored. Here we report the median

dRsq$_{oos}$ of 500 resampled models for each EEG-E/I measure.

Supplemental Analyses

EEG-E/I reliability assessment

We implemented a cross-channel correlation approach to estimate a heuristic reliability of our EEG data and EEG-

based measures. Due to basic principles of volume conduction (Burle et al., 2015), as well as our intention to

measure relatively large-scale variations in physiological activity, we expected highly homogeneous estimates of

EEG measures across our measured channels. A lack of such a correlation for all EEG measures would indicate

poor EEG data quality, whereas a lack of correlation within a single EEG measure may indicate computational

instability of that measure. Because each of our EEG-based methods involved first estimating a value for each

channel we were able to, within each method, estimate the cross-channel correlations for our analyzed posterior

electrodes. We tested these correlations within subjects by finding the pairwise cross-channel partial rank

correlations in estimated E/I values, partialling out participant-level intercepts. We then report the median cross-

channel partial rank correlation (see Figure S3). While we do not have a strict reliability criterion for these

correlation measures, we believe that the relative cross-channel correlations should provide a general sense of the

computational stability of the measures; amplitude, fE/I, and 1/f measures demonstrated acceptable reliability.

Between-subjects variability relative to within-subjects variability

In light of differences in between-subjects relative to within-subjects correspondences between EEG-based and

MRS-based measures of E/I, we sought to quantify the relative between-subjects and within-subjects variances for

each measure. To determine between-subjects variances we first found each participant's median value for each

measure, then calculated the variances of these median values. To determine within-subjects variances we first

calculated each participant's variance for each measure, then found the median of these variances. The ratio of

between-subjects variance to within-subjects variances is reported in Figure S4, with no clear bias toward larger

between-subjects variance nor within-subjects variance.

Results

We first assessed data quality and excluded 5-minute windows in which at either fE/I ratio or MRS-E/I ratio

demonstrated high noise relative to signal; amplitude, 1/f, and NMM-E/I ratio measures do not have established

cutoff thresholds for exclusion. MRS data quality was quantified using the ratio of the uncertainty of molecules'

estimated concentration relative to the corresponding estimate; as in the originally published work (Tamaki et al.

2020), a 20% level of the Cramer-Rao lower bound was used for MRS exclusion. We assessed EEG quality using

the detrended fluctuation analysis (DFA) exponent coefficient criterion which Bruining et al. (2020) describe in

conjunction with the fE/I method; this involves estimating the DFA coefficient and excluding windows in which

the coefficient is less than .6. While the original sample included 18 participants' datasets, three participants had

only three or fewer remaining MRS values and were excluded from further analysis. This left 15 participants data,

with a mean number of 5-minute samples of 13.1 (i.e., 65.5 minutes).

Between-subjects associations between EEG measures and MRS-based E/I

Inter-individual differences in certain measures of EEG-E/I were correlated with MRS-E/I (see Figure 1 & Table

1). Each of the candidate algorithms produced E/I estimates with more than 5% of cross-validated predictive

variance explained in at least one frequency band (i.e., $dRsq_{oos} > .05$); we consider each of the links with positive

$dRsq_{oos}$ values to be reliable. The criticality-based fE/I approach derived from alpha oscillatory activity was most

closely linked to MRS-E/I across participants, followed by 1/f slope, then NMM-E/I derived from low beta activity,

and then fE/I derived from theta band. All other measures, including overall amplitudes, were not reliably predictive

of inter-individual differences in MRS-E/I. The lack of association with overall amplitudes provides a justification

for the candidate algorithms' approaches to estimating E/I ratio; further, the strong performance of criticality-based

alpha-band E/I supports the developer's findings regarding this algorithm (Bruining et al. 2020; Diachenko et al.

2024).

Figure 1. Between-subject associations between EEG-E/I measures and MRS-E/I. *Correlation of by-participant random intercepts from the Bayesian multivariate mixed-effects model Each panel is sorted by decreasing dRsq$_{oos}$ (i.e., measures at the top have the highest out-of-sample variance explained). Dashed line separates variables explaining reliable out-of-sample variance with those that do not; we consider all associations above the dashed line to be reliable.*

EEG measure	dRsq$_{oos}$	Correlation (r)
1/f slope	0.131	0.211
Amplitude: alpha	negative	0.081
Amplitude: lowBeta	negative	-0.054
Amplitude: theta	negative	-0.132
fE/I: alpha	0.190	0.258
fE/I: lowBeta	negative	-0.09
fE/I: theta	0.112	0.129
nmmEI: alpha	negative	0.106
nmmEI: lowBeta	0.103	0.066
nmmEI: theta	negative	-0.049

Table 1. Between-subject associations between EEG-E/I measures and MRS-E/I. *Each EEG measure's association with MRS-based E/I ratio is shown in the form of cross-validated out-of-sample variance explained (dRsq$_{oos}$) and effect size extracted from a Bayesian multivariate mixed-effects model (r). All dRsq$_{oos}$ values above zero are considered to be reliable, with values below replaced by "negative".*

Within-subjects associations between EEG measures and MRS-based E/I

After controlling for participant-level effects, several approaches to EEG-E/I were reliably associated with MRS-E/I (i.e., $dRsq_{oos} > 0$; see Figure 2 & Table 2). While this wide range of EEG-E/I approaches providing within-subjects out-of-sample predictiveness for MRS-E/I is promising, a closer investigation of the effects tempers this promise somewhat. First, although out-of-sample variance explained was positive, it was quite small, with only simple amplitude measures providing more than 1% of predictive value. Second, of the EEG measures with positive $dRsq_{oos}$ values, only theta amplitude had a positive correlation with MRS- based E/I ratio (r =.08). These results are in striking contrast to the between-subjects findings, where a relatively large amount of variance was explained with positive relations between EEG-E/I and MRS-E/I measures.

Figure 2. Within-subject associations between EEG-E/I measures and MRS-E/I.) Correlation of by-participant random intercepts from the Bayesian multivariate mixed-effects model. Each panel is sorted by decreasing $dRsq_{oos}$ (i.e., measures at the top have the highest out-of-sample variance explained). Dashed line indicates whether variables explained out-of-sample variance or did not; we consider all associations above the dashed line to be reliable.

EEG measure	$dRsq_{oos}$	Correlation (r)
1/f slope	negative	-0.079
Amplitude: alpha	0.021	-0.118
Amplitude: lowBeta	0.013	-0.097
Amplitude: theta	0.005	0.081
fE/I: alpha	0.004	-0.112

fE/I: lowBeta	0.001	-0.066
fE/I: theta	negative	0.051
nmmEI: alpha	0.009	-0.120
nmmEI: lowBeta	negative	0.009
nmmEI: theta	negative	-0.036

315 **Table 2. Within-subject associations between EEG-E/I measures and MRS-E/I.** *Each EEG measure's association*
316 *with MRS-based E/I ratio is shown in the form of cross-validated out-of-sample variance explained (dRsq$_{oos}$) and*
317 *effect size extracted from a Bayesian multivariate mixed-effects model (r). All dRsq$_{oos}$ values above zero are*
318 *considered to be reliable, with values below replaced by "negative".*

Discussion

We have seen that EEG can be used to estimate E/I ratio in a manner that is compatible with, but not wholly
overlapping with, variations in E/I ratio estimated from MRS. This mechanistic basis in the ratio between glutamate
and GABA was true for several distinct approaches to EEG-based E/I ratio. In particular, EEG-based E/I ratio
between-subjects was associated with MRS-based E/I ratio between-subjects, to the extent that they are comparable
to (or even larger than) the correlations between MRS neurotransmitter concentrations found when comparing
different estimation algorithms for MRS measures of GABA (Craven et al. 2022). In particular, the "functional E/I"
algorithm derived from criticality theory was most closely associated with between-subjects differences in MRS-
based E/I ratio; this reliance on temporal variations in alpha power corroborates the work of the developers of the
fE/I algorithm (Bruining et al., 2020; Diachenko et al., 2024). Beyond this criticality-based EEG-based E/I ratio
measure, each of the other EEG-based E/I ratio approaches were also positively associated with between-subjects
variations in MRS-based E/I ratio. These results showed broad support for each of the approaches, which were
themselves not highly correlated (see Figure S2). A lack of isomorphism between the EEG-based measures means
that future work may benefit from combining these algorithms to best characterize cortical E/I. The relative
contribution of estimates from separate frequencies is of particular interest; the generative mechanisms underlying
variations in theta, alpha, and beta rhythms provides the eletrophysiologist with a rich and multidimensional signal
from which to infer shifts in cortical states. Indeed, independent frequency bands have been previously associated
with glutamate and/or GABA levels (Porjesz et al., 2002; Tamaki et al., 2020), and a broad spectrum of frequencies
showed links to MRS-based E/I ratio when analyzed with different algorithms in the current work (i.e., theta and
alpha analyzed with fE/I; low beta analyzed with a neural mass model; gamma when calculating a 1/f slope). We
believe that combining amplitude and E/I estimates from several frequency bands may provide additional precision,
but we are hesitant to attempt such a combinatorial search within our limited dataset.
341
In contrast to between-subjects patterns of E/I ratio, within-subjects associations between MRS-based E/I ratio and
EEG-based E/I ratio were much weaker; indeed, only simple low beta amplitude was reliably associated with

within-subjects variations in MRS-based E/I ratio in the same direction (i.e., negative) as with between-subjects

variations in MRS-based E/I ratio. The reasons for the weakness of these associations cannot be known with

certainty, but it is likely to arise partly to a decrease in signal strength and an increase in noise when compared to

between-subject comparisons. That is, estimating EEG-based E/I ratio as well as MRS-based E/I ratio on windows

of only 5 minutes is likely to lead to relatively noisy estimates; while shorter measurement windows measuring

GABA with MRS have been used in the past (Frank et al. 2022), longer windows (e.g., 10 minutes) are more

standard. Unfortunately our available data is limited enough that estimating such within-subjects associations

between EEG-based E/I ratio and MRS-based E/I ratio appears to be largely overwhelmed by the reduced signal-

to-noise ratio; the MR context of these estimates may also have itself reduced data quality in estimating EEG-based

E/I.

There may be alternative sources of divergences between EEG-based and MRS-based E/I ratios. On one hand, the

neural mechanisms giving rise to each of our measured signals may be distinct; while MRS measured bulk

concentrations of molecules in a relatively deep and spatially precise portion of posterior cortex, our EEG

measurements were reflecting temporal variations in the activity of relatively superficial and widespread cortical

neurons. Similarly, the causal determinants of oscillatory activities, and their variations over time, are not yet known

with temporal or molecular precision; it may be the case that distinct cell types, neuromodulators, or long-range

connections are influencing EEG signals which would not be reflected in the measurement of Glx and GABA+ in

a single voxel within posterior cortices (Ahmad et al. 2022). The relations between EEG-based E/I ratios and MRS-

based E/I ratio may also be nonlinear, such that different EEG analysis algorithms could capture different aspects

of underlying MRS-based E/I ratio; larger datasets would be needed to determine whether an optimal combination

of EEG-based measures could better account for MRS-based E/I ratio.

Our results also reinforce the fact that the phenomena we are considering may be varying over time on

fundamentally different timescales. One of the most notable functions of variations in excitation and inhibition are

their changes over developmental time, that is, years or even decades (Hensch, 2004; Takesian & Hensch, 2013),

while in contrast, cognition-related modulation of E/I would necessarily operate on sub-minute timescales (Hellyer

et al., 2016). The methods we considered provide clear tendencies toward longer or shorter timescales, with MRS-

based measures needing a minimum of several minutes, NMM-based measures providing estimates which are

nominally relevant on the sub-second level, and the other methods falling somewhere in between. It may be possible,

then, that these measures simply do not reflect underlying cortical changes that operate on similar timescales,

leading to a lack of evident within-person relations between them.

Robust links between EEG-based E/I ratio and MRS-based E/I ratio at a between-subjects level provides validation

for EEG-based measures to be used in certain areas of research for which they have developed, namely, in

investigating special populations such as individuals with ASD (Bruining et al. 2020), Alzheimer's disease (van Nifterick et al., 2023), or monogenetic neurodevelopmental disorders (Geertjens et al., 2022). Our results indicate that the between-person differences in E/I revealed by contrasting these groups with healthy controls are likely to have common mechanistic bases (i.e. ratio of glutamate to GABA) whether they are measured using EEG or MRS. In contrast, for research which relies heavily on both within-person and between-person contrasts, such as the study of neuroplasticity (Shibata et al., 2017) or vigilance (Yang et al., 2023), EEG-based E/I ratio measures may not allow the assumption of mechanistic isomorphism.

While our results indicate that several recently developed algorithms for measuring E/I using EEG are indeed reflecting variations in the cortical ratio of glutamate to GABA, several limitations our present in our findings. The size of our dataset does not allow for precise estimates of effect sizes nor compelling rejection of candidate EEG-based E/I ratio measures, and the study of sleeping humans may lead to idiosyncratic results when contrasted to wakefulness; each of these limitations motivates future comparisons using concurrent multimodal imaging in awake humans.

Acknowledgements
We would like to thank our funding sources: NIH (K99EY034891, R01EY019466, R01EY027841, R01EY031705, P30GM149405); NSF-BSF (BCS2241417). We would also like to thank Michael Freund for invaluable input when designing the statistical analyses.

References

Ahmad, J., Ellis, C., Leech, R., Voytek, B., Garces, P., Jones, E., Buitelaar, J., Loth, E., Dos Santos, F. P., Amil, A. F., Verschure, P. F. M. J., Murphy, D., & McAlonan, G. (2022). From mechanisms to markers: Novel noninvasive EEG proxy markers of the neural excitation and inhibition system in humans. *Translational Psychiatry*, *12*(1), 467. https://doi.org/10.1038/s41398-022-02218-z

Balz, J., Keil, J., Roa Romero, Y., Mekle, R., Schubert, F., Aydin, S., Ittermann, B., Gallinat, J., & Senkowski, D. (2016). GABA concentration in superior temporal sulcus predicts gamma power and perception in the sound-induced flash illusion. *NeuroImage*, *125*, 724–730. https://doi.org/10.1016/j.neuroimage.2015.10.087

Bruining, H., Hardstone, R., Juarez-Martinez, E. L., Sprengers, J., Avramiea, A.-E., Simpraga, S., Houtman, S. J., Poil, S.-S., Dallares, E., Palva, S., Oranje, B., Matias Palva, J., Mansvelder, H. D., & Linkenkaer-Hansen, K. (2020). Measurement of excitation-inhibition ratio in autism spectrum disorder using critical brain dynamics. *Scientific Reports*, *10*(1), 9195. https://doi.org/10.1038/s41598-020-65500-4

Burle, B., Spieser, L., Roger, C., Casini, L., Hasbroucq, T., & Vidal, F. (2015). Spatial and temporal resolutions of EEG: Is it really black and white? A scalp current density view. *International Journal of Psychophysiology*, *97*(3), 210–220. https://doi.org/10.1016/j.ijpsycho.2015.05.004

Craven, A. R., Bhattacharyya, P. K., Clarke, W. T., Dydak, U., Edden, R. A. E., Ersland, L., Mandal, P. K., Mikkelsen, M., Murdoch, J. B., Near, J., Rideaux, R., Shukla, D., Wang, M., Wilson, M., Zöllner, H. J., Hugdahl, K., & Oeltzschner, G. (2022). Comparison of seven modelling algorithms for γ-aminobutyric acid-edited proton magnetic resonance spectroscopy. *NMR in Biomedicine*, *35*(7), e4702. https://doi.org/10.1002/nbm.4702

Dale, G., Cochrane, A., & Green, C. S. (2021). Individual difference predictors of learning and generalization in perceptual learning. *Attention, Perception, & Psychophysics*. https://doi.org/10.3758/s13414-021-02268-3

Delorme, A., & Makeig, S. (2004). EEGLAB: An open source toolbox for analysis of single-trial EEG dynamics including independent component analysis. *Journal of Neuroscience Methods*, *134*(1), 9–21. https://doi.org/10.1016/j.jneumeth.2003.10.009

Diachenko, M., Sharma, A., Smit, D. J. A., Mansvelder, H. D., Bruining, H., De Geus, E., Avramiea, A.-E., &

Linkenkaer-Hansen, K. (2024). Functional excitation-inhibition ratio indicates near-critical oscillations

across frequencies. *Imaging Neuroscience*, *2*, 1–17. https://doi.org/10.1162/imag_a_00318

Duncan, N. W., Wiebking, C., & Northoff, G. (2014). Associations of regional GABA and glutamate with

intrinsic and extrinsic neural activity in humans—A review of multimodal imaging studies. *Neuroscience*

and Biobehavioral Reviews, *47*, 36–52. https://doi.org/10.1016/j.neubiorev.2014.07.016

Edden, R. A. E., Muthukumaraswamy, S. D., Freeman, T. C. A., & Singh, K. D. (2009). Orientation

discrimination performance is predicted by GABA concentration and gamma oscillation frequency in

human primary visual cortex. *The Journal of Neuroscience: The Official Journal of the Society for*

Neuroscience, *29*(50), 15721–15726. https://doi.org/10.1523/JNEUROSCI.4426-09.2009

Gao, R., Peterson, E. J., & Voytek, B. (2017). Inferring synaptic excitation/inhibition balance from field

potentials. *NeuroImage*, *158*, 70–78. https://doi.org/10.1016/j.neuroimage.2017.06.078

Geertjens, L., van Voorst, T. W., Bouman, A., van Boven, M. A., Kleefstra, T., Verhage, M., Linkenkaer-Hansen,

K., Nadif Kasri, N., Cornelisse, L. N., & Bruining, H. (2022). Following Excitation/Inhibition Ratio

Homeostasis from Synapse to EEG in Monogenetic Neurodevelopmental Disorders. *Genes*, *13*(2), 390.

https://doi.org/10.3390/genes13020390

Hahn, G., Ponce-Alvarez, A., Monier, C., Benvenuti, G., Kumar, A., Chavane, F., Deco, G., & Frégnac, Y.

(2017). Spontaneous cortical activity is transiently poised close to criticality. *PLoS Computational*

Biology, *13*(5), e1005543. https://doi.org/10.1371/journal.pcbi.1005543

He, B. J. (2014). Scale-free brain activity: Past, present, and future. *Trends in Cognitive Sciences*, *18*(9), 480–487.

https://doi.org/10.1016/j.tics.2014.04.003

Hellyer, P. J., Jachs, B., Clopath, C., & Leech, R. (2016). Local inhibitory plasticity tunes macroscopic brain

dynamics and allows the emergence of functional brain networks. *NeuroImage*, *124*(Pt A), 85–95.

https://doi.org/10.1016/j.neuroimage.2015.08.069

Hensch, T. K. (2004). Critical Period Regulation. *Annual Review of Neuroscience*, *27*(1), 549–579.

https://doi.org/10.1146/annurev.neuro.27.070203.144327

Juarez Martinez, E. L., Bruining, H., Sprengers, J., Simpraga, S., Houtman, S., Poil, S.-S., Mansvelder, H. D.,

Jansen, F., Oranje, B., Hardstone, R., & Linkenkaer-Hansen, K. (2019). O-20 Epileptiform and non-

epileptiform EEG abnormalities in Autism Spectrum Disorder relate to opposite excitation-inhibition

balance disturbances. *Clinical Neurophysiology*, *130*(7), e27–e28.

https://doi.org/10.1016/j.clinph.2019.04.336

Kat, R., Linkenkaer-Hansen, K., Koopmans, M. A., Houtman, S. J., Bruining, H., & Kas, M. J. H. (2024).

Assessment of the excitation-inhibition ratio in the Fmr1 KO2 mouse using neuronal oscillation

dynamics. *Cerebral Cortex (New York, N.Y.: 1991)*, *34*(5), bhae201.

https://doi.org/10.1093/cercor/bhae201

Lendner, J. D., Helfrich, R. F., Mander, B. A., Romundstad, L., Lin, J. J., Walker, M. P., Larsson, P. G., &

Knight, R. T. (2020). An electrophysiological marker of arousal level in humans. *eLife*, *9*, e55092.

https://doi.org/10.7554/eLife.55092

Linkenkaer-Hansen, K., Nikouline, V. V., Palva, J. M., & Ilmoniemi, R. J. (2001). Long-range temporal

correlations and scaling behavior in human brain oscillations. *The Journal of Neuroscience: The Official

Journal of the Society for Neuroscience*, *21*(4), 1370–1377. https://doi.org/10.1523/JNEUROSCI.21-04-

01370.2001

Porjesz, B., Almasy, L., Edenberg, H. J., Wang, K., Chorlian, D. B., Foroud, T., Goate, A., Rice, J. P., O'Connor,

S. J., Rohrbaugh, J., Kuperman, S., Bauer, L. O., Crowe, R. R., Schuckit, M. A., Hesselbrock, V.,

Conneally, P. M., Tischfield, J. A., Li, T.-K., Reich, T., & Begleiter, H. (2002). Linkage disequilibrium

between the beta frequency of the human EEG and a GABAA receptor gene locus. *Proceedings of the

National Academy of Sciences of the United States of America*, *99*(6), 3729–3733.

https://doi.org/10.1073/pnas.052716399

Provencher, S. W. (1993). Estimation of metabolite concentrations from localized *in vivo* proton NMR spectra.

Magnetic Resonance in Medicine, *30*(6), 672–679. https://doi.org/10.1002/mrm.1910300604

Scott, K. E., King, R. A., Cochrane, A., Kalish, C., & Shutts, K. (2023). Direct Assessments of Social Skills Can

Complement Teacher Ratings in Predicting Children's Academic Achievement. *Journal of Cognition and

Development*, 1–25. https://doi.org/10.1080/15248372.2023.2216291

Shibata, K., Sasaki, Y., Bang, J. W., Walsh, E. G., Machizawa, M. G., Tamaki, M., Chang, L.-H., & Watanabe, T.

(2017). Overlearning hyperstabilizes a skill by rapidly making neurochemical processing inhibitory-

dominant. *Nature Neuroscience*, *20*(3), 470–475. https://doi.org/10.1038/nn.4490

Takesian, A. E., & Hensch, T. K. (2013). Balancing Plasticity/Stability Across Brain Development. In *Progress in*

Brain Research (Vol. 207, pp. 3–34). Elsevier. https://doi.org/10.1016/B978-0-444-63327-9.00001-1

Tamaki, M., Wang, Z., Barnes-Diana, T., Guo, D., Berard, A. V., Walsh, E., Watanabe, T., & Sasaki, Y. (2020).

Complementary contributions of non-REM and REM sleep to visual learning. *Nature Neuroscience*,

23(9), 1150–1156. https://doi.org/10.1038/s41593-020-0666-y

van Nifterick, A. M., Mulder, D., Duineveld, D. J., Diachenko, M., Scheltens, P., Stam, C. J., van Kesteren, R. E.,

Linkenkaer-Hansen, K., Hillebrand, A., & Gouw, A. A. (2023). Resting-state oscillations reveal disturbed

excitation-inhibition ratio in Alzheimer's disease patients. *Scientific Reports*, *13*(1), 7419.

https://doi.org/10.1038/s41598-023-33973-8

Yang, B., Zhang, H., Jiang, T., & Yu, S. (2023). Natural brain state change with E/I balance shifting toward

inhibition is associated with vigilance impairment. *iScience*, *26*(10), 107963.

https://doi.org/10.1016/j.isci.2023.107963

Yokoyama, H., & Kitajo, K. (2023). A data assimilation method to track excitation-inhibition balance change

using scalp EEG. *Communications Engineering*, *2*(1), 92. https://doi.org/10.1038/s44172-023-00143-7

Supplemental Material

Bayesian Multivariate Linear Mixed-Effects Model

The following is a schematic showing the specification of the Bayesian Multivariate Linear Mixed-Effects Model

(BMVLMEM) estimated using **rstan** via **brms**, with each outcome variable modeled with a Gaussian response

distribution. Within the same model, and estimated simultaneously, all outcome variables (to the left of the tilde)

were predicted by a group-level intercept, an autoregressive term *ar()* of order 1 grouped by subject and with the

number of the 5-minute block as the variable *time*, and a subject-level intercept. In addition, the correlation matrix

of the subject-level intercepts was estimated (*subjectR*). Because this model specification accounted for effects of

time and inter-individual differences, the remaining variance left unexplained was intra-individual variation. The

correlation matrix of residuals, estimated in conjunction with the full BMVLMEM, therefore represented the within-

subjects associations between the outcome variables. Note that our primary interest was linking each EEG measure

with MRS-based E/I ratio, which we report in the main results. We also report the remainder of the correlation

matrices, including correlations between EEG measures and with Glx and GABA+ estimates, below (see Figure

S2). We tested the robustness of this model by fitting alternate models excluding the autoregressive terms as well

as modeling the outcome variables as Student T distributions rather than Gaussian, but these did not change the

qualitative pattern of results, and we report only the results of this primary model here.

Figure S1. Bayesian Multivariate Mixed-Effects Model specification and correlation matrix estimation.

Associations among EEG measures

In addition to our primary questions regarding links between EEG-E/I measures and MRS-based E/I, we

additionally explored two additional questions. First, we assessed the extent to which different EEG-based measures

of E/I were themselves collinear; second, we assessed the associations between each EEG-E/I measure was

associated with either Glx or GABA+, as opposed to these molecules' ratio in the form of MRS-E/I. To assess these

relations we extracted the by-participant random intercepts and the residual correlations from the Bayesian

multivariate linear mixed-effects model (see Figure S1 & S2; see also Figures 1b, 2b).

Figure S2. Correlations among measures apart from MRS-E/I (i.e., EEG measures as well as separated Glx and

GABA+ concentration estimates). Above the diagonal are between-subjects correlations (see Figure 1b); below the

diagonal are within-subjects correlations (see Figure 2b). Cells of EEG measures with reliable out-of-sample

predictiveness of MRS-E/I are outlined. All estimates are drawn from a single multivariate mixed-effects model.

Across-channel correlations

One way to assess the reliability of EEG-based measures, which were each estimated separately for each channel, was to examine the correlations between the same measure across the posterior channels we analyzed. Due to our interest in relatively macro-scale changes in E/I, as well as the basic properties of volume conduction (Burle et al. 2015), we expected that our EEG-based E/I estimates would have highly positive correlations with one another; this would indicate that the underlying algorithms are computationally stable and that our data quality was high. For most measures we do observe the expected large positive correlations between channels, although the NMM-based estimates are much more weakly inter-correlated (See Figure S3). Broadly, then, we see that measures of amplitude, fE/I, and 1/f slope all demonstrate expected cross-channel correlations indicating reliability, while the low correlations of NMM measures may be due to true underlying ability to measure independent measures from nearby electrodes, or may be due to computational instability of the NMM approach; further investigation of this topic may be of interest for future research.

Figure S3. Median rank correlations between analyzed posterior channels' estimates of EEG-E/I. Most estimates were highly correlated across channels, although NMM-based estimates had relatively low cross-channel reliability.

Ratio of between-subjects to within-subjects variance

As a second exploration into the consistency of within-subjects estimates, which may influence the reliability of

within-subjects E/I measures, we examined the ratio of between-subjects variance to within-subjects variance.

Figure S4. Ratios of between-subjects variances to within-subjects variances. Most measures had less than a 3:1

ratio of these variances, with MRS-based E/I having between-subjects variances approximately 1.45 times as large

as within-subjects variances.