Altair-LSFM A High-Resolution, Easy-to-Build Light-Sheet Microscope for Sub-Cellular Imaging.

John Haug[1,2], Seweryn Gałecki[1,2,3], Hsin-Yu Lin[1,2], Xiaoding Wang[1,2], and Kevin M. Dean[1,2]

Affiliations:

[1] *Lyda Hill Department of Bioinformatics, UT Southwestern Medical Center, Dallas, TX 75390, USA.*

[2] *Cecil H. and Ida Green Center for Systems Biology, UT Southwestern Medical Center, Dallas, TX 75390, USA.*

[3] *Department of Systems Biology and Engineering, Silesian University of Technology, Akademicka 16, 44-100 Gliwice, Poland.*

Correspondence:
kevin.dean@utsouthwestern.edu

Abstract

Although several open-source, easy-to-assemble light-sheet microscope platforms already exist—such as mesoSPIM, OpenSPIM, and OpenSpin—they are optimized for imaging large specimens and lack the resolution required to visualize sub-cellular features, such as organelles or cytoskeletal architectures. In contrast, Latice Light-Sheet Microscopy (LLSM) achieves the resolution necessary to resolve such fine structures but, in its open-source implementation, can be alignment- and maintenance-intensive, often requiring specialist expertise. To address this gap, we developed Altair-LSFM, a high-resolution, open-source, sample-scanning light-sheet microscope specifically designed for sub-cellular imaging. By optimizing the optical pathway in silico, we created a custom baseplate that greatly simplifies alignment and assembly. The system integrates streamlined optoelectronics and optomechanics with seamless operation through our open-source software, *navigate*. Altair-LSFM achieves lateral and axial resolutions of approximately 235 nm and 350 nm, respectively, across a 266-micron field of view after deconvolution. We validate the system's capabilities by imaging sub-diffraction fluorescent nanospheres and visualizing fine structural details in mammalian cells, including microtubules, actin filaments, nuclei, and Golgi apparatus. We further demonstrate its live-cell imaging capabilities by visualizing microtubules and vimentin intermediate filaments in actively migrating cells.

Introduction

Light-sheet fluorescence microscopy (LSFM) has revolutionized volumetric imaging by enabling rapid, minimally invasive 3D investigations of diverse biological specimens[1]. By illuminating the sample with a thin sheet of light from the side and capturing 2D images in a highly parallel format, LSFM dramatically reduces photobleaching and out-of-focus blur. Although the optical foundations of LSFM were established as early as 1903 and later adapted for cleared specimens[2], it was the demonstration of LSFM on living, developing embryos in 2004[1] that triggered a wave of innovation, leading to specialized variants tailored to diverse biological contexts. Collectively, these methods have facilitated the long-term tracking of cells through embryological development[3], the mapping of brain architecture[4] and activation patterns[5], and much more, making LSFM indispensable for a wide array of dynamic, 3D imaging applications.

While these milestones underscore LSFM's transformative potential, it wasn't until the early 2010s that researchers harnessed LSFM for sub-cellular imaging[6]. Achieving this level of detail requires optimization of both resolution and sensitivity, parameters fundamentally governed by the numerical aperture (NA) of the microscope objectives used. In LSFM, lateral resolution depends on the fluorophore's emission wavelength and the NA of the detection objective, whereas photon collection efficiency scales with the square of the detection NA. Consequently, high-NA objectives are essential for resolving fine, low abundance biological structures while maximizing signal collection. Axial resolution, in turn, is set by the detection objective's depth of focus and the thickness of the illumination beam. When the illumination beam is thinner than the depth of focus, its thickness defines the axial resolution[7]; conversely, when the beam is thicker than the depth of focus, the depth of focus defines the axial resolution, and fluorescence elicited outside this region contributes to the image as blur. Importantly, there is a trade-off between field of view, axial resolution, and NA: pushing for high axial resolution often constrains the accessible field of view, necessitating careful mechanical and optical design choices.

Bounded by these fundamental constraints, several methods have been developed to achieve sub-cellular resolution in LSFM. For example, one can illuminate the specimen with a propagation-invariant beam[6] or an optical lattice[8]. This can be done coherently, as in Lattice Light-Sheet Microscopy (LLSM)[8], or incoherently, as in Field Synthesis[9]. However, the four-beam "square" optical lattice, which was used in 16 of the 20 figure subpanels in the

original LLSM study, was later found to provide little measurable improvement in resolution or sectioning compared to a traditional Gaussian beam[10]. Another approach, dual view inverted Selective Plane Illumination Microscopy (diSPIM), captures images from multiple orthogonal perspectives and computationally fuses them using iterative deconvolution, significantly improving axial resolution[11]. However, this method requires precise image registration and intensive computational processing. Axially Swept Light-sheet Microscopy (ASLM)[12] extends the field of view while maintaining high axial resolution but operates at lower speeds and sensitivity compared to LLSM and diSPIM, making it less suitable for fast volumetric imaging. Oblique plane microscopy (OPM) offers another alternative by imaging an obliquely launched light-sheet with a non-coaxial and complex optical train, allowing for single-objective light-sheet imaging but introducing substantial alignment challenges[13]. While these techniques offer powerful solutions for sub-cellular imaging, they all require expert assembly and routine alignment, limiting their widespread adoption. Turn-key commercial variants, such as the ZEISS Lattice Lightsheet 7, offer automated operation and high stability but remain costly and allow limited end-user modifiability. As a result, there remains a critical need for a high-resolution, accessible LSFM system that combines state-of-the-art imaging performance with straightforward assembly, reproducibility, and lower cost.

To address these limitations, we developed Altair-LSFM, a high-resolution, open-source light-sheet microscope that achieves sub-cellular detail while remaining accessible and easy to use. Altair-LSFM is built upon two guiding optical principles. First, in LLSM, the sole improvement in lateral resolution comes from the use of a higher-NA detection objective, which we incorporate to maximize both resolution and photon collection efficiency. Second, when diffraction effects are fully accounted for, a tightly focused Gaussian beam achieves a beam waist and propagation length that is comparable to that of a square lattice, eliminating the need for specialized optical components while preserving high axial resolution. By leveraging these principles, Altair-LSFM delivers optical performance on par with LLSM but without the added design complexity of LLSM. To streamline assembly and ensure reproducibility, we designed the optical layout for Altair-LSFM in silico, enabling a pre-defined optical alignment with minimal degrees of freedom. A custom-machined baseplate with precisely positioned dowel pins locks optical components into place, minimizing degrees of freedom and removing the need for fine manual adjustments. Additionally, by simplifying the optomechanical design and integrating compact optoelectronics, Altair-LSFM reduces system complexity, making advanced light-sheet imaging more practical for a wider range of laboratories.

By combining high-resolution imaging with an accessible and reproducible design, Altair-LSFM addresses a critical gap in LSFM—bringing sub-cellular imaging capabilities to a broader scientific community. Its reliance on fundamental microscopy principles rather than overly complex optical systems ensures both performance and simplicity, while its modular architecture allows for straightforward assembly and operation. By eliminating the need for specialized optics and intricate alignment procedures, Altair-LSFM significantly lowers the barrier to adoption, making advanced light-sheet imaging feasible for laboratories that lack the resources or expertise to implement more complex systems. This combination of performance, accessibility, and scalability establishes Altair-LSFM as a powerful and practical solution for a wide range of laboratories.

Results

Survey of Open-Source LSFM Designs.

Before designing Altair-LSFM, we first evaluated existing open-source LSFM implementations to identify common design features, constraints, and trade-offs (**Table 1**). Many systems, such as UC2[14], pLSM[15], and EduSPIM[16], were explicitly developed with cost-effectiveness in mind, relying on low-cost components and simplified designs to maximize accessibility. Others, including OpenSPIM[17,18], OpenSPIN[19], and mesoSPIM[20,21], were optimized for imaging large specimens, such as developing embryos or chemically cleared tissues. Most of these systems employed modular construction methods based on rail carriers or cage systems, which, while reducing alignment complexity compared to free-space optics, still retain degrees of freedom that can lead to misalignment and increase setup difficulty. Moreover, these microscopes generally operate at low magnification and low NA, limiting their ability to resolve sub-cellular structures. Among the surveyed designs, only diSPIM[11,22] was explicitly developed for sub-cellular imaging, built with a dovetail-based system for precise optical alignment. However, diSPIM's most widely deployed configuration uses NA 0.8 objectives, which limits its photon collection efficiency and resolution. Consequently, the cell biology community lacks an open-source light-sheet microscope that combines state-of-the-art resolution with ease of assembly, robust optical alignment, and streamlined computational processing.

Design Principles of Altair-LSFM.

Building on these findings, we designed Altair-LSFM to achieve performance comparable to the open-source
variant of LLSM[8] while maintaining a compact footprint and streamlined assembly. Although cost-effectiveness was
an important consideration throughout the design process, achieving sensitive, high-resolution imaging necessitated
the use of high-NA optics, precision stages, stable laser sources, and high-performance, low-noise, high quantum
efficiency cameras, all of which inherently increase system cost. To streamline procurement and integration, we
minimized the number of required manufacturers while maintaining high-performance components. Including our
optical table and laser source, the estimated price for Altair-LSFM is $150,000. A detailed list of all system
components, their sources, and associated costs is provided in **Supplementary Tables 1 and 2**, and a broader
discussion of the design trade-offs, including the rationale for proprietary versus open-source hardware, and
associated cost-benefit considerations, is provided in **Supplementary Note 1**.
This initial iteration of Altair-LSFM is specifically designed for imaging thin, adherent cells on 5 mm glass
coverslips in aqueous media (n ~ 1.33). For imaging such specimens, a sample-scanning approach is preferred over
a light-sheet-scanning approach, as it minimizes the optical path length through the specimen, enabling use of more
tightly focused illumination beams that improve axial resolution (**Supplementary Figure 1**). If optical tiling is
employed, Altair-ASLM could also be used for imaging expansion microscopy specimens[4]. While Altair-LSFM could
be used for superficial imaging in semi-transparent embryos, systems implementing multiview illumination and
detection schemes are generally better suited for such specimens[23]. Similarly, cleared tissue imaging typically requires
high-refractive index media (~1.45-1.56) and solvent-compatible objectives, along with methods such as ASLM or
diSPIM that decouple the tradeoff between field of view and axial resolution[24,25].
Altair-LSFM is configured with a detection path that is nearly identical to that of LLSM, ensuring similar
resolution (~230 nm × 230 nm × 370 nm) and photon collection efficiency. Specifically, it includes a 25x NA 1.1
water-dipping physiology objective (Nikon N25X-APO-MP) with a 400 mm achromatic tube lens (Applied Scientific
Instrumentation), ensuring Nyquist sampling (130 nm pixel size) across the full width of a standard 25 mm CMOS
camera (Hamamatsu Orca Flash 4.0 v3), yielding a total field of view of 266 microns. Emission filters were positioned
in the focusing space immediately before the camera, and the entire detection assembly was built around a dovetail-
based tube system, to ensure robust alignment and mechanical stability (**Figure 1a**). To facilitate precise axial
positioning and accommodate different sample types, the entire detection assembly was mounted on a 50 mm travel
focusing stage.
With the detection path establishing the necessary criteria for resolution, field of view, and optical alignment
(e.g., beam height), we next designed the illumination system. In LSFM, the foci of the illumination and detection
objectives must precisely overlap without mechanical interference, limiting the choice of compatible objectives. To
meet these requirements, we selected a 20x NA 0.6 long-working distance water immersion objective (Thorlabs
TL20X-MPL). The spacing between this combination of illumination and detection objectives limits the size of usable
coverslips to 5 mm, a constraint that is shared by the original LLSM design. While handling and mounting small
coverslips can be challenging, we addressed this by designing a custom-machined coverslip holder to streamline the
mounting process. For users wishing to accommodate larger coverslips, the Nikon 25x objective can be substituted
with a Zeiss W Plan-Apochromat 20x/1.0, whose slimmer form factor allows the co-focus between the illumination
and detection objectives to occur beyond the physical body of the lenses, enabling the use of virtually any coverslip
size[26]. Guided by these constraints, we selected optical components capable of generating a theoretically diffraction-
limited light-sheet using straightforward magnification calculations.
The complete illumination system was designed for a collimated input beam with a 2 mm diameter, which
first passes through an achromatic doublet lens (f = 30 mm) and then a second achromatic doublet (f = 80 mm) that
expands and re-collimates it. After expansion, the beam passes through a rectangular aperture before reaching an
achromatic cylindrical lens (f = 75 mm). The rectangular aperture is conjugate to the back pupil plane of the
cylindrical lens, enabling precise tuning of the light-sheet's NA, and consequently its thickness and propagation
length. This adjustability allows optimization of the light-sheet for specimens of different thicknesses. The cylindrical
lens focuses the beam in one direction to form the initial light-sheet, and its focal length was chosen to provide
sufficient spacing between optical elements for practical assembly. The shaped beam is then directed onto a resonant
galvanometer, which improves illumination uniformity by rapidly pivoting the light-sheet to average out shadowing
artifacts arising from scattering and absorption within the sample (conceptual example shown in **Supplementary
Figure 2**)[27,28]. After reflection from a 45-degree tilted mirror, the beam is relayed through an achromatic doublet (f =
250 mm) before entering the back aperture of the illumination objective, where it is finally focused onto the sample.
This optical arrangement ensures a well-defined, dynamically pivoted light-sheet that provides uniform illumination
while mitigating shadowing effects.

162
<u>In Silico Optimization of Altair-LSFM.</u>
To ensure optimal illumination performance, we modeled the full illumination pathway of Altair-LSFM in
Zemax OpticStudio (Ansys), systematically optimizing the relative placement of every optical element to achieve the
desired focusing and collimation properties (**Figure 1b**). Each lens was iteratively adjusted to minimize aberrations
and ensure precise beam shaping, enabling the formation of a well-defined light-sheet. The design was centered
around a 488 nm illumination wavelength, with spatial axes defined following standard conventions: the Y-dimension
represents the laser propagation direction, Z corresponds to the detection axis, and X is orthogonal to both. The final
illumination system, depicted in **Figure 1b**, was optimized to generate a diffraction-limited light-sheet with a full-
width-half-maximum (FWHM) of ~0.385 μm in Z, spanning the full 266 μm field of view, as shown in **Figures 1c-**
d.
Beyond idealized modeling, designing a physically realizable system requires an understanding of how
fabrication tolerances affect optical performance. To assess system robustness, we performed a tolerance analysis,
which quantifies sensitivity to mechanical perturbations. This analysis evaluates how small positional or angular
deviations of optical elements—caused by manufacturing imperfections—impact key performance metrics such as
light-sheet thickness and displacement from the ideal position, allowing us to systematically evaluate system stability
(**Supplementary Figure 3a**). The perturbations analyzed were based on standard machining tolerances, typically
±0.005 inches, with higher-precision machining achievable at ±0.002 inches at increased cost. Given that Altair-
LSFM was designed assuming the use of Polaris mounts, which incorporate DIN-7m6 ground dowel pins to aid with
alignment, we considered the impact of angular misalignments caused by dowel pin positioning errors. In the worst-
case scenario—where one dowel pin was offset by +0.005 inches and the other by -0.005 inches—the resulting
angular deviation was ~1.45 degrees (**Supplementary Figure 3b**). To further assess system resilience, we conducted
Monte Carlo simulations incorporating these perturbations, simulating a range of misalignment scenarios to quantify
their effect on light-sheet performance. Our results showed that finer machining tolerances resulted in a worst-case
performance closer to the nominal system, as visualized in **Supplementary Figure 3c**, which compares the nominal,
best, and worst configurations. Notably, the analysis identified that angular offsets in the galvo mirror had the most
significant impact on light-sheet quality, highlighting the importance of tighter machining tolerances for this
component to maximize system stability and performance.
190
<u>Optomechanical Design of Altair-LSFM.</u>
Based on our simulation results, standard machining tolerances were deemed sufficient to construct a custom
baseplate that ensures robust alignment and a compact, plug-and-play design. Unlike cage- or rail-based systems,
custom baseplates minimize variability by enforcing a fixed spatial relationship between optical components,
enabling assembly by non-experts. Where possible, we eliminated all unnecessary degrees of freedom, restricting
manual adjustments to only a few critical components. Specifically, we retained laser collimation (tip/tilt/axial
position), galvo rotation, folding mirror alignment (tip/tilt), and objective positioning (tip/tilt/axial position).
To translate the numerically optimized positions of each optical element into a manufacturable design, the
coordinates were imported into computer-aided design (CAD) software (Autodesk Inventor), ensuring precise
positioning of all associated optomechanics. Where possible, Polaris optical posts and mounts were used to maintain
consistency in mounting schemes and element heights. For components where a commercially available Polaris-
compatible mount did not exist, such as the rotation mount (Thorlabs RSP1) for the cylindrical lens and the horizontal
aperture (Thorlabs VA100), custom adapters were developed to seamlessly integrate them into the system. This
approach allowed us to account for the offset between the optical element and its mechanical mount, ensuring that
the baseplate was precisely machined with dowel pin locations and mounting holes (**Figure 2a, Supplementary**
Figure 4). Additionally, the baseplate features four mounting holes at its corners, spaced such that it can be directly
secured to an optical table or elevated using additional posts, allowing for easy adjustment of the illumination path
height. This modular, precision-engineered design is meant to ensure both ease of use and general mechanical
stability, enabling integration of Altair-LSFM into alternative experimental setups.
Beyond the illumination path, the full microscope system is visualized in **Supplementary Figure 5**. It
incorporates a variety of translational and custom mounting elements to facilitate precise sample positioning and
stable imaging. A sample chamber was designed and 3D printed to match the working distances and clearances of the
chosen illumination and detection objectives, offering two port configurations: one for traditional orthogonal imaging
and another linear configuration that allows direct imaging of the light-sheet itself (**Figure 2b, Supplementary**
Figure 6). Each port is equipped with two sets of O-rings, creating a liquid-proof seal around the objectives while

still permitting smooth translation of the detection objective for focusing. Additionally, the snug fit of the O-rings
naturally guide the user toward proper positioning of the illumination and detection objectives, decreasing the
likelihood of alignment errors. The sample positioning assembly consists of three motorized translation stages
(Applied Scientific Instrumentation), enabling precise positioning of the sample in x, y, and z. To enable rapid Z-
stack acquisition, we designed an angled bracket ($\theta = 29.5$ degrees) for mounting a high-speed piezo (PiezoConcept
HS1.100), which attaches directly to the sample positioning stages (**Figure 2c**). The sample is secured using a custom-
designed sample holder for 5 mm glass coverslips, which features a clam-based mechanism-the coverslip is placed
within a circular recess and secured in place by a screw-down clamp. Due to the angled sample scanning
configuration, our collected image stacks must undergo a deskewing operation. All custom component designs, and
deskewing software, are available for download at https://thedeanlab.github.io/altair.

Optoelectronic Design of Altair-LSFM.
In addition to simplifying the optomechanical design, we also streamlined the electronics and control
architecture of Altair-LSFM to minimize complexity and improve system integration. To achieve this, we
consolidated all control electronics into a single controller (TG16-BASIC, Applied Scientific Instrumentation), which
manages the operation of all linear translation stages (X, Y, Z, and F), as well as the power supply for the resonant
galvo and sample scanning piezo. This approach significantly reduces the number of auxiliary controllers and power
supplies, simplifying the physical setup. Currently, all timing operations are performed using a 32-channel analog
output device (PCIe-6738, National Instruments), which is responsible for generating the global trigger, controlling
the camera's external trigger, modulating the laser through analog and digital signals, setting the piezo control voltage,
and providing the DC voltage for adjusting the resonant galvo amplitude. The resonant galvo used for shadow
reduction operates at 4 kHz, ensuring that it is not rate-limiting for any acquisition mode described here. An overview
of the electronics used in the system, along with an associated wiring diagram, is provided in **Supplementary Figure
7** and **Supplementary Table 3**.
All control electronics are operated through *navigate*, our open-source light-sheet microscope control
software, which integrates hardware coordination, waveform generation, and data acquisition within a unified
software environment[29]. The combined performance of the control electronics and *navigate* defines the system's
maximum temporal resolution. Mechanically, the acquisition of a z-stack is constrained by the response time of the
sample-scanning piezo. Approximating the piezo as a first-order system gives a characteristic response time of ~0.35/f
(seconds), where f is the actuator's resonant frequency[30]. For our piezo (HS100, PiezoConcept), this gives an ideal
response time of ~0.23 ms; however, accounting for additional physical considerations such as the weight of a sample
holder, we expect this value to realistically be on the order of 1-5 ms for small step sizes. We also evaluated the rate
at which a Z-stack could be acquired with *navigate* using representative settings for coverslip-mounted cells (50-
micron z-stack, 0.25-micron step size, camera field of view of 512x2048). With a 10 ms exposure time, the system
achieved image acquisition rates as fast as 62.5 Hz, with an average dead time of ~7.25 ms due to camera readout
and piezo stepping (**Supplementary Table 4**). Moreover, as demonstrated previously, the data-writing performance
of *navigate* varies slightly depending on imaging parameters (e.g., number of z-slices and time points, owing to
metadata overhead), with write speeds surpassing 1 gigavoxel/s under optimal conditions[29]. Consequently, the
integrated hardware and control software establish a unified, optoelectronic platform that balances performance,
stability, and accessibility for advanced light-sheet applications.

Alignment and Characterization of Altair-LSFM.
To evaluate optical performance, we first assembled and aligned the Altair-LSFM illumination system. The
fiber-coupled laser source (Oxxius L4CC), which provides four excitation wavelengths (405 nm, 488 nm, 561 nm,
and 638 nm), was introduced and collimated using tip/tilt mounts. The collimated beam was then directed onto the
resonant galvo, which was rotated to reflect the beam downward toward the optical table. From there, the folding
mirror was adjusted to guide the beam along the optical axis of the remaining components. Finally, the lateral position
of the illumination objective was fine-tuned to ensure coaxial back-reflections, completing the alignment process.
With the optical path aligned, we proceeded to validate system performance by characterizing the generated light-
sheet, where visualization of the light-sheet is accomplished by a solution of fluorescein in transmission. As shown
in **Figure 3a**, the light-sheet focus spans the full 266 µm field of view, closely matching our simulation results. Cross-
sectional analysis of the full-width-at-half-maximum (FWHM) in the z-dimension, presented in **Figure 3b**, reveals a
z-FWHM of ~0.415 µm.

To assess the system's resolution, we imaged 100 nm fluorescent beads. Our image-processing pipeline involves first deskewing our acquired volumetric image stack using custom Python routines, and then deconvolution via PetaKit5D[31] (see Methods). The need for shearing arises when the scan axis does not align with the optical detection axis, as is the case for LLSM and Altair-LSFM when operating in a sample-scanning format, as well as both sample-scanning and laser-scanning OPMs. The point spread function of a single isolated fluorescent bead is shown in **Figures 3c-e**. The Gaussian-fitted distribution of FWHM measurements, performed on a population of fluorescent beads across a z-stack, is shown in **Figure 3f**. Prior to deconvolution, the average FWHM values measured across the bead population were 328 nm in x, 330 nm in y, and 464 nm in z. After deconvolution with PetaKit5D, these values improved to 235.5 nm in x, 233.5 nm in y, and 350.4 nm in z, achieving our desired resolution goals for sub-cellular imaging.

Sub-Cellular Imaging with Altair-LSFM

        To demonstrate the imaging capabilities of Altair-LSFM in a biological context, we prepared and imaged mouse embryonic fibroblasts (MEFs) cells stained for multiple subcellular structures. The staining protocol enabled visualization of the nucleus (DAPI, 405 nm, cyan), microtubules (488 nm, gray), actin filaments (561 nm, gold), and the Golgi apparatus (638 nm, magenta), corresponding to the excitation channels of our system. Deconvolved maximum intensity projections of the labeled cells is shown in **Figure 4a** and **Figure 4f**, with each individual corresponding fluorescence channel presented in **Figures 4b-e** and **Figures 4g-j**. The imaging results reveal fine nucleolar features within the nucleus, with perinuclear Golgi structures distinctly visible. Additionally, stress fibers are clearly resolved in the actin channel, and individual microtubules appear well-defined, highlighting the system's ability to capture cytoskeletal structures with high resolution. These results confirm that Altair-LSFM provides the sub-cellular resolution, optical sectioning, and multi-color imaging performance necessary for quantitative biological imaging applications. To further assess performance in live specimens, we demonstrated dual-channel live-cell imaging. We modified the sample chamber to provide temperature control (**Supplementary Note 2, Supplementary Figure 8**) and imaged retinal pigment epithelial (RPE) cells with endogenously GFP and TagRFP-T tagged microtubules and vimentin, respectively (**Supplementary Video 1, Figure 5**). The cells exhibited robust motility, with time-lapse sequences revealing continuous, cell-side reorganization of microtubule and vimentin intermediate filaments throughout their bodies. Together, the fixed- and live-cell results establish that Altair-LSFM supports high-contrast, multi-color volumetric imaging at sub-cellular resolution in both static and dynamic cellular contexts.

Discussion:

        In this work, we demonstrated the viability of a baseplate-based approach for the dissemination a high-performance light-sheet microscope that is both accessible and straightforward to assemble by non-experts. By combining optical simulations, precision-machined component design, and experimental validation, we developed Altair-LSFM, a system that delivers sub-cellular resolution imaging with minimal alignment requirements. Characterization using fluorescent beads confirmed that Altair-LSFM achieves a resolution of 328, 330, and 464 nm before deconvolution, which improves to ~235 and 350 nm after deconvolution, in XY, and Z, respectively. These values are on par with the original, open-source version of LLSM (~230 and 370 nm, in XY, and Z, respectively[32]), confirming that our approach achieves state-of-the-art performance but in a streamlined, cost-effective, and optically less complex format. For example, the open-source LLSM illumination path includes approximately 29 optical components, each requiring precise lateral, angular, and coaxial alignment and maintenance. In contrast, Altair-LSFM contains only nine such elements. By this metric, Altair-LSFM is considerably simpler to assemble and maintain, further supporting our overarching goal of making high-resolution LSFM systems accessible to non-specialist laboratories. Nonetheless, it is worth noting that the original LLSM system offered a greater number of illumination modes (e.g., square, hexagonal, and structured illumination) and supported imaging in both a sample- and light-sheet scanning configurations (**Supplementary Note 3**). A complete parts list, and estimated cost, are provided in **Supplementary Tables 1 and 2**, respectively, offering a transparent roadmap for users looking to adopt and build the system. To aid planning, **Supplementary Table 5** summarizes expected build and validation times, stratified by prior experience with optical system assembly and operation.

        A number of open-source designs have also extended LSFM into the sub-cellular regime, including implementations of LLSM and diSPIM. These platforms have been instrumental in advancing dissemination and training within the imaging community, though they typically require routine optical alignment and operation by dedicated personnel. Commercial LLSM instruments from 3i and ZEISS have increased the availability of LLSM and have contributed substantially to disseminating this technology. According to vendor materials, the ZEISS variant

of LLSM provides automated operation and long-term stability, providing a user-friendly, turn-key solution for sub-cellular imaging. The system's design, which incorporates a meniscus lens to enable oblique imaging through a coverslip, simplifies setup and usability, albeit with a modest reduction in achievable resolution (reported deconvolved resolution: ~290 x 450-900 nm) relative to the original LLSM implementation and Altair-LSFM. However, acquisition and service costs remain high, and system modification by end users is limited. Altair-LSFM addresses a different need: an openly documented, modifiable, and reproducible path to sub-cellular LSFM that non-specialist laboratories can build, customize, and maintain at a fraction of the cost of a commercial system.

Building on this successful prototype, future efforts will focus on expanding both imaging capabilities and user experience. One natural evolution of this approach is the development of more advanced light-sheet microscope designs, such as ASLM[12,33] and OPM[13,34], which offer additional flexibility for imaging a broader range of sample types. Notably, OPM avoids the challenges associated with non-standard sample mounting and, owing to its single objective architecture, is fully compatible with standard environmental chambers used for live-cell imaging. Another avenue for improvement is the optimization of Altair-LSFM for cleared-tissue imaging, further extending its applicability into tissue contexts. Additionally, we aim to eliminate the need for an external analog output device, consolidating all triggering and waveform generation within a single unified controller, which will further reduce hardware dependencies and enhance system efficiency.

Another important consideration is the long-term scalability and routine maintenance of Altair-LSFM in a variety of lab environments. Multi-site benchmarking and community feedback will be pivotal to ensure consistent, reproducible performance across different setups. To aid planning, we also provide guidance on data storage in **Supplementary Note 4**. Future enhancements—such as self-alignment routines—could further boost imaging quality and throughput. To accelerate widespread adoption, we have thoroughly documented the entire assembly process in our GitHub repository[35], which is also provided as a **Supplementary Document.** Although the construction of custom optical systems may seem intimidating to non-experts, our dissemination strategy draws inspiration from other successful open-source projects such as mesoSPIM, which has seen widespread adoption, including >30 implementations worldwide, through a similar model of exhaustive documentation, open-source control software, and community support via user meetings and workshops. For expert users who wish to tailor the instrument, we also provide all Zemax illumination-path simulations and CAD files, along with step-by-step optimization protocols, enabling modification and re-optimization of the optical system as needed. These customization resources are intended for users with prior experience in optical and optomechanical design, while the default configuration remains turnkey for non-experts.

A persistent challenge in advanced microscopy is the lengthy interval—from instrument conceptualization to commercialization—often spans close to a decade. By fostering open collaboration and continuous software-hardware integration, we envision Altair-LSFM evolving into a robust, ever-improving platform, well-suited to meet future research challenges in high-resolution, volumetric imaging. Integrating these systems with *navigate*[29], we aim to further democratize intelligent imaging workflows and broaden the reach of cutting-edge instrumentation (**Supplementary Note 5**). With high-NA imaging, reduced mechanical and optical complexity, and lower cost, Altair-LSFM stands poised to accelerate LSFM adoption, delivering a powerful yet accessible solution for researchers immediately seeking access to high-resolution, cutting-edge, volumetric imaging.

Acknowledgements

The authors would like to thank Calvin Jones and Dr. Sophia Theodossiou (Boise State University) for their assistance in designing and printing the custom sample chamber, and Melissa Glidewell for her initial evaluation of optical tolerances. This work was supported by the National Institutes of Health (U54CA268072 and RM1GM145399).

Conflicts of Interest

K.M.D. is a co-inventor on a patent covering ASLM and a founder of Discovery Imaging Systems, LLC. K.M.D. also has consultancy agreements with 3i, Inc (Denver, CO, USA).

Author Contributions

J.H., formal analysis, investigation, methodology, validation, visualization, and writing. S.G. and H.L, resources, visualization, and writing. X.W., investigation, methodology. K.M.D. funding acquisition, investigation, methodology, project administration, software, resources, supervision, visualization, and writing.

Materials and Methods

Acquisition and Simulation Computer.

  All microscope control and optical simulations were performed on a Colfax SX6300 workstation, configured to handle high-speed data acquisition and processing. It is equipped with dual Intel Xeon Silver 4215R processors (8 cores, 16 threads, 3.2 GHz), 256 GB of DDR4 3200 MHz ECC RAM, a 7.68 TB Samsung PM9A3 NVMe SSD for high-speed data acquisition, a 20 TB Seagate Exos X20 HDD for long-term data storage, a PNY NVIDIA T1000 4 GB GPU, and an Intel X710-T2L dual-port 10GbE.

Cell Culture.

  All cells were maintained at 37°C in a humidified incubator with 5% CO_2 and cultured in a 12-well plate on 5 mm cover slips, pre-rinsed with 70% ethanol. Mouse embryonic fibroblasts (MEFs) were cultured in Dulbecco's Modified Eagle's Medium (DMEM, Gibco) supplemented with 10% fetal bovine serum (FBS, Gibco) and 100 μg/mL penicillin-streptomycin. RPE-hTERT Vimentin-GFP/mTubulin-RFP cells were generated by TALEN-based genome editing[36] and grown in ATCC-formulated DMEM/F12 supplemented with 10% FBS and 1% antibiotic–antimycotic. For imaging, cells were seeded on 5-mm round #0 coverslips placed in 6-well plates. During imaging, the coverslip was secured in a chamber and bathed in prewarmed media. Specifically, U2OS cells were imaged in FluoroBrite DMEM (Thermo Fisher) containing 5% FBS and 1% Anti-Anti, and RPE hTERT cells were imaged in DMEM/F12 medium without phenol red, supplemented with 5% FBS and 1% Anti-Anti. All imaging procedures were performed at 37 °C

Immunofluorescence.

  MEFs were cultured to approximately 50% confluency before processing. Cells were first rinsed with pre-heated (37°C) 1x Phosphate-Buffered Saline (PBS), and then briefly permeabilized and fixed with pre-heated PEM buffer [80 mM PIPES, 5 mM EGTA, 2 mM $MgCl_2$, (pH: 6.8)], supplemented with 0.3% Triton-X and 0.125% glutaraldehyde (GA) for 30 seconds. A secondary fixation was then performed in preheated PEM buffer containing 2% paraformaldehyde (PFA) for 15 minutes at 37 °C. Following fixation, cells were washed three times with 1x PBS (2 minutes each). Unless otherwise indicated, all subsequent incubations were performed at room temperature with constant agitation. Residual aldehydes were quenched using 5 mM glycine for 10 minutes, after which the cells were blocked for 1 hour in 3% bovine serum albumin (BSA) and 0.01% Triton-X in 1x PBS. For indirect immunofluorescence, cells were incubated overnight at 4°C with primary antibodies diluted in staining buffer [1% BSA + 0.01% Triton-X in 1x PBS]: mouse anti-α-Tubulin (Sigma-Aldrich, #T9026, 1:250) and rabbit anti-GOLGA/GM130 (Proteintech, #11308-1-AP, 1:500). After three washes with PBST (1x PBS containing 0.01% Triton-X, 2 minutes each), cells were incubated for 1 hour with secondary antibodies diluted in staining buffer: donkey anti-mouse CF488A (Biotium, #20014-1, 1:500) and donkey anti-rabbit AlexaFluor 647 (Thermo Fisher Scientific, #A-31573, 1:500). Actin filaments were stained with phalloidin-CF568 (Biotium, #00044, 1:50) in 1x PBS for 1 hour. Finally, cells were incubated in DAPI nuclear dye (Thermo Fisher Scientific, #62248, 300 nM) in 1x PBS for 10 min. Samples were stored at 4°C in 1x PBS with 0.02% sodium azide (NaN_3) until imaging.

Preparation of Fluorescent Bead Samples.

  A 5 mm glass coverslip was placed inside a petri dish, and approximately 100 μL of (3-Aminopropyl)triethoxysilane (APTS) at a concentration of 5 mM was applied to its surface. The APTS was incubated for 10–30 minutes to promote bead adhesion, after which the coverslip was lightly washed three times with deionized water. Fluorescent beads (Fluoresbrite YG Microspheres 0.10 μm, Polyscience, Inc) were diluted to the desired concentration (typically 10^{-3} or 10^{-4} for a normal distribution, 10^{-6} for a sparse distribution) and applied to the treated coverslip, where they were incubated for 2–20 min, with longer incubation times increasing bead density. Finally, the coverslip was lightly washed with deionized water to remove unbound beads before imaging.

Image Deskewing.

  After image acquisition, deskewing was performed to correct for the non-orthogonal scanning geometry between the piezo stage and the optical axes of the microscope. A custom Python script available on our GitHub repository, was used to perform deskewing. The user provides the path to the image stack along with the relevant imaging parameters: z-step size, xy pixel size, and the deskew angle. In our configuration, the deskew angle corresponds to 90°–60.5°, where 60.5° represents the angle between the normal of the sample mount and the microscope's y-axis.

431
432 <u>Image Deconvolution.</u>
433   Deconvolution was performed using PetaKit5D[37] with standard operating parameters. All datasets were
processed with a background level set to 100, and two iterations of the Optical Transfer Function Masked Wiener
(OMW) deconvolution algorithm were applied. The Wiener parameter (alpha) was set to 0.005, the Optical Transfer
Function Cumulative Threshold to 0.6, and the Hann window bounds to 0.8–1. No edge erosion was applied, and the
resulting data were saved as 16-bit images. PSFs were simulated using the PSFGenerator[38] package according to the
illumination wavelength and numerical aperture of the light sheet, and the emission wavelength and numerical
aperture of the detection objective. PSFs were modeled using the Richards & Wolf 3D Optical Model with a refractive
index of 1.3333.
441
442 <u>Custom Machining and Fabrication.</u>
443   All metal components were machined from 6061-T6x aluminum by Protolabs or Xometry, adhering to
444 standard machining tolerances of ±0.005 inches. The original sample chamber was 3D printed using a Formlabs Form
445 3B resin printer with standard black resin. Our live-cell sample chamber was machined from 6061-T6x aluminum
446 from Xometry. CAD files for all custom parts and procedures on how to place an order from Xometry using them are
447 provided as a supplementary file, with up-to-date versions available on GitHub.
448
449

REFERENCES

Huisken, J., Swoger, J., Del Bene, F., Wittbrodt, J. & Stelzer, E. H. Optical sectioning deep inside live embryos by selective plane illumination microscopy. *Science* **305**, 1007-1009 (2004). https://doi.org/10.1126/science.1100035

Voie, A. H., Burns, D. H. & Spelman, F. A. Orthogonal-plane fluorescence optical sectioning: three-dimensional imaging of macroscopic biological specimens. *J Microsc* **170**, 229-236 (1993). https://doi.org/10.1111/j.1365-2818.1993.tb03346.x

Lange, M. *et al.* A multimodal zebrafish developmental atlas reveals the state-transition dynamics of late-vertebrate pluripotent axial progenitors. *Cell* **187**, 6742-6759 e6717 (2024). https://doi.org/10.1016/j.cell.2024.09.047

Gao, R. *et al.* Cortical column and whole-brain imaging with molecular contrast and nanoscale resolution. *Science* **363** (2019). https://doi.org/10.1126/science.aau8302

Ahrens, M. B., Orger, M. B., Robson, D. N., Li, J. M. & Keller, P. J. Whole-brain functional imaging at cellular resolution using light-sheet microscopy. *Nat Methods* **10**, 413-420 (2013). https://doi.org/10.1038/nmeth.2434

Planchon, T. A. *et al.* Rapid three-dimensional isotropic imaging of living cells using Bessel beam plane illumination. *Nat Methods* **8**, 417-423 (2011). https://doi.org/10.1038/nmeth.1586

Gao, L., Shao, L., Chen, B. C. & Betzig, E. 3D live fluorescence imaging of cellular dynamics using Bessel beam plane illumination microscopy. *Nat Protoc* **9**, 1083-1101 (2014). https://doi.org/10.1038/nprot.2014.087

Chen, B. C. *et al.* Lattice light-sheet microscopy: imaging molecules to embryos at high spatiotemporal resolution. *Science* **346**, 1257998 (2014). https://doi.org/10.1126/science.1257998

Chang, B.-J. *et al.* Universal light-sheet generation with field synthesis. *Nature Methods* **16**, 235-238 (2019). https://doi.org/10.1038/s41592-019-0327-9

Chang, B.-J., Dean, K. M. & Fiolka, R. Systematic and quantitative comparison of lattice and Gaussian light-sheets. *Optics Express* **28** (2020). https://doi.org/10.1364/oe.400164

Wu, Y. *et al.* Spatially isotropic four-dimensional imaging with dual-view plane illumination microscopy. *Nat Biotechnol* **31**, 1032-1038 (2013). https://doi.org/10.1038/nbt.2713

Dean, Kevin M., Roudot, P., Welf, Erik S., Danuser, G. & Fiolka, R. Deconvolution-free Subcellular Imaging with Axially Swept Light Sheet Microscopy. *Biophysical Journal* **108**, 2807-2815 (2015). https://doi.org/10.1016/j.bpj.2015.05.013

Sapoznik, E. *et al.* A versatile oblique plane microscope for large-scale and high-resolution imaging of subcellular dynamics. *eLife* **9** (2020). https://doi.org/10.7554/eLife.57681

Diederich, B. *et al.* A versatile and customizable low-cost 3D-printed open standard for microscopic imaging. *Nat Commun* **11**, 5979 (2020). https://doi.org/10.1038/s41467-020-19447-9

Chen, Y. *et al.* Low-cost and scalable projected light-sheet microscopy for the high-resolution imaging of cleared tissue and living samples. *Nat Biomed Eng* **8**, 1109-1123 (2024). https://doi.org/10.1038/s41551-024-01249-9

Jahr, W., Schmid, B., Weber, M. & Huisken, J. eduSPIM: Light Sheet Microscopy in the Museum. *PLoS One* **11**, e0161402 (2016). https://doi.org/10.1371/journal.pone.0161402

Girstmair, J., Moon, H., Brillard, C., Haase, R. & Tomancak, P. Time to Upgrade: A New OpenSPIM Guide to Build and Operate Advanced OpenSPIM Configurations. *Adv Biol (Weinh)* **6**, e2101182 (2022). https://doi.org/10.1002/adbi.202101182

Pitrone, P. G. *et al.* OpenSPIM: an open-access light-sheet microscopy platform. *Nat Methods* **10**, 598-599 (2013). https://doi.org/10.1038/nmeth.2507

Gualda, E. J. *et al.* OpenSpinMicroscopy: an open-source integrated microscopy platform. *Nat Methods* **10**, 599-600 (2013). https://doi.org/10.1038/nmeth.2508

Vladimirov, N. *et al.* Benchtop mesoSPIM: a next-generation open-source light-sheet microscope for cleared samples. *Nat Commun* **15**, 2679 (2024). https://doi.org/10.1038/s41467-024-46770-2

Voigt, F. F. *et al.* The mesoSPIM initiative: open-source light-sheet microscopes for imaging cleared tissue. *Nat Methods* **16**, 1105-1108 (2019). https://doi.org/10.1038/s41592-019-0554-0

Kumar, A. *et al.* Dual-view plane illumination microscopy for rapid and spatially isotropic imaging. *Nature Protocols* **9**, 2555-2573 (2014). https://doi.org/10.1038/nprot.2014.172

23 McDole, K. *et al.* In Toto Imaging and Reconstruction of Post-Implantation Mouse Development at the
Single-Cell Level. *Cell* **175**, 859-876 e833 (2018). https://doi.org/10.1016/j.cell.2018.09.031
24 Chakraborty, T. *et al.* Light-sheet microscopy of cleared tissues with isotropic, subcellular resolution. *Nature*
Methods **16**, 1109-1113 (2019). https://doi.org/10.1038/s41592-019-0615-4
25 Guo, M. *et al.* Rapid image deconvolution and multiview fusion for optical microscopy. *Nat Biotechnol* **38**,
1337-1346 (2020). https://doi.org/10.1038/s41587-020-0560-x
26 Moore, R. P. *et al.* A multi-functional microfluidic device compatible with widefield and light sheet
microscopy. *Lab Chip* **22**, 136-147 (2021). https://doi.org/10.1039/d1lc00600b
27 Huisken, J. & Stainier, D. Y. Even fluorescence excitation by multidirectional selective plane illumination
microscopy (mSPIM). *Opt Lett* **32**, 2608-2610 (2007). https://doi.org/10.1364/ol.32.002608
28 Ricci, P. *et al.* Removing striping artifacts in light-sheet fluorescence microscopy: a review. *Prog Biophys*
Mol Biol **168**, 52-65 (2022). https://doi.org/10.1016/j.pbiomolbio.2021.07.003
29 Marin, Z. *et al.* Navigate: an open-source platform for smart light-sheet microscopy. *Nat Methods* (2024).
https://doi.org/10.1038/s41592-024-02413-4
30 Franklin, G. F. P., J. D.; Emami-Naeini, A. *Feedback Control of Dynamic Systems*. 8th edition edn, (Pearson,
2019).
31 Ruan, X. *et al.* Image processing tools for petabyte-scale light sheet microscopy data. *Nat Methods* **21**, 2342-
2352 (2024). https://doi.org/10.1038/s41592-024-02475-4
32 Chen, B.-C. *et al.* Lattice light-sheet microscopy: Imaging molecules to embryos at high spatiotemporal
resolution. *Science* **346** (2014). https://doi.org/10.1126/science.1257998
33 Dean, K. M. *et al.* Isotropic imaging across spatial scales with axially swept light-sheet microscopy. *Nature*
Protocols (2022). https://doi.org/10.1038/s41596-022-00706-6
34 Chang, B.-J. *et al.* Real-time multi-angle projection imaging of biological dynamics. *Nature Methods* **18**,
829-834 (2021). https://doi.org/10.1038/s41592-021-01175-7
35 Dean, K. M., Haug, J. & Gałecki, S. *altair*, <https://thedeanlab.github.io/altair/> (2025).
36 Gan, Z. *et al.* Vimentin Intermediate Filaments Template Microtubule Networks to Enhance Persistence in
Cell Polarity and Directed Migration. *Cell Syst* **3**, 500-501 (2016). https://doi.org/10.1016/j.cels.2016.11.011
37 Liu, G. *et al.* Characterization, comparison, and optimization of lattice light sheets. *Sci Adv* **9**, eade6623
(2023). https://doi.org/10.1126/sciadv.ade6623
38 Kirshner, H., Aguet, F., Sage, D. & Unser, M. 3-D PSF fitting for fluorescence microscopy: implementation
and localization application. *J Microsc* **249**, 13-25 (2013). https://doi.org/10.1111/j.1365-2818.2012.03675.x
39 Otomo, K. *et al.* descSPIM: an affordable and easy-to-build light-sheet microscope optimized for tissue
clearing techniques. *Nat Commun* **15**, 4941 (2024). https://doi.org/10.1038/s41467-024-49131-1
40 Liu, Y., Rollins, A. M. & Jenkins, M. W. CompassLSM: axially swept light-sheet microscopy made simple.
Biomed Opt Express **12**, 6571-6589 (2021). https://doi.org/10.1364/BOE.440292
41 Lamb, J. R., Mestre, M. C., Lancaster, M. & Manton, J. D. Direct-view oblique plane microscopy. *Optica* **12**,
469-472 (2025). https://doi.org/10.1364/OPTICA.558420
42 McDermott, S. *et al.* Multi-modal microscopy imaging with the OpenFlexure Delta Stage. *Opt Express* **30**,
26377-26395 (2022). https://doi.org/10.1364/OE.450211
43 Dean, K. M. *et al.* Diagonally Scanned Light-Sheet Microscopy for Fast Volumetric Imaging of Adherent
Cells. *Biophys J* **110**, 1456-1465 (2016). https://doi.org/10.1016/j.bpj.2016.01.029
44 Voigt, F. F. *et al.* The mesoSPIM initiative: open-source light-sheet microscopes for imaging cleared tissue.
Nat Methods **16**, 1105-1108 (2019). https://doi.org/10.1038/s41592-019-0554-0
45 Yang, B. *et al.* Epi-illumination SPIM for volumetric imaging with high spatial-temporal resolution. *Nat*
Methods **16**, 501-504 (2019). https://doi.org/10.1038/s41592-019-0401-3
46 Chen, B. *et al.* Increasing the field-of-view in oblique plane microscopy via optical tiling. *Biomed Opt*
Express **13**, 5616-5627 (2022). https://doi.org/10.1364/BOE.467969
47 Chen, B. *et al.* Resolution doubling in light-sheet microscopy via oblique plane structured illumination.
biorxiv (2022). https://doi.org/10.1101/2022.05.19.492671
48 McFadden, C. *et al.* Adaptive optics in an oblique plane microscope. *Biomed Opt Express* **15**, 4498-4512
(2024). https://doi.org/10.1364/BOE.524013
49 Edelstein, A., Amodaj, N., Hoover, K., Vale, R. & Stuurman, N. Computer control of microscopes using
microManager. *Curr Protoc Mol Biol* **Chapter 14**, Unit14 20 (2010).
https://doi.org/10.1002/0471142727.mb1420s92

558
559 **FIGURES**
560

561
Figure 1. (a) Rendering of the detection arm elements. (b) Zemax Opticstudio layout and beam path of optimized illumination
arm, where L1, L2, L3, and L4 are 30-, 80-, 75-, and 250-mm achromatic doublets, respectively, and ILO is the TL20X-MPL
illumination objective. (c) The simulated light-sheet beam profile in the xz plane at the focus of the illumination objective. The
inset shows an enlarged region of the illumination light-sheet, highlighting light-sheet thickness and uniformity. (d) The cross-
sectional profile through the center of the light-sheet beam profile in (c), where the FWHM of the light-sheet was found to be
0.382 µm.
568
569
570

Figure 2. (a) Rendering of the completed illumination arm baseplate, with an inset showing the dowel pin holes compatible with the Polaris mounting line from Thorlabs. (b) Overhead view of the imaging configuration of our system, where our detection objective and illumination objectives are placed orthogonal to each other and the sample is scanned diagonally in the space between them in the axial direction shown by the white dashed line. (c) Rendering of our sample mounting and translation system. Here, a piezo motor is mounted onto an angled adapter to allow precise translation over the diagonal region between the objectives. Our custom 5 mm coverslip sample holder is also featured, where the inset shows an exploded assembly of the holder.

579
Figure 3. (a) Experimental light-sheet beam profile at the focus. The light-sheet was visualized in a transmission geometry with
fluorescence derived from a fluorescein solution. (b) The center cross-section profile of (a), showing both raw data and a fitted
curve with a FWHM of ~0.415 μm. (c–e) Maximum-intensity projections for an isolated 100 nm fluorescent bead. All three
orthogonal perspectives are provided to reveal any potential optical aberrations. A slight degree of coma is observable in the XZ
view. (f) Gaussian-fitted distribution of the FWHM of beads imaged in a z-stack in each dimension both before (solid) and after
(dashed) deconvolution.
586
587

589
Figure 4. Lateral maximum intensity projections of mouse embryonic fibroblasts (MEFs) fluorescently labeled with nuclei
(cyan), tubulin (gray), actin (gold), and the Golgi apparatus (magenta). (a) Maximum intensity projection of the full z-stack in
the xy plane. (b–e) Individual channels corresponding to (a): (b) nuclei, (c) microtubules, (d) actin, and (e) Golgi apparatus. (f)
Maximum intensity projection of a second z-stack in the xy plane. (g–j) Individual channels corresponding to (f): (g) nuclei, (h)
microtubules, (i) actin, and (j) Golgi apparatus. Nuclei were labeled with DAPI, actin filaments with phalloidin, and both
microtubules and the Golgi apparatus were stained using indirect immunofluorescence.

602
603 **Figure 5.** Selected time points from a time-lapse sequence of actively migrating retinal pigment epithelial (RPE) cells, showing
604 vimentin (blue) and microtubules (orange). The series comprises 50 frames; representative time points are displayed.
605
606

607
608

Microscope	Illumination Optics	Detection Optics	Design
OpenSPIM[18]	Olympus UMPLFLN 10XW NA 0.3 (Water)	UMPLFLN 20XW NA 0.5 (Water)	Rail Carrier
X-OpenSPIM[17]	Nikon CFI Plan Fluor 10X NA 0.3 (Water)	Nikon CFI Apochromat NIR 40X W NA 0.8 (Water)	Rail Carrier
EduSPIM[16]	Zeiss LSFM 5X NA 0.1 (Air)	Zeiss LD Epiplan 5X NA 0.13 (Air)	Cage System
OpenSPIN[19]	Nikon CFI Plan Fluor 4X NA 0.13 (Air) Nikon Plan Fluor 10X NA 0.3 (Air)	Nikon CFI Plan Fluor 4X NA 0.13 (Air) Nikon CFI75 LWD 16X NA 0.8 (Water)	Rail Carrier
UC2[14]	Generic 4X NA 0.14 (Air)	Generic 4X NA 0.14 (Air) Generic 10X NA 0.3 (Air)	3D Printed Components
pLSM[15]	Mitutoyo Plan Apo 10X NA 0.28 (Air)	Mitutoyo Plan Apo 10X NA 0.28 (Air) ASI 54-10-12 16.67X NA 0.4 (Multi-Immersion)	Cage System
descSPIM[39]	500- and 150-mm cylindrical lenses (Air)	Thorlabs TL2X-SAP 2X NA 0.1 (Air)	Cage System
mesoSPIM[21]	Nikon 50 mm f/1.4 G (Air)	Olympus MVPLAPO 1X NA 0.15 (Air)	Rail Carrier
BT-mesoSPIM[20]	Nikon 50 mm f/1.4 G (Air)	Variable. Magnification 2-20X, NA 0.1-0.28 (Air)	Cage System
diSPIM[11]	Nikon CFI Apochromat NIR 40X W NA 0.8 (Water)	Nikon CFI Apochromat NIR 40X W NA 0.8 (Water)	Dovetail Tube System
CompassLSM[40]	Olympus XLFLUOR 4x NA 0.28 (Air/Water)	Olympus MVX PLAPO 1x NA 0.25 (Air) Olympus MVX PLAPO 2XC NA 0.5 (Air) Olympus UPlanFL 4x NA 0.13 (Air) Nikon CFI Plan Apo 10XC NA 0.5 (Water)	Rail Carrier
Lattice Light-Sheet Microscopy (LLSM)[8]	Special Optics 54-10-7 28.6X NA 0.67 (Water)	Nikon CFI75 Apochromat 25XC NA 1.1 (Water)	Free Space Optics
Altair-LSFM	Thorlabs TL20X-MPL 20X NA 0.6 (Water)	Nikon CFI75 Apochromat 25XC NA 1.1 (Water)	Custom Baseplate & Dovetail Tube System

609 **Table 1. LSFM variants and their associated illumination and detection optics.** The table lists the type of microscope, the
610 illumination and detection optics-including NA where available and immersion type in parentheses-as well as the overall design
611 architecture (e.g., rail carrier, cage system, etc.).

SUPPLEMENTARY FIGURES

Supplementary Figure 1. Comparison of sample- and light-sheet-scanning modes. (a) In high-resolution light-sheet
microscopy, the specimen must be positioned precisely at the intersection of the illumination and detection objective focal planes.
To minimize aberrations in the excitation (blue) and detection (green) light paths, the specimen must be mounted at an angle that
prevents marginal rays from interacting with the coverslip. In this configuration, only a narrow cross-section of an adherent cell
is illuminated. (b) With a sample-scanning approach, the illumination beam requires a propagation length just sufficient to cover
the thickest portion of the specimen—typically the nucleus—at the angle defined by the coverslip. For Altair-LSFM, the sample
is mounted at ~30°, so a 6 μm-thick nucleus requires a beam propagation length of 6 μm / sin 30° ≈ 12 μm, which can be achieved
with an illumination NA of ~0.285, producing a beam thickness of ~1 μm. The acquired volume is indicated by the dashed
outline. (c) In contrast, a light-sheet-scanning configuration—where the light sheet and detection objective are synchronously
translated in z—must generate a beam long enough to span the full cell diameter. For an adherent cell ~30 μm in diameter, the
sheet must extend 30 μm / sin 30° ≈ 60 μm, requiring an illumination NA of ~0.128 and yielding a sheet thickness of ~2.3 μm.
Together, these schematics illustrate how sample scanning enables the use of shorter, thinner light sheets that improve axial
resolution while maintaining uniform illumination. The illumination NA required to achieve a given beam propagation length
was estimated using the PSFGenerator package[38].

628
629
630
631

633
Supplementary Figure 2. Educational illustration depicting the conceptual function of the resonant galvo unit. Without pivoting
of the light-sheet, objects within a sample can cast shadows due to scattering or refraction. When the resonant galvo is engaged,
the illumination sheet rapidly pivots at a frequency of 4 kHz such that the sample is effectively illuminated from multiple
directions, and the shadows are correspondingly displaced. As a result, light effectively "reaches around" objects, and the
shadows are averaged out over the image acquisition period. This figure is intended as a conceptual aid to help readers visualize
the role of the resonant galvo rather than act as a quantitative representation.
640

642
643
644 **Supplementary Figure 3.** (a) Depiction of the merit function criteria used in our tolerance analysis, where we observed how the
645 beam profile in the perturbed instances changes in both size and position. (b) Schematic of the Polaris dowel pin mounting
646 configuration when considering machining tolerances, where in a worst-case scenario the angle offset would be 1.454 degrees.
647 (c) Nominal, best case, and worst-case beam profiles in xz for both coarse (+-0.005", top row) and fine (+-0.002", bottom row)
648 machining tolerances.
649

650
651
652 **Supplementary Figure 4.** Process of affixing a post to the baseplate, where one first places the post onto dowel pins inserted
653 into the corresponding holes and then fixes the post to the baseplate with a screw.
654

656
657 **Supplementary Figure 5.** CAD rendering of our full system consisting of an illumination path, a detection path, and a dedicated
658 sample positioning assembly.
659
660

Double O-Ring Grooves

662
663
664 **Supplementary Figure 6.** (a) CAD rendering of our custom sample chamber, featuring three possible objective ports, each with
665 two sets of O-rings to ensure a liquid-proof seal. (b) Top-down rendering of the traditional imaging configuration for the system,
666 where the illumination and detection objectives are placed orthogonal to one another. (c) The second transmissive imaging
667 configuration of the system used to image the beam itself, where the illumination objective is place directly in front of the
668 detection objective.

669
670 **Supplementary Figure 7.** General wiring diagram of the system showing all the optoelectrical and optomechanical components
671 used, and an inset showing how these components are wired into the NI DAQ.
672
673

675
676 **Supplementary Figure 8.** CAD renderings of our custom heated sample chamber design. This updated design utilizes
677 thermocouples and heating pad elements for temperature regulation, enabling live-cell imaging capabilities for Altair-LSFM.
678
679
680

681
682

683
684 **Supplementary Video 1.** Representative frame from a time-lapse of four RPE-hTERT cells with endogenously tagged
685 cytoskeletal markers: microtubules (red) and vimentin (blue).
686
687

SUPPLEMENTARY TABLES

Name	Manufacturer	Description	Qty	Approximate Cost
Shared Equipment				
TG16-BASIC	ASI	Tiger Controller – 16 Bay System	1	$6,350
PCIe-6738	NI	Data Acquisition Card	1	$2,200
SCB-68A	NI	Noise Rejecting Terminal Block	1	$500
SHC68-68-A2	NI	Test Cable Assembly	1	$250
784-736-02R	TMC	36x60x18" Performance Series Optical Top	1	$6,275
14UD-42X-24	TMC	Ultradamp Vibration Isolation with Casters	1	$9,300
SX6300	Colfax International	Colfax SX6300 Workstation	1	$6,800
Detection Path				
LS-100-AMCCH	ASI	100 mm Linear Focusing Stage, 16 TPI	1	$2,250
TGDCM2	ASI	2-Axis Stage Control Card	1	$1,050
C60-EXT-15	ASI	15 mm Tube Extension	1	$75
RAO-0051	ASI	M32x0.75 Threaded Sleeve	1	$150
FW-0002-8	ASI	8-Position Filter Wheel	1	$3,500
FW-C-MNT-K1	ASI	Filter Wheel to MIM Adapter Kit	1	$400
C60-TUBE-400	ASI	400 mm Achromatic Tube Lens	1	$875
TGFW	ASI	Filter Wheel Control Card	1	$1,150
C13440-20CU	Hamamatsu	ORCA Flash4.0 V3	1	$16,500
OH-CAMRA-1007	Hamamatsu	Firebird CamLink Board	1	$2,000
N25X-APO-MP	Thorlabs	Nikon 25x NA 1.1 Detection Objective	1	$33,810
445/20-25nm	Semrock	Brightline Bandpass filter	1	$375
529/24nm	Semrock	Brightline Bandpass filter	2	$375
605/15-25nm	Semrock	Brightline Bandpass filter	1	$375
676/29-25nm	Semrock	Brightline Bandpass filter	1	$375
Sample Positioning				
LS-5012	ASI	Breadboard Adapter	1	$160
LS-5013	ASI	Right Angle Bracket	1	$250
DV-6010-C	ASI	Dovetail Mount Pair	1	$230
LS-50-AMCLLS	ASI	50 mm Linear Stage with Stainless Steel Slide	1	$2,425
LS-100-AMERL	ASI	100 mm Linear Stage, 16 TPI, Extended, Right	1	$3,100
LS-50-AMELL	ASI	50 mm Linear Stage	1	$2,250
TGADEPT	ASI	Piezo Control Card	1	$1,500
HS1.100	PiezoConcept	Piezo Concept 100 Micron Piezo Stage	1	$4,100
ADAPTHS1BB	PiezoConcept	Adapter Plate for PiezoConcept HS1	1	$120
Angle Bracket Adapter	Xometry	Angle adapter for mounting piezo at an angle	1	$592.58
Illumination Path				
L4CC	Oxxius	Multicolor Laser Source	1	25,000
P3-405B-FC-1	Thorlabs	Fiber Cable Single Mode FC/APC	1	$120

CFC11A-A	Thorlabs	Fiber Collimator	1	$370
Polaris-K1XY	Thorlabs	Kinematic Mount for Fiber Laser Collimator	1	$1375
AC254-030-A-ML	Thorlabs	Achromatic Lens f=30mm (L1)	1	$125
AC254-080-A-ML	Thorlabs	Achromatic Lens f=80mm (L2)	1	$115
ACY254-075-A	Thorlabs	Achromatic Cylindrical Lens f=75mm (L3)	1	$445
AC254-250-A-ML	Thorlabs	Achromatic Lens f=250mm (L4)	1	$90
PF10-03-P01	Thorlabs	1" Protected Silver Mirror	1	$55
TL20X-MPL	Thorlabs	Illumination Objective	1	$4820
VA100CP	Thorlabs	Rectangular Aperture	1	$315
IDA12	Thorlabs	Circular Aperture Iris	1	$60
Polaris-P150	Thorlabs	1" Diameter Polaris Mounting Post, 1.5" Length	1	$45
Polaris-P2	Thorlabs	1" Diameter Polaris Mounting Post, 2" Length	1	$45
Polaris-P3	Thorlabs	1" Diameter Polaris Mounting Posts, 3" Length	3	$45
Polaris-P075*	Thorlabs	1" Diameter Polaris Mounting Post, 0.75" Length	1	$45
Polaris-P225*	Thorlabs	1" Diameter Polaris Mounting Post, 2.25" Length	1	$45
Polaris-P250*	Thorlabs	1" Diameter Polaris Mounting Post, 2.5" Length	2	$45
Polaris-MA45	Thorlabs	Polaris 45 Degree Adapter for Mirror Mount	1	$50
Polaris-B1S	Thorlabs	Polaris Flexure-Closed Lens Mount	3	$110
Polaris-1XY	Thorlabs	Polaris XY Translation Mount for Illumination Objective	1	$1020
Polaris-K1S4	Thorlabs	Polaris 1" Mirror Mount	1	$185
SM1A12	Thorlabs	Thread Adapter for Illumination Objective into Polaris-1XY	1	$25
6SC04KA040-01Y	Novanta	1-Axis 4 kHz Resonant Galvo and Servo	1	$3,700
Galvo Holder	Protolabs	Holder for Galvo	1	$400
TGPOW-12-3	ASI	Galvo Low Noise Power Supply +12V 3A	1	$950
RSP1 Adapter	Xometry	Custom Adapter for Thorlabs RSP1 to Polaris Posts	1	$80
VA100CP Adapter	Xometry	Custom Adapter for Thorlabs VA100CP to Polaris Posts	1	$80
CP02 Adapter	Xometry	Custom Adapter for Thorlabs CP02 to Polaris Posts	1	$80
Illumination Path Baseplate	Xometry	Baseplate for Illumination Path	1	$1000
Live-Cell Imaging				
Custom Sample Chamber	Xometry	Custom Designed Live-Cell Sample Chamber	1	$530
1797N11	McMaster Carr	Benchtop Autotuning Temperature Controller, Type J Thermocouple, 1 Bay	1	$835
1797N103	McMaster Carr	Benchtop Autotuning Temperature Controller, Type J Thermocouple, 2 Bay	1	$1390
5586N11	McMaster Carr	3" Dual Thermocouple 1/8" Diameter Probe, Type J	1	$120
5843N12	McMaster Carr	1" Threaded Thermocouple 1/4"-20 Threading	1	$100
35765K373	McMaster Carr	2x5" Adhesive Backed Heat Sheet	1	$80
35475K362	McMaster Carr	5x1" Ultrathin Heat Sheet	1	$120
35765K367	McMaster Carr	6x1" Adhesive Backed Heat Sheet	1	$75

Supplementary Table 1. Detailed equipment list. Prices are approximate and subject to change. *Indicates that the part was custom ordered from Thorlabs.

Group	Approximate Cost
Illumination Path	$41,195
Sample Positioning	$14,727
Detection Path	$63,635
Shared Equipment	$31,675
Live-Cell Imaging	$3250
Total:	$154,482

695 **Supplementary Table 2.** Approximate cost.

696
697

Component	Analog/Digital	Ground Pin	Active Pin
Resonant Galvo	Analog	14	13
Piezo Motor	Analog	11	10
Camera	Digital	43	9
Fiber Laser (FL) Output Shutter	Digital	39	5
FL λ = 405 nm AO Port	Analog	55	21
FL λ = 405 nm IO Port	Digital	42	8
FL λ = 488 nm AO Port	Analog	18	52
FL λ = 488 nm IO Port	Digital	41	7
FL λ = 561 nm AO Port	Analog	20	54
FL λ = 561 nm IO Port	Digital	41	40
FL λ = 638 nm AO Port	Analog	50	16
FL λ = 638 nm IO Port	Digital	39	6

698 **Supplementary Table 3.** Electrical pinouts used on National Instruments PCIe-6738 data acquisition card. All analog and digital
699 connections were made using a National Instruments SCB-68A shielded terminal block.

700
701

Exposure Time (ms)	Average Frame Rate (Hz)
10	62.5
50	17.6
100	9.2
200	4.8

702 **Supplementary Table 4.** Acquisition performance for a 50 μm z-stack acquired at 0.25 μm step size (200 frames; 2048 × 512
703 pixels per frame). The mean inter-frame dead time was 7.25 ms, of which ~1 ms arose from piezo stepping; the remainder was
704 dominated by camera readout.

706
707
708

Experience	Illumination Path Assembly	Full System Assembly	Fine Alignment	Imaging & Validation
Novice	~1-3 hours	1-4 Days	1 Week	2 Weeks
Moderate	~1-3 hours	1-4 Days	1 Week	1 Week
Expert	~1 hour	1 Day	1-2 Days	1 Week

709 **Supplementary Table 5.** Approximate time considerations based on user experience level. A novice is defined as someone
710 entirely new to optical systems, with no prior experience in their operation or alignment. A moderate user has some prior
711 experience operating or using optical systems but limited experience assembling or aligning them. An expert user has substantial
712 experience designing, building, and aligning custom optical systems and is therefore expected to complete setup and validation
713 tasks more efficiently.
714
715

SUPPLEMENTARY NOTES

Supplementary Note 1. Design Rationale and Cost Considerations for Altair.

A core design objective of Altair-LSFM was to develop a high-performance, open-source light-sheet microscope that is accessible to a broad community of users, including those without extensive optical design or engineering experience. While we prioritized cost-effectiveness wherever possible, several design choices were made to balance performance, reliability, and ease of adoption, rather than minimizing cost alone. Moreover, we sought to minimize the complexity of sourcing, configuring, and integrating components from disparate vendors by favoring consolidated, multipurpose hardware. Despite this, end users are free to customize the hardware configuration to suit their experimental needs. Different detection objectives, stages, filter wheels, or cameras can be readily incorporated, as *navigate* natively supports a broad range of hardware devices. New hardware can also be easily integrated through *navigate's* modular device interface, enabling users to expand functionality or adapt the system to specific equipment without extensive reconfiguration.

The estimated total cost of a complete Altair-LSFM system in its default configuration, including the optical table and laser source, is approximately $150,000. Although this may still represent a barrier for some research groups, it is substantially lower than most commercial systems offering comparable sub-cellular resolution performance (e.g., LLSM systems from 3i or Zeiss, which are ~$600,000 and >$800,000 USD, respectively, or a diSPIM from ASI, which is ~$250,000). These values very substantially depending on system configuration and are provided only as approximate guides based on publicly available information, including instrumentation, published news articles, and personal communications. One major cost driver in LLSM-based systems is the use of a spatial light modulator, which is a relatively low-efficiency device and necessitates upgrading to higher-power laser sources[37] (e.g., ~500 mW). For Altair-LSFM, a full list of system components, vendors, and approximate costs is provided in **Supplementary Tables S1 and S2**. Below, we outline the primary cost drivers in the system, our rationale for selecting them, and potential alternatives that could be used in future variants to reduce cost, albeit by potentially compromising system performance.

Illumination and Detection Objectives

The illumination and detection objectives used in LSFM must be treated as a single, coupled optical system. For Altair-LSFM, the primary cost driver is the detection/illumination pair built around the Nikon N25X-APO-MP 25×/1.1 NA detection objective (≈ $33,000), which must be paired with either the Thorlabs TL20X-MPL 20×/0.6 NA illumination objective (≈ $5,000) or the Special Optics 54-10-7@488–910 nm (≈ $15,000). The Special Optics objective provides a slightly higher numerical aperture (0.66 NA) but a shorter working distance (3.74 mm) compared to the Thorlabs TL20X-MPL (0.6 NA, 5.5 mm). Both are optimized for water immersion and achromatically corrected across the visible spectrum. Using the vectorial Richards & Wolf 3D optical model, the expected illumination PSF at 488 nm and maximum NA is approximately 451 × 2240 nm (XY × Z) for the Special Optics 54-10-7 and 496 × 2711 nm for the Thorlabs TL20X-MPL. While the higher NA of the Special Optics lens marginally improves resolution, the increased working distance of the Thorlabs objective makes it compatible with alternative detection objectives and facilitates imaging with larger coverslips (see below). Moreover, in practical applications, the full numerical aperture of these objectives is rarely used, as doing so would require exceptionally thin specimens.

Users seeking to reduce cost may substitute the Nikon 25× with a Zeiss W Plan-Apochromat 20×/1.0 (≈ $7,000). This objective is compatible with the existing detection path (no different tube lens required; aberration corrections are internal to the primary objective) and, when paired with the TL20X-MPL for illumination, is expected to deliver similar practical performance while easing sample handling by allowing coverslips larger than 5 mm in diameter. A more aggressive cost reduction is to redesign the optical train around Nikon N40X-NIR 40×/0.8 objectives for both illumination and detection. However, because vendor ray files/Zemax models are not available for these lenses, such a redesign would require introducing additional alignment degrees of freedom and tolerancing steps, increasing assembly complexity. Moreover, the lower NA would reduce raw resolution to ~400 nm laterally and axially[12] and halve photon collection, which scales with NA^2, lowering sensitivity—tradeoffs that may be unacceptable for low-signal or fast volumetric imaging. While the combination of objectives used in this implementation of Altair-LSFM has a total list price of approximately $38,000, substituting the detection objective with the Zeiss W Plan-Apochromat 20×/1.0 would reduce this cost to ≈ $12,000, and a full redesign around Nikon 40×/0.8 objectives for both illumination and detection would further reduce the total to ≈ $6,000, providing a clear path toward more cost-effective configurations depending on experimental needs and available resources

<u>Scientific Camera</u>

Scientific CMOS (sCMOS) cameras are a major investment in Altair-LSFM. Older Hamamatsu ORCA-Flash 4.0 units could sometimes be obtained near ~$15k, whereas current-generation sCMOS from major vendors (Hamamatsu, Photometrics, PCO, etc.) typically fall in the $30k–$40k range. The cost is justified by characteristics that are especially important for light-sheet imaging: high quantum efficiency, low read noise with effective suppression of dark current, large sensors that enable highly parallel acquisition across a wide field, and fast readout rates that support high frame rates. In our configuration (50x effective magnification, 6.5 µm pixels), the camera provides Nyquist-sampled pixels (~130 nm) across a wide 25 mm sensor, which is critical for capturing ~150–200 planes per adherent cell per channel at biologically relevant speeds—particularly for live-cell experiments.

Lower-cost industrial CMOS cameras (e.g., Ximea MU196CR-ON, recently demonstrated in a Direct-View OPM[41] configuration) can in principle substitute for sCMOS in budget-constrained builds. However, in our experience these sensors exhibit higher noise floors and reduced dynamic range, which limits sensitivity in low-signal regimes. They are also typically slower than leading sCMOS cameras and show greater variability in fixed-pattern defects (e.g., hot pixels), often necessitating calibration and post-processing. For applications that demand sub-cellular resolution at high speed and low illumination, we therefore recommend sCMOS as the default choice; industrial CMOS can be considered for cost-reduced variants with the understanding that overall performance will be compromised (sensitivity, speed, and image uniformity).

<u>ASI Equipment</u>

Altair-LSFM consolidates operation of all motion axes and the emission filter wheel into a single ASI Tiger Controller, including motorized XYZ sample positioning, a high-speed piezo Z scan for volumetric acquisition, and a motorized focus (F) axis for precise co-focusing of the detection plane. The complete system—XYZ and F stages, piezo stage, motorized emission filter wheel, ASI Tiger controller, and basic optomechanical adapters—totals ~$31,000 (~20% of system cost).

Cost-reduced variants are possible, but each entails performance or complexity trade-offs. Replacing motorized XYZ/F with manual stages can save ~$12,000, but removes critical capabilities such as autofocus, 3D tiling, and multi-position acquisition. Eliminating the piezo and relying solely on linearly encoded Z stages lowers upfront cost and complexity, yet significantly increases repositioning time and reduces volumetric throughput, which is especially limiting for live-cell imaging. Worth noting, our sample scanning piezo could deliver higher bandwidth with the vendor's dedicated controller; however, we favor a unified Tiger Controller-based control stack to minimize the number of controllers to wire, configure, and maintain, thereby streamlining adoption for non-experts.

Open-source mechanical platforms (e.g., OpenFlexure[42]) could, in principle, be adapted to further reduce cost, but would require custom assembly and software integration—shifting burden to the end user—and may exhibit reduced accuracy/precision and increased hysteresis compared with the closed-loop stages used here. Similarly, the motorized emission filter wheel can be omitted in favor of a fixed multi-band emission filter (saving ~$5,000), but this increases spectral crosstalk and often necessitates post-acquisition spectral unmixing, complicating workflows and potentially reducing sensitivity for dim samples.

<u>Analog and Digital Control</u>

Altair-LSFM uses a National Instruments (NI) 6738 (PXIe/PCIe form factor) for real-time analog and digital control. The board provides 32 analog outputs with 16-bit DAC resolution at up to 1 MS/s update rate, which we use to generate waveforms for the resonant/galvo drive, piezo position control, and analog laser intensity. The card also exposes 10 digital I/O lines that we use for laser modulation (TTL) and camera triggering/synchronization. We selected this platform because it is readily available internationally, offers robust, deterministic timing, and comes with long-term driver support and tooling that reduces integration burden across operating systems and labs. In future releases, we aim to eliminate the NI card by consolidating triggering and waveform generation into the ASI Tiger Controller, further reducing hardware count, wiring, and software dependencies while keeping the system turnkey for non-experts. Importantly, we opted to avoid lower-cost microcontroller (MCU) solutions (e.g., USB microcontrollers with external DACs) because they carry several practical disadvantages:

- Timing determinism and jitter: General-purpose MCUs and USB links typically exhibit µs–ms-scale jitter and non-deterministic latency, complicating tight synchronization between camera exposure, galvo phase, laser blanks, and piezo motion.
- Waveform fidelity and throughput: Many MCUs cannot sustain simultaneous, multi-channel DAC streaming at 1 MS/s.

- Noise and analog performance: MCU-centric solutions often have higher analog noise, poorer calibration/drift, and require custom electrical interfaces.
- Scalability and maintenance: NI provides stable drivers, diagnostics, and a clearer path for multi-OS support.
- Feature trade-offs: Replacing the NI card would push more complexity into software/firmware and wiring.

Supplementary Note 2. Environment Chamber Design.

To support live-cell imaging with Altair-LSFM, we developed a temperature-controlled sample chamber (**Figure S8**). Typical cell viability temperatures span ~25 °C for yeast to 37 °C for mammalian cells. The chamber integrates adhesive heating pads and embedded thermocouples in the chamber wall, regulated by a TempCo controller to maintain a fixed setpoint. Relative to our initial design, we removed the secondary illumination port (formerly used for linear light-sheet imaging), which allowed us to mount larger heaters along two exterior walls for more uniform heating of the chamber volume. To minimize thermal gradients— which can induce drift or optical aberrations (e.g., with the Nikon 25× objective), we also provide indirect objective heating. Two add-on hoods surround the illumination and detection ports; each wrapped with heating pads. In total, the system heats three zones: (1) illumination-objective hood, (2) detection-objective hood, and (3) the two external walls opposite the objective ports. All off-the-shelf components (outside the custom chamber) were sourced from McMaster-Carr; the total live-cell upgrade cost was ~$3,250 (**Table S2**).

Commercial environmental chambers often maintain 5% CO_2 (stabilizing pH in bicarbonate-buffered media) and add humidification to limit evaporation; turnkey systems of this type typically cost on the order of $20,000. Such fully enclosed atmospheres are uncommon for light-sheet microscopes because multiple objectives contact the specimen, precluding a sealed enclosure, with the notable exception of a purpose-built enclosure reported previously[23]. In the open-source implementation of LLSM, as well as the early LLSM variant commercialized by 3i, environmental control was achieved by enclosing both the specimen and the objectives in temperature-regulated blocks through which heated or chilled water was circulated, while pH stabilization was maintained using 10 mM HEPES buffer. However, humidity and CO_2 were not controlled in this configuration. We adopt a similar strategy in Altair-LSFM, using temperature-controlled components and HEPES-buffered media to maintain a stable imaging environment. Given our ~50 mL chamber volume, evaporation is minimal even during extended imaging sessions. In contrast, OPMs, and the more recent LLSM variant commercialized by ZEISS, are inherently compatible with commercially available environmental chambers and therefore avoid many of the practical constraints associated with multi-objective light-sheet systems.

Supplementary Note 3. Light-Sheet Illumination and Acquisition Modes

LLSM Illumination Modes

The original implementation of Lattice Light-Sheet Microscopy (LLSM), introduced by Chen, Legant, Wang et al[32], is a highly flexible platform capable of generating multiple illumination patterns, each optimized for different biological specimens. This flexibility arises from its use of a spatial light modulator (SLM) to define the illumination pattern at the back focal plane of the illumination objective. The system can operate in a dithered, or time-averaged square and hexagonal lattice modes, as well as in a structured illumination mode, providing a wide range of trade-offs between resolution, field of view, and imaging speed. However, the square lattice rapidly became the most widely used due to its ease of operation and compatibility with deconvolution workflows. Indeed, in the original 2014 publication, 16 of the 20 figure subpanels utilized the square lattice configuration, while only one panel was dedicated to each of the hexagonal or structured illumination modes.

The square lattice provides strong axial confinement with minimal side-lobe energy, producing uniform, high-contrast optical sectioning that is suitable for most cellular imaging applications. The hexagonal lattice, by contrast, improves axial resolution but is accompanied by side-lobes that increase in intensity with laser propagation distance, limiting its use to particularly thin specimens. These side lobes also necessitate computational post-processing for their removal, which becomes increasingly challenging when their intensity approaches ~50% of the main lobe, a condition that can occur even for modest beam propagation lengths[10]. These beams can also operate in a structured illumination (SIM) mode, wherein the lattice pattern is stepped or phase-shifted laterally to enhance optical resolution in both the X and Z dimensions. Because the orientation of the illumination pattern is fixed, resolution along the Y axis (e.g., the laser propagation direction) remains diffraction limited. Importantly, this mode requires 5 phase-shifted images per optical section to reconstruct a single high-resolution plane, substantially increasing both illumination dose and acquisition time. The computational reconstruction is also considerably more intensive than for standard lattice modes. Although structured illumination is supported in the commercial

implementation of LLSM offered by 3i, its use in practice remains limited due to these experimental and
computational demands.
The recently developed ZEISS Lattice Lightsheet 7 represents a streamlined and user-friendly evolution of
the original LLSM design, prioritizing ease of operation over full optical flexibility. Unlike the earlier
implementations, which supports multiple lattice geometries and structured illumination modes, the ZEISS system
offers three predefined "Sinc" beam configurations. Each configuration corresponds to a specific trade-off between
light-sheet length and thickness (e.g., 15×550 nm, 30×700 nm, and 100×1400 nm, each available with or without
side lobes).
886
<u>Volume Acquisition Modes</u>
To acquire volumetric data, both the original and 3i systems can operate in sample-scanning and light-sheet-
scanning modes, whereas both Altair-LSFM and the ZEISS implementation of LLSM function exclusively in a
sample-scanning format. In sample scanning, the specimen is translated through a stationary light-sheet, whereas in
light-sheet scanning, the light-sheet is scanned in the Z-direction through a stationary specimen synchronously with
the position of the detection objective (see **Supplementary Figure 1**). Each mode offers distinct advantages and
trade-offs. Sample scanning provides the simplest architecture to assemble and operate but requires shearing of the
data to place the data in its proper spatial context. It is particularly advantageous for specimens with a large aspect
ratio, such as highly adherent cells. In the light-sheet-scanning configuration, the sheet is scanned using a linear
galvanometer conjugate to the back pupil of the illumination objective. This design necessarily introduces an
additional optical fold into the illumination train, and the plane conjugate to the galvo must typically be relayed to
the back pupil of the illumination objective—often with an f-theta lens and tube lens pair. The galvo sweep must also
be calibrated to ensure precise synchronization between the light-sheet position and the detection objective's focal
plane. Consequently, compared to sample-scanning, light-sheet-scanning increases both alignment complexity and
cost. Unlike sample scanning, the acquired data are immediately in their correct spatial context, eliminating the need
for post-processing shearing. Light-sheet scanning is particularly useful for specimens with a more spherical aspect
ratio. In the original LLSM publication, this mode was used to image biological processes such as microtubule and
histone dynamics during mitosis, *Tetrahymena thermophila* swimming behavior, T-cell immunological-synapse
formation, and *C. elegans* embryogenesis. It is also advantageous for vibration-sensitive specimens, such as
neutrophil-like cells migrating within a compliant extracellular matrix, where sample translation could induce
unwanted mechanical perturbations in the extracellular matrix[43].
908
<u>Resolution.</u>
While the original LLSM platform supports square, hexagonal, and structured illumination modes, our
discussion on resolution here remains focused on the square lattice. Importantly, for both square-lattice light sheets
and Gaussian light sheets, axial resolution is tightly coupled to the propagation length of the illumination beam: Both
square lattice light-sheets, which do not behave as propagation-invariant beams, and Gaussian beams broaden in
diameter as a function of propagation length. Consequently, like-for-like comparisons must match detection NA,
sheet thickness at focus, light sheet propagation length, and post-processing.
The original LLSM work described lattice light-sheets by inner/outer NA rather than by sheet thickness and
propagation length, which complicates direct comparisons to Gaussian sheets. More recent reports with bead-based
measurements (FWHM of 100-nm fluorophore beads) yielded a raw lateral and axial resolution of 312 nm × 666 nm
for an excitation wavelength of 488 nm. For comparison, the original publication reported a resolution of ~230 ×
370 nm, which is consistent with the use of shorter propagation length illumination beam and deconvolution. For
comparison, the ZEISS implementation reports raw resolutions of 330 x 500-1000 nm and deconvolved resolutions
of 290 x 450 – 900 nm, depending on the selected light-sheet configuration. The reduced resolution likely reflects
the compromises inherent to imaging in an open-top geometry, which requires the use of a meniscus lens to
accommodate the optical path. For Gaussian beams, a frequent source of confusion in the literature is the use of
paraxial Gaussian-beam formulae to estimate thickness and propagation length at NAs where diffraction effects are
non-negligible. At the illumination NAs used in Altair-LSFM, scalar/vector diffraction modeling better predicts the
realized beam properties than simple Gaussian optics. Thus, when propagation length and focus thickness are
matched, a diffraction-limited Gaussian sheet can deliver performance comparable to a square lattice, without
introducing side lobes.
Quantitative comparisons of resolution depend not only on the optics but also on the exact algorithmic
implementation of deskewing (shearing) and deconvolution. For deconvolution, outcomes are sensitive to PSF

quality, background estimation, regularization, and iteration count; moreover, most algorithms assume a
non-aberrated, shift-invariant PSF, an assumption that degrades with specimen heterogeneity. In our measurements,
Altair-LSFM achieves ~235 nm × 350 nm after deconvolution, comparable to the deconvolved values reported for
square-lattice LLSM under matched detection NA and sampling. These reported measurements were performed on
100 nm fluorescent beads and likely reflect illumination beams optimized for the thinnest biological specimens.
Thicker specimens would require longer propagation lengths and correspondingly thicker light sheets, yielding
resolutions closer to those previously reported—approximately 312 × 666 nm before deconvolution or 230 × 460 nm
after deconvolution, assuming a ~30% reduction in the point spread function dimensions.
940
Comparison with other Light-Sheet Modalities.
diSPIM attains near-isotropic resolution by imaging the same specimen from two orthogonal detection paths
and fusing the volumes with multiview deconvolution. Reported performance ranges from ~330 nm isotropic in the
original implementation[22] to ~380 nm isotropic in commercial systems. For cleared-tissue variants of diSPIM using
mixed-immersion 17.9×/0.4-NA objectives, single-view resolutions of ~840 nm (lateral) and 4600 nm (axial) have
been improved to ~800 nm isotropic after registration and one iteration of deconvolution[25]. In practice, diSPIM excels
when large fields of view and improved axial sectioning are required and when multiview registration and
deconvolution are acceptable parts of the workflow. High-resolution ASLM systems use aberration-free remote
focusing to translate the light sheet along its propagation direction in synchrony with a camera's rolling shutter,
effectively decoupling axial sectioning from field of view. Early implementations with ~0.8-NA detection achieved
~400 nm isotropic resolution[12]; adaptations for high-RI cleared samples have reported ~330 nm isotropic resolution[24].
Large field of view variants such as the mesoSPIM[44] use electro-tunable lenses to scan the illumination beam and
report typical resolutions of ~2.5 µm (lateral) and ~5 µm (axial). Both diSPIM and ASLM excel when one needs to
maximize the field of view while maintaining a high axial resolution.
Recent advances in OPM[45] have enabled sub-cellular imaging while preserving a single-objective, inverted
geometry that is compatible with standard sample preparation, environmental chambers, and autofocus systems. A
high-NA OPM has reported 299 × 731 nm (raw) and ~209 × 523 nm (after deconvolution), albeit with short working
distance[13]. Longer-working-distance, water-dipping OPMs extend penetration and support optical tiling (e.g.,
volumes on the order of 800 × 500 × 200 µm) with raw resolutions around ~400 × 1220 nm[46]. OPM also allows novel
illumination approaches, such as DaXi, which used an image flipper to perform multiview imaging with ~450 nm
lateral and ~2 µm axial resolution throughout a ~3000 × 800 × 300 µm volume. Likewise, by incorporating an image
rotator into the optical path, structured illumination could be leveraged to improve the lateral resolution to ~140 nm[47].
And lastly, because of the shared optical train, a single deformable mirror is capable simultaneously correcting
aberrations in both the illumination and detection[48]. Given the rapid evolution of OPMs in particular, and LSFM more
broadly, the comparisons provided here are intended to situate Altair-LSFM in context, not to offer an exhaustive
review.
967
Supplementary Note 4. Data Storage and Handling
Storage costs are approximate and are expected to vary widely between institutions, depending on negotiated
contracts, available infrastructure, and funding models. The cost estimates provided here are intended solely as a
practical guide for planning purposes and should not be considered definitive or universally applicable. For example,
large cloud providers list prices that vary from roughly $0.023 to $0.00099 per GB per month, with additional
monitoring, retrieval, and transfer fees that vary by storage class. In contrast, the local computing infrastructure at
UT Southwestern Medical Center charges a one-time fee of $300 per TB, which is amortized over five years.
Advantageously, to reduce costs to end-users, our local file system includes an automated 100 PB tape archive: data
inactive for more than 12 months are transparently migrated while remaining visible as placeholders and are
automatically recalled when accessed. Our lab operates with a 130 TB quota, which costs ~$8,000 per year. In general,
we typically budget $2k per year per experimentalist for storage and compute, rising to $10–12k per year for users
that rely on high-end GPUs. These expenses are routinely incorporated into federally funded grant budgets. To operate
within the confines of such a quota, we recommend several simple rules to manage data overhead.
• Save data in a Zarr format, which is supported by *navigate* and uses lossless blosclz compression by default.
• Immediately assess data for quality. *Navigate* automatically saves maximum-intensity projections (MIPs) that
can be reviewed quickly in Fiji/ImageJ on standard computers, enabling rapid assessment of data quality.
Evaluating data in two dimensions is substantially faster than loading full 3D stacks; datasets of insufficient
quality should be deleted immediately to prevent unnecessary storage costs.

•   Store only the raw image data. Saving Postprocessing routines, such as deconvolution, increase the storage
footprint. Instead, we reprocess data on demand using high-performance tools such as PetaKit5D[31]. Importantly,
to support reproducibility, one must record processing parameters such as deconvolution iterations and point-
spread functions alongside each dataset to enable faithful reprocessing.
990
Supplementary Note 5. Comparison of *navigate* with other Open-Source Microscope Control Software.
A wide variety of open-source software packages are available for microscope control, the most popular of
which is Micro-Manager[49], a highly extensible and widely adopted platform. Both *navigate* and Micro-Manager
provide user-friendly graphical interfaces and support image-based feedback control, making them accessible to a
broad community of users. Micro-Manager's greatest strength lies in its extensive library of device drivers, which
supports a vast array of commercial hardware from multiple manufacturers. Although Micro-Manager has been
successfully used to control light-sheet microscopes, it typically requires manual hardware configuration and custom
scripting to implement advanced or non-standard acquisition workflows.
In contrast, *navigate* was developed from the ground up to provide turnkey support for multiple light-sheet
architectures, including both sample-scanning and light-sheet–scanning LSFM configurations, as well as ASLM and
OPM. While its hardware library is more focused than Micro-Manager's, *navigate* was developed in tandem with the
Altair-LSFM hardware, enabling tightly integrated, preconfigured acquisition routines optimized for this system. This
co-design minimizes setup time, eliminates the need for user-side customization, and ensures reliable synchronization
across devices. The result is a software environment that provides robust performance, efficient data handling, and
streamlined operation for non-expert users.
Navigate also offers advanced data management capabilities through native support for multiple file formats,
including TIFF, HDF5, N5, and Zarr. Each file is saved with embedded Open Microscopy Environment (OME)
metadata and is fully compatible with BigDataViewer, facilitating interoperability with downstream image analysis
pipelines. Additionally, *navigate's* modular Python-based architecture allows expert users to extend functionality,
integrate new devices, and leverage the extensive Python ecosystem for intelligent or adaptive acquisition workflows.
Although *navigate* is provided as the default control platform for Altair-LSFM, the system can, in principle,
be configured to operate with Micro-Manager or other open-source control frameworks. We welcome and encourage
community-led efforts to build such compatibility. Ultimately, our goal with *navigate* is to provide a ready-to-use,
flexible, and extensible control environment that lowers the barrier to advanced light-sheet imaging while supporting
continued community innovation and customization.
1016

(a)

Hamamatsu
Orca Flash4.0 v3

ASI C60-TUBE-400

Nikon N25X-APO-MP

(b)

x *y* *z*

(c)

x *z*

20 μm

FWHM:
~0.382 *μm*

Intensity (A.U.)

Distance (μm)

(a)

(b)

Intensity (A.U.)

Image Data
Fitted Curve

FWHM: ~0.415 μm

Distance (μm)

(c)

1 μm   1 μm   1 μm

(f)

Frequency (counts)

Original Bead FWHM:
x: 328.4 nm
y: 330.4 nm
z: 464.8 nm

Deconvolved Bead FWHM:
x: 235.5 nm
y: 233.5 nm
z: 350.4 nm

Bead FWHM (nm)

(a)

(b) λ_ex=405 nm

(c) λ_ex=488 nm

(d) λ_ex=561 nm

(e) λ_ex=638 nm

20 μm

x
y

(f)

(g) λ_ex=405 nm

(h) λ_ex=488 nm

(i) λ_ex=561 nm

(j) λ_ex=638 nm

20 μm

20 μm

20 μm

x
y

(a)

Sample

(b) Imaging Volume

Scanning Direction

(c) Imaging Volume

Scanning Direction

(a) Nominal Beam Size and Position

Changing Size and Position of Beam

(b)

0.394 "

0.394 "

+0.005"   -0.005"

$\tan\theta = .005/.197$
$\theta = 1.454°$

0.005"

0.197"

(c)

Nominal | Best Case | Worst Case

Tol: -+0.005"   0.266 mm

Tol: -+0.002"   0.266 mm

Sample Positioning Unit

Illumination Path

Detection Path

(a) Double O-Ring Grooves

(b)

(c)

Objective Port Hoods

Threaded Thermocouple Holes x4

Heating Pads x3

O-ring Grooves

Chamber Mounting Holes

0.000 min

10 μm