GLMdenoise improves multivariate pattern analysis of fMRI data

Ian Charest*[1,2], Nikolaus Kriegeskorte[2,3], Kendrick N. Kay[4]

[1]School of Psychology, University of Birmingham

[2]Medical Research Council Cognition and Brain Sciences Unit, University of Cambridge

[3]Department of Psychology, Zuckerman Mind Brain Behavior Institute, Columbia University

[4]Center for Magnetic Resonance Research (CMRR), Department of Radiology, University of Minnesota

*Corresponding author (i.charest@bham.ac.uk)

RUNNING TITLE: GLMdenoise improves multivariate pattern analysis

KEYWORDS: BOLD fMRI, general linear model, cross-validation, correlated noise, representational similarity analysis, decoding, classification, denoising, multivariate pattern analysis

ABSTRACT

GLMdenoise is a denoising technique for task-based fMRI. In GLMdenoise, estimates of spatially correlated noise

(which may be physiological, instrumental, motion-related, or neural in origin) are derived from the data and

incorporated as nuisance regressors in a general linear model (GLM) analysis. We previously showed that

GLMdenoise outperforms a variety of other denoising techniques in terms of cross-validation accuracy of GLM

estimates (Kay et al., 2013a). However, the practical impact of denoising for experimental studies remains unclear.

Here we examine whether and to what extent GLMdenoise improves sensitivity in the context of multivariate

pattern analysis of fMRI data. On a large number of participants (31 participants across 4 experiments; 3 T,

gradient-echo, spatial resolution 2–3.75 mm, temporal resolution 1.3–2 s, number of conditions 32–75), we

perform representational similarity analysis (Kriegeskorte et al., 2008a) as well as pattern classification (Haxby et

al., 2001). We find that GLMdenoise substantially improves replicability of representational dissimilarity matrices

(RDMs) across independent splits of each participant's dataset (average RDM replicability increases from r = 0.46

to r = 0.61). Additionally, we find that GLMdenoise substantially improves pairwise classification accuracy

(average classification accuracy increases from 79% correct to 84% correct). We show that GLMdenoise often

improves and never degrades performance for individual participants and that GLMdenoise also improves across-

participant consistency. We conclude that GLMdenoise is a useful tool that can be routinely used to maximize the

amount of information extracted from fMRI activity patterns.

1. INTRODUCTION

Noise is a critical concern when collecting and analyzing functional magnetic resonance imaging (fMRI) data. The

blood oxygenation-level dependent (BOLD) signal measured with fMRI contains many sources of noise (e.g.,

physiological noise, instrumental noise) that are mixed with task-specific signals of interest. In order to draw valid

conclusions regarding how a cognitive experiment affects the BOLD signal, it is necessary to extract meaningful

signals from the data, limiting various noise contaminations. Classical analyses of fMRI data involve performing a

general linear model analysis (Friston et al., 1994, 1995b; Worsley and Friston, 1995). This consists of modelling

the time-series of each fMRI voxel using a design matrix that characterizes the onsets of an experiment's

conditions. These events are convolved with a hemodynamic response function (HRF; Boynton et al., 1996;

Lindquist et al., 2009), and then a least-squares optimization is performed to minimize the distance between the

data and the model. The result of this process is a set of beta weights that characterize fMRI voxel activities.

A common approach to improve the sensitivity of the model is to incorporate nuisance regressors in the design

matrix (Friston et al., 1995a; Lund et al., 2006). These nuisance regressors often include participant motion

estimates and/or linear and non-linear drift terms, with the goal of improving parameter estimates by accounting

for these potential sources of noise (see Ciric et al., 2017 for how nuisance regressors are applied the context of

resting-state fMRI). The choice of these regressors is often arbitrary, dependent on the philosophy of the software

package used to analyze the data, and may harm task-related estimates if they are inaccurate characterizations

of the noise. To address these issues, we previously introduced GLMdenoise (Kay et al., 2013a). GLMdenoise is

a denoising technique, inspired by previous work (Behzadi et al., 2007; Bianciardi et al., 2009; Fox et al., 2006),

that improves signal-to-noise-ratio (SNR) by automatically deriving the noise regressors entered in the general

linear model (GLM) through careful cross-validated analysis of the fMRI time-series. The noise regressors are

derived by application of principal components analysis (PCA) on time-series of voxels unrelated to the

experimental paradigm, and cross-validation is used to automatically select the appropriate number of regressors

for each given dataset. The noise regressors derived in GLMdenoise are general and can encompass many

different types of noise, including motion-related noise, physiological noise, and neural noise[1]. A MATLAB

toolbox that implements GLMdenoise is freely available at http://cvnlab.net/GLMdenoise/.

In the initial study introducing the technique (Kay et al., 2013a), we showed that GLMdenoise outperforms a

variety of other denoising methods on a number of datasets. Our metric of performance was univariate cross-

validation accuracy of GLM response-amplitude estimates (beta weights). This criterion quantifies how accurately

estimates of beta weights match experimentally observed BOLD time-series data. GLMdenoise computes this

metric on a voxel-by-voxel basis and does not make reference to any specific brain regions. Although this

approach is rigorous and objective, it remains unclear to what extent GLMdenoise brings practical benefits to

experimental studies.

---

[1] Note that 'noise' is operationally defined as signal fluctuations that are not captured by the GLM design matrix, and so the noise regressors may include genuine, neurally-driven BOLD signals that are not of interest to the experimenter.

The use of multivariate pattern analysis (MVPA), including pattern classification (Haxby et al., 2001; Haynes and

Rees, 2006; Kamitani and Tong, 2005; Kriegeskorte et al., 2006; for a review see Haxby, 2012) and

representational similarity analysis (RSA) (Charest et al., 2014; Kriegeskorte et al., 2008b, 2008a; Kriegeskorte

and Kievit, 2013; Nili et al., 2014) is growing in popularity in neuroimaging studies. These powerful methods

enable the use of fMRI to investigate the information represented in patterns of activity within brain regions. In

classical MVPA, a classification algorithm is used to determine whether fMRI response patterns contain

information that discriminate different conditions. In RSA, fMRI response patterns are compared between all

pairwise experimental conditions to reveal the representational geometry characteristic of a given brain region.

These comparisons are assembled in a representational dissimilarity matrix (RDM). These RDMs are useful as

they provide some insight into a brain region's information and reveal the format in which it is represented. This

approach is increasingly popular in cognitive neuroscience, as it provides a common ground to relate data from

multiple measurement techniques (e.g., electrophysiology, behavior, fMRI, computational models, etc.; see

Carlson et al., 2013; Cichy et al., 2016a, 2016b, 2014 for examples and Kriegeskorte and Kievit, 2013 for a

review).

In light of this paradigm shift in functional neuroimaging, a high priority for neuroscientists is to optimize data

quality before attempting MVPA. A number of studies have combined GLMdenoise with multivariate analyses (for

example, see Allen et al., 2018; Charest et al., 2014; Erez et al., 2016), but none have evaluated whether it

improves such analyses. Thus, an important question is whether GLMdenoise brings benefits to MVPA and

whether the benefits are sufficiently substantial and consistent across studies and participants to justify the

complications associated with the integration of GLMdenoise into the analysis. Because GLMdenoise improves

the ability of GLM beta weights to generalize to unseen data (Kay et al., 2013a), these beta weights have

increased accuracy, and it is reasonable to expect that any subsequent analysis of those beta weights will

produce higher quality results. But fMRI data and analyses are complex, and it remains a valuable empirical

question whether GLMdenoise in fact improves multivariate analyses and how large the improvement might be

(e.g., 1% or 10% increase in percent correct for classification performance).

In this paper, we systematically assess the impact of GLMdenoise on multivariate analyses of a large number of

participants compiled from four different experiments. Although these are all visual experiments, we believe the

principles underlying the technique will likely generalize to other types of experiments (e.g. auditory, cognitive,

motor). The stimuli in the experiments ranged from abstract patterns to images of bodies, faces, places and

objects (see Materials and Methods). In addition to their condition-rich designs (the experiments range from 32

conditions to 75 conditions), these experiments all had an ample number of repetitions to perform split-half

analyses. Being able to perform split-half analyses is critical for evaluating data reliability and replicability. We

analyzed these datasets using pattern classification and representational similarity analyses in regions of interest

(ROIs) along the ventral visual stream, which included primary visual cortex, visual word form area, fusiform face

area, and human inferior temporal cortex. We observed consistent and substantial improvements to results when

using GLMdenoise in the analysis pipeline.

2. MATERIALS AND METHODS

2.1 Participants and datasets

We collected fMRI data from 31 distinct participants. Informed written consent was obtained from all participants. Experimental protocols were approved by the Stanford University Institutional Review Board, Washington University Human Research Protection Office, and the Cambridge Psychology Research Ethics Committee. Each participant's dataset consisted of either one or two scan sessions, and each scan session consisted of multiple runs. All fMRI data were collected using a 3T MR scanner and a T2*-weighted, single-shot, gradient-echo pulse sequence with interleaved slice acquisition (see Table 1 for details). Regions-of-interest (ROIs) were defined based on independent localizer data.

Experiment 1 (3 participants; Participants 1–3). These data are taken from a previously published study (Kay et al., 2013b) and correspond to datasets 1–3 from the original GLMdenoise paper (Kay et al., 2013a). In this experiment, participants viewed high-contrast black-and-white noise patterns while performing a task at central fixation. Each stimulus condition lasted 3 s, and conditions varied with respect to the visual field location of the noise patterns (we refer to these locations as apertures). There were 69 conditions: 31 vertical apertures (ordered from left to right), 31 horizontal apertures (ordered from bottom to top), and 7 circular apertures (ordered from center to periphery). The ROI for this experiment is primary visual cortex (V1). (Note: this experiment originally consisted of 5 sets of runs; in order to achieve even test-retest splits of the data, we include in this paper only the first 4 sets of runs.)

Experiment 2 (3 participants; Participants 4–6). These data are taken from a previously published study (Kay et al., 2015). In this experiment, participants viewed grayscale faces while performing one of three tasks. Each stimulus condition lasted 3.5 s, and conditions varied with respect to the visual field location of the faces and the task performed. There were 75 conditions: 25 locations (taken from a 5 x 5 grid; ordered from left to right, then top to bottom) x 3 tasks (digit task: one-back task on centrally presented digits, dot task: detection of a dot superimposed on the faces, face task: one-back task on face identity). The ROI for this experiment is fusiform face area (FFA), combining both the posterior fusiform gyrus (pFus-faces/FFA-1) and middle fusiform gyrus (mFus-faces/FFA-2) subdivisions of FFA (Weiner et al., 2014).

Experiment 3 (5 participants; Participants 7–11). In this experiment, participants viewed a variety of grayscale stimuli (e.g., faces, words, texture patterns) while performing a one-back task on the stimuli. Each stimulus condition lasted 4 s (e.g., four 100%-contrast faces presented for 800 ms each with a gap of 200 ms), and there were 32 conditions. The ROI for this experiment is visual word form area (VWFA), defined as word-selective cortex in and around the left occipitotemporal sulcus (Yeatman et al., 2013).

Experiment 4 (20 participants; Participants 12–31). These data are taken from a previously published study (Charest et al., 2014). In this experiment, participants were paired and each participant viewed images that were

familiar to each participant in a pair (18 images per participant, consisting of bodies, faces, places, and man-made objects) as well as 36 object images (common to all participants). There were 72 conditions in total. Each stimulus condition lasted 1 s, and participants performed an anomaly-detection task indicating whether the stimulus had been subtly changed. The ROI for this experiment is human inferotemporal cortex (hIT), which is defined as a wide expanse of posterior and anterior temporal cortex, including fusiform face area, lateral occipital complex, and parahippocampal place area.

In each experiment, conditions were presented in random or pseudorandom order within each run, and rest periods were included between conditions and at the beginning and end of each run. In some participants (Participants 7–31), every condition was presented at least once during each run. In other participants (Participants 1–6), conditions were split across multiple runs. For example, Participants 4–6 involved 75 conditions which were split across three runs, each containing 25 conditions; together, the three runs comprise a run set and multiple run sets were collected over the course of the scan session. The specific characteristics of each participant's dataset are detailed in Table 1.

2.2 Data pre-processing

The first five volumes (Experiments 1–2) or eight volumes (Experiment 4) of each run were discarded to allow longitudinal magnetization to reach steady-state. Differences in slice acquisition times were corrected using sinc interpolation (Experiments 1–4). Measurements of the static magnetic field (B_0) were used to correct volumes for spatial distortion (Experiments 1–3). Motion correction was performed using SPM (Experiments 1–4). Final data interpolation occurred at the original voxel resolution (Experiments 1–2, 4) or the resolution of the cortical surface reconstruction generated by FreeSurfer based on T1-weighted anatomical data (Experiment 3).

2.3 Summary of GLMdenoise procedure

A summary of the major steps in GLMdenoise is provided here (for full details, please see Kay et al., 2013a). We start with a baseline GLM that includes task regressors capturing effects related to the experiment and polynomial regressors capturing low-frequency drift. A procedure to estimate the HRF is performed, and the accuracy of the GLM is quantified using leave-one-run-out cross-validation. Voxels whose cross-validated R^2 values are less than 0% are then considered for the noise pool. Note that this selection is not tailored to any specific contrast or effect that might exist in the data, but simply assesses whether any of the task regressors produce non-zero variance in the time series for a given voxel. Moreover, even if the noise pool contains voxels of interest, it is still possible to improve GLM estimates for such voxels (Kay et al., 2013a). The noise pool is further refined to brain voxels by discarding voxels whose mean signal intensity fall below one half of the 99th percentile of mean signal intensity values across all voxels. Next, we extract the time-series data observed for voxels in the noise pool, project out the polynomial regressors, and perform principal components analysis (PCA) on these time series. We add the PCs in decreasing order of variance explained to the GLM as nuisance regressors, and systematically evaluate cross-validation performance as a function of the number of PCs added. Finally, the optimal number of PCs is

selected (based on median cross-validated R^2 performance across task-related voxels) and used to obtain the

final response-amplitude estimates (beta weights).

2.4 General linear model (GLM) analysis

For each participant, runs were split into two groups using either an even/odd split (Experiments 1–3) or a by-

session split (Experiment 4). Each group of runs was analyzed using GLMdenoise

(http://cvnlab.net/GLMdenoise/), with denoising enabled (optimal number of PCs added to the GLM) and

denoising disabled (no PCs added to the GLM). A few notes on the application of GLMdenoise to our datasets:

Although this paper describes results for specific regions of interest, the denoising itself was not tailored in any

way to these regions but was applied to each dataset in its entirety (as is the default). Regarding the choice of

HRF, we used the default 'optimize' option, indicating that the HRF is estimated from the data. Since the

denoising procedure occurs after HRF estimation (see Section 2.3), the denoised and undenoised results reflect a

common HRF. Finally, the entire GLMdenoise procedure (including the internal use of cross-validation) was

applied independently to each split of the data; this strict splitting ensures that no improper "parameter sharing" or

"data peeking" occurred.

To prepare the data for multivariate pattern analysis, beta weights from the GLM analysis were converted to t

units (Misaki et al., 2010) by dividing each voxel's beta weights by the square root of the average squared

standard error. The final result of the GLM analysis is a set of four matrices containing multivoxel activity patterns.

These matrices are denoted $\mathbf{P}_{i,d}$ where i = 1 (first data split, referred to as *Test*) or 2 (second data split, referred to

as *Re-test*) and d = 1 (denoising disabled, referred to as *Baseline*) or 2 (denoising enabled, referred to as

Denoised). Each $\mathbf{P}_{i,d}$ has dimensions v x c where v is the number of voxels in the region of interest and c is the

number of experimental conditions.

To test GLMdenoise against the common practice of including motion parameters in the GLM design matrix, we

also fit two additional GLMs. The first GLM extends the baseline GLM by including the 6 rigid-body transformation

parameters obtained from motion correction (x, y, z, *pitch*, *roll*, *yaw*). The second GLM includes not only the rigid-

body parameters but also their squares, their temporal derivatives, and the squares of the temporal derivatives

(Friston et al., 1996), yielding a total of 24 additional parameters in the GLM design matrix. The beta weights

produced by these two additional GLMs are compared to those produced by GLMdenoise using the multivariate

analyses detailed below.

2.5 Representational similarity analysis (RSA)

For conceptual background and further details on RSA, we refer the reader to other papers (Charest et al., 2014;

Kriegeskorte et al., 2008a; Kriegeskorte and Kievit, 2013; Nili et al., 2014). Each set of multivoxel activity patterns

$\mathbf{P}_{i,d}$ was converted into a representational dissimilarity matrix (RDM) $\mathbf{R}_{i,d}$ using one minus Pearson's correlation (r)

as the metric of dissimilarity. Specifically, the element in the mth row and nth column of $\mathbf{R}_{i,d}$ was computed as one

minus the correlation between the mth and nth columns of $\mathbf{P}_{i,d}$. Each $\mathbf{R}_{i,d}$ has dimensions c x c where c is the

number of experimental conditions. We then computed three metrics of RDM replicability. *Baseline* is Pearson's

correlation between the lower triangles of $\mathbf{R}_{1,1}$ and $\mathbf{R}_{2,1}$, and indicates RDM replicability when there is no denoising

of either split of the data. *Denoised* is Pearson's correlation between the lower triangles of $\mathbf{R}_{1,2}$ and $\mathbf{R}_{2,2}$, and

indicates RDM replicability when there is denoising of both splits of the data. *Baseline/Denoised* is the average of

Pearson's correlation between the lower triangles of $\mathbf{R}_{1,1}$ and $\mathbf{R}_{2,2}$ and Pearson's correlation between the lower

triangles of $\mathbf{R}_{1,2}$ and $\mathbf{R}_{2,1}$, and indicates how well a denoised RDM from one split of the data correlates with an

undenoised RDM from the other split of the data. Results are very similar when using Spearman's correlation as

the measure of RDM replicability (data not shown).

To calculate error bars and statistical significance, a bootstrapping procedure was used. In this procedure, a

bootstrap sample is constructed by resampling experimental conditions with replacement. The resulting activity

patterns are used to compute RDMs, separately for each split of the data. These bootstrapped RDMs are then

compared using Pearson's correlation (as detailed above). The process is repeated 1,500 times to assess

variability due to sampling of experimental conditions. *P*-values are calculated by quantifying the fraction of

bootstrap samples where a given comparison of interest does not hold (for example, the fraction of cases where

Denoised does not lead to higher replicability than Baseline). Note that when calculating RDM metrics, artifactual

zeros in RDMs are ignored (multiple instances of the same condition lead to zero distances).

2.6 Cross-validated Mahalanobis distance

Recently, multivariate noise-normalized cross-validated Mahalanobis distance (crossnobis) has been proposed as

a novel method for computing RDMs (Walther et al., NeuroImage 2016; Diedrichsen et al. PloS Biol 2017).

Crossnobis provides unbiased estimates of distances, and can be viewed as an alternative approach to denoising

in the context of RSA. In brief, noise covariance between voxels is estimated from GLM residuals and used to

whiten regression coefficients (beta weights), and distances are estimated on an independent partition of the data.

To evaluate the crossnobis method, we performed two analyses. The first analysis involved computing cross-

validated Mahalanobis distances based on the design matrix of the baseline GLM (no PCs). This enables

assessment of the replicability of RDMs when computed using crossnobis distances. The second analysis

involved computing cross-validated Mahalanobis distances based on the design matrix of the final GLM identified

by GLMdenoise (optimal number of PCs). This provides an assessment of whether the crossnobis method can

benefit from the nuisance regressors identified by GLMdenoise. Note that in these analyses, strict data splitting is

observed: the cross-validation used in the crossnobis procedure is fully confined within each data split.

2.7 Classification analysis

We performed a simple correlation-based classification analysis, similar to that in (Haxby et al., 2001). Let m and

n refer to indices of two distinct experimental conditions. For both d = 1 (Baseline) and d = 2 (Denoised)**,** we

computed the 2 x 2 matrix $\mathbf{C}_d$ consisting of Pearson's correlations between activity patterns, where the rows

correspond to activity patterns for conditions m and n from the first split of the data (the mth and nth columns of

$\mathbf{P}_{1,d}$) and the columns correspond to activity patterns for conditions m and n from the second split of the data (the

mth and nth columns of $\mathbf{P}_{2,d}$). If the diagonal elements of $\mathbf{C}_d$ are larger than the off-diagonal elements, this

indicates that conditions m and n can be well discriminated. To convert $\mathbf{C}_d$ to a single number representing

percent correct, we assess whether element (1,1) is greater than (2,1) and whether (2,2) is greater than (1,2) (this

treats the first split as the training data and the second split as the testing data) as well as whether element (1,1)

is greater than (1,2) and whether (2,2) is greater than (2,1) (this treats the second split as the training data and

the first split as the testing data). Percent correct is calculated as the proportion of these four cases where a

successful outcome is observed (i.e. diagonal element larger than off-diagonal element). We performed this

procedure for every pair of experimental conditions, and then averaged performance across pairs. This yields a

single number (pairwise decoding accuracy) that indicates how well conditions can be discriminated from one

another.

To assess the statistical significance of the difference in accuracy between Baseline and Denoised, we performed

a permutation test in which undenoised and denoised activity patterns are randomly swapped. Specifically, each

column of $\mathbf{P}_{1,1}$ is swapped with the corresponding column of $\mathbf{P}_{1,2}$ with probability 0.5, and this procedure is

repeated for the columns of $\mathbf{P}_{2,1}$ and $\mathbf{P}_{2,2}$. After random swapping, differences in accuracy are computed just as in

the original procedure. The p-value is taken to be the fraction of permutation iterations that exhibit a difference in

accuracy that is equal to or larger than the observed difference.

3. RESULTS

We examined to what extent GLMdenoise improves sensitivity in the context of multivariate pattern analysis of fMRI data. To this end, we collected and analysed datasets from 31 fMRI participants. Each dataset involved a large number of experimental conditions presented multiple times over the course of the experiment. We split each dataset into halves (test and re-test) and applied a GLM analysis to each half with and without the use of GLMdenoise. The beta weights returned by the GLM analyses were then assessed using representational similarity analysis (RSA) and pattern classification.

3.1 Representational similarity analysis: GLMdenoise improves the replicability of representational dissimilarity matrices

We obtained representational dissimilarity matrices by correlating the pattern of beta weights obtained for each experimental condition (Figure 1). For individual participants, the denoising appears to lead to clearer representational structure shared between test and re-test results (see Supplementary Figure 1 for results on all participants). To further visualize GLMdenoise's impact on the similarity structure of the RDMs, we applied classical multi-dimensional scaling (MDS; metric stress) to the RDMs obtained from Participant 18 (Figure 2). MDS for the test and re-test RDMs after denoising (bottom row) shows clearer categorical structure (the categories are depicted with red, orange, blue, and cyan circles) than MDS of the test and re-test RDMs when no denoising was performed (top row). In addition, the right column shows that denoising reduces the displacement (or error) of each stimulus in the representational space.

To further quantify these effects, we computed three performance metrics for all participants. We compared the replicability of the test and re-test RDMs constructed without denoising (Baseline), denoising both data-splits (Denoised), and denoising only one data-split (Baseline/Denoised). Plotting these metrics, we see that RDM replicability is substantially higher when using GLMdenoise (Denoised) compared to baseline (Baseline). In several cases, there are very sizable improvements (Figure 3A), increasing from correlations near 0 to modest correlation values. The high variability in the amount of improvement obtained by denoising is consistent with earlier observations (Kay et al., 2013a) and reflects the fact that the amount of overlap between noise effects and experimental effects depends on a variety of factors such as the number of conditions, their temporal ordering, and incidental differences across participants (such as the amount of head motion).

It is possible that improved replicability reflects biased RDMs. For example, one can imagine a procedure that artificially creates RDM values that are all biased towards 0. Such a procedure would yield enhanced replicability values, but would yield inaccurate RDMs. The Baseline/Denoised metric indicates how well a denoised RDM matches an undenoised RDM from a separate split of the data. Across participants, this metric is higher than Baseline (Figure 3B). This establishes an important control: a raw (undenoised) RDM is better predicted by a denoised RDM compared to another raw RDM. This provides evidence that denoising does not induce bias to RDM structure, but rather, denoises the RDM structure, pushing it closer to the true RDM structure.

3.2 Representational similarity analysis: Comparing GLMdenoise to other popular methods

We compared improvements in RDM replicability provided by GLMdenoise to that provided by other denoising methods. One popular method is to include motion parameters in the GLM design matrix; we evaluated a version of this method that involves 6 regressors (rigid-body motion parameters) and a version that involves 24 regressors (rigid-body parameters plus squares and temporal derivatives). We observe an increase in RDM replicability compared to Baseline when including motion parameters (Figure 5A, second and third columns), but the improvements are not as large as those observed under GLMdenoise (Figure 5A, first column).

We also assessed RDM replicability for RDMs constructed using cross-validated Mahalanobis distance (Diedrichsen and Kriegeskorte, 2017; Walther et al., 2016). This approach provides unbiased distance estimates and accounts for fMRI noise structure (see Methods). RDM replicability using cross-validated Mahalanobis distance does not show improvements compared to Baseline (Figure 5A, fourth column), perhaps because estimation of noise covariance requires large amounts of data to achieve robust results. However, we explored an analysis in which the noise regressors identified by GLMdenoise are incorporated into the procedure for computing cross-validated Mahalanobis distance. We find that this combination strategy works well: introducing GLMdenoise yields improvements to RDM replicability (Figure 5B).

3.3 Representational similarity analysis: GLMdenoise improves consistency across participants

Thus far, we have only shown that GLMdenoise improves RDM replicability within participants. Do these benefits extend to improved replicability across participants? For each participant, we calculated a single RDM that reflects all data collected for that participant and then calculated Pearson's correlation between all pairs of participants within each experiment. We find that the majority of pairwise participant comparisons are improved when using GLMdenoise (Figure 6A) and that these improvements are greater than those observed using the motion-parameter approach (Figure 6B). This indicates that not only does GLMdenoise improve the quality of results for individual participants, but these improvements also translate to reduced variability at the group level, thereby enhancing the ability to make inferences about generalization of representational geometries across participants.

3.4 Pattern classification analysis: GLMdenoise improves decoding accuracy

We have established, using RSA, that multivariate similarity structure has better replicability when using GLMdenoise. If GLMdenoise improves replicability of representational structure, does this also translate into better decoding accuracies between experimental conditions? We performed a complementary analysis that quantifies how well conditions can be discriminated from one another based on fMRI activity patterns, in line with classical MVPA approaches.

We compared the average pairwise decoding accuracy before and after the use of GLMdenoise (see Methods for details). All participants exhibit an increase in decoding accuracy, and in 24 of 31 participants, this increase is statistically significant at $p < 0.05$ (Figure 3C). Since discriminability may be dependent on the specific conditions used in each of our four experiments, we computed the average increase in decoding accuracy independently for each experiment (Figure 3D). We find that in all four experiments, GLMdenoise provides substantial improvements in decoding accuracy, increasing percent correct by 4–6% on average across participants.

3.5 GLMdenoise improves brain-representational predictions of perceived object dissimilarity

To further assess whether GLMdenoise provides better estimates of task-related BOLD signals, we exploited behavioral measurements available in one of our experiments. Such measurements are independent of the physiological measurements provided by fMRI, and thus could provide independent validation of the fMRI results. In Experiment 4, participants engaged in a behavioral experiment in which they were asked to arrange the stimuli used in the fMRI experiment according to their similarity using an interactive display (Charest et al., 2014; Kriegeskorte and Mur, 2012). The purpose of this experiment was to characterize each participant's unique subjective experience of the stimuli and to potentially link these perceptual effects to the participant's brain representations (Charest et al., 2014). We computed Pearson's correlation between RDMs computed from a region of interest drawn around the inferior temporal cortex of the participants (brain RDM) and RDMs computed from the behavioral experiment (behavior RDM). This was done for the subset of stimuli that were common across all participants. For every participant, we observed an increase in correlation between the brain RDM and the behavior RDM when using GLMdenoise to construct the brain RDM (Figure 4). This is an important observation because the denoising performed on the fMRI data has no access to the behavioral similarity structure in any way. The improvement in brain-behavior correlation demonstrates that GLMdenoise improves the accuracy of information extracted from the brain data.

4. DISCUSSION

4.1. GLMdenoise yields more reliable estimates of task-related activity patterns

In this study, we have shown that our earlier observation of improved cross-validation accuracy of beta weights after application of GLMdenoise (Kay et al., 2013a) translates into practical benefits for studies using multivariate analyses. First, representational dissimilarity matrices estimated from independent splits of the data from each participant are more replicable after application of GLMdenoise. This indicates that GLMdenoise improves the reliability of activity pattern estimates and representational geometries. This improved reliability of pattern estimates also translates to greater pattern classification accuracies, stronger correlations between perceptual judgments and brain representations, and improved consistency of representational geometries at the group level.

4.2 GLMdenoise estimates and removes a wide variety of sources of nuisance variation

The philosophy behind GLMdenoise is similar to existing strategies for removing noise from neuroimaging data. Several denoising practices exist in which nuisance regressors are considered and removed from the data. Perhaps the most common denoising practice is the inclusion of motion parameters as additional regressors in the general linear model (Bright and Murphy, 2015; Monti, 2011; Pernet, 2014). Other sources of noise that are often included involve auxiliary physiological measurements, such as cardiac and respiratory measurements to predict some of the physiological noise components in the BOLD signal (Birn et al., 2006; Chang et al., 2009; Glover et al., 2000; Hagberg et al., 2012; Shmueli et al., 2007). There are two key advantages offered by GLMdenoise over these existing methods. One is that GLMdenoise captures all of these types of nuisance effects. Another is that GLMdenoise removes nuisance effects in a way that is specifically designed to not overfit the data. For example, as we showed previously (Kay et al., 2013a) and as shown in the present study (see Figure 5A), including motion parameters in the linear model often does help, but also has the capacity to hurt. As a matter of design, GLMdenoise optimizes the number of noise regressors used on each dataset. This is important because whether modeling out nuisance effects is effective depends on the magnitude of the noise, the magnitude of the task-related signals, and the amount of correlation between the noise and task-related signals, all of which may depend on the participant and the experiment (Kay et al., 2013a).

One possible concern with using GLMdenoise is that it somehow leads to fMRI beta weights that do not reflect the 'true' activity patterns elicited by the experimental conditions. For example, if a denoising method altered beta weights by biasing them towards the mean beta weight, this would improve replicability at the expense of pulling condition-specific activity patterns away from the true underlying activity patterns. Such bias could potentially underlie the observation that denoised RDMs are smoother than baseline RDMs (see Figure 1). There are three considerations that argue against this possibility. First, considering the nature of the technique, we see that there is no explicit mixing of signals across voxels (aside from the fact that the nuisance regressors are derived from a common noise pool): each voxel is independently modeled by the GLM and there is no restriction on the weights associated with the nuisance regressors for each voxel. Thus, it is difficult to see how some sort of smoothing

bias could result from the GLMdenoise procedure. Second, in our RDM analysis, we found that undenoised RDMs are better predicted, using an independent split of the data, by denoised RDMs than by undenoised RDMs. This suggests that denoising does not induce bias but instead reduces variance. Third, we exploit the similarity judgments collected in Experiment 4 as an external validation of brain RDM estimates. We were able to confirm, using this different measurement modality, that denoising brain measurements improves the correspondence between perceived similarity and the brain's similarity structure. Given these considerations, we suggest that GLMdenoise provides substantially better estimates of task-related activity patterns without inducing appreciable bias.

4.3 What preconditions and complications are associated with the application of GLMdenoise?

The GLMdenoise technique is general (it requires only a design matrix and fMRI time-series) and fully automated (it requires no hand-tuning of parameters, although it can be customized if desired). Furthermore, because no physiological recordings nor additional fMRI data are required, the technique can be retrospectively applied to existing fMRI datasets. Despite these appealing features, it is important to recognize some caveats and limitations:

- Since GLMdenoise relies on cross-validation of task-related BOLD signals, GLMdenoise is not applicable to resting-state fMRI.
- GLMdenoise requires multiple fMRI runs, with presentation of each condition more than once. This is necessary because GLMdenoise involves cross-validation across runs. Conventional denoising techniques are recommended for experiments with only one repetition per condition.
- Because GLMdenoise is fully data-driven, the nature of the noise removed is unclear without further analyses. Moreover, the amount of noise removed and its properties may vary across experiments and participants.
- A central assumption of GLMdenoise is that the fMRI measurements (including both task-related signals and noise sources) are relatively stationary across runs. In other words, evoked BOLD signals should be replicable across runs and general trial distributions should be relatively balanced throughout the experiment.
- The number of noise regressors in GLMdenoise is, by default, optimized with respect to all voxels exhibiting task-related signals. It is possible that specific brain regions might degrade in accuracy while the rest of the dataset improves. If one desires, one can restrict the optimization to specific voxels of interest. This and other customizations are implemented in the GLMdenoise toolbox.

Bearing in mind these caveats and limitations, we believe that the substantial improvements in the quality of MVPA results we have demonstrated make GLMdenoise a valuable analysis tool.

5. AUTHOR CONTRIBUTIONS

I.C. and K.K. conducted the experiments, analyzed the data, and wrote the paper. All authors discussed the results and edited the manuscript.

6. ACKNOWLEDGMENTS

We thank J. Winawer for helpful comments. This work was supported by an European Research Council (ERC) Starting Grant ERC-2017-StG 759432 (to I.C.), by an UK Medical Research Council Grant MC-A060-5PR60 and an ERC Starting Grant ERC-2010-StG 261352 (to N.K.), and by the McDonnell Center for Systems Neuroscience and Arts & Sciences at Washington University (to K.K.).

7. COMPETING INTERESTS

The authors confirm that there are no competing interests.

8. APPENDIX A. SUPPLEMENTARY DATA

Supplementary data associated with this article can be found, in the online version, at doi:XXX.

REFERENCES

Allen, E.J., Moerel, M., Lage-Castellanos, A., De Martino, F., Formisano, E., Oxenham, A.J., 2018. Encoding of natural timbre dimensions in human auditory cortex. NeuroImage 166, 60–70. doi:10.1016/j.neuroimage.2017.10.050

Behzadi, Y., Restom, K., Liau, J., Liu, T.T., 2007. A component based noise correction method (CompCor) for BOLD and perfusion based fMRI. NeuroImage 37, 90–101. doi:10.1016/j.neuroimage.2007.04.042

Bianciardi, M., van Gelderen, P., Duyn, J.H., Fukunaga, M., de Zwart, J.A., 2009. Making the most of fMRI at 7 T by suppressing spontaneous signal fluctuations. NeuroImage 44, 448–454. doi:10.1016/j.neuroimage.2008.08.037

Birn, R.M., Diamond, J.B., Smith, M.A., Bandettini, P.A., 2006. Separating respiratory-variation-related fluctuations from neuronal-activity-related fluctuations in fMRI. NeuroImage 31, 1536–1548. doi:10.1016/j.neuroimage.2006.02.048

Boynton, G.M., Engel, S.A., Glover, G.H., Heeger, D.J., 1996. Linear systems analysis of functional magnetic resonance imaging in human V1. J. Neurosci. Off. J. Soc. Neurosci. 16, 4207–4221.

Bright, M.G., Murphy, K., 2015. Is fMRI "noise" really noise? Resting state nuisance regressors remove variance with network structure. NeuroImage 114, 158–169. doi:10.1016/j.neuroimage.2015.03.070

Carlson, T.A., Tovar, D.A., Alink, A., Kriegeskorte, N., 2013. Representational dynamics of object vision: The first 1000 ms. J. Vis. 13, 1–1. doi:10.1167/13.10.1

Chang, C., Cunningham, J.P., Glover, G.H., 2009. Influence of heart rate on the BOLD signal: the cardiac response function. NeuroImage 44, 857–869. doi:10.1016/j.neuroimage.2008.09.029

Charest, I., Kievit, R.A., Schmitz, T.W., Deca, D., Kriegeskorte, N., 2014. Unique semantic space in the brain of each beholder predicts perceived similarity. Proc. Natl. Acad. Sci. 111, 14565–14570.

Ciric, R., Wolf, D.H., Power, J.D., Roalf, D.R., Baum, G.L., Ruparel, K., Shinohara, R.T., Elliott, M.A., Eickhoff, S.B., Davatzikos, C., Gur, R.C., Gur, R.E., Bassett, D.S., Satterthwaite, T.D., 2017. Benchmarking of participant-level confound regression strategies for the control of motion artifact in studies of functional connectivity. NeuroImage 154, 174–187. doi:10.1016/j.neuroimage.2017.03.020

Cichy, R.M., Khosla, A., Pantazis, D., Oliva, A., 2016a. Dynamics of scene representations in the human brain revealed by magnetoencephalography and deep neural networks. NeuroImage. doi:10.1016/j.neuroimage.2016.03.063

Cichy, R.M., Pantazis, D., Oliva, A., 2016b. Similarity-Based Fusion of MEG and fMRI Reveals Spatio-Temporal Dynamics in Human Cortex During Visual Object Recognition. Cereb. Cortex bhw135. doi:10.1093/cercor/bhw135

Cichy, R.M., Pantazis, D., Oliva, A., 2014. Resolving human object recognition in space and time. Nat. Neurosci. 17, 455–462. doi:10.1038/nn.3635

Diedrichsen, J., Kriegeskorte, N., 2017. Representational models: A common framework for understanding encoding, pattern-component, and representational-similarity analysis. PLoS computational biology 13, e1005508. doi:10.1371/journal.pcbi.1005508

Erez, J., Cusack, R., Kendall, W., Barense, M.D., 2016. Conjunctive Coding of Complex Object Features. Cereb. Cortex 26, 2271–2282. doi:10.1093/cercor/bhv081

Fox, M.D., Snyder, A.Z., Zacks, J.M., Raichle, M.E., 2006. Coherent spontaneous activity accounts for trial-to-trial
variability in human evoked brain responses. Nat. Neurosci. 9, 23–25. doi:10.1038/nn1616

Friston, K.J., Williams, S., Howard, R., Frackowiak, R.S., Turner, R., 1996. Movement-related effects in fMRI
time-series. Magn Reson Med 35, 346–355.

Friston, K.J., Frith, C.D., Turner, R., Frackowiak, R.S.J., 1995a. Characterizing Evoked Hemodynamics with fMRI.
NeuroImage 2, 157–165. doi:10.1006/nimg.1995.1018

Friston, K.J., Holmes, A.P., Poline, J.-B., Grasby, P.J., Williams, S.C.R., Frackowiak, R.S.J., Turner, R., 1995b.
Analysis of fMRI Time-Series Revisited. NeuroImage 2, 45–53. doi:10.1006/nimg.1995.1007

Friston, K.J., Holmes, A.P., Worsley, K.J., Poline, J.B., Frith, C.D., Frackowiak, R.S.J., 1994. Statistical
parametric maps in functional imaging: A general linear approach. Hum. Brain Mapp. 2, 189–210.

Glover, G.H., Li, T.Q., Ress, D., 2000. Image-based method for retrospective correction of physiological motion
effects in fMRI: RETROICOR. Magn. Reson. Med. 44, 162–167.

Hagberg, G.E., Bianciardi, M., Brainovich, V., Cassara, A.M., Maraviglia, B., 2012. Phase stability in fMRI time
series: effect of noise regression, off-resonance correction and spatial filtering techniques. NeuroImage
59, 3748–3761. doi:10.1016/j.neuroimage.2011.10.095

Haxby, J.V., 2012. Multivariate pattern analysis of fMRI: The early beginnings. Neuroimage 62, 852–855.
doi:10.1016/j.neuroimage.2012.03.016

Haxby, J.V., Gobbini, M.I., Furey, M.L., Ishai, A., Schouten, J.L., Pietrini, P., 2001. Distributed and Overlapping
Representations of Faces and Objects in Ventral Temporal Cortex. Science 293, 2425–2430.

Haynes, J.D., Rees, G., 2006. Decoding mental states from brain activity in humans. Nat. Rev. Neurosci. 7, 523–
34.

Kamitani, Y., Tong, F., 2005. Decoding the visual and subjective contents of the human brain. Nat. Neurosci. 8,
679–85.

Kay, K.N., Rokem, A., Winawer, J., Dougherty, R.F., Wandell, B.A., 2013a. GLMdenoise: a fast, automated
technique for denoising task-based fMRI data. Front. Neurosci. 7. doi:10.3389/fnins.2013.00247

Kay, K.N., Weiner, K.S., Grill-Spector, K., 2015. Attention Reduces Spatial Uncertainty in Human Ventral
Temporal Cortex. Curr. Biol. 25, 595–600. doi:10.1016/j.cub.2014.12.050

Kay, K.N., Winawer, J., Mezer, A., Wandell, B.A., 2013b. Compressive spatial summation in human visual cortex.
J. Neurophysiol. 110, 481–494. doi:10.1152/jn.00105.2013

Kriegeskorte, N., Goebel, R., Bandettini, P.A., 2006. Information-based functional brain mapping. PNAS 103,
3863–3868.

Kriegeskorte, N., Kievit, R.A., 2013. Representational geometry: integrating cognition, computation, and the brain.
Trends Cogn. Sci. 17, 401–412.

Kriegeskorte, N., Mur, M., 2012. Inverse MDS: Inferring Dissimilarity Structure from Multiple Item Arrangements.
Front. Psychol. 3.

Kriegeskorte, N., Mur, M., Bandettini, P.A., 2008a. Representational similarity analysis – connecting the branches
of systems neuroscience. Front. Syst. Neurosci.

Kriegeskorte, N., Mur, M., Ruff, D.A., Kiani, R., Bodurka, J., Esteky, H., Tanaka, K., Bandettini, P.A., 2008b.
Matching categorical object representations in inferior temporal cortex of man and monkey. Neuron 60,
1126–1141.
Lindquist, M.A., Loh, J.M., Atlas, L.Y., Wager, T.D., 2009. Modeling the Hemodynamic Response Function in
fMRI: Efficiency, Bias and Mis-modeling. Neuroimage 45, S187–S198.
doi:10.1016/j.neuroimage.2008.10.065
Lund, T.E., Madsen, K.H., Sidaros, K., Luo, W.-L., Nichols, T.E., 2006. Non-white noise in fMRI: Does modelling
have an impact? NeuroImage 29, 54–66. doi:10.1016/j.neuroimage.2005.07.005
Misaki, M., Kim, Y., Bandettini, P.A., Kriegeskorte, N., 2010. Comparison of multivariate classifiers and response
normalizations for pattern-information fMRI. NeuroImage 53, 103–118.
doi:10.1016/j.neuroimage.2010.05.051
Monti, M.M., 2011. Statistical Analysis of fMRI Time-Series: A Critical Review of the GLM Approach. Front. Hum.
Neurosci. 5. doi:10.3389/fnhum.2011.00028
Nili, H., Wingfield, C., Walther, A., Su, L., Marslen-Wilson, W., Kriegeskorte, N., 2014. A Toolbox for
Representational Similarity Analysis. PLoS Comput. Biol. 10, e1003553.
doi:10.1371/journal.pcbi.1003553
Pernet, C.R., 2014. Misconceptions in the use of the General Linear Model applied to functional MRI: a tutorial for
junior neuro-imagers. Front. Neurosci. 8. doi:10.3389/fnins.2014.00001
Shmueli, K., van Gelderen, P., de Zwart, J.A., Horovitz, S.G., Fukunaga, M., Jansma, J.M., Duyn, J.H., 2007.
Low-frequency fluctuations in the cardiac rate as a source of variance in the resting-state fMRI BOLD
signal. NeuroImage 38, 306–320. doi:10.1016/j.neuroimage.2007.07.037
Walther, A., Nili, H., Ejaz, N., Alink, A., Kriegeskorte, N., Diedrichsen, J., 2016. Reliability of dissimilarity
measures for multi-voxel pattern analysis. NeuroImage 137, 188–200.
doi:10.1016/j.neuroimage.2015.12.012
Weiner, K.S., Golarai, G., Caspers, J., Chuapoco, M.R., Mohlberg, H., Zilles, K., Amunts, K., Grill-Spector, K.,
2014. The mid-fusiform sulcus: A landmark identifying both cytoarchitectonic and functional divisions of
human ventral temporal cortex. NeuroImage 84, 453–465. doi:10.1016/j.neuroimage.2013.08.068
Worsley, K.J., Friston, K.J., 1995. Analysis of fMRI Time-Series Revisited—Again. NeuroImage 2, 173–181.
doi:10.1006/nimg.1995.1023
Yeatman, J.D., Rauschecker, A.M., Wandell, B.A., 2013. Anatomy of the visual word form area: adjacent cortical
circuits and long-range white matter connections. Brain Lang. 125, 146–155.
doi:10.1016/j.bandl.2012.04.010
33

  FIGURES

Figure 1. GLMdenoise improves the quality of representational dissimilarity matrices (RDMs). Each

participant's fMRI dataset was split into two halves (Test, Re-test), and each half was analyzed with a standard

GLM (Baseline) or with GLMdenoise (Denoised). The results of each analysis are used to construct an RDM,

which indicates the dissimilarity between the multivoxel activity patterns associated with each pair of experimental

conditions. (A) Results for a participant from Experiment 1 (Participant 3). The yellow circle highlights a section of

the RDMs for which denoising yields clearer structure and improves replicability across splits of the data. (B)

Results for a participant from Experiment 2 (Participant 4). Same format as A. (C) Results for a participant from

Experiment 4 (Participant 26). Same format as A. (D) Metrics of RDM quality. We computed three metrics

quantifying the replicability of the lower triangles of the RDMs. *Baseline* is the test-retest correlation of the

undenoised RDMs. *Denoised* is the test-retest correlation of the denoised RDMs. *Baseline/Denoised* is the

correlation between an undenoised RDM and a denoised RDM (correlation values for the two possible cases are

averaged). See Supplementary Figure 1 for RDM results for all participants.

Figure 2. Multidimensional scaling (MDS) illustrates the benefit of denoising RDMs. We apply classical MDS to visualize the similarity structure of the RDMs obtained for Participant 18. Each point is color-coded with regards to stimulus category (red: places, orange: objects, blue: bodies, cyan: faces) and shows the actual stimulus presented to the participant. To quantify the replicability of MDS results across Test and Re-test, we co-registered the two sets of results by first normalizing the scale of each MDS result and then rotating the Re-test MDS result to minimize the error with respect to the Test MDS result. The colored lines depict the distance between Test and Re-test results. Short lines indicate that an item's position in the representational space is stable across data halves. Long lines suggest that the underlying activity patterns contain noise that is corrupting the RDM results. Denoising substantially improves test-retest replicability of MDS results and increases clustering of similar points. Note that this is just an illustrative example suggesting the potential impact of denoising on neuroscientific results; systematic evaluation of denoising performance for all participants and experiments is provided in later figures.

Figure 3. GLMdenoise consistently improves RDM quality and classification performance. (A) RDM metrics for each participant. Error bars (68% confidence intervals) and statistical significance levels were calculated by bootstrapping experimental conditions. The top row of asterisks indicates *p*-values for Baseline/Denoised > Baseline, while the bottom row of asterisks indicates *p*-values for Denoised > Baseline. Many participants exhibit a statistically significant increase in performance relative to Baseline. Importantly, no participant exhibits a statistically significant decrease in performance relative to Baseline. (B) Summary of RDM metrics. For each participant, we compute the increase in correlation relative to Baseline. The median increase across participants is shown (error bars and statistical significance were computed by bootstrapping participants). (C) Classification performance for each participant. The asterisks indicate *p*-values for Denoised > Baseline (permutation test; see Methods). Many participants exhibit a statistically significant increase in performance, and no participant exhibits a decrease in performance. (D) Summary of classification performance. For each participant, we compute the increase in performance relative to Baseline. The mean increase across participants (separated by experiment) is shown. Error bars (standard errors) and statistical significance (*t*-test) were computed parametrically due to the small number of participants in Experiments 1–3.

Figure 4. Denoising of brain-based RDMs improves correspondence with behavior-based RDMs. In

Experiment 4, participants were asked to make behavioral judgments about the stimuli used in the fMRI

experiment, and an RDM was constructed from these behavioral judgments. We averaged the Test and Re-test

RDMs derived from the fMRI data and then correlated the lower triangle of this brain-based RDM to the lower

triangle of the behavior-based RDM. This figure shows the correlation observed for each participant, before and

after denoising. Black dots indicate the median across participants. Nearly all (19/20) participants show an

increase in correlation and this increase in correlation is statistically significant (two-tailed sign test).

Figure 5. Comparison of GLMdenoise to other approaches. We evaluated the potential benefits of using
GLMs augmented with motion parameter estimates and of constructing RDMs using cross-validated Mahalanobis
distances (Diedrichsen and Kriegeskorte, 2017; Walther et al., 2016). (A) Summary of results. Each 'x' indicates
for one participant the increase in RDM replicability (correlation between split-half RDMs) observed relative to
Baseline. The black dot indicates the median increase across participants (error bars indicate 68% confidence
intervals obtained by bootstrapping participants). (B) GLMdenoise can be combined with cross-validated
Mahalanobis distances. We calculated the replicability of RDMs constructed with the cross-validated Mahalanobis
distance method, either using the GLM design matrix in the Baseline model (*x*-axis) or using the GLM design
matrix provided by GLMdenoise (*y*-axis). Each dot corresponds to one participant. The results show that
GLMdenoise is compatible with cross-validated Mahalanobis distance and can improve results.

Figure 6. GLMdenoise improves across-participant consistency of representational geometries. For each

participant, we averaged the split-half activity patterns to obtain a single set of activity patterns, computed RDMs

from these activity patterns, and then computed RDM-to-RDM correlations between all pairs of participants. (For

Experiment 4, we restricted this analysis to the 36 of the 72 conditions that were common across participants.) (A)

Improvements observed using GLMdenoise. Results with no denoising (*x*-axis) are compared against results with

GLMdenoise (*y*-axis). Each light dot indicates one pairwise correlation, and each dark dot indicates the centroid of

all pairwise correlations observed for a given experiment. (B) Improvement observed using Motion regressors (24

regressors). Same format as panel A. Overall, GLMdenoise and, to a lesser degree, motion regressors improve

across-participant consistency. The black arrow highlights cases in which improvements are especially large. This

is consistent with earlier observations that denoising appears to be especially helpful for datasets where signal

quality is initially low (see Figure 3).

1 **Table 1. Summary of datasets.**

Experiment	Participants	Number of conditions	Condition duration (seconds)	Number of repetitions per run (or run set)	Number of runs (or run sets)	Scanner	Voxel size (mm)	TR (seconds)	TE (ms)	Flip angle (deg)	Volume dimensions	Number of volumes per run	Total number of runs	Data split
1	1–3	69	3	1	4	3T1	2.5	1.323751	29.7	71	64 x 64 x 21	270	8	even/odd
2	4–6	75	3.5	1	4	CNI	2	2.006553	31	77	80 x 80 x 26	136	12	even/odd
3	7–11	32	4	2	10	NIL	2.5	2	30	77	80 x 80 x 28	156	10	even/odd
4	12–31	72	1	1	18 (9 per session)	CBU	3 x 3 x 3.75	2	30	78	64 x 64 x 32	216	18	by session

3T1 = Lucas Center at Stanford University, 3T GE Signa HDX scanner, Nova quadrature or 8-channel RF coil;

CNI = Stanford Center for Neurobiological Imaging, 3T GE Signa MR750 scanner, Nova 16-channel RF coil; NIL

= Neuroimaging Laboratory at Washington University, 3T Siemens Skyra scanner, Siemens 32-channel RF coil;

CBU = Medical Research Council–Cognition and Brain Sciences Unit, 3T Siemens Trio scanner, Siemens 12-

channel RF coil. Additional notes: All experiments used a T2*-weighted, single-shot, gradient-echo pulse

sequence, either spiral-trajectory (3T1) or echo-planar imaging (CNI, NIL, CBU).

Supplementary Figure 1. RDM results for all participants. Same format as Figure 1.