Deep Learning provides exceptional accuracy to ECoG-based Functional Language Mapping for epilepsy surgery

Harish RaviPrakash[a], Milena Korostenskaja[b,c,d], Eduardo M. Castillo[c,d], Ki H. Lee[d], Christine M. Salinas[d], James Baumgartner[d], Syed M. Anwar[a], Concetto Spampinato[e,a], Ulas Bagci[a,*]

[a]*Center for Research in Computer Vision, University of Central Florida, FL, USA*
[b]*Functional Brain Mapping and Brain Computer Interface Lab, AdventHealth Orlando, FL, USA*
[c]*MEG Lab, AdventHealth Orlando, FL, USA*
[d]*AdventHealth Medical Group Epilepsy at Orlando, AdventHealth Orlando, FL, USA*
[e]*Department of Electrical, Electronics and Computer Engineering, University of Catania, Catania, Italy*

Abstract

The success of surgical resection in epilepsy patients depends on preserving functionally critical brain regions, while removing pathological tissues. Being the gold standard, electro-cortical stimulation mapping (ESM) helps surgeons in localizing the function of eloquent cortex through electrical stimulation of electrodes placed directly on the cortical brain surface. Due to the potential hazards of ESM, including increased risk of provoked seizures, electrocorticography based functional mapping (ECOG-FM) was introduced as a safer alternative approach. However, ECoG-FM has a low success rate when compared to the ESM. In this study, we address this critical limitation by developing a new algorithm based on deep learning for ECoG-FM and thereby we achieve an accuracy comparable to ESM in identifying eloquent language cortex. In our experiments, with 11 epilepsy patients who underwent presurgical evaluation (through deep learning-based signal analysis on 637 electrodes), our proposed algorithm made an exceptional 23% improvement with respect to the conventional ECoG-FM analysis (~60%). We obtained the state-of-the-art accuracy of 83.05% in identifying language regions, which has never been achieved before. Our findings have demonstrated, for the first time, that deep learning powered ECoG-FM can serve as a stand-alone modality and avoid likely hazards of the ESM in epilepsy surgery. Hence, reducing the potential for developing post-surgical morbidity in the language function.

Keywords: Deep Learning, Electro-cortical Stimulation Mapping (ESM), Electrocorticography (ECoG), Real Time Functional Mapping (RTFM)

Word Counts: 5999. Abstract - 211

1. Introduction

Epilepsy is a chronic neurological disorder characterized by recurrent, unpredictable seizures with over 65 million reported cases around the world (1). Approximately 20% of these patients are diagnosed with *drug-resistant epilepsy (DRE)*. The only possible treatment in a majority of these cases is surgical intervention. During epilepsy surgery the pathological brain tissue, which is associated with seizures, might be surgically removed. While epilepsy surgery is a curative option for drug-resistant epilepsy, neurosurgeons need to avoid removing tissues associated with language, sensory, and motor functions. This calls for an accurate identification and localization of these functionally significant brain regions. The surgical procedure can be performed more accurately with a precise localization for preventing any corresponding post-surgical neurological/functional deficits. This would ensure an improved and sustainable post-surgical quality of life for patients presented for brain surgery.

Electro-cortical stimulation mapping (ESM) has been considered as the gold standard for functional cortex localization in epilepsy surgery. ESM is an invasive procedure that uses electrodes placed on the surface of the brain (grid electrodes) or within the brain (depth electrodes). It is considered vital for reducing the risk of language deficits post-surgery and therefore, expanding surgical options. ESM has a long history of serving as the main modality for pre-surgical functional mapping of epilepsy patients. Acute electrical cortical stimulation was successfully performed in 1950 during epilepsy surgery by Penfield and colleagues (2,3). During ESM, pairs of electrodes covering the region of interest (in our case - eloquent cortex) are stimulated by delivering a brief electric pulse. The stimulation temporarily disables/inhibits the cortical area of interest (creates a temporary functional lesion). Behavioral changes such as unusual sensation, involuntary movements, or language impairments (i.e., speech paucity), observed during stimulation indicates that the tested area is essential to that task performance, and its resection might lead to functional deficits. Ojemann et al. (4) studied language localization using ESM, on a large dataset of 117 patients. The study found that there was sufficiently large individual variability in the exact location of language function and concluded that there was a need for an improved language localization model. Much later, more standard and effective tasks for expressive language localization, such as verb generation (5) and picture naming (6), were tested with the increased use of ESM.

However, one major drawback of ESM is its potential to induce after-discharges (7), which could result in seizures. Since stimulation provoked seizures can occur rather frequently during ESM procedures (8), ESM tests often need to be repeated, leading to extended time and effort from medical professionals (neuropsychologists and/or neurologists). In some cases, the ESM procedure cannot be completed due to repeated seizure activity and/or its consequences.

The current limitations of the ESM have created a strong need for establishing other independent functional mapping modalities to identify eloquent cortex. Unfortunately, as of now, none of the existing neuro-imaging modalities are flexible enough to provide

functional mapping results in real time in the operating room. Therefore, the search for a stand-alone methodology for functional eloquent cortex localization has been continuing and resulted in attempts to use electrocorticography (ECoG) as a viable alternative. ECoG is the invasive version of electroencephalography (EEG) and sometimes also referred to as intracranial encephalography, demonstrating excellent temporal resolution like EEG. Importantly, ECoG equipment is portable and can be utilized both at the patients' bed-side and intra-operatively. Unlike EEG, it overcomes the problem of poor spatial resolution, since the activity of interest is recorded directly from the cortical brain surface. It also avoids the problem of electrical signal attenuation in EEG caused by the signal propagation through tissues surrounding the brain. To record ECoG signals, a craniotomy (removal of the skull section: *bone flap*) is performed and the dura is opened to access the brain tissue. The arrays of grid of electrodes (**Figure 1a, left**) are then placed on the exposed cerebral cortex. Following this, ECoG-based functional mapping (ECoG-FM) is performed, while task-based responses from grid electrodes are recorded. Since there is no external electrical stimulation during this process, ECoG-FM is considered as a safer alternative to ESM. When performed in real time (9), ECoG-FM procedure can be referred to as real-time functional mapping (RTFM) (10–13). **Figure 1a** demonstrates the general setup for ECoG-FM recordings.

1.1 Related works and existing critical challenges

ECoG-based approaches have been used successfully for motor cortex localization (10,11,14–16). In comparison, the localization of functional language cortex appears far more complex and challenging (17). Current localization approaches are based on detecting positive response channels (called *active channels or active electrodes*) among the set of all channels. A baseline recording of each channel at resting-state is used to determine signal characteristics at specific frequency ranges. Most often, power of the ECoG signal lies within the α, β, and (primarily) high-γ (70Hz-170Hz) frequency bands (9,18). These values are compared with the signal power measured during the execution of language task. The results of this approach for language mapping have not achieved desirable accuracy. For example, Arya et al. (19) studied high-γ response from ECoG recording of 7 patients during spontaneous conversation. The results showed low specificity and accuracy. In a follow up study, Arya et al. (20) demonstrated high-gamma modulation for the story-listening task and achieved high specificity, but sensitivity remained low. Korostenskaja et al. (21) showed that similar to the results for motor cortex, ECoG-FM can be used for eloquent language cortex localization as a complimentary technique with ESM, but not as a stand-alone modality. It has also been demonstrated that ECoG-FM can be used as a guiding tool for ESM, thereby reducing the time of ESM procedure and decreasing the risk of provoked seizures (13,22).

Despite their potential, the current ECoG-FM approaches are not found capable enough to be used as a stand-alone methodology for accurate language mapping. To address these challenges and provide ECoG-FM more independence in eloquent

language cortex localization, we fill in the following currently existing methodological gaps:

i   Available approaches compare a channel's signal with its resting-state (baseline) recording and do not compare the channels' characteristics to other recorded channels.

ii The signal characteristics in the frequency range beyond high-γ band have not been explored yet to the best of our knowledge.

iii There has been limited work on validation of ECoG-FM for language cortex localization; hence, there are more evidences needed for utilization of ECoG-FM in the clinics.

Figure 1: Overview of a) the language localization framework with ECoG-based functional mapping (ECoG-FM) approach. ECoG signal recording, data transfer, storage, research and clinical paths, and tasks are illustrated. ECoG signals are obtained in response to task-related changes (e.g., picture naming) from grid electrodes implanted on the cortical surface in the subdural space, b) the proposed ECoG signal classification approach for each channel on the cortical surface in the subdural space. PRC - Positive Response Channel, NRC - Negative Response Channel. Each individual step is considered as a "module" in the overall system design.

In our previous works (23,24), we showed the feasibility of utilizing conventional
machine learning methods for channel response classification by using the whole
signal spectrum (not limited to *α, β* & *high γ*) and without using the baseline recording.
This was one of the first machine learning based approaches in this field with strong
results and demonstrated the potential of ECoG-FM signal to be analyzed more
accurately compared to conventional signal processing based descriptive methods.

1.2 Summary of our contributions

We propose an innovative deep learning algorithm for accurately classifying the
channel response of eloquent cortex, alleviating the current challenges of ECoG-FM.
We also show the effectiveness of using deep learning methods in problems with
limited number of patients but sufficient samples to achieve desired performance. Our
main contributions are as follows,

1. We have used the complete ECoG signal frequency spectrum for the first time
to the best of our knowledge to identify signal characteristics for mapping
language cortex.
2. Our innovative deep learning models achieve state-of-the-art performance in
language cortex mapping using ECoG-FM. We have achieved 82% sensitivity
in classifying both positive and negative response channels.
3. We have shown that deep learning models can be successfully used in studies
even with a limited number of subjects and low dimensional (1D) data. The
requirement for sufficient data to train our deep learning model is satisfied as
we show that the number of data points (due to a dense grid placement and
high-resolution signal) are adequate and our experimental results add credence
to these findings.
4. Our results have indicated that with the proposed deep learning-based
classification model, ECoG-FM can be reliably used as a standalone technique
for functional language mapping.

2. Materials and Methods

An overview of the proposed system is illustrated in **Figure 1b**. We pre-processed
the ECoG signals using temporal filtering such that the selected samples were
synchronized with the start and end points of the task resulting in equal length blocks.
We then divided the equal length ECoG signal blocks into overlapping sub-blocks of
data. Our aim was to learn *discriminative signal patterns* and eventually reduced the
computational load (Step 1). We learned different sets of signal features independently:
frequency domain (i.e. auto-regression) and time domain (deep learning-based
features) in Step 2 and Step 3, respectively. After we combined the learned features,
we trained a recurrent neural network (RNN), a class of deep learning algorithm suited
for analyzing sequential data, to classify sub-blocks of signals (Step 4). Finally, we
used the majority voting technique to combine these sub-block labels and determine
an overall (PRC or NRC) channel label (Step 5). In the following sub-sections, we will
describe each module of our proposed system in detail.

2.1 Dataset

The study was approved by the Institutional Review Board at AdventHealth
Orlando, Orlando, USA. We recruited eleven patients with drug-resistant epilepsy, who
underwent pre-surgical evaluation with ECoG grid implantation. All patients provided
their written informed consent to participate in this study. The patients were teenagers
and adults with an average age of 23.18 ± 11.61 years (See Supplementary **Table 1**
for summary of the patient demographics).

2.2 Pre-processing ECoG Signal (Step 1)

As a first step of preparing the recorded data for deep learning-based analysis, non-
task/control time points in the signal were eliminated using temporal filtering. Hence,
the spontaneous activity recordings before the start and trailing signals at the end of
the experiment were discarded from the blocks. These synchronized and uniform
length blocks were fed to the deep networks for functional channel classification (See
Supplementary for more details about this step).

2.3 Time Domain RNN (Step 2)

Our goal was to find discriminative signal patterns from ECoG signals, which are
time varying and non-stationary 1D sequences. They are non-stationary because task
based ECoG recordings can have signal statistics which depend on the time relative to
the events. Inspired by the effectiveness of recurrent neural networks in sequence
classification tasks in different domains (25–27), we have developed RNN based deep
neural network algorithms to extract discriminative features from time-domain ECoG
data. We hypothesized that limitations of the conventional spectral (frequency-based)
or time-based signal analysis methods can be overcome with RNN based methods. In
RNNs outputs from previous time steps are taken as input for the current time step,
thereby forming a directed cyclic graph. RNNs thus learn the relationships in sequential
data thereby retaining higher contextual information.
221

The ECoG signal consists of over a thousand samples every second; to learn signal
characteristics from such a noisy data, we first used popular EEG features (28–30). A
sliding window approach was applied to extract features, which were then
concatenated into a single feature vector to represent the control and active-task blocks
in the signal. The extracted features included mean, skew, kurtosis, peak to peak value,
and Hjorth values (details in supplementary).
228

The time domain features were fed to the learning module illustrated in **Figure 2**.
The complete ECoG signal contained both control and active task signals, thus; the
sub-blocks of control signals were ignored and the input to this time domain module
was sub-blocks of active task signals. Recently, 1D convolutional networks have been
shown to perform well in time series forecasting and classification tasks (31,32). We
designed the module to have two paths comprising of 1D convolutional layers and long-
short term memory blocks. LSTM, introduced in 1997 (33), is a type of RNN that has
the ability to learn long-term dependencies of data. In literature, LSTM and its variants

have primarily been used in 1D sequence classification tasks (34,35) and prediction
tasks (36,37). In our experiments, we used multiple LSTM layers in different exploratory
configurations to learn a more complex feature representation of the input signal.
240
2.4 Frequency Domain Features (Step 3)

One of the objectives of our study was to analyze multi-domain (time and frequency
independently) and hybrid-domain (time and frequency combined) signal
characteristics. This kind of thorough comparison has never done before to the best of
our knowledge for ECoG-FM. In this step (Step 3), we focused on the spectral
characterization of signals. Conventional ECoG signal classification approaches are
based on frequency-domain, where spectral analysis of the signal is performed to
identify the channel response. Traditionally, spectral estimation of the signals is
performed by fitting a parametric time domain model to the ECoG signals. One of the
most commonly employed models/approaches in this category is the autoregressive
model. An AR model for a discrete signal $x[n]$ is represented as,

$$x[n] = -\sum_{k=1}^{k=p} a_p[k]x[n-k] + w[n], \tag{1}$$

255 where $a_p[k]$ are the AR coefficients, p is the order of the AR model, $w[n]$ is a zero
256 mean white noise process with a variance ρ. Once the model in Eq. (1) is solved, the
257 resulting AR parameters were used for characterization of the ECoG signal from
258 frequency-domain perspective.
259
260 Methods to solve for the AR parameters are diverse, we used the reflection
261 coefficient estimation-based methods (see Supplementary for details of the parameter
262 selection procedure).
263

265 **Figure 2:** Deep network structure for extraction of time domain features from the input signal. Note that
266 these features are combined with frequency domain features (Auto-Regressive) later for final prediction
267 of the channels.

2.5 Fusion for Hybrid Domain (Step 4)

Using LSTMs in Step 2, we learned a different set of features (i.e., time domain) than the AR features that were generated in Step 3. In domain fusion step (Step 4), these two (largely) complimentary features were combined to obtain a hybrid signal representation model with a new deep network setting, Domain Fusion Network (DFN) (See **Figure 3**). Although the merging of the two feature vectors can be done in multiple ways, we used a concatenation approach to get full benefit of each domain (time vs. frequency).

Figure 3: Deep network structure of the fusion module. AR (i.e., frequency) features (orange) and time-domain features (green) are concatenated and classified.

In concatenation, we assumed independence of features; hence, we did not use element-wise multiplication or other approaches for data merging. Since convolution helps identify local patterns and reduce redundant information in the data, the complete feature vector (after concatenation) was then passed through multiple layers of 1D convolutions with an activation function, to weight each feature based on its contribution to the classification problem (PRC vs NRC). Following the 1D convolution layers, the output feature maps were spatially averaged using Global Average Pooling (38), making the DFN more robust to spatial translations of the input data and introducing structural regularization to the feature maps. Finally, we inserted a single fully connected layer into the DFN and used a sigmoid activation to perform the final classification.

2.6 Majority Voting (Step 5)

The output of the domain fusion model was a label for the input signal, which was a sub-block. Signal from each channel/electrode was made up of hundreds of sub-blocks of the signals with reasonable overlapping. Therefore, for classifying a channel as either PRC or NRC, we hypothesize that the output that is observed more commonly is assigned as the final label. For this purpose, we apply majority voting on the output for each sub-block. For instance, if a channel included 354 sub-blocks and more than 50% of sub-blocks indicated a positive response, that channel was labelled as a PRC. As a rule, whenever the number of negative and positive responses are equal, the

299 channel will not be assigned any label. Although, we did not observe any such channel
300 in our experiments.

3. Experiments and Results

3.1 Task Paradigm

ECoG signals from the implanted subdural grids are split into two streams: one for
continuous clinical seizure monitoring and the other for ECoG-FM (**Figure 1a**). The tool
used to record the incoming ECoG signal was BCI2000(9). A baseline recording of the
cortical activity was first acquired to capture the "resting-state" neuronal activity.
Following this *baseline* recording step, paradigms similar to those employed in ESM or
functional magnetic resonance imaging (fMRI) were used to record the task-related
ECoG signal for functional mapping (39). **Figure 4** shows one such paradigm,
mimicking the exact details of the experimental setup we have used for the language
comprehension task. Alternate 30 second blocks of ECoG data during "control" and
"active" conditions were recorded continuously at a fixed sampling rate of 1200 Hz.
313
For the language comprehension task, the *active condition* implies listening to a
story, while the control task involves listening to broadband noise (40). For the active
condition (i.e., listening to a story), a different story was selected for each block in order
to keep the patient attentive and responsive. Both control and active sequences would
activate sense of hearing, but the story listening task will particularly activate the
language function. We hypothesize that this would suffice in eliciting the desired
response for mapping eloquent cortex related to language function and our results have
verified this hypothesis. For this purpose, the system recorded information from 128
ECoG channels (128 electrodes in **Figure 4**) by using *g.USBamp bio-signal amplifiers*
(g.tec Medical Engineering GmbH, Austria) with subdural ground and reference
electrodes.
325

327 **Figure 4:** Subdural grid localization and position of ECoG electrodes (128 of them) on the brain surface
328 of individual patient are illustrated (left). For a sample of 1 min language test, signals from both control
329 and active tasks are illustrated (right).

3.2 Training Paradigms

Our overall goal was to successfully (and automatically) identify positive response channels (PRCs) and negative response channels (NRCs) in ECoG-FM data using new machine learning models, specifically based on deep neural networks. The ground truth (i.e., reference standard) was inferred from the gold standard ESM results. Owing to the large imbalance in the number of PRCs and NRCs (NRCs outnumbering PRCs by 3:1), we randomly selected equal number of NRCs to balance the data and avoid potential data imbalance problem when training deep learning models.

Each channel's signal comprised of blocks of active task data and control data, where each active task block was from a different story. The discriminative power of these stories in the classification task was unknown. There is a possibility that features from one story could play a more significant role than others. Additionally, the discriminative power of any particular feature is unknown. To ascertain the role of these, we divided our experimental evaluation approaches into three main categories for data classification. Each approach depended upon the way active task data was included, and the features used in the training process. This structured experimental procedure helped us in determining the usefulness of each component of the signal and provided insights into the response of brain regions (through channel responses) to different signals. We performed experiments with different features and architectures.

3.3 Our Proposed Deep Network Architectures

In task-based experiments, a response is generally expected only during the active task period and not in the control or rest period. We used fully convolutional network (FCN) and long short-term memory (LSTM) architectures in the time domain module, since these have shown success in various time-series classification problems (41,42). We built our network by first analyzing the effect of using time domain features during the active task (represented as Active Time- AT). We tested our proposed time domain module by varying the network. We used an FCN (represented as AT^1) and then added LSTM module to the network (represented as AT^2). For frequency domain analysis, we added the auto regressive (AR) features to the frequency domain module by passing it through a fully connected layer (represented as $AT-AR^1$). **Figure 5a** shows the architectures (the superscripts indicate the variation within an architecture) including AT^1, AT^2 and $AT-AR^1$. In the domain fusion module, we tested different combinations of 1D convolutions (represented as $AT-AR^2$) and fully connected layers (represented as $AT-AR^3$). We also varied the depth of the frequency domain module by adding an additional fully connected layer in the network (represented as $AT-AR^4$). The network structures including $AT-AR^2$, $AT-AR^3$, and $AT-AR^4$ are shown in **Figure 5b**. We empirically determined the number of epochs required to train the network such that to avoid overfitting. Our experimental paradigms used time and frequency domain features individually and also in a hybrid manner (combined). We also analyzed the effect of active and control task data.

3.4 Model Validation

In supervised machine learning approaches, where a model is trained using ground-truth labels, the goal is to maximize predictive accuracy. However, therein lies the risk of memorizing the data rather than learning the optimal features. This problem of memorizing the data or learning the structure of the data to be the noise in the data is often referred to as **overfitting** (43). It is important for a classification model to be able to generalize to unseen data and avoid the problem of overfitting. The method of testing how the analysis/model generalizes to an independent test dataset is known as cross-validation. When a completely independent dataset is not available, as is generally the case, the available data is split into training data and validation/test data. There are different types of cross-validation approaches such as leave-one-out cross-validation, hold-out method, *k*-fold cross-validation, to name a few (44).

Shuffle-split Cross Validation

Previously, due to the time-consuming nature of training a deep learning model, we applied the hold-out method to validate our proposed models (45). In this method, the model is trained on a part of the available data, while the remaining data is held for testing/validating the model. For effectively testing the generalization and robustness of our proposed models, we validated them using the shuffle-split cross-validation approach. In the shuffle-split cross-validation method, the data is randomly sampled and split into training and testing splits iteratively, similar to the hold-out method. The results are averaged across the number of iterations. This can be seen as repeating the hold-out method k times, such that the data for training and validation is randomly sampled each time. The use of shuffle-split method allows sampling different data combinations rather than a single sampling as in k-fold cross-validation. Since the blocks were randomly assigned to the training and test folds, we ensured that no data from an electrode (channel) was represented in both training and testing folds simultaneously. Hence, if a block of data was assigned to a particular set (training/test), then all blocks belonging to that channel were assigned to the same (training/test) set. This ensured a fair evaluation with better generalization accuracy and helped in avoiding overfitting. For 30-fold cross validation, we repeated the experiments 30 times and used each of these distinct and non-overlapping training-testing sets to evaluate our model accuracies. Prediction accuracy was then calculated by averaging the results of these 30 experiments.

3.5 Training on individual features on active task data (Training Paradigm-I)

In this approach, we assumed that the channel response was similar for different stimuli (story) used in this study. Our experimental paradigm consisted of 5 different stories and thus, in this approach, no distinction was made with regards to the story. All of the active task data (i.e., five different story tasks) from a channel were used together for training the network. Among the time domain features (See Section: Methods), we found using random forest method that activity feature gave the best results. Therefore, all our proposed deep learning architecture (**Figure 5**) were first tested using the activity feature (**Table 1**). The addition of LSTM improved the

performance of the time domain module. This was further improved by the addition of
the frequency domain features using the domain fusion module. We found that
increasing the depth of the frequency domain module did not have any obvious benefit
in classification performance.

Figure 5: Deep network structure of a) AT^1, AT^2 (with added dotted green) and AT-AR^1 (with added
dotted red and green) and b) AT-AR^2, AT-AR^3 (replace fusion model with the dotted red model) and
AT-AR^4 (with added FC in dotted box).

We also tested our hypothesis that the story listening task (active task) was more
discriminative in identifying the eloquent cortex. To compare information present in the
active and control task data, we replicated our best performing models (AT−AR² and
AT-AR³) and fed it with control task data (represented as - CT−AR² and CT-AR³, where
CT represents control time). We observed that sensitivity of the control data model was
lower than that of active data model, indicating a lower discriminative power (**Table 1**)
and confirmed our hypothesis. To identify the best features for the channel
classification task, we fed the best performing model (AT−AR³), with different hand-

crafted features and performed cross-validation. The performance with different features was found to be similar (**Table 2**). The mobility feature showed the best performance with high sensitivity and accuracy compared to the other features.

Table 1: Channel classification accuracy for different network architectures. AT- active time, AR – auto regression, CT- control time.

Model	Block Accuracy %	Sensitivity %	Specificity %	Accuracy %
AT^1	63.33	83.33	58.33	70.83
AT^2	65.83	66.66	74.99	70.83
$AT-AR^1$	77.5	91.67	58.33	74.99
$AT-AR^2$	80.83	99.99	66.67	83.33
$AT-AR^3$	83.33	91.67	74.99	83.33
$AT-AR^4$	83.33	91.67	74.99	83.33
Comparing active and control data (Training Paradigm-I)				
$AT-AR^2$	75.93	77.97	79.66	78.81
$AT-AR^3$	78.13	86.44	72.88	79.66
$CT-AR^2$	73.9	76.27	72.88	74.58
$CT-AR^3$	73.05	72.88	72.88	72.88

Table 2: Channel classification performance parameters (with mean and variance) for active task data with individual hand-crafted time domain features using the AT-AR^3 model (training paradigm-I).

Features	Sensitivity % $\mu \pm \sigma$	Specificity % $\mu \pm \sigma$	Accuracy % $\mu \pm \sigma$
Mean	83.33 ± 10.09	81.11 ± 9.61	82.22 ± 6.71
Skew	81.67 ± 9.47	81.67 ± 9.95	81.67 ± 5.54
Kurtosis	82.78 ± 11.97	79.17 ± 10.03	80.97 ± 7.81
P2P	82.22 ± 10.91	80.00 ± 9.77	81.11 ± 7.11
Activity	82.22 ± 9.31	79.44 ± 10.70	80.83 ± 7.88
Mobility	**84.17 ± 9.22**	**81.11 ± 8.85**	**82.64 ± 6.55**
Complexity	84.17 ± 8.70	79.44 ± 10.70	81.81 ± 6.67

3.6 Training with multiple features on active task data – feature fusion (Training Paradigm-II)

We hypothesized in this experiment that different features can provide complementary information and can be combined to enhance the model performance. The top performing features from individual feature training (**Table 2**) – mobility, skew, mean, peak-to-peak (P2P), were used to test the hypothesis. The other three features were not used on the basis that they had a marginally lower specificity. Different approaches to feature fusion were tested in the form of early fusion and late fusion. In the early fusion approach, different features were used as input channels to the best performing network architecture (AT-AR^3). In late fusion, we tested two different approaches: first, separate time domain models were retrained for each hand-crafted feature, and a single frequency domain module was trained. The domain fusion module was used to combine these time and frequency domain modules (represented as AT-AR^3-LF^1). Secondly, we experimented by combining the frequency domain module prior to the feature fusion layer (represented as AT-AR^3-LF^2). The performance of these models is presented in **Table 3**.

3.7 Training with individual features on individual stories/active task data (Training Paradigm-III)

In previous experiments so far, we assumed that the channel responds in a similar manner to different stimuli (stories). However, it is plausible that the channel may respond differently to different stimuli. In this training approach, we now assumed that the channel responds differently to different stimuli (stories). The task paradigm consisted of 5 different stories corresponding to 5 different task blocks. We hypothesized that PRCs respond differently to the NRCs for each of these stories. We separated the signals based on the story and train the network in a similar manner as in section 3.6. Each story was trained with its own time domain and frequency domain modules using the AT-AR^3 network. These different networks were then combined and fed through a fully connected layer. Deep networks with different features as inputs were trained and the performance is compared in **Table 4,** where the features column shows the particular value (mobility, mean, and activity) computed for each story.

Table 3: Channel classification performance parameters for different approaches using feature fusion from time and frequency domains (training paradigm-II). AT- Active time, AR- autoregressive, EF- early fusion, LF- late fusion.

Model	Sensitivity % μ ± σ	Specificity % μ ± σ	Accuracy % μ ± σ
AT-AR^3-EF	79.99 ± 9.76	83.89 ± 11.37	81.94 ± 6.48
AT-AR^3-LF^1	82.22 ± 10.70	80.83 ± 9.42	81.53 ± 7.43
AT-AR^3-LF^2	**85.83 ± 7.80**	**80.27 ± 11.07**	**83.05 ± 6.35**

480   **Table 4:** Channel classification performance (mean and variance) for individual active task data,
481   using each story independently (training paradigm-III).

Features	Sensitivity %	Specificity %	Accuracy %
	$\mu \pm \sigma$	$\mu \pm \sigma$	$\mu \pm \sigma$
Mobility$_{story}$	**85.55 ± 10.07**	**79.44 ± 10.91**	**82.5 ± 6.21**
Mean$_{story}$	83.61 ± 10.42	78.88 ± 11.53	81.25 ± 7.35
Activity$_{story}$	83.05 ± 9.73	80.55 ± 11.45	81.8 ± 6.93

4. Discussions and Concluding Remarks

In this paper, we proposed novel deep learning architectures to classify the channel
response of ECoG signals. The results showed the state-of-the-art classification
accuracy of **83.05**% with high specificity and sensitivity of **80.3**% & **85.8**%, respectively,
in determining whether the channel was positive (has a response) or negative (has no
response) in relation to the task stimulus. The different features and fusion approaches
have given us the flexibility in maximizing different metrics, where as an example we
can improve the specificity to 83.9% (with a 1% drop in accuracy). In general, with AT-
AR^3-LF^2 is our best performing model with values >80% for all performance metrics
including accuracy, sensitivity and specificity. Traditionally, the accuracy of ECoG-FM
is high for mapping sensory and motor function, but relatively low for language
modality. On an average, ECoG functional language mapping had a lower sensitivity
(62%) and higher specificity (75%) to detect language-specific regions (for a
comprehensive review, see Korostenskaja et al. (40)). This is in contrast to the results
for hand motor (100% sensitivity and 79.7% specificity) and hand sensory (100%
sensitivity and 73.87% specificity) ECoG-based mapping(46). The results of our current
study demonstrate that the accuracy for mapping eloquent cortex using ECoG-FM can
now be comparable to both sensory and motor ECoG-FM accuracies. The language
ECoG-FM accuracy values we have achieved are the highest among those reported
so far (47). Although a number of studies have demonstrated successful utilization of
the ECoG-FM as a complimentary tool for ESM (13,22). There was not enough
evidence to support the use of ECoG-FM as a stand-alone methodology for functional
language mapping due to its relatively low accuracy compared with ESM (40,46). The
outcome of our research has indicated the potential of ECoG-FM, to be considered as
a stand-alone modality for eloquent language cortex localization.

It is possible that some features of the ECoG signal, reflecting the complex nature
of language processing, were omitted from consideration when restricting the language
ECoG-FM analysis to the gamma frequency band only. Expanding analysis to the
whole spectrum of frequencies in our study, therefore, has exceeded the results gained
from prior analysis approaches. It contributed to the improved classification accuracy
and confirmed the results of previous studies, pointing towards the complex nature of
language processing that needs to be considered during the analysis of
neurophysiological data. The results of our current study would have a wide-ranging

applicability in clinical practice. In particular, our proposed approach can be utilized to
prevent functional morbidity post-surgery in patients with pharmacoresistant epilepsy.
In addition, this can also be used to increase the accuracy of the eloquent cortex
mapping in patients undergoing resection of brain tumours(48) and arteriovenous
malformations (49).
522
Deep learning-based ECoG-FM approaches can also be successfully applied in
various fields of adaptive neuro-technologies (e.g., neuromodulation), where ECoG-
based mapping is performed to determine the best area for responsive stimulation. For
example, for defining the neural correlates of tics, the involuntary movements and/or
sounds, to be used for responsive stimulation in patients with Tourette's syndrome
(50,51) and for bidirectional neurostimulation via fully implantable neural interfaces in
Parkinson's disease (52). The applicability of our proposed approach extends as well
towards the fields of developmental disorders (e.g., autism) (53,54), psychiatry (e.g.,
major depression (55) and obsessive-compulsive disorder (OCD) (56), addiction (57),
eating disorders and obesity (58,59), where neurostimulation can be potentially utilized
to provide treatment and improve patients' quality of life.

4.1 Why Deep Learning in Studies with Limited Subjects
It is traditionally argued that deep learning models are data intensive and only fit to
problems where adequate training data is available. The inherently low dimensional
nature of physiological data (such as ECoG and EEG) both in terms of samples and
subjects has historically restricted this field from taking advantage of the recent
advances in machine learning (led by novel deep learning architectures). This trend is
arguable for multiple reasons. The number of subjects (which in most of these studies
is low) is not a good parameter to decide whether we can use deep learning-based
methods. Our results clearly support this argument, where the number of subjects (11
for training the models) could seem small. But the overall data (from 128 electrodes at
1200 samples per second) having millions of samples was highly sufficient to efficiently
train our deep learning models. Our classification accuracy (83.05%) and sensitivity
(85.8%) bodes well for selecting deep learning methods in our proposed models. This
trend can also be seen in other recent studies[52-55] and we are observing a paradigm
shift in classification tasks using 1D physiological data. At the same time, deep learning
models are developed that can work with small data. In particular, Bayesian deep
learning models are shown to have good performance even when the labelled training
data is scarce[55]. We conclude that even with limited subjects, the data could be
sufficient for successfully using deep learning methods in 1D data classification tasks
such as ECoG-FM.

4.2 Limitations and future perspectives
Despite the state-of-the-art results in ECoG-FM predictions, there are some
limitations of our work to be noted. First, our experimental paradigm (**Figure 4**) involves
five different stories being played to the subject. The responses to these stories, have
some inherent similarities, but overall are different. Therefore, training the deep
learning model with a single label for the whole channel could add noise to the model.

Though we have tested the effect of training the network, while treating each story
individually, this reduces the overall data available to train the model. We believe that
these results can be improved by including additional data and then training the system
individually for each story in the paradigm. Second, the subjects used in this initial
validation study were a mix of teenagers and adults. Smith[56] found that the effect of
epilepsy and seizures on children and adults was different i.e., the rules learned about
the behavior of the brain in adults is different for children. Hence, a more
comprehensive study with focus on children/teenagers is needed. This is one of our
future aims to test the proposed machine learning based approach in different patient
populations; however, patient recruitment is difficult due to the involvement of surgery,
and disease prevalence.
571
Finally, in the proposed approach, due to the exploratory and research nature of
our study, the classification was not performed in real-time. We have used
retrospective data for validating the innovations and are currently working on the real-
time clinical implementation of the algorithm. We intend to extend this study for
mapping functional language cortex in prospective subjects. We believe that
implementing such a reliable technology will increase current presurgical and intra-
operative functional mapping accuracy, expand surgical treatment opportunities,
prevent post-surgical language morbidity, and improve patient outcomes.

580
Acknowledgements

The authors acknowledge The Central Florida Health Research (CFHR) grant for
supporting this study.

Authors' Contributions
Idea development, current study conception: MK, UB, EMC.
Deep learning design, computational experiments: HR, CS, SMA, UB.
Patient recruitment, IRB process, ECoG tasks, ESM experiments: MK, CMS, EMC,
and KHL.
Manuscript writing, editing, and significant revision: All authors.
590

References

1.   Patricia S. About Epilepsy: The Basics [Internet]. Epilepsy Foundation; 2018.
Available from: https://www.epilepsy.com/learn/about-epilepsy-basics

2.   Penfield W, Rasmussen T. The cerebral cortex of man; a clinical study of
localization of function. 1950;

3.   Penfield W, Roberts L. Mapping the speech area. Speech brain Mech.
1959;103–18.

4.   Ojemann G, Ojemann J, Lettich E, Berger M. Cortical language localization in
left, dominant hemisphere: an electrical stimulation mapping investigation in 117

patients. J Neurosurg. 1989;71(3):316–26.

5.   Ojemann JG, Ojemann GA, Lettich E. Cortical stimulation mapping of language
cortex by using a verb generation task: effects of learning and comparison to
mapping based on object naming. J Neurosurg. 2002;97(1):33–8.

6.   Edwards E, Nagarajan SS, Dalal SS, Canolty RT, Kirsch HE, Barbaro NM, et al.
Spatiotemporal imaging of cortical activation during verb generation and picture
naming. Neuroimage. 2010;50(1):291–301.

7.   Pouratian N, Cannestra AF, Bookheimer SY, Martin NA, Toga AW. Variability of
intraoperative electrocortical stimulation mapping parameters across and within
individuals. Journal of Neurosurgery Publishing Group; 2004.

8.   Bank AM, Schevon CA, Hamberger MJ. Characteristics and clinical impact of
stimulation-evoked seizures during extraoperative cortical mapping. Epilepsy
Behav. 2014;34:6–8.

9.   Schalk G, Leuthardt EC, Brunner P, Ojemann JG, Gerhardt LA, Wolpaw JR.
Real-time detection of event-related brain activity. Neuroimage. 2008;43(2):245–
9.

10.   Leuthardt EC, Miller K, Anderson NR, Schalk G, Dowling J, Miller J, et al.
Electrocorticographic frequency alteration mapping: a clinical technique for
mapping the motor cortex. Oper Neurosurg. 2007;60(suppl_4):ONS--260.

11.   Miller KJ, Shenoy P, Miller JW, Rao RPN, Ojemann JG, others. Real-time
functional   brain   mapping   using   electrocorticography.   Neuroimage.
2007;37(2):504–7.

12.   Kapeller C, Korostenskaja M, Prueckl R, Chen P-C, Lee KH, Westerveld M, et
al. CortiQ-based real-time functional mapping for epilepsy surgery. J Clin
Neurophysiol. 2015;32(3):e12--e22.

13.   Prueckl R, Kapeller C, Gruenwald J, Ogawa H, Kamada K, Korostenskaja M, et
al. Passive functional mapping guides electrical cortical stimulation for efficient
determination of eloquent cortex in epilepsy patients. In: 2017 39th Annual
International Conference of the IEEE Engineering in Medicine and Biology
Society (EMBC). 2017. p. 4163–6.

14.   Towle VL, Syed I, Berger C, Grzesczcuk R, Milton J, Erickson RK, et al.
Identification of the sensory/motor area and pathologic regions using ECoG
coherence. Electroencephalogr Clin Neurophysiol. 1998;106(1):30–9.

15.   Qian T, Zhou W, Ling Z, Gao S, Liu H, Hong B. Fast presurgical functional
mapping using task-related intracranial high gamma activity. J Neurosurg.
2013;119(1):26–36.

16.   Vansteensel MJ, Bleichner MG, Dintzner LT, Aarnoutse EJ, Leijten FSS, Hermes
D, et al. Task-free electrocorticography frequency mapping of the motor cortex.
Clin Neurophysiol. 2013;124(6):1169–74.

17. Alkawadri R, Gaspard N, Hirsch LJ, Spencer DD. T105. A novel method for
ECOG-based localization of function. Clin Neurophysiol. 2018;129:e43.

18. Prueckl R, Kapeller C, Potes C, Korostenskaja M, Schalk G, Lee KH, et al.
cortiQ-Clinical software for electrocorticographic real-time functional mapping of
the eloquent cortex. In: Engineering in Medicine and Biology Society (EMBC),
2013 35th Annual International Conference of the IEEE. 2013. p. 6365–8.

19. Arya R, Wilson JA, Vannest J, Byars AW, Greiner HM, Buroker J, et al.
Electrocorticographic language mapping in children by high-gamma
synchronization during spontaneous conversation: Comparison with
conventional electrical cortical stimulation. Epilepsy Res [Internet]. 2015;110:78–
87. Available from:
http://www.sciencedirect.com/science/article/pii/S0920121114003271

20. Arya R, Wilson JA, Fujiwara H, Vannest J, Byars AW, Rozhkov L, et al.
Electrocorticographic high-gamma modulation with passive listening paradigm
for pediatric extraoperative language mapping. Epilepsia. 2018;59(4):792–801.

21. Korostenskaja M, Kamada K, Guger C, Salinas CM, Westerveld M, Castillo EM,
et al. Electrocorticography-Based Real-Time Functional Mapping for Pediatric
Epilepsy Surgery. J Pediatr Epilepsy. 2015;4(04):184–206.

22. Prueckl R, Kapeller C, Gruenwald J, Guger C, Fernandes F, Walchshofer M, et
al. O202 Combining the strengths of passive functional mapping and electrical
cortical stimulation. Clin Neurophysiol. 2017;128(9):e243.

23. RaviPrakash H, Korostenskaja M, Lee K, Baumgartner J, Castillo E, Bagci U.
Automatic response assessment in regions of language cortex in epilepsy
patients using ECoG-based functional mapping and machine learning. In:
Systems, Man, and Cybernetics (SMC), 2017 IEEE International Conference on.
2017. p. 519–24.

24. Korostenskaja M, RaviPrakash H, Bagci U, Lee KH, Chen PC, Salinas C, et al.
Gold Standard for epilepsy/tumor surgery coupled with deep learning offers
independence to a promising functional mapping modality. In: Guger C, Allison
B, Ushiba J, editors. Brain-Computer Interface Research: A State-of-the-Art
Summary 6. Springer International Publishing: Cham; 2017.

25. Graves A, Schmidhuber J. Framewise phoneme classification with bidirectional
LSTM and other neural network architectures. Neural Networks. 2005;18(5–
6):602–10.

26. Baccouche M, Mamalet F, Wolf C, Garcia C, Baskurt A. Spatio-Temporal
Convolutional Sparse Auto-Encoder for Sequence Classification. In: BMVC.
2012. p. 1–12.

27. Wang J, Yang Y, Mao J, Huang Z, Huang C, Xu W. Cnn-rnn: A unified framework
for multi-label image classification. In: Proceedings of the IEEE conference on
computer vision and pattern recognition. 2016. p. 2285–94.

28. Inuso G, La Foresta F, Mammone N, Morabito FC. Brain activity investigation by
EEG processing: Wavelet analysis, kurtosis and Renyi's entropy for artifact
detection. Proc 2007 Int Conf Inf Acquis ICIA. 2007;195–200.

29. Pollock VE, Schneider LS, Lyness SA. EEG amplitudes in healthy, late-middle-
aged and elderly adults: normality of the distributions and correlations with age.
Electroencephalogr Clin Neurophysiol. 1990;75(4):276–88.

30. Hjorth B. EEG analysis based contributions on time domain properties.
Electroencephalogr Clin Neurophysiol [Internet]. 1970;306–10. Available from:
http://ac.els-cdn.com.ezlibproxy1.ntu.edu.sg/0013469470901434/1-s2.0-
0013469470901434-main.pdf?_tid=44c4f902-55ad-11e7-ae24-
00000aacb35f&acdnat=1497959013_c82140ec01fb64b12901b87d9aba3f05

31. Goodfellow SD, Goodwin A, Greer R, Laussen PC, Eytan D, Goodfellow SD, et
al. Towards Understanding ECG Rhythm Classification Using Convolutional
Neural Networks and Attention Mappings ECG Classification Using
Convolutional Neural Networks and Attention Mappings. Mlhc-2018 [Internet].
2018;85(August):1–18. Available from:
https://static1.squarespace.com/static/59d5ac1780bd5ef9c396eda6/t/5b73729d
562fa79aabf87383/1534292642748/9.pdf

32. Zabihi M, Rad AB, Kiranyaz S, Särkkä S, Gabbouj M. 1D Convolutional Neural
Network Models for Sleep Arousal Detection. 2019;(Schulz 2008):1–10.
Available from: http://arxiv.org/abs/1903.01552

33. Hochreiter S, Schmidhuber J. Long short-term memory. Neural Comput.
1997;9(8):1735–80.

34. Liu Q, Zhou F, Hang R, Yuan X. Bidirectional-Convolutional LSTM Based
Spectral-Spatial Feature Learning for Hyperspectral Image Classification. arXiv
Prepr arXiv170307910. 2017;

35. Nowak J, Taspinar A, Scherer R. LSTM Recurrent Neural Networks for Short
Text and Sentiment Classification. In: International Conference on Artificial
Intelligence and Soft Computing. 2017. p. 553–62.

36. Flunkert V, Salinas D, Gasthaus J. DeepAR: Probabilistic Forecasting with
Autoregressive Recurrent Networks. arXiv Prepr arXiv170404110. 2017;

37. Gammulle H, Denman S, Sridharan S, Fookes C. Two Stream LSTM: A Deep
Fusion Framework for Human Action Recognition. In: Applications of Computer
Vision (WACV), 2017 IEEE Winter Conference on. 2017. p. 177–86.

38. Lin M, Chen Q, Yan S. Network in network. arXiv Prepr arXiv13124400. 2013;

39. Korostenskaja M, Chen P-C, Salinas CM, Westerveld M, Brunner P, Schalk G,
et al. Real-time functional mapping: potential tool for improving language
outcome in pediatric epilepsy surgery: Case report. J Neurosurg Pediatr.
2014;14(3):287–95.

40.   Korostenskaja M, Wilson AJ, Rose DF, Brunner P, Schalk G, Leach J, et al. Real-
time functional mapping with electrocorticography in pediatric epilepsy:
comparison with fMRI and ESM findings. Clin EEG Neurosci. 2014;45(3):205–
11.

41.   Karim F, Majumdar S, Darabi H, Chen S. LSTM Fully Convolutional Networks for
Time Series Classification. IEEE Access. 2017;6:1662–9.

42.   Karim F, Majumdar S, Darabi H, Harford S. Multivariate LSTM-FCNs for time
series classification. Neural Networks. 2019;116:237–45.

43.   Dietterich T. Overfitting and undercomputing in machine learning. ACM Comput
Surv. 1995;27(3):326–7.

44.   James G, Witten D, Hastie T, Tibshirani R. An introduction to statistical learning.
Vol. 112. Springer; 2013.

45.   Arlot S, Celisse A. A survey of cross-validation procedures for model selection.
Stat Surv. 2010;4:40–79.

46.   Kapeller C, Korostenskaja M, Prueckl R, Chen P-C, Lee KH, Westerveld M, et
al. CortiQ-based Real-Time Functional Mapping for Epilepsy Surgery. J Clin
Neurophysiol. 2015;32(3):e12--e22.

47.   Arya R, Horn PS, Crone NE. ECoG high-gamma modulation versus electrical
stimulation for presurgical language mapping. Epilepsy Behav. 2018;79:26–33.

48.   Ogawa H, Kamada K, Kapeller C, Hiroshima S, Prueckl R, Guger C. Rapid and
minimum invasive functional brain mapping by real-time visualization of high
gamma activity during awake craniotomy. World Neurosurg. 2014;82(5):912--e1.

49.   Kamada K, Ogawa H, Saito M, Tamura Y, Anei R, Kapeller C, et al. Novel
techniques of real-time blood flow and functional mapping. Neurol Med Chir
(Tokyo). 2014;54(10):775–85.

50.   Molina R, Okun MS, Shute JB, Opri E, Rossi PJ, Martinez-Ramirez D, et al.
Report of a patient undergoing chronic responsive deep brain stimulation for
Tourette syndrome: proof of concept. J Neurosurg. 2018;129(2):308–14.

51.   Shute JB, Okun MS, Opri E, Molina R, Rossi PJ, Martinez-Ramirez D, et al.
Thalamocortical network activity enables chronic tic detection in humans with
Tourette syndrome. NeuroImage Clin. 2016;12:165–72.

52.   Swann NC, de Hemptinne C, Miocinovic S, Qasim S, Ostrem JL, Galifianakis
NB, et al. Chronic multisite brain recordings from a totally implantable
bidirectional neural interface: experience in 5 patients with Parkinson's disease.
J Neurosurg. 2018;128(2):605–16.

53.   Sinha S, McGovern RA, Sheth SA. Deep brain stimulation for severe autism:
from pathophysiology to procedure. Neurosurg Focus. 2015;38(6):E3.

54.   Sturm V, Fricke O, Bührle CP, Lenartz D, Maarouf M, Treuer H, et al. DBS in the
basolateral amygdala improves symptoms of autism and related self-injurious
behavior: a case report and hypothesis on the pathogenesis of the disorder.
Front Hum Neurosci. 2013;6:341.

55.   Coenen VA, Sajonz B, Reisert M, Bostroem J, Bewernick B, Urbach H, et al.
Tractography-assisted deep brain stimulation of the superolateral branch of the
medial forebrain bundle (slMFB DBS) in major depression. NeuroImage Clin.
2018;20:580–93.

56.   Vázquez-Bourgon J, Martino J, Sierra MP, Infante JC, Mart\'\inez MÁM, Ocón R,
et al. Deep brain stimulation and treatment-resistant obsessive-compulsive
disorder: A systematic review. Rev Psiquiatr Salud Ment. 2017;

57.   Wang TR, Moosa S, Dallapiazza RF, Elias WJ, Lynch WJ. Deep brain stimulation
for the treatment of drug addiction. Neurosurg Focus. 2018;45(2):E11.

58.   Val-Laillet D, Aarts E, Weber B, Ferrari M, Quaresima V, Stoeckel LE, et al.
Neuroimaging and neuromodulation approaches to study eating behavior and
prevent and treat eating disorders and obesity. NeuroImage Clin. 2015;8:1–31.

59.   Oterdoom DLM, van Dijk G, Verhagen MHP, Jiawan VCR, Drost G, Emous M,
et al. Therapeutic potential of deep brain stimulation of the nucleus accumbens
in morbid obesity. Neurosurg Focus. 2018;45(2):E10.