# From skylight input to behavioural output: a computational model of the insect polarised light compass

Evripidis Gkanias[1*], Benjamin Risse[2], Michael Mangan[3], Barbara Webb[1*]

**1** School of Informatics, The University of Edinburgh, Edinburgh, United Kingdom
**2** Faculty of Mathematics and Computer Science, University of Münster, Münster, Germany
**3** Department of Computer Science, University of Sheffield, Sheffield, United Kingdom

* Corresponding author
E-mail: ev.gkanias@ed.ac.uk (EG)
E-mail: bwebb@inf.ed.ac.uk (BW)

## Abstract

Many insects navigate by integrating the distances and directions travelled on an outward path, allowing direct return to the starting point. Fundamental to the reliability of this process is the use of a neural compass based on external celestial cues. Here we examine how such compass information could be reliably computed by the insect brain, given realistic constraints on the sky polarisation pattern and the insect eye sensor array. By processing the degree of polarisation in different directions for different parts of the sky, our model can directly estimate the solar azimuth and also infer the confidence of the estimate. We introduce a method to correct for tilting of the sensor array, as might be caused by travel over uneven terrain. We also show that the confidence can be used to approximate the change in sun position over time, allowing the compass to remain fixed with respect to 'true north' during long excursions. We demonstrate that the compass is robust to disturbances and can be effectively used as input to an existing neural model of insect path integration. We discuss the plausibility of our model to be mapped to known neural circuits, and to be implemented for robot navigation.

## Author summary

We propose a new hypothesis for how insects process polarised skylight to extract global orientation information that can be used for accurate path integration. Our model solves the problem of solar/anti-solar meridian ambiguity by using a biologically constrained sensor array, and includes methods to deal with tilt and time, providing a complete insect celestial compass output. We analyse the performance of the model using a realistic sky simulation and various forms of disturbances, and compare the results to both engineering approaches and biological data.

## Introduction                                                                    1

Orientation cues are required for spatial behaviours from following a straight line [1] to    2
migrating across continents [2] (for a theoretical proof see [3]). Idiothetic cues such as    3
those generated in the mammalian vestibular system are useful for short time periods    4
but are inherently compromised by accumulating errors. To avoid this limitation, many    5

animals, in particular insects, have developed an array of sensory systems to detect allothetic directional cues in their environments: magnetic (butterflies [4], moths [5], ants [6]), wind (moths [7], ants [8]), and visual [solar compass - (honeybees [9], crickets [10], locusts [11], butterflies [12], ants [13], dung beetles [14]); star compass - (dung beetle [15])]. The benefit of such accurate external compass systems is exemplified in the behaviour of desert ants, who utilise the sky polarisation pattern. In a habitat with few if any landmarks, these ants can integrate the distance and directions travelled on a tortuous search path of up to a kilometre in length and make a direct return home when food is found [16]. Our main aim in this paper is to study the potential accuracy with which an insect can estimate its allocentric direction from the sky polarisation pattern, given realistic constraints on the environmental cues, the sensory system, and the various sources of disturbances.

The primary directional cue used for path integration by central place foraging insects such as desert ants [17] is the sky (sometimes called the celestial compass). The position of the sun (or moon) in the sky - as well as providing a direct directional reference point - determines the properties of light across the skydome including intensity and chromatic gradients, and a specific pattern of polarisation. Linear polarisation of light is the convergence of orientation of oscillation of the electromagnetic wave to a single plane. As light from the sun passes through earth's atmosphere it undergoes a scattering process [18–21] producing differing levels of polarisation across the sky-dome relative to the position of the sun. From the point of view of an earth based observer, as the angular distance from the sun increases from $0°$ to $\leq 90°$, the degree of linear polarisation in skylight increases, with the principal axis of polarisation perpendicular to the observer-sun axis, forming concentric rings around the sun. Angular distances above $90°$ have decreasing degree of linear polarisation [22].

The insect celestial compass has been studied extensively in the honeybee *Apis mellifera* [9, 23], the cricket *Gryllus campestris* [10, 24–26], the locust *Schistocerca gregaria* [11, 27], the monarch butterfly *Danaus plexippus* [12], the dung beetle *Scarabaeus lamarcki* [14] and the desert ant *Cataglyphis bicolor* [13]. Insects perceive polarised light through a specially adapted region of their upper eye known as the *dorsal rim area* (DRA). The ommatidia of the DRA contain light sensing elements (microvilli) that have adapted a preference to light of a specific polarisation angle. Ommatidia in the DRA are connected to *polarisation sensitive (POL) neurons* in the *medulla* of the insect optic lobe which follow a sinusoidal activation profile under a rotating linear polarisation input [10]. The maximum and minimum activation is separated by $90°$, consistent with an antagonistic input from at least two polarisation-sensitive channels with orthogonal e-vector tuning orientation. The identity and spike-rate of each POL neuron thus encodes information about the *angle* and *degree* of polarisation for the specific region of sky from which the associated ommatidia samples. An array of such sensing elements arranged appropriately may hence be sufficient to decode the sun position, without using any additional sky cues [28].

From the optic lobe the pathway for polarised light processing has been traced through several neuropils in the insect brain. Key processing stages for polarised light are the dorsal rim lamina and medulla, specific layers of the lobula, the anterior optic tubercle, and the lateral complex with giant synapses; before reaching a highly structured midline neuropil known as the central complex (CX) [27, 29]. A variety of neuron types within the CX region have been shown to have polarisation dependent responses, including CX inputs in the form of three types of tangential neurons [27] (TL1, TL2 and TL3) which synapse with columnar neurons [11, 30, 31] in the ellipsoid body/lower division of the central body. Most strikingly, intracellular recordings from neurons in the CX protocerebral bridge have revealed an orderly polarisation tuning preference across the eight columns, described as an internal compass or map [32]. More

recently, the same structure has been observed through neurogenetic imaging in                        58
Drosophila to act as a ring attractor encoding the heading direction of the insect                      59
relative to a prominent visual cue [33]. However, there remains an inconsistency                        60
between these observations, as the polarisation tuning appears to range from $0°$ to $180°$             61
with each successive column tuned $\sim 22.5°$ degrees apart [32], whereas the fly's compass            62
covers $360°$, changing by $\sim 45°$ per column [33].                                                  63

   In a recent model, we used anatomical constraints for processing within the CX to                   64
explain how compass information in the protocerebral bridge could be combined with                      65
speed information to carry out path integration, and subsequently steer home [34]. This                 66
model assumed a $360°$ compass across the 8 TB1 cells could be derived from sky                         67
polarisation cues. In this paper, we first determine whether in principle such a signal                 68
can be recovered from a simulated array of POL-neurons stimulated by a realistic sky                    69
polarisation pattern. We further investigate whether this signal can deal with, or be                   70
plausibly corrected for, potential disturbances such as partially obscured sky, tilting of             71
the sensor array, and the movement of the sun with passing time. We evaluate the                        72
potential accuracy of compass information both in absolute terms, and in the context of                73
path integration. Finally we show how the discrepancy in biological data for the                        74
protocerebral bridge tuning pattern [32, 33] might be resolved, by testing our model                    75
with artificial polarisation patterns.                                                                  76

# Materials and methods                                                                                 77

## Overview                                                                                             78

This study investigates how navigating insects can transform solar light into an                        79
earth-based compass signal that is sufficiently stable and accurate to drive precise path              80
integration behaviour. Fig 1 provides an overview of the modelling pipeline. We start                   81
with a physical model of skylight, which is used as input to a biomimetic sensor array                 82
based on the desert ant eye. We then take a more direct computational approach to                       83
generate compass output from the insect eye input, by defining a hypothetical neural                    84
architecture that will reconstruct the sun position from this input, with additional                    85
mechanisms to correct for tilt and for passing time. As the precise neural connectivity                86
underlying these transformations in the insect is unknown, this is a proof of principle                87
that can provide hypotheses for future investigation of this circuit (see discussion). We              88
then use the output of the compass as input to an existing biologically constrained                     89
model of path integration in the central complex, and test it in a closed loop agent                   90
simulation.                                                                                             91

## Skylight                                                                                             92

To test our neural model, we need to simulate the incoming light using a skylight dome                  93
model. Previous computational studies of the insect POL-system have often copied the                   94
typical stimulus input from experimental studies, i.e., a rotating linear polariser [37].              95
However, the topology of the ommatidia and the neural processing of the compass                        96
system in the insect brain have evolved under real sky conditions, hence using a more                  97
realistic input can be critical to understanding the function. Specifically, as we will                98
show, the real sky pattern breaks the symmetry conditions that inherently prevent $360°$               99
directions being recovered from a simple linear polarisation cue.                                      100

   We use the skylight dome model described in [35], which gives a very realistic                      101
luminance and linear polarisation information pattern (Fig 2D). Given the position of                  102
the sun and a set of points in the sky, it generates the *luminance*, *degree* (DOP) and              103
*angle of polarisation* (AOP) for those points. Tuning by geo-referenced input                        104

**Fig 1. Overview of the modelling pipeline.**
Our simulation consists of four consecutive models (left to right). Given the position of the sun, a realistic skylight model [35] provides the predicted luminance, degree and angle of linear polarisation for every point in the sky-dome. This provides input to the eye model, based on biological data from insects [10, 36], which defines an array of polarisation sensitive photo-receptors facing different parts of the sky, and uses opponent processing to produce luminance-independent POL-neuron responses. The compass model provides a hypothesis for the unknown neural process that converts the POL-neuron response to a true compass signal in the TB1 neurons; this also utilises information about tilt of the sensor array, and allows for the movement of the sun with passing time. Finally, the compass neuron output is used along with speed as input to an anatomically grounded model of the central complex [34] which performs path integration and produces an output signal that can steer the insect back home.

parameters allows realistic sky patterns to be estimated for specific locations. Therefore, plugging into the model the location from our own desert ant fieldwork site (Seville, Spain) allows us to run simulated experiments for desert ants. This way, we can study the response of their POL-sensitive neurons using near natural stimuli.

## The Insect Eye

### Dorsal rim ommatidia

We developed a simulated sensory unit to mimic the function of the ommatidia in the DRA of the desert ant (Fig 2B). We consider each ommatidium to be an individual sensorial unit that can be freely arranged in space to match the compound structure of the real ant's DRA (Fig 2E).

For an insect, the acceptance angle of the ommatidia affects the volume of skylight perceived and the maximum polarisation contrast sensitivity. This is defined by the optical properties of the cornea and the crystalline cones. Light passing through these lenses is focused through a light-guide onto 8 light sensitive cells (rhabdoms) that have a preference for one of two groups of perpendicularly oriented microvilli, that work as linear polarisation filters (Fig 2 C).

For each simulated ommatidium in our model we define a fixed acceptance angle, $\rho = 5.4°$, and spectral sensitivity, $\lambda_{\max} = 350$ wavelength, based on the ant eye [36] and use 2 perpendicularly arranged photo-receptor channels. We notate $s_{\parallel}$ ($s_{\perp}$) the stimulus of the photo-receptor channels that have parallel (perpendicular) aligned polarisation filters with respect to the ommatidium orientation. These follow a sinusoidal response curve to the e-vector orientation with the highest value when fully aligned with the preferred polarisation angle and the lowest when perpendicular. The photo-receptor neuron transforms this raw input using a square-root activation function, $r = \sqrt{s}$ which reduces the skewness for $s > 1$, but increases it for $s < 1$, transforming the sinusoid as shown in Fig 2G. This transformation is essential in order to penalise the high

**Fig 2. Processing stages of light in the biological and artificial DRA.**
(A) The DRA is composed of hexagonal ommatidia. (B) The position of the DRA on the desert ant eye. (C) An ommatidium on the DRA of the compound eye of the *Cataglyphis* has 8 photo-receptor cells, from which the direction of the microvilli of 2, 3, 4, 6, 7 and 8 denote the parallel direction of the ommatidium, while the one of the microvilli 1 and 5 denote the perpendicular direction; the colour violet indicates sensitivity to the ultra violet spectrum. (D) Information available in the sky-dome (luminance, degree and angle of polarisation). (E) Schematic of the sensor array in the eye model: hexagons are different units (ommatidia); lines denote the direction of the polarisation filters, with long and short lines representing the parallel and perpendicular filter respectively. (F) Model of a POL-unit: the photo-receptor neurons combine a UV-sensor (photo-receptor) and a polarisation filter (microvilli), and have a square-root activation function. The normalised difference of the photo-receptor neurons is calculated by the POL interneurons: $\frac{r_\parallel - r_\perp}{r_\parallel + r_\perp}$. The empty triangular and dashed synapses denote excitatory and inhibitory connections respectively. (G) Simulated response of the two photo-receptors in one unit in partially linearly polarised light of intensity $I = 1$ (degree of polarisation, $d = 0.9$). (H) Simulated response of the POL-neuron to the input of Fig 2G; the dashed line shows the response of the POL-OP interneuron, and the solid line is the response of the POL-neuron (normalised difference). A, B and C figures adapted and modified from [38], [39] (with the permission of the American Association of Physics Teachers) and [40]. F, G and H are after [10].

illuminations of the bright sky. It acts similarly to the logarithmic transformation $r = \log(s)$, introduced by [41] and used on the Sahabot robot [42]. The main advantage of the square-root transformation is that it can be applied to zero values (darkness or linearly polarised light perpendicular to the filter orientation). As the exact transformation of the photo-receptors signal in the insect's eye remains unknown [43], any transformation that reduces the skewness could be theoretically correct.

**POL-neurons: Polarisation contrast**                                    

The first stage of the global-orientation encoding in insects is performed by the       138
*polarisation* units in the medulla of the optic lobe [10]. These units encode polarisation    139
information from different points of the insect's environment, creating a polarisation    140
map. We follow the approach described in [41] to define how light perceived from our     141
sky model is transformed into POL-neuron activity. This produces illumination            142
insensitivity in each POL-neuron, capturing only the polarisation contrast in specific   143
e-vector directions.                                                                     144

   The photo-receptor cells propagate their response to the POL-neuron output via two    145
interneurons (see Fig 2F). The *polarisation-opponent* (POL-OP) interneuron (left)       146
computes the difference between the responses of the photo-receptor neurons,             147
$r_{\mathrm{OP}} = r_\parallel - r_\perp$, similarly to the output (POL-neuron) in [42]. The *polarisation-pooling*   148
(POL-PO) interneuron (right) approximates the overall intensity of the input light, by   149
pooling the responses of the opponent components, $r_{\mathrm{PO}} = r_\parallel + r_\perp$, and is used as a   150
normalisation factor that removes this luminance information from the signal. Both       151
interneurons propagate the logarithm of their output signal to the POL-neuron.           152

   The POL-OP interneuron excites the output POL-neuron, while the POL-PO               153
interneuron inhibits it, i.e. $\log(r) = \log(r_{\mathrm{OP}}) - \log(r_{\mathrm{PO}}) = \log\left(\frac{r_{\mathrm{OP}}}{r_{\mathrm{PO}}}\right)$. As a result the   154
activity of the output neuron is independent of the luminance. This feature is very      155
important, as the activity of the POL-neurons in insects' optic lobe is not correlated to    156
the light intensity [13, 44]. This has been previously modelled by normalising the       157
response of POL-neurons using the values measured from different                         158
directions [24, 42, 45, 46] (scanning model). Finally, the output neuron transforms the    159
response using an exponential activation function in order to bring back the sinusoidal   160
shape:                                                                                   161

$$r_{\mathrm{POL}} = \exp\left[\log\left(\frac{r_{OP}}{r_{PO}}\right)\right] = \frac{r_{OP}}{r_{PO}} = \frac{r_\parallel - r_\perp}{r_\parallel + r_\perp} = \frac{\sqrt{s_\parallel} - \sqrt{s_\perp}}{\sqrt{s_\parallel} + \sqrt{s_\perp}} \tag{1}$$

   The above set of interneurons, along with the photo-receptors and the output          162
POL-neuron compose a POL unit (Fig 2F). Fig 2G illustrates the response of the           163
antagonistic photo-receptor neurons in a POL unit when the perceived light is partially   164
and linearly polarised (degree of polarisation, $d = 0.9$). The dashed line in Fig 2H    165
illustrates the response of the POL-OP interneuron and the solid line shows the          166
normalised POL-neuron response after dividing (inhibiting) by the POL-PO signal.         167

   The output signal of our POL-neuron thus matches that found in insect POL             168
neurons [41]. However, we note there is no specific evidence for the hypothesised        169
interneurons in this model.                                                              170

**Dorsal Rim Area: Layout**                                               171

We simulated the sampling pattern of the entire ant DRA by homogeneously                 172
distributing simulated ommatidia on the dome using the *icosahedron triangulation*       173
method, as widely used in computer graphics for sphere representations. The resulting    174
pattern of polarisation preferences in our population of simulated ommatidia matches     175
the fan-like shape reported in ants [36, 44, 47] (Fig 2D). More specifically, each       176
ommatidium, with *acceptance angle* $\rho = 5.4°$, is aligned to its respective concentric   177
notional ring centred at the zenith of a dome. Using the above method, we place $n = 60$    178
ommatidia on a dome-shaped surface, and the outer notional ring with radius $28°$        179
results in a $\omega = 56°$ *receptive field* for the whole eye model. Note that the view of each   180
ommatidium can overlap with its neighbours. The *receptive field* is around half that of    181
the ants' DRA on the frontocaudal axis, and the total number of ommatidia are           182
similarly 50% that of the real animal, keeping the resolution approximately the same.    183

The output of the ant eye model is a population ($n = 60$) of neurons closely ⁠184
matching the known characteristics of the POL neurons of the medulla of the optic lobe. ⁠185
This population thus forms the biologically constrained input layer for our visual ⁠186
processing model. ⁠187

## The Compass ⁠188

We built a *compass model* to transform the responses of the POL-neurons into the ⁠189
desired activation patterns of the TB1-neurons used for path integration. Although the ⁠190
anatomical pathway is known [48], the neurobiological processes on this pathway are as ⁠191
yet uncertain, so we have taken an information processing approach: given biologically ⁠192
realistic POL-neuron responses gathered from the skylight simulation we examine ⁠193
whether this input provides enough information for a biomimetic central complex model ⁠194
to drive steering. Fig 3 shows an overview of the model. The connection of ⁠195
POL-neurons to SOL-neurons in the *solar layer* implements a *sum-of-sinusoids* model ⁠196
to recover an estimate of the solar azimuth. The *gating function* adjusts the connection ⁠197
weights to compensate for tilting of the sensor array. The *true compass layer* uses the ⁠198
confidence of the estimate to predict and compensate for the changing sun position over ⁠199
time. We describe each of these steps in more detail below. ⁠200

**Fig 3. Overview of the compass model.**
The light information stimulates the photo-receptor neurons. Using the eye model, this is transformed to a POL-neuron population code. Tilting information (orange) is propagated through the gating function and creates a mask for the POL-neurons' response, altering the relative weighting of information from different parts of the sensor array (see Fig 4). By combining information across the array, the response of SOL-neurons encodes an estimate of the solar azimuth and elevation. The TCL-layer uses the elevation information along with passing time as an ephemeris function (green) which modulates its input weights to rotate the SOL-neuron output and provide a true north estimate. The response across the TCL-neurons is in the form of a sine-wave which can be decoded to determine an estimate of the azimuth (phase) and of the confidence of that estimate (amplitude). Note however that CX path integration circuit can use the TCL-neuron activity directly, without this explicit decoding.

## Sum-of-sinusoids 

The basic computation of the model is a *Sum-of-Sinusoids*, where the input is the 60 
POL-neuron responses and the output is the position of the sun represented in an 
8-neuron population code, named the *Solar Layer* (SOL). Each POL-neuron is 
connected to all SOL-neurons with a sinusoidal weighting function that represents the 
difference between the azimuthal direction of that POL-neuron's receptor in the sensor 
array, $\phi^j$, and the preferred direction of the SOL-neuron $\left(\phi_{\mathrm{SOL}}^{\mathrm{pref}}\right)^\xi$. Thus each 
SOL-neuron sums a set of sinusoids with the same frequency, different phases 
(depending on $\phi^j$), and different amplitudes (depending on the POL-neurons activity), 
resulting in another sinusoid. Specifically, the response of the neurons of the solar layer 
is given by the equation below, 

$$r_{\mathrm{SOL}}^\xi = \sum_{j=1}^{n_{\mathrm{POL}}} \underbrace{\frac{n_{\mathrm{SOL}}}{n_{\mathrm{POL}}} \cdot \sin\left[\alpha^j - \left(\phi_{\mathrm{SOL}}^{\mathrm{pref}}\right)^\xi\right]}_{W_{\mathrm{SOL}}^{j,\xi}} \cdot r_{\mathrm{POL}}^j \qquad (2)$$

where $n_{\mathrm{POL}} = 60$ and $n_{\mathrm{SOL}} = 8$ are the number of POL- and SOL-neurons respectively, 
$r_{\mathrm{POL}}^j$ and $r_{\mathrm{SOL}}^\xi$ are their responses and $W_{\mathrm{SOL}}^{j,\xi}$ are the weights of the synapses connecting 
them. The weight depends on the orientation of the primary axis of the $j^{\mathrm{th}}$ ommatidium, 
$\alpha^j = \phi^j - 90°$, and on the preference angle of the respective $\xi^{\mathrm{th}}$ SOL-neuron, 
$\left(\phi_{\mathrm{SOL}}^{\mathrm{pref}}\right)^\xi = \xi \cdot 360°/n_{\mathrm{SOL}}$. 

Effectively, this equation activates each SOL neuron in proportion to the degree of 
polarisation opposite its preferred direction. As the degree of polarisation is maximum 
in the anti-solar position, the response of the SOL-neurons contains information about 
the predicted solar azimuth, and the confidence of this prediction. For analysis, we can 
decode the population code using Fast Fourier Transform (FFT), 

$$R = \sum_{\xi=1}^{n_{\mathrm{SOL}}} r_{\mathrm{SOL}}^\xi e^{-i360°(\xi-1)/n_{\mathrm{SOL}}} \qquad (3)$$

where $R \in \mathbb{C}$. The angle of this complex number gives the solar azimuth, $\phi_s'$, while the
magnitude imply the confidence of this prediction, $\tau_s = \frac{1}{\sigma_s}$,

$$\phi_s' = 360° - \tan^{-1}\left[\frac{\mathrm{Im}(R)}{\mathrm{Re}(R)}\right], \qquad\qquad \tau_s = ||R|| - 90° \qquad (4)$$

Note however that the insect does not need to extract this information explicitly. 

## Tilt compensation mechanism 

The above computation of azimuth assumes the DRA is aligned with the sky dome and 
its zenith point is always pointing towards the sky zenith. In nature, the DRA of the 
animals may not remain aligned to the zenith, particularly in walking animals such as 
ants which do not fully stabilise their head position [49]. As the eye deviates from the 
zenith, the predictions of the above model become less and less accurate. Therefore, we 
added a gating function that receives information about the sensor tilt and modulates 
the response of the solar layer (see Fig 3 orange connections). 

Specifically, the gating function uses the known head-tilt angle (see Discussion for 
where this may come from for the animal) to preferentially select inputs from 
ommatidia facing towards the most interesting region in the sky, in the form of a 
Gaussian ring shape centred on the zenith point (see Fig 4): 

$$g^j(\theta_t, \phi_t) = \exp\left\{-\frac{1}{2}\left[\frac{\sin\left(\theta_g - \theta^j\right)\cos\theta_t + \cos\left(\theta_g - \theta^j\right)\sin\theta_t\cos\left(\phi_t - \phi^j\right)}{\sigma_g}\right]^2\right\} \quad (5)$$

where $\theta^j$ and $\phi^j$ are the elevation and azimuth of the relative position of the respective ommatidium. The radius of this ring, $\theta_g = 40°$, denotes the dominant focus direction of the system, i.e. where the peak of the Gaussian bump should be placed. The width of the ring (variance), $\sigma_g = 13°$, stands for the soft elevational receptive field for the SOL-neurons, i.e. the smoothing parameter.

**Fig 4. The gating function that compensates for tilt.**
The differing weightings of ommatidia input under three levels of tilt [(A) $\theta_t = 0°$, (B) $\theta_t = 30°$ and (C) $\theta_t = 60°$] are shown, with darker shading indicating higher weighting. The inner dashed black circle delineates the actual receptive field of the simulated sensor (28° radius, equivalent to $\omega = 56°$ receptive field). The extended array (greyed out units) illustrates how this weighting adheres to a Gaussian function defined on the sky dome. The blue circle shows the dominant focus of the sensor ($\theta_g = 40°$), and the green arrow shows the smoothing parameter ($\sigma_g = 13°$).

The sum-of-sinusoids from the previous section then changes to:

$$r_{\text{SOL}}^{\xi} = \sum_{j=1}^{n_{\text{POL}}} \underbrace{\frac{n_{\text{SOL}}}{n_{\text{POL}}} \cdot \sin\left[\alpha^j - \left(\phi_{\text{SOL}}^{\text{pref}}\right)^{\xi}\right] \cdot g^j(\theta_t, \phi_t)}_{W_{\text{SOL}}^{j,\xi}} \cdot r_{\text{POL}}^j \tag{6}$$

**Time compensation mechanism**

We extend the above model to provide a method by which insects might compensate for the changing celestial sky pattern over the course of the day and seasons. In particular, the aim is to provide a stable geocentric compass even though the solar azimuth varies compared to the true north. This is usually assumed to require an internal clock and calculation or learning of the ephemeris function [50, 51]. Here we suggest a possible solution that uses the current polarisation information only to estimate the ephemeris function and thus continuously adjust the compass. This is based on the observation that the confidence of the estimate of the solar azimuth is related to the solar elevation (see Discussion), from which we can infer the rate of change of the azimuth.

We add an extra layer to our model, the *true compass layer* (TCL), which is a copy of the SOL but the preference angle of its neurons change through time (see Fig 3). The basic response of this layer is given by:

$$r_{\text{TCL}}^{k} = \sum_{\xi=1}^{n_{\text{SOL}}} \underbrace{\frac{n_{\text{TCL}}}{n_{\text{SOL}}} \cos\left[\left(\phi_{\text{TCL}}^{\text{pref}}\right)^{k} - \left(\phi_{\text{SOL}}^{\text{pref}}\right)^{\xi}\right]}_{W_{\text{TCL}}^{\xi,k}} \cdot r_{\text{SOL}}^{\xi} \tag{7}$$

where $\left(\phi_{\text{TCL}}^{\text{pref}}\right)^{k} = k \cdot 360°/n_{\text{TCL}}$ is the preference angle of the $k^{\text{th}}$ TCL-neuron and $n_{\text{TCL}} = 8$ is the size of TCL-population.

As described earlier, we can derive from this output the direction of the sun, $\phi_s'$, and the confidence of the prediction, $\tau_s$. In a low-noise environment and for a specific set of responses, the confidence can be transformed to a prediction of the solar elevation using the function below:

$$\theta_s' = 26° \cdot \left[1 - 2\frac{\sin^{-1}(1 - \tau_s)}{180°}\right] + 15° \tag{8}$$

with domain $\{\tau_s \in \mathbb{R} | 0 \le \tau_s \le 2\}$ and range $\{\theta_s' \in \mathbb{R} | 18° < \theta_s' < 67°\}$ (see Fig 5A). When the confidence is high enough the predicted elevation, $\theta_s'$, can be used to approximate the change rate of the solar azimuth using the following equation (illustrated in Fig 5B):

$$\frac{\mathrm{d}\phi_s}{\mathrm{d}t} = \exp\left(\frac{54° - \theta_s}{10}\right) + 9° \tag{9}$$

**Fig 5. Using confidence of the estimate to compensate for time.**
(A) The confidence value of the compass response varies with the solar elevation (black dots). Within the range $18° - 67°$ this relationship can be used to estimate the elevation using Eq (8) (red dots). (B) The rate of change of the solar azimuth over time depends on the elevation [coloured dots represent different times of the day from morning (blue) to the evening (red)] and can be approximated using Eq (9) (black line). (C) Showing the solar elevation with respect to the solar azimuth for different times of the year. Each of the 12 imaginary curves in B and C correspond to the $21^{\text{st}}$ of every month; the sampling rate in each day is every 10 minutes from sunrise to sunset.

Integrating the above equation through time and using the information that the sun is always moving clockwise, we can approximate the shift of our predicted solar azimuth, $\phi_s'$, required to get a global orientation (see Fig 5C). This is implemented by introducing an update rule for the TCL-layer:

$$\left(\phi_{\text{TCL}}^{\text{pref}}\right)^{k} \leftarrow \left(\phi_{\text{TCL}}^{\text{pref}}\right)^{k} + \frac{\mathrm{d}\phi_s}{\mathrm{d}t} \tag{10}$$

which updates the connections between the solar layer and the TCL-neurons through a recurrent connection (see Fig 3 green connections). Fig 6 shows the response and weights for all the different layers along with the corrections of the global direction when we add the tilt and time compensation mechanisms. The above integration gives an alternative answer to the question of how insects can develop their *ephemeris function* without using a clock.

**Fig 6. Step-by-step processing of the compass model.**
(A) The sum-of-sinusoids mechanism detects the solar azimuth. (B) The tilt compensation mechanism corrects the predicted solar azimuth using tilting information; the sensor has been tilted 30° NNW. (C) The time compensation mechanism corrects for the solar azimuth changes using the solar elevation; 8 hours have passed so the sun has moved 120° clockwise but the compass is still aligned to the same direction. The white, orange and green areas show the response of the POL-, SOL- and TCL-neurons respectively; red denotes excitation and blue suppression. The set of synaptic weights connecting each layer is shown under the disc. Orange background means that the activity is affected by the gating function, and green that it is affected by the time compensation mechanism. In the white disc, different points are the relative positions of the POL units on the sensor; the round green mark is the point of the sensor that is aligned with the zenith of the sky, and the yellow circle is the sun position. The black arrow with the dashed line is the decoded prediction of the solar azimuth from the TCL-neurons; the numbering refers to the identities of the neurons in weight matrices below.

## Central Complex

The TCL-neuron output described above provides the required compass input that was assumed to be available in a previous anatomically constrained model of path integration in the insect central complex [34]. In that model, a set of 8 TB1 neurons with preferred directions $\{k \cdot 45° | k = 1, ..., 8\}$ were activated with a sinusoidal relationship to the heading of the agent. We thus use an exact copy of this CX model, replacing its idealised input with our polarisation-derived compass signal to test its efficacy and robustness.

## Evaluation

### Measuring compass accuracy

In order to evaluate the performance of the model, we introduce an objective function, $J$, which measures the average error across multiple predictions of the solar azimuth. Each prediction is made for a different sun position and tilting orientation. More specifically, we tested 17 tilting orientations, namely 8 homogeneously distributed on a 60° tilted ring, 8 on a 30° ring and one pointing towards the zenith. For each of those

tilting orientations, we sample 500 homogeneously distributed sun positions on the sky 289
dome, giving a total of 8500 predictions. The error is given by the following equation, 290

$$J = \frac{1}{8500} \sum_{t=1}^{17} \sum_{s=1}^{500} ||[(\phi_{t,s} - \phi'_{t,s} + 180°) \mod 360°] - 180°|| \tag{11}$$

where $\phi_{t,s}$ and $\phi'_{t,s}$ are the real and estimated solar azimuths. 291

We report the error as the mean absolute angular error plus/minus the standard 292
error (MAE $\pm$ SE). A more detailed description of the objective function can be found 293
in S1 Appendix. We also report the confidence of the predictions, $\tau_s$, as a value that 294
shows how much we should rely on the respective predictions. Fig 7A gives a schematic 295
representation of the objective function. 296

**Fig 7. The objective function and the accuracy of the compass.**
(A) Schematic representation of the objective function; the yellow and green suns witness the real and estimated sun position;
the stem around the green sun denotes the variance of the estimation. (B) Mean absolute angular error (coloured solid lines),
MAE $\pm$ SE, and confidence (black dashed line), $\tau_s$, against the solar elevation for different disturbance levels, when the sensor
points towards the zenith. (C) The mean absolute angular error (black solid line) and confidence (black dashed line) against
the disturbance level.

The same objective function was used to explore the parameter space in both the 297
design and the computational model of the sensor. The parameters for the layout of our 298
sensor along with those of the computational model are inspired by biological features 299
in insects, and specifically the *Cataglyphis* ants. Nevertheless, we are interested in 300
exploring different set-ups that may perform better than the one that biology indicates. 301

### Sensory noise 302

By adding perturbations of the polarisation signal in the simulation, we can evaluate 303
the robustness of the sensor in noisy environments. In a natural environment, this could 304
be caused by a sensor malfunction, clouds, vegetation or other objects that can block 305
the light from the sky or destroy the polarisation pattern (note however that in the UV 306
spectrum, cloud has a relatively small effect light propagation). In practice, a noise 307
level, $\{\eta \in \mathbb{R} | 0\% \leq \eta \leq 100\%\}$, specifies the percentage of ommatidia that fail to 308
contribute to the input. These are uniformly distributed across the surface of the eye. 309

### Behavioural simulations

The aim of our model was to fill in the missing link between the compass information available from the sky and the path integration behaviour of insects. We therefore assess the performance using a simulated ant in a simulated world using the accurate sky model. The agent takes a predefined foraging path sampled from real ant data [52], which is translated into a sequence of directions and distances that the agent follows for its outward journey. It uses the insect eye and visual processing model described above as input to the CX path integration model [34], and the consequent CX output to control its inward journey. The ability of the agent to return home by the direct path is assessed using the same methods as in [34] allowing direct comparison between the use of simulated input and our network. We also test with conditions of additional sensor disturbance and head-tilt caused by uneven terrain.

### Simulating neurophysiological experiments

As outlined in the introduction, neurophysiological recordings from the protocerebral bridge of insects appears to show a compass output that spans only $[0°, 180°]$. To see if we can account for this result, which is discrepant with our model, we perform a simulated neurophysiology study in which we record the response of the TCL-neurons in our model using the same stimulus conditions as the animal experiments. Thus, we expose the artificial DRA to a uniform light source filtered by rotating linear polariser, and construct tuning preference curves for the TCL-neurons.

# Results

## Compass accuracy without tilt

We first evaluate our compass model in conditions where it always points towards the zenith. The average error in the absence of noise is $J = 0.28° \pm 0.1620°$ for $N = 1000$ sun positions homogeneously distributed on the sky-dome, and the average confidence was $\tau_s = 2.08$, which is quite high (see Fig 7B and C to compare with regular confidence levels).

The solar elevation strongly affects the polarisation pattern in the sky, and as a result the accuracy of the compass predictions. Fig 7B reports the error measured for different solar elevations, and different levels of disturbance. Note we measure the elevation as the angular distance from the zenith point (thus the horizon corresponds to an elevation of $90°$). The blue line, which is hardly visible and lying on the bottom of the figure, is the error for samples without disturbance. The dashed line is the average confidence reported across all the reported disturbance levels. It is not hard to notice that, apart from the error, the confidence is also affected by the solar elevation.

In the model, we use this latter effect to our advantage, to estimate the elevation from the confidence. Fig 8A-C show how the different disturbance levels affect the estimation of the solar elevation, $\theta'_s$ (black dots – real, red dots – predicted), using the confidence, $\tau_s$. Fig 8D shows the predicted against the real solar azimuth change rate.

Fig 7C gives a summary of the effect of the noise on our model's predictions. We notice that as the disturbance grows so does the error of the predictions, but the confidence drops. This suggests we should not trust the predictions of our model when the disturbance of the sensory input is more than 85%, but for lower noise levels the compass still gives predictions with less than $25°$ error, which can be sufficient for the path integration task (see later results).

**Fig 8. Dealing with time and light disturbance.**
Transformation of the compass response to solar elevation, and to the derivative of the solar azimuth function. (A -
C) Function of the elevation with respect to the response with disturbance $\eta = 6\%$, $\eta = 26\%$ and $\eta = 43\%$; the red dots are
the predicted solar elevation given the compass response, and the black dot denote the real values; the dashed lines give the
range of the function. (D) Function of the real derivative of the solar azimuth against its prediction using Eq (9); black line
shows perfect match of the two derivatives; colour denotes the time: blue is for morning and red is for evening.

## Effects of head tilt

Navigating ants are subject to large changes in their head pitch angle, particularly when
carrying objects such as food or nest mates [49]. Here we assess how this might impact
the accuracy of their celestial compass.

As we described in the methods, we filter the connections between the POL- and
SOL-neurons using a gating function. With this function deactivated, and thus all
ommatidia providing input to the solar layer, the performance of the model drops
significantly. Fig 9 A, B and C demonstrates the increased error of the predictions for
different sun positions as the sensor is tilted for 0°, 30° and 60° respectively, and
Table 1 summarises the respective average error along with the overall error.

**Table 1. Mean absolute error before and after using the gating function.**

|  | before gating | | after gating | | N |
|---|---|---|---|---|---|
| $J_{\theta_t=0°}$ | 0.63° | ± 0.01° | 0.47° | ± 0.01° | 500 |
| $J_{\theta_t=30°}$ | 35.68° | ± 0.01° | 9.53° | ± < 0.01° | 4,000 |
| $J_{\theta_t=60°}$ | 104.01° | ± 0.01° | 13.16° | ± < 0.01° | 4,000 |
| $J$ | 65.78° | ± 0.62° | 10.71° | ± 0.12° | 8,500 |

N, number of samples used for this error; $J_{\theta_t=0°}$, MAE ± SE for 0° tilting; $J_{\theta_t=30°}$,
MAE ± SE for 30° tilting; $J_{\theta_t=60°}$, MAE ± SE for 60° tilting; $J$, overall MAE ± SE;
MAE, mean average azimuthal error; SE, standard error.

Activating the gating function, the influence of each ommatidium to the responses of
the solar layer becomes a function of the tilting parameters, producing much more
robust results (Fig 9D-F). More specifically, the overall average error drops to
$J = 10.71° \pm 0.12°$ ($N = 8,500$).

The default parameters for the gating function were selected using exhaustive global
optimisation. More specifically, we fixed the design and network parameters and explore
the different combinations of the parameters, $\theta_g$ and $\sigma_g$, in the gating function. As the
number of parameters in the function is very small and their range is also constrained,

**Fig 9. Dealing with tilt for a variety of gating parameters.**

Angular error of the expected direction of the sensor for different tilted angles and gating parameters. (A-F) Visualisation of the azimuthal angular error with respect to the sun position, i.e. $\epsilon \in [0, 90]$ and $\alpha \in [0, 360)$, for three tilting angles of the sensor – (A, D) $\sim 0°$, (B, E) $\sim 30°$, (C, F) $\sim 60°$; without (A-C) and with (D-F) gating. Shading shows the value of the objective function - darker shading is for higher error values. (G) Average angular error for different gating parameters. The lowest cost (green star; $J = 10.71° \pm 0.12°$, $N = 8,500$) is for ring radius $\theta_g = 40°$ and width (variance) $\sigma_g = 13°$.

exhaustive global optimisation was not a very costly process. Fig 9G witnesses that the current combination of sensor layout and compass model perform best for a gating function with a ring shape of $\theta_g = 40°$ radius and $\sigma_g = 13°$ thickness.

The radius of the ring could be interpreted as the dominant angle of focus or the most informative direction. Moreover, our optimal main focus angle is $40°$ from the zenith point differs to the $25°$ angle, suggested in [24].

## Exploration of the structural parameters

The sensor layout and the number of neurons in the computational model were based on biological data, but it is of interest to examine the effect of varying these parameters. The performance error of the compass (including tilted conditions) for a range of layout parameters is illustrated in Fig 10 C. The green line on this figure indicates the receptive field with the lowest error for the given number of units. The performance with respect to the receptive field seems to be independent from the number of units used. More specifically, the best performance on average was for $\omega = 55.99° \pm 0.33°$.

The error observed on the slice set by the green line in Fig 10C, where $\omega \approx 56°$, is illustrated in Fig 10A. This figure shows that there is a sharp drop of the error up to $n = 60$ of units, after which there is not a significant improvement. A slice on the other axis, for $n = 60$, is illustrated in Fig 10B, which shows that the best design parameters for the sensor are $\omega \approx 56°$ receptive field and $n = 60$ number of units. The average error reported for these parameters is $J = 10.71° \pm 0.12°$. However, the lowest error reported was $J = 9.55° \pm 0.12°$ for $n = 336$ and $\omega = 56°$.

**Fig 10. Optimal compass structural parameters.**
The performance of the compass for different topological parameters. (A) The error as a function of the number of units, $n$; the receptive field is fixed at $\omega = 56°$. (B) The error as a function of the receptive field, $\omega$; the number of units is fixed at $n = 60$ units. (C) Values of the objective function on the $\omega \times n$ plane; red shades illustrate the degree of error; the green line shows the receptive field value associated with the minimum error for different number of units.

The number of SOL- and TCL-neurons were selected based on the CX model described in [34]. However, we explored different populations of neurons and compare the performance to the one of the proposed model. Our results showed that less than 8 SOL inteneurons increase the error to $J = 47.49° \pm 0.32°$, while more interneurons do not change the performance. Similarly, as long as we have at least 4 TCL-neurons, the performance of the sensor does not change for any number of SOL-neurons.

## Path integration

To demonstrate the performance of the sensor in a more realistic scenario, we integrated the compass and path integration [34] models, testing how the compass accuracy affects the foraging and homing paths. We create an environment with a simulated sky and let an agent navigate in it. We guide our agent to food-source, using 133 different routes from Spanish desert ants *Cataglyphis velox* [52] and let the agent return to the nest using its path integrator. In addition, we test the performance of the agent under different sky conditions, by adding noise to the polarisation pattern.

Fig 11 summarises the results of the above experiment. The faded coloured lines are the outward paths and the bold ones are the inward. The colour of the line identifies the different disturbance level. We use similar evaluation methods to [34] to allow direct comparison. Fig 11G and H show the overall performance of the agent in the path integration task with respect to the tortuosity of the inward route, $\tau = \frac{L}{C}$, where $L$ is the distance from the nest and $C$ is the distance travelled.

This shows that in most cases, the agent is moving in the correct direction until it reaches the nest and then does a systematic search for the nest. An exception is for $\eta \approx 96\%$, where the agent continues moving in the same direction not realising how far it has travelled. Overall, for disturbance $\eta \leq 87\%$ the agent seems to navigate without

**Fig 11. Behavioural simulation for the path integration task.**

Testing the celestial compass on path integration tasks. We set up the experiments to take place at 9am in Seville, Spain (37°23′33.03″N, 5°53′01.95″W). (A, C, D, E) snapshots of the POL-neurons activity for different disturbance levels as an indicator of the information provided while navigating. (B) The uneven terrain map; red colour denote hills and blue valleys; the marked region is the one cropped for the F and I plots. (F) Five representative routes of ants in different disturbance levels for an even [(I) uneven] terrain and their respective inward paths; different colours are for different noise levels; the faded lines are the outward paths and the bold ones are the inward. (G) Deviation from the best possible route during homing for different noise levels for even [(H) uneven] terrain.

noticeable problems. However, for higher noise levels we see a drop in the performance    418
of the navigation task, walking at least twice the distance between the nest and feeder    419
for $\eta \approx 96\%$. Interestingly, the performance of the agent is affected very little by the    420
uneven terrain, which shows that the tilting of the agent is not a problem anymore. The    421
figures in S3 Fig and in S4 Fig show the detailed paths of all the agents for all the    422
tested disturbance levels.    423

The terrain used here is drawn from a normal distribution, allowing the agent to tilt for a maximum of 45°. The outward paths are consequently distorted by compass and distance errors while following the predefined sequence of directions and distances, but the homing paths still successfully guide the agent back to the nest, suggesting that any systematic bias in compass or distance information caused by uneven terrain is balanced out between the outward and inward routes. However, it is clear that the uneven terrain introduces an extra level of disturbance. Finally, we noticed that as we increase the noise level in the sky, the disturbance due to terrain becomes less apparent, i.e. the paths look more alike in the even and uneven terrains.

## Experimental paradigm

We have noticed that the output of our compass model, the TCL-neurons, is not identical to the electrophysiological responses of the locusts' TB1-neurons reported in [32]. However, this is not surprising, as the testing conditions of the two experiments were very different. Therefore, we tried to simulate the same environment and compare the responses of our output layer to the one recorded from locusts.

We found that the response of the simulated compass neurons closely resembles the double preference angles recorded in locust TB1-neurons [32] when stimulated by a rotating linear polariser under a uniform light source (Fig 12B and D). This contrasts dramatically with the response of the same simulated neurons when exposed to the natural skylight pattern (see Fig 12F). Moreover, calculating the preferred directions from the response of the simulated neurons under the linear polariser, for each column (Fig 12C), produces results rather comparable to the locust (Fig 12A). These data have been interpreted in [32] as supporting a $[0, \sim 180°]$ 'map' of polarisation directions across the protocerebral bridge, increasing by $\sim 22.5°$ per column (see fitted line, Fig 12A). Our results suggest this effect may be a consequence of the experimental procedure rather than revealing the true directional preference - relative to the sky pattern - of these neurons, which may instead resemble Fig 12E.

## Discussion

To perform path integration, insects need to transform polarised skylight to a global orientation. We have proposed a mechanism to explain how this might occur in the insect brain, given known anatomical constraints of the optic lobe and the protocerebral bridge. Our optic lobe model contains a large number ($\sim 60$) of polarisation-opponent neurons that respond to the degree and direction of polarisation received from each ommatidium. The protocerebral bridge should (to match previous work on path integration) contain exactly 8 compass neurons with sinusoidal tuning to 8 cardinal directions, ideally able to compensate for tilt and time. We show that this can be obtained by a weighting function that takes into account the fact that each ommatidium points at a specific region of the sky, and that the sky polarisation pattern has a specific relationship to the sun position. Most previous models have either assumed a simple linear polarisation as input [37], or, if physically implemented and tested under real skylight, have used a limited number of receptors (for a review see [54]). However, neurophysiological investigation of the receptive fields of central complex neurons suggests they could act as matched filters to the specific pattern of polarised light in natural skylight [28]. By combining a realistic sky model and receptor layout we show it is possible to obtain a good estimate of heading direction, sufficient for accurate path integration, robust to noise, able to compensate for head tilt that might occur with rough terrain, and to adapt to sun movement, providing a powerful celestial compass sensor based on the polarisation pattern.

**Fig 12. Real and simulated response of compass neurons for artificial and natural polarised light.**
E-vector orientation resulting in maximum excitation, $\phi_{max}$, for TB1-neurons in different columns of the CX (A,B) and TCL neurons in our simulation, determined by circular statistics (Rayleigh test [53]): (A) real data of TB1-neurons ($N = 15$) in the PB of the locust brain, reconstructed from original data supplied by Stanley Heinze after [32] (inset shows the naming of the columns in the PB), (C) simulated TCL-neurons under a rotating linear polariser, and (E) under a rotating natural sky ($N = 100$, $\eta = 50\%$); black dots show individual samples, red squares show the mean $\phi_{max}$ and red stars show the $\phi_{max}$ in a condition without external disturbance ($\eta = 0\%$); red lines are best linear fit to the data points. (B,D,F) show corresponding examples for specific neurons from four of the CX columns; bin width 10°; black solid lines indicate background activity; red lines indicate the $\phi_{max}$ direction.

## Obtaining solar azimuth from polarisation information

In our model, each neuron in the SOL layer integrates the signal from all sensory units. The relative azimuth of the sensor unit in the array to the preferred direction of

the compass unit determines its weighting. As a result, the response across the compass units effectively represents the direction in the sky with the highest degree of polarisation, the anti-solar azimuth, from which the solar azimuth can be directly inferred. Our model thus counters the common assumption that a polarisation-based compass sensor must inherently have a 180° degree ambiguity and requires some additional signal to resolve the 360° directionality (see e.g. [45, 55]). Another consequence is that the best compass performance is not when the sun is on the horizon (thus producing the maximum degree of polarisation, largely in one direction, in the zenith) as has been sometimes assumed. In fact, for sun exactly on the horizon or exactly on the zenith, precise symmetry in the resulting polarisation pattern will result in ambiguity and low confidence in our model. The highest confidence occurs when the anti-solar azimuth falls within the receptive field of the sensor (modulated by the gating function), which corresponds to a solar elevation $\theta_s > 66°$ (i.e., nearer to, but not on, the horizon).

Note however that for higher elevations, specifically, for $0° \leq \theta_s \leq 30°$ the sun itself would fall in the receptive field of the sensor. This suggests a parallel processing system based on sky luminance could form a complementary mechanism for determining the solar azimuth that would be accurate for solar elevations where the polarisation one is not. A speculative pathway for this could originate in the two out of the eight photo-receptors in the ommatidia of the desert ants that are sensitive in a wider range of the spectrum [40] (see Fig 2C), which could detect a sufficient light intensity gradient, and (in a similar way to our POL to SOL processing) form a novel skylight intensity compass. The two pathways could then be combined in the CX to form a complete insect celestial compass, consistent with the observation [40, 56] that the insect's compass appears to integrate multiple modalities of light [57, 58]. Specifically, recent neurophysiological results show that all polarisation sensitive neuron types in the CX also show azimuth-dependent responses to an unpolarised UV or green light spot [55, 59].

## Neurobiological plausibility

Our model represents a proposed mapping from POL to TB1 neurons in a computational form, i.e., using a weight matrix derived from theoretical considerations rather than following details of the neural connectivity in the insect brain. Here we consider whether there is a plausible neural substrate for this computation.

Tangential neurons (TL) of the lower central body (CBL) represent the actual input of the polarisation pathway to the CX, with at least three TL types which are all polarisation sensitive. As their name suggests, these neurons provide input tangentially across all columns in the CBL. As such, they could form the basis for the 'fully connected' mapping in our model between POL- and SOL-neurons, as CX columnar neurons innervating the same CBL region could potentially sample from all POL inputs. A plausible candidate would be the CL1 neurons: their receptive filed is about 60° wide and their signal-to-noise ratio is relatively low [11]. There is evidence that CL1-neurons may be homologous to the EBw.s neurons of the ellipsoid body (EB) in flies [33], which represent landmark orientation and are used for visual navigation. This suggests the same neurons may get information from the visual field, such as the horizon line, which could provide the pitch and roll information that our model assumes will be integrated at this stage of processing to correct for tilting. A fascinating possibility is that this putative TL-CL1 mapping, which would need a rather well-tuned set of weights to extract the compass heading, could be a self-organising network, or at least could be calibrated by the experience of the animal, e.g., if it makes coordinated rotations under the sky, as many insects have been observed to do [15, 60].

Columnar neurons innervate the protocerebral bridge (PB) and are presumed to connect to TB1 neurons, hence this could form the physiological basis of our model's

connections from SOL- to TCL-neurons. In other insects, the equivalent neurons to TB1 have been shown to form part of a ring-attractor network to encode heading relative to a visual target [33], which can also hold and update this information in the dark (based on self movement). The PB has recurrent connections to the lower central body (ellipsoid body in flies) which could provide the feedback hypothesised in our model to compensate for time. Alternatively, it has been noted [61] that there is a potential neural pathway from circadian pacemaker circuitry in the accessory medulla to the PB, which could provide an alternative way to adjust the compass with the time of day. As shown in our results (see also [28]) it may be difficult to interpret the real encoding principles of these neurons using isolated cues if they have evolved to be tuned to the combined input pattern of the real sky, and are potentially modulated by time and the tilting orientation of the animal. Specifically, we see that the robust $[0, \sim 360°]$ representation of direction in our simulated TCL neurons appears to be a noisy, $[0, \sim 180°]$ representation when using a rotating polariser as the stimulus, resembling the data from [32].

## The sensor array

We found that the resolution and receptive field of the sensor are optimal for $n = 60$ units resolution and $\omega = 56°$ receptive field. However, the DRA of *Cataglyphis* has more units (ommatidia) and broader receptive field in the frontocaudal axis ($\omega_a \approx 120°$). This asymmetric design of the DRA might be explained if we assume the ant's head is tilted more often around the mediolateral axis; as they do not appear to significantly stabilise their head orientation while running up and down hills [62] or while carrying a load [49]; whereas there is some evidence that they do stabilise when their body is tilted around the frontocaudal axis [62, 63]. Therefore more samples on the frontocaudal axis would increase the confidence of their compass when running. Other insect species have distinctive differences in the layout of their dorsal rim: in the precise number of ommatidia, their alignment pattern, their acceptance angle and their spectral sensitives (see Table 2; for a review see [54, 64]). These might suggest similar adaptations to the specific requirements of habitat, foraging time, task and motor control.

**Table 2. Properties of dorsal rim ommatidia in different species.**

|  | ant [13, 44] | cricket [40, 65, 66] | bee [9] |
|---|---|---|---|
| $n$ | $\sim 112$ | $530 - 680$ | $\sim 120$ |
| $\rho_{max}$ | $5.4°$ | $35°$ | $14°$ |
| $\lambda_{max}$ | $350\,nm$ (UV) | $440\,nm$ (blue) | $350\,nm$ (UV) |

$n$, number of facets; $\rho_{max}$, acceptance angle; $\lambda_{max}$, spectral sensitivity.

## POL-compass design for robotics

In this study we used a somewhat generalised DRA, as it was specifically our intent to consider how we might construct an equivalent sensor for a robot, preferably at a low cost. The insect celestial compass has already inspired the design of a number of polarisation compass sensors, particularly as a robust alternative to magnetic compass sensing for robot applications [54]. The approach applied in the Sahabot [42, 45, 46] introduced a number of biomimetic aspects, including POL-OP units, but used only 3, each with a relatively small acceptance angle, all pointing towards the zenith, and oriented in angles with $60°$ difference. The dominant polarisation direction was recovered either by rotational scanning or by using a look up table, with additional light

sensing used to decide between the solar and anti-solar directions. The output angular error reported for flat terrain experiments is 1.5°. Chu et al. [67] improved this design, using blue filters on photo-receptors with wider acceptance angles, $\rho \approx 53°$, to obtain to 0.2° angular error. More recently Dupeyroux et al. [68] used UV sensors with orthogonally aligned HNP'B polarisers that were rotated 360° every 42 seconds using a stepper motor. Calculating a compass direction from this method produced from 0.3° to 1.9° peak errors in clear and cloudy skies respectively. Similar robot implementations include those by [69, 70]. Alternative approaches use a camera [71–75] or multi-camera system [70, 71, 76], or specialised image sensors with different polarisation sensitivity for each pixel [54, 77]. The best performance so far has been achieved by Stürzl [75], who built a single camera sensor with 3 lenses and 3 polarisers oriented in different angles. The sensor estimates the angle and degree of polarisation of the skylight, and fits a sky-model on the input stream to estimate the parameters, which are the solar azimuth and elevation. In addition, they also estimate a covariance matrix that shows the confidence of their prediction. Their approach also works in tilted environments by integrating inertial measurement unit (IMU) data.

Our model suggests an alternative sensor design, in which a larger number of POL-OP sensors are used to sample specific areas of the sky, but these do not form a complete image as in the camera-based systems described above. Such a sensor could be built from off-the-shelf components, e.g., using pairs of UV-Index photodiodes and linear polarisation filters to imitate dorsal rim ommatidia photo-receptor neurons. The components could be mounted on a dome, creating a similar DRA to ant eyes. As we have shown, the subsequently computation to recover heading direction is relatively low-cost and could easily be carried out on a robot-compatible microprocessor, which could also run our path integration model. We hope to build this sensor and test it on a robot in future work.

## Conclusion

As well as building a physical implementation, there are several other ways in which this model could be developed in future. One consideration already discussed above would be to integrate parallel processing of luminance and spectral cues, which can provide complementary information to polarisation, and thus enhance the reliability with which the solar azimuth can be determined over a wider range of conditions. A second would be to examine whether a more direct mapping can be made between the computational processing we have proposed and the detailed neuroanatomy of the layers intervening between the POL neurons in the medulla and the compass neurons in the CX. However, we believe it is key that such a model remains grounded in understanding of the real task constraints the circuit needs to support, i.e., the natural environment conditions under which insect path integration evolved and operates.

## Acknowledgments

This work was supported by EPSRC grant EP/M008479/1 "Invisible cues". We thank Stanley Heinze and Uwe Homberg for providing the biological data in Fig 12 and discussion of these results.

## References

1. Souman JL, Frissen I, Sreenivasa MN, Ernst MO. Walking straight into circles. Current biology. 2009;19(18):1538–1542.

2. Åkesson S, Hedenström A. How migrants get there: migratory performance and orientation. AIBS Bulletin. 2007;57(2):123–133.

3. Cheung A, Vickerstaff R. Finding the way with a noisy brain. PLoS computational biology. 2010;6(11):e1000992.

4. Etheredge JA, Perez SM, Taylor OR, Jander R. Monarch butterflies (Danaus plexippus L.) use a magnetic compass for navigation. Proceedings of the National Academy of Sciences. 1999;96(24):13845–13846.

5. Baker RR, Mather JG. Magnetic compass sense in the large yellow underwing moth, Noctua pronuba L. Animal Behaviour. 1982;30(2):543–548.

6. Freas CA, Schultheiss P. How to navigate in different environments and situations: lessons from ants. Frontiers in psychology. 2018;9:841.

7. Chapman JW, Reynolds DR, Mouritsen H, Hill JK, Riley JR, Sivell D, et al. Wind selection and drift compensation optimize migratory pathways in a high-flying moth. Current Biology. 2008;18(7):514–518.

8. Wystrach A, Schwarz S. Ants use a predictive mechanism to compensate for passive displacements by wind. Current Biology. 2013;23(24):R1083–R1085.

9. Greiner B, Cronin TW, Ribi WA, Wcislo WT, Warrant EJ. Anatomical and physiological evidence for polarisation vision in the nocturnal bee Megalopta genalis. Journal of Comparative Physiology A. 2007;193(6):591–600.

10. Labhart T. Polarization-opponent interneurons in the insect visual system. Nature. 1988;331(6155):435.

11. Heinze S, Gotthardt S, Homberg U. Transformation of polarized light information in the central complex of the locust. Journal of Neuroscience. 2009;29(38):11783–11793.

12. Heinze S, Reppert SM. Sun compass integration of skylight cues in migratory monarch butterflies. Neuron. 2011;69(2):345–358.

13. Labhart T. Polarization-sensitive interneurons in the optic lobe of the desert ant Cataglyphis bicolor. Naturwissenschaften. 2000;87(3):133–136.

14. Dacke M, el Jundi B, Smolka J, Byrne M, Baird E. The role of the sun in the celestial compass of dung beetles. Philosophical Transactions of the Royal Society of London B: Biological Sciences. 2014;369(1636):20130036.

15. Dacke M, Baird E, Byrne M, Scholtz CH, Warrant EJ. Dung beetles use the Milky Way for orientation. Current Biology. 2013;23(4):298–300.

16. Huber R, Knaden M. Egocentric and geocentric navigation during extremely long foraging paths of desert ants. Journal of Comparative Physiology A. 2015;201(6):609–616.

17. Wehner R. Polarization vision–a uniform sensory capacity? Journal of Experimental Biology. 2001;204(14):2589–2596.

18. Strutt JW. XV. On the light from the sky, its polarization and colour. The London, Edinburgh, and Dublin Philosophical Magazine and Journal of Science. 1871;41(271):107–120.

19. Rayleigh JWSB. On the scattering of light by small particles; 1871.

20. Rayleigh L. X. On the electromagnetic theory of light. The London, Edinburgh, and Dublin Philosophical Magazine and Journal of Science. 1881;12(73):81–101.

21. Rayleigh L. XXXIV. On the transmission of light through an atmosphere containing small particles in suspension, and on the origin of the blue of the sky. The London, Edinburgh, and Dublin Philosophical Magazine and Journal of Science. 1899;47(287):375–384.

22. Coulson KL. Polarization and Intensity of Light in the Atmosphere. A Deepak Pub; 1988.

23. Menzel R, Snyder AW. Polarised light detection in the bee, Apis mellifera. Journal of comparative physiology. 1974;88(3):247–270.

24. Labhart T. How polarization-sensitive interneurones of crickets see the polarization pattern of the sky: a field study with an opto-electronic model neurone. Journal of Experimental Biology. 1999;202(7):757–770.

25. Labhart T, Petzold J, Helbling H. Spatial integration in polarization-sensitive interneurones of crickets: a survey of evidence, mechanisms and benefits. Journal of Experimental Biology. 2001;204(14):2423–2430.

26. Henze MJ, Labhart T. Haze, clouds and limited sky visibility: polarotactic orientation of crickets under difficult stimulus conditions. Journal of Experimental Biology. 2007;210(18):3266–3276.

27. Vitzthum H, Müller M, Homberg U. Neurons of the central complex of the locust Schistocerca gregaria are sensitive to polarized light. Journal of Neuroscience. 2002;22(3):1114–1125.

28. Bech M, Homberg U, Pfeiffer K. Receptive fields of locust brain neurons are matched to polarization patterns of the sky. Current Biology. 2014;24(18):2124–2129.

29. Homberg U, Heinze S, Pfeiffer K, Kinoshita M, El Jundi B. Central neural coding of sky polarization in insects. Philosophical Transactions of the Royal Society B: Biological Sciences. 2011;366(1565):680–687.

30. Turner-Evans D, Wegener S, Rouault H, Franconville R, Wolff T, Seelig JD, et al. Angular velocity integration in a fly heading circuit. Elife. 2017;6.

31. Green J, Adachi A, Shah KK, Hirokawa JD, Magani PS, Maimon G. A neural circuit architecture for angular integration in Drosophila. Nature. 2017;546(7656):101.

32. Heinze S, Homberg U. Maplike representation of celestial E-vector orientations in the brain of an insect. Science. 2007;315(5814):995–997.

33. Seelig JD, Jayaraman V. Neural dynamics for landmark orientation and angular path integration. Nature. 2015;521(7551):186.

34. Stone T, Webb B, Adden A, Weddig NB, Honkanen A, Templin R, et al. An anatomically constrained model for path integration in the bee brain. Current Biology. 2017;27(20):3069–3085.

35. Wilkie A, Ulbricht C, Tobler RF, Zotti G, Purgathofer W. An analytical model for skylight polarisation. In: Rendering Techniques; 2004. p. 387–398.

36. Labhart T. The electrophysiology of photoreceptors in different eye regions of the desert ant, Cataglyphis bicolor. Journal of Comparative Physiology A: Neuroethology, Sensory, Neural, and Behavioral Physiology. 1986;158(1):1–7.

37. Sakura M, Lambrinos D, Labhart T. Polarized skylight navigation in insects: model and electrophysiology of e-vector coding by neurons in the central complex. Journal of neurophysiology. 2008;99(2):667–682.

38. Zhang W, Cao Y, Zhang X, Liu Z. Sky light polarization detection with linear polarizer triplet in light field camera inspired by insect vision. Applied optics. 2015;54(30):8962–8970.

39. Smith GS. The polarization of skylight: An example from nature. American Journal of Physics. 2007;75(1):25–35.

40. Labhart T. Can invertebrates see the e-vector of polarization as a separate modality of light? Journal of Experimental Biology. 2016;219(24):3844–3856.

41. Nilsson DE, Labhart T, Meyer E. Photoreceptor design and optical properties affecting polarization sensitivity in ants and crickets. Journal of Comparative Physiology A. 1987;161(5):645–658.

42. Lambrinos D, Kobayashi H, Pfeifer R, Maris M, Labhart T, Wehner R. An autonomous agent navigating with a polarized light compass. Adaptive behavior. 1997;6(1):131–161.

43. Rossel S, Wehner R. Polarization vision in bees. Nature. 1986;323(6084):128.

44. Wehner R. Desert ant navigation: how miniature brains solve complex tasks. Journal of Comparative Physiology A. 2003;189(8):579–588. doi:10.1007/s00359-003-0431-1.

45. Lambrinos D, Möller R, Labhart T, Pfeifer R, Wehner R. A mobile robot employing insect strategies for navigation. Robotics and Autonomous systems. 2000;30(1):39–64.

46. Smith F, Stewart D. Robot and Insect Navigation by Polarized Skylight. In: Proceedings of the International Joint Conference on Biomedical Engineering Systems and Technologies-Volume 4. SCITEPRESS-Science and Technology Publications, Lda; 2014. p. 183–188.

47. Zollikofer C, Wehner R, Fukushi T. Optical scaling in conspecific Cataglyphis ants. Journal of Experimental Biology. 1995;198(8):1637–1646.

48. Schmitt F, Stieb SM, Wehner R, Rössler W. Experience-related reorganization of giant synapses in the lateral complex: Potential role in plasticity of the sky-compass pathway in the desert ant Cataglyphis fortis. Developmental neurobiology. 2016;76(4):390–404.

49. Ardin P, Mangan M, Wystrach A, Webb B. How variation in head pitch could affect image matching algorithms for ant navigation. Journal of Comparative Physiology A. 2015;201(6):585–597.

50. Wehner R, Müller M. How do ants acquire their celestial ephemeris function? Naturwissenschaften. 1993;80(7):331–333.

51. Towne WF. Honeybees can learn the relationship between the solar ephemeris and a newly-experienced landscape. Journal of Experimental Biology. 2008;211(23):3737–3743.

52. Mangan M, Webb B. Spontaneous formation of multiple routes in individual desert ants (Cataglyphis velox). Behavioral Ecology. 2012;23(5):944–954.

53. Batschelet E, Batschelet E, Batschelet E, Batschelet E. Circular statistics in biology. vol. 111. Academic press London; 1981.

54. Karman SB, Diah SZM, Gebeshuber IC. Bio-inspired polarized skylight-based navigation sensors: A review. Sensors. 2012;12(11):14232–14261.

55. El Jundi B, Pfeiffer K, Heinze S, Homberg U. Integration of polarization and chromatic cues in the insect sky compass. Journal of Comparative Physiology A. 2014;200(6):575–589.

56. Wystrach A, Schwarz S, Schultheiss P, Baniel A, Cheng K. Multiple sources of celestial compass information in the Central Australian desert ant Melophorus bagoti. Journal of Comparative Physiology A. 2014;200(6):591–601.

57. el Jundi B, Warrant EJ, Byrne MJ, Khaldy L, Baird E, Smolka J, et al. Neural coding underlying the cue preference for celestial orientation. Proceedings of the National Academy of Sciences. 2015;112(36):11395–11400.

58. Pfeiffer K, Homberg U. Coding of azimuthal directions via time-compensated combination of celestial compass cues. Current biology. 2007;17(11):960–965.

59. Pegel U, Pfeiffer K, Homberg U. Integration of celestial compass cues in the central complex of the locust brain. Journal of Experimental Biology. 2018;221(2). doi:10.1242/jeb.171207.

60. Wehner R. The ant's celestial compass system: spectral and polarization channels. 1997; p. 145–185.

61. Homberg U. Sky compass orientation in desert locusts—evidence from field and laboratory studies. Frontiers in behavioral neuroscience. 2015;9:346.

62. Seidl T, Wehner R. Walking on inclines: how do desert ants monitor slope and step length. Frontiers in zoology. 2008;5(1):8.

63. Raderschall CA, Narendra A, Zeil J. Head roll stabilisation in the nocturnal bull ant Myrmecia pyriformis: implications for visual navigation. Journal of Experimental Biology. 2016; p. jeb–134049.

64. Labhart T, Meyer EP. Detectors for polarized skylight in insects: a survey of ommatidial specializations in the dorsal rim area of the compound eye. Microscopy research and technique. 1999;47(6):368–379.

65. Labhart T, Hodel B, Valenzuela I. The physiology of the cricket's compound eye with particular reference to the anatomically specialized dorsal rim area. Journal of Comparative Physiology A. 1984;155(3):289–296.

66. Blum M, Labhart T. Photoreceptor visual fields, ommatidial array, and receptor axon projections in the polarisation-sensitive dorsal rim area of the cricket compound eye. Journal of Comparative Physiology A. 2000;186(2):119–128.

67. Chu J, Zhao K, Zhang Q, Wang T. Construction and performance test of a novel polarization sensor for navigation. Sensors and Actuators A: Physical. 2008;148(1):75–82.

68. Dupeyroux J, Diperi J, Boyron M, Viollet S, Serres J. A novel insect-inspired optical compass sensor for a hexapod walking robot. In: IROS 2017-IEEE/RSJ International Conference on Intelligent Robots and Systems; 2017.

69. Chahl J, Mizutani A. Biomimetic attitude and orientation sensors. IEEE Sensors Journal. 2012;12(2):289–297.

70. Zhang S, Liang H, Zhu H, Wang D, Yu B. A camera-based real-time polarization sensor and its application to mobile robot navigation. In: Robotics and Biomimetics (ROBIO), 2014 IEEE International Conference on. IEEE; 2014. p. 271–276.

71. Horvath G, Barta A, Gal J, Suhai B, Haiman O. Ground-based full-sky imaging polarimetry of rapidly changing skies and its use for polarimetric cloud detection. Applied optics. 2002;41(3):543–559.

72. Horstmeyer R, Euliss G, Athale R. Flexible multimodal camera using a light field architecture. In: Computational Photography (ICCP), 2009 IEEE International Conference on. IEEE; 2009. p. 1–8.

73. Manakov A, Restrepo J, Klehm O, Hegedus R, Eisemann E, Seidel HP, et al. A reconfigurable camera add-on for high dynamic range, multispectral, polarization, and light-field imaging. ACM Transactions on Graphics. 2013;32(4):47–1.

74. Zhang W, Cao Y, Zhang X, Yang Y, Ning Y. Angle of sky light polarization derived from digital images of the sky under various conditions. Applied Optics. 2017;56(3):587–595.

75. Stürzl W. A Lightweight Single-Camera Polarization Compass with Covariance Estimation. In: Proceedings of the IEEE International Conference on Computer Vision; 2017.

76. Stürzl W, Carey N. A fisheye camera system for polarisation detection on UAVs. In: European Conference on Computer Vision. Springer; 2012. p. 431–440.

77. Sarkar M, Bello DSS, Van Hoof C, Theuwissen AJ. Integrated polarization-analyzing CMOS image sensor for detecting the incoming light ray direction. IEEE Transactions on Instrumentation and Measurement. 2011;60(8):2759–2767.

## Supporting information

**S1 Appendix.  Details of the objective function.**

**S2 Appendix.  Integrating the model for infinite SOL-neurons.**

**S3 Fig.  Path integration in even terrains - detailed paths.** Outward (away from the nest – red solid line) and inward paths (towards the nest – black dashed line) of 133 ants using the proposed compass to orient themselves in different disturbance levels. In the perfect condition we extract the direction from the data, while in the rest of them we use the compass to extract the global orientation of the agent. The outward paths were adapted from [52], and the inward paths are the outcome of the path integration network described in [34].

**S4 Fig. Path integration in uneven terrains - detailed paths.** Outward (away from the nest – red solid line) and inward paths (towards the nest – black dashed line) of 133 ants using the proposed compass to orient themselves in uneven terrains and different disturbance levels. In the perfect condition we extract the direction from the data, while in the rest of them we use the compass to extract the global orientation of the agent. The outward paths were adapted from [52], and the inward paths are the outcome of the path integration network described in [34].